UNCLASSIFIED 408898

DEFENSE DOCUMENTATION CENTER

FOR

SCIENTIFIC AND TECHNICAL INFORMATION

CAMERON STATION, ALEXANDRIA. VIRGINIA



UNCLASSIFIED

NOTICE: When government or other drawings, specifications or other data are used for any purpose other than in connection with a definitely related government procurement operation, the U. S. Government thereby incurs no responsibility, nor any obligation whatscover; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use or sell any patented invention that may in any way be related thereto.

00 40889 JPRS: 19,051 OTS: 63-21747 6 May 1963 COPY NONLINEAR EFFECTS AND PARAMETRIC REGENERATION DURING THE INTERACTION OF WAVES IN WAVEGUIDE SYSTEMS WITH LONG ELECTRON FLOWS 23.2 AD by S. A. Akhmanov at al - USSR ات ا U . . · · · • . U. S. DEPARTMENT OF COMMERCE OFFICE OF TECHNICAL SERVICES JOINT PUBLICATIONS RESEARCH SERVICE Building T-30 Ohio Dr. and Independence Ave., S.W. Washington 25, D. C.

Price: .50

- · · .

.

. -

FOREWORD

This publication was prepared under contract for the Joint Publications Research Service as a translation or foreign=language research service to the various federal government departments.

The contents of this material in no way represent the policies, views or attitudes of the U. S. Government or of the parties to any distribution arrangement.

- PROCURRIGINT OF JPRS REPORTS

All JFRS reports may be ordered from the Office of Technical Services. Reports published prior to 1 February 1963 can be provided, for the most part, only in photocopy (xerox). Those published after 1 February 1963 will be provided in printed form.

Details on special subscription arrangements for JPRS social science reports will be provided upon request.

No cumulative subject index or catalog of all JPRS reports has been compiled.

All JPRS reports are listed in the <u>Monthly Catalog of U.S.</u> <u>Government Publications</u>, available on subscription at \$4.50 per year (\$6.00 foreign), including an annual index, from the Superintendent of Documents, U.S. Government Printing Office, Washington 25, D.C.

All JPRS scientific and technical reports are cataloged and subject-indexed in <u>Technical Translations</u>, published semimonthly by the Office of Technical Services, and also available on subscription (\$12.00 per year domestic, \$16,00 foreign) from the Superintendent of Documents. Semiannual indexes to <u>Technical Translations</u> are available at additional cost.

. 1 .

JPRS:

JPRS: 19,051

NONLINEAR EFFECTS AND PARAMETRIC RECENERATION DURING THE INTERACTION OF WAVES IN WAVEGUIDE SYSTEMS WITH LONG FLECTRON FLOWS

-U3SR-

[Following is the translation of an article by S.A. Akhmanov, S.D. Gvozdover, A.S. Gorsakov, and V.G. Dmitriyev in the Russian-language publication <u>Zhurnal Tekhnicheskov Fisiki</u> (Journal of Technical Physics), Vol XXXIII, No 1, Moscow, 1963, pages 90-99.]

This is a report on the results of an experimental study of the interaction of waves in waveguide systems with long electron flows. The experiments were carried out in the centimeter and decimeter wavelength ranges with a free-drift electron flow (nonlinear space charge wave interaction) and an electron beam associated with a retarding system (nonlinear interaction of space charge waves with retarding system field). Special attention was devoted to the study of factors determining the effectiveness of parametric regeneration running waves of a small signal by the energy of intensive injection running waves; the ratio of signal and injection frequencies varied over wide limits. It has been established that in systems of this type, as a rule one has to deal with a considerable number of combination frequencies which substantially affect the course of nonlinear and parametric processes.

Introduction

Of increasing interest at present is the study of the propagation and interaction of waves in nonlinear waveguide systems. Studies of phenomena in such systems are described in a number of theoretical papers (see refs 1-4, 10, 15) whose results point to the possibility of obtaining various nonlinear effects. The character of the latter depends on the form of the nonlinearity (active or reactive nonlinearity) and the dispersive properties of the system. Of practical interest are nonlinear phenomena in stron-dispersion waveguide systems where a finite number of practically interesting applications (parametric amplification, wide-band frequency transformation, modulation, amplitude limiting, etc.). The experimental study of this complex of questions and the oreation of the corresponding radio electronic devices at the present can be carried out with waveguide systems using the nonlinear properties of a solid (waveguide systems with reactive semiconductor nonlinearity (ref 3) or ferrites (ref 4) or waveguide systems employing the nonlinear properties of electron beams (ref 6) or gas discharge plasma (ref 5).

It should be noted that despite the considerable progress achieved in recent years in the development of nonlinear solid-state reactances, the possibilities of using the latter in wave systems, especially in the unf (ultra-highfrequency) range, where the indicated phenomena are of the greatest interest, are limited. In present practice it is possible to create only filter-type systems containing nonlines elements with concentrated constants. On the other hand, using the nonlinear properties of electron flows, it is possible to obtain purely distributed nonlinear waveguide systems with widely varying characteristics.

The subject of the present study are the results of an experimental study of nonlinear wave interaction and especially the phenomena of parametric regeneration in waveguide systems with long electron flows employing the longitudinal interaction of electrons with high-frequency fields. To our knowledge, the experimental study of such systems is described only in ref 6 which deals with the interaction of waves in a free-drift electron flow and does not consider a number of important questions (combination frequency spectrum arising during interaction [see note], the bandwidth of the parametric regeneration mechanism, nonlinear effects, etc.). ([Note:] As far as we know, the first one to point out the fundamental role of higher combination frequencies arising in the process of parametric interaction was as. Tager (ref 11)).

Paveruide systems with long electron flows can be constructed in two ways: with an electron flow frifting freely inside a conducting cylinder (drift tube) and a system in which the electron flow is connected with a retarding line (e.g., S spiral). In both variants, nonlinear effects can be produced upon the introduction into the system of a powerful injection wave as a result of the nonlinearity of the electron flow. If we are interested in parametric regeneration, the possible types of injection and signal waves in the indicated systems can be summarized in a table.

Injection Nava	Signal Wave
1. Cn electron beam space charge waves (sev)	Cn electron beam sow
2. Cn electon beam sow 3. In retarding system	In retarding system On electron beam sor

It is necessary to note an important difference of system 1 from systems 2, 3 (ace table). In system 1 nonlinear effects are determined solelyby the nonlinearity of the electron beam. The latter can be regarded as a reactive nonlinearit insemuch as the intensity of the electron flow in the process of interaction remains unchanged; the injection and signal voltages are given as boundary conditions at the input of the interaction space. In systems 2, 3 the nonlinearity is of a more complex character (a certain role may also be played by effects associated with the transfer of electron energy to high-frequency fields), while the injection and signal voltages determine not only the boundary conditions, but also the outer forces distributed elong the system.

The present study considers the results of an experimental investigation of systems 1 and 2.

#1. Experimental Apparatus: Results of Experiment

2.1. Flam of Experiment

In accordance with the foregoing, the experimental setu; envisaged the study of phenomena in the interaction of waves both it a free electron flow and in flow associated with a retarding system. It was deemed advisable to carry out the measure ments over a wide interval of variation of injection and signal frequencies, power levels, and watem parameters. Considerable attention was devoted to the study of the spectrum of combinatio frequencies arising in the waveguide system under investigation.

Ine experimental study of the indicated phenomena was carried out on the equipment shown in Fig 1. The object of investigation consisted in electron-waves in the form of runningwave tubes (RUE) with two (Fig 1,a) or three spirals. In the latter case, a free electron drift section was included between the second and third spirals (Fig 1,b). The first spiral in both cases was used for the modulation of the electron flow at the injection frequency $f_{\rm H_{\odot}}$; the signal of frequency $f_{\rm C_{\odot}}$ was intro-

duced and taken off either through the second spiral (Fig 1,a) or the second and third spirals in the study of phenomena in a free-drift electron flow (Fig 1,b).



Figure 1. Block diagram of experimental setup. A -- RWT with two spirals; b -- RWT with three spirals and electron drift section. A = Drift; B = RWT power supp. C = Injection generator; D = Signal generator; E = fH. filte F = Spectrum analyzer; G = F; H = Oscillograph; I = Superhereceiver. Indication of the signal and combination frequencies was carried out with the aid of a superheterodyne receiver and spectral analyzers of the corresponding range; measures were also incorporated for the filtering of injection power at the indicator input. The systems were studied in the centimeter and decimeter wavelength ranges. The inputs and outputs of the experimental systems, depending on the range were either of the weveguide or coaxial type; in the latter case it was possible to study the frequency characteristics of systems.

2.2. Farametric lave Regeneration in Free-Srift Electron Flow

The study of parametric regeneration in a free-drift electron flow was first carried out with a two-fold ratio of signal and injection frequencies

i.e., near the so-called degenerate regime of the basic parametric resonance. It was discovered that in the experimental systems there arose, in particular, waves with a differential frequency $f_{0} = f_{0} = f_{0}$ and the additive frequencies

$$f_{x_1} = f_{y_1} + f_{c_1},$$

$$f_{x_2} = f_{y_1} + f_{y_1},$$

as well as a wave with a frequency of the injection harmonic $2f_{\rm u}$. Combination-frequency waves of a higher order were not registered.

As was shown in the experiment, the character of interaction of the space-charge waves in a free-drift electron field depends to a great extent on the accelerating voltage of the drift section V_{AD} . (Fig 2). In the absence of flow modulation

by injection, the power of signal wave Te varies periodically

with drift voltage (curve 1); this periodicity should be ascribe to the interference of the fast and slow space charge waves at t signal frequency (ref 14). Upon the introduction into the flow of the powerful injection wave (an injection power of about 20 mwt corresponds to the curves in Fig 2) the picture changes radically: in the region of low accelerating voltages there is a clearly defined region of parametric amplification (to 35 d of the signal wave (curve 2); in the same voltage range one also observes an increase in the power of the differential-frequency wave $\Gamma_{\rm curve}$ 3). The power of the additive-frequency waves $F_{\rm a}$ (curve 4), as well as of the injection wave harmonic, could be registered only in the region of relatively high acceleration voltages, despite the sufficiently high sensitivity of the spect ral analyzers (\sim 10⁻¹⁰ watt).



Figure 2. The power of waves of various frequencies (in relative units) as a function of the drift $V_{\mu\mu}$ in a free electron flow. Surve 1 corresponds to the absence of injection; curves 2, 3, 4

characterize the dependence, respectively, of the power of the signal wave P_{o} , the differential-frequency wave P_{p} , and the additive-frequency wave P on the voltage V. Beam current $I_{o} = 650$ microaups; $f_{o} = 2900$ mc/sec; $f_{H_{o}} = 5850$ mc/sec; injection power $P_{H_{o}} \simeq 20$ mwt:

 $\mathbb{P}_{\mathbf{c}_{\bullet}}/\mathbb{P}_{\mathbf{c}_{\bullet_{0}}} \neq \mathbb{P}_{\mathbf{p}_{\bullet}}/\mathbb{P}_{\mathbf{p}_{\bullet_{0}}} \neq \mathbb{P}_{\mathbf{a}}/\mathbb{P}_{\mathbf{a}_{0}} \cdot$

Studies of the frequency characteristics of a system with free electron drift showed that parametric regeneration occurs over a very wide range of frequencies (Fig 3). This factmade it possible to pass on to other ratios of the signal and injection frequencies $f_{\rm H_{\star}}$ and $f_{\rm C_{\star}}$; in particular, phenomena wer





figure 3. Frequency characteristic of system with electron drift in decimeter range.

Figure 4. Relative effectivenet: of parametric wave regeneration (for signal) with low-frequency (region I) and high-frequency (region III) injection. Region II -- injection filter band.

studied for a signal frequency close to the injection frequency $f_{\rm H} \simeq f_{\rm c}$. In this case it was possible to investigate the contin

uous transition from the "high-frequency" injection regime $(f_{\rm H_{\bullet}} > f_{\rm C_{\bullet}})$ to the "low-frequency" injection regime $(f_{\rm H_{\bullet}} < f_{\rm C_{\bullet}})$ In both cases, no qualitative changes were observed in the character of parametric regeneration. This applies both to the value of parametric amplification (see Fig 4, which shows the dependence of the parametric gain of the signal on infection frequency varying uniformly in the neighborhood of the signal frequency $f_{\rm C_{\bullet}}$, and th combination frequency spectrum which

experiences practically no changes with the transition from high. to low-frequency injection.

Let us note that each electrical regime of the experiment al systems has a corresponding optimal injection power at the system input. The dependence of signal wave intensity on the input injection power takes the form of a series of increasing maxima.

2.3. Monlinear Effects in Javeguide Systems There the Electron Flow is Associated With a Retarding Line

In the study of waveguide systems of the indicated type it was established that the presence of a spiral retarding line considerably alters the picture of wave interaction. The character of the interaction is basically determined by the accelersting voltage of the spiral $V_{\rm Ch}$. This is illustrated by typical

curves of the relative signal wave power and differential and additive frequencies as a function of the spiral voltage (Fig ()). In the absence of modulation on the injection frequency there is a picture typical for RAT's of the interaction of the space charge waves of the signal with frequency f in the beam with the signal wave in the spiral (curve 1). Upon introduction into

the electron beam (with the aid of supplementary spiral as in Fig 1), of injection waves of frequency $f_{H_1} \simeq 2f_{C_1}$ there appear

two characteristic maxima of signal wave regeneration (curve 2) located symmetrically with respect to the region of voltages corresponding to optimal RAT amplification (henceforth we shall call this voltage region the RAT-interaction region). On the contrary, in the region of RAT interaction the introduction of injection leads to a sharp (up to 50-db) suppression of the signal wave.

As in systems with free electron flow, in spirel systems there arises a combination frequency spectrum including the differential and additive frequencies (curves 3 and 4, respectively). It is characteristic that the curves of the regenerated signal and differential frequency have a similar character, while the additive frequency wave can be distinguished only in the Refrestion region.

Farametric regeneration in spiral systems, just as in systems with a free electron flow has an extremely wide bandwidet: the band of amplified frequencies in the decimeter wavelength range is about 500 mc/sec with amplification to 20 db. Each electrical regime in the experimental system has a corresponding

.

injection wave power which is optimal from the standpoint of parametric regeneration; the corresponding dependence has the form of a number of maxima increasing with the power of the injection wave (Fig 6).



Figure 5. Power of waves of various frequencies (in relative units) as a function of spiral voltage in system where electron flow is associated with retarding spiral line. Curve 1 corresponds to the absence of injection, curves 2, 3, an 4 correspond to the dependence, respectively, of the signal wave differential wave, and additive wave $P_{c.}$, $P_{p.}$, and $P_{f.}$ on the voltage $V_{c..}$. The beam current is 650 microamps; $f_{c.} = 2900$ mo/ sec; $f_{H.} = 5850$ mc/sec; $P_{H.} = 15 \div 20$ mwt; $P_{c.}/P_{c.0} \neq P_{p.}/P_{p.0}$ $\neq P_{f.}/F_{f.}$.

Measurements in the system with the spiral line for $f_{\rm H} \simeq f_{\rm C}$ were carried out in a conventional RWT whose input received the signal and injection with the sid of a dual triode (the signal and injection generators were operated independently ([Note:] These measurements were carried out by V.N. Yeshtokin). Upon the introduction into the RWT of an injection wave, the phenomena in the system were substantially determined by the spiral voltages. In the center of the RWT-interaction region there was a suppression of the signal by injection, while with spiral voltages exceeding the RWT-interaction potential, the introduction of injection led to some increase in signal intensity. This is illustrated in Fig 7 showing the intensities of the weak signal of frequency $f_{\rm C}$ =9440 mc/sec at the RWT output

as a function of the power of the injection wave of frequency $f_{\rm H_{\circ}} = 9520$ mc/sec. The curve parameter is the spiral voltage: curve i was taken in the potential of RWT interaction, and curve

atin.

2 and 3 in the range of voltages higher than the indicated potential. Let us note that in the range of voltages less than



Figure 6. Derendence of the perametric signal wave gain on the injection power $P_{\rm H}$ in a system where the electron flow is astoclated with a spiral retording line for $f_{\rm H_{\star}} = 2f_{\rm c}$. Figure 7. Dependence of the transmission coefficient of flow-spiral line system on injection power $x_{\rm F}$ for $f_{\rm H} \simeq f_{\rm C}$ and various spiral voltages. Corve 1 taken with RWT-interaction voltage; curves 2 and taken at higher voltages.

ReT-interaction potential, one observed only signal suppression by injection. The strong dependence of weak signal intensity on injection nower illustrated in Fig 7 is the reason for the experimentally-observed cross-modulation phenomenon. This phenomenon, consisting in the transfer of modulation from the injection wave to the signal wave, can be of some interest from the stadpoint of both modulation transference and the cossibility of creating a modulation amplifier.

#2. Piscussion

At the present time, as far as we know, there is no sufficiently complete theory of parametric wave interaction in nonlinear waveguide systems ([Note:] Refs 12 and 13 are of some interest in this connection). In the selection of experimental system parameters and in order to obtain quantitative concepts of the character of the parametric regeneration process, sumlysis based on the consideration of the dispersive characteristics of systems and the general principles of the theory of parametric interaction is waveguide systems is convenient. Let us turn first of all to the consideration of experimental data on wave interaction in a free electron flow.



ある、とは、からなるのであるとなるな人をないてきょうななどできます。 ひょうそう しょう マイ・マン・マン・マール チャル ター・シング しんちょう しょう マ

いたいかん ちちそう

Figure 8. Dispersion characteristics of slow (1) and fast (2) space charge waves in free electron flow. The synchronism line OM corresponds to the case of an absence of deisperion.

In the general case in z nonlinear waveguide system such as the electron flow, upon the interaction of the signal wave of frequency $f_{\rm c}$, with the injection wave of frequency $f_{\rm H}$, there is formed a spectrum of combination frequencies

$$f_{\rm mn} = {\rm m} f_{\rm H_{\bullet}} \pm {\rm n} f_{\rm c_{\bullet}}. \tag{1}$$

The intensity of the wave generated at some combination frequency f_{mn} is substantially determined by the shift with report to the propagation constants β between the indicated wave and the signal and injection waves

 $\Delta \beta_{mn} = \beta_{mn} - (f_{mn}/f_{2...H_{*}}) \cdot \beta_{c...S_{*}}$ (2)

In a dispersionless system all the mn are equal to zero; increasing waves do not arise. The latter possible only is a dispersive system where the energy exchange is considerable for a finite number of waves. Under certain conditions, such a system is an electron beam whose dispersion characteristics are given by the equation

$$h(t) = (2\pi t/u_0)(1 \pm Ru_0/2\pi t),$$
 (3)

1 2

where the signs " \pm " correspond to the slow and fast space char, waves at the frequency f; Rup 13 the reduced plasma frequency for a finite cross-section beam; u₀ is the electron velocity. Schematically, the dispersive characteristics (3) are shown in Fig 8, where we likewise see the shifts (2) for the additive frequencies and injection harmonic.

9

The indicated shifts [see note] increase with rising frequency; as a result of this, only a finite number of waves practically take part in the electron flow in the process of parametric interaction. ([Note:] Results of a precise calculation lead to a system of equations for the amplitudes of waves V_1 and phases Φ_1

$$dV_{1}/dz = a_{1}V_{1}V_{k} ein \phi_{k} + a_{1}V_{1}V_{k} sin \phi_{j} + \dots,$$

$$d \varphi_1/dz = \Delta_1 + a_k(V_1V_1/V_k) \cos \varphi_1 + \dots,$$

where a_1 are constant coefficients; $\Delta_1 = \Delta_{11}^* - \Delta_{2k}^* - \Delta_{2k}^*$; Δ_{2k}^* , Δ_{3k}^*

From expression (3) and Fig 8 we see that the dispersion of space charge waves in the beam is substantially determined by the accelerating voltage of the electron drift section; in particular, the dispersion increases with the reduction of the indicated voltage. There is a corresponding decrease in the humber of combination waves effectively particulating in interactio, with signal and injection waves, while the effectiveness of the parametric regeneration of the signal wave increases. With very small drift potentials, the shift in signal and injection wave phase velocities begins to play a significant role; here we can likewise have the effect of potential sag in the beam (see ref 7) which leads to signal cutoff.

The indicated factors lead to some optimal voltage of the drift section from the standpoint of parametric regeneration



Figure 9. Dependence of parametric signal wave gain on drift voltage in free electron flow. 1 -- experimental curve; 2 -- theoretical curve calculated taking into account only the signal waves and differential frequency. The fall in signal wave intensity with increasing drift voltage can be explained both by the reduction of beam dispersion and the related increasing effect of waves of higher combination frequencies and the reduction of effective beam length. The effec of the latter can be evaluated from the signal amplification formula (ref 9) which takes into account only the signal and differential frequency waves

$$= 41 \,\mathrm{mN}$$

(m is the modulation coefficient; N_0 is the number of plasma

wavelengths over the length of the drift section). In Fig 9, curve 2 is calculated, in accordance with (4), with m = 0.7. In actuality, the drop in signal intensity with increasing voltage can occur much faster (curve 1), and this can be explained by the interaction of signal waves and injection waves with waves at the higher (additive, et al.) combination frequencies.

As shown in calculations, to explain the periodic dependence of signal power on the injection wave power (Fig 6), as well as phenomena with low-frequency injection, it is necessary to take in a considerable number of combination frequencies (see footnote above). The indicated periodicity can be explained by the transformation of the signal wave and differential-frequency wave energy into the energy of additive-frequency wave energy, and vice-zersa, for example (ref 8).

The low-frequency injection system in the investigated weak-dispersion systems does not differ in principle from the regime of nigh-frequency injection; the initial equations (see footnote above) in both cases differ only in the conditions at the system input. Here the frequency spectra of waves taking part in the interaction are wholly equivalent. As shown by qualitative calculations for the electron flow model in the form of an equivalent transmission line, an exponential rise in the wave amplitudes in the case of high-frequency injection (f_H $\simeq 2f_{\rm c}$) is possible upon the inclusion of the differential

frequency wave only, while in the case of low-frequency injection it is necessary to take into account waves with the additive and the two differential frequencies. Apparently, in the latter case the low-frequency injection of frequency $f_{\rm H} < f_{\rm C}$ plays the

role of high-frequency injection with respect to the differential frequency $f_{p_{\perp}} = f_{E_{\perp}} - f_{c_{\perp}}$; to have an increase in the wave amplitude at the frequency $f_{p_{\perp}}$ it is necessary for the wave with the second differential frequency $f_{H_{\perp}} - f_{p_{\perp}}$ to be present. Here the signal frequency turns out to be an equivalent "additive" frequency.

It should be pointed out that in the case of low-frequenc injection a definite role can be played by parametric regeneratic processes at the higher parametric resonance frequencies ($f_{\rm H} \simeq f_{\rm S} \sim 0.5 f_{\rm O}$). However, the threshold flow modulation coefficient at the injection frequency rises considerably.

(4)

The fall in signal wave intensity with increasing drift voltage can be explained both by the reduction of beam dispersion and the related increasing effect of waves of higher combination frequencies and the reduction of effective beam length. The effec of the latter can be evaluated from the signal amplification formula (ref 9) which takes into account only the signal and differential frequency waves

$$G = 41 \text{mN}_{q} \tag{4}$$

(m is the modulation coefficient; N_{q} is the number of plasma

wavelengths over the length of the drift section). In Fig 9, curve 2 is calculated, in accordance with (4), with m = 0.7. In actuality, the drop in signal intensity with increasing veltage can occur much faster (curve 1), and this can be explained by the interaction of signal waves and injection waves with waves at the higher (additive, et al.) combination frequencies.

As shown in calculations, to explain the periodic dependence of signal power on the injection wave power (Fig 6), as well as phenomena with low-frequency injection, it is necessary to take in a considerable number of combination frequencies (see footnote above). The indicated periodicity can be explained by the transformation of the signal wave and differential-frequency wave energy into the energy of additive-frequency wave energy, and vice-rersa, for example (ref 8).

The low-frequency injection system in the investigated weak-dispersion systems does not differ in principle from the regime of high-frequency injection; the initial equations (see footnote above) in both cases differ only in the conditions at the system input. Here the frequency spectra of waves taking part in the interaction are wholly equivalent. As shown by qualitative calculations for the electron flow model in the form of an equivalent transmission line, an exponential rise in the wave amplitudes in the case of high-frequency injection ($f_{\rm H} \simeq 2f_{\rm c}$) is possible upon the inclusion of the differential

frequency wave only, while in the case of low-frequency injection it is necessary to take into account waves with the additive and the two differential frequencies. Apparently, in the latter case the low-frequency injection of frequency $f_{\rm H} < f_{\rm C}$ plays the

role of high-frequency injection with respect to the differential frequency $f_{p_{\star}} = f_{H_{\star}} - f_{c_{\star}}$; to have an increase in the wave amplitude at the frequency $f_{p_{\star}}$ it is necessary for the wave with the second differential frequency $f_{H_{\star}} - f_{p_{\star}}$ to be present. Here the signal frequency turns out to be an equivalent "additive" frequency.

It should be pointed out that in the case of low-frequenc injection a definite role can be played by parametric regeneratic processes at the higher parametric resonance frequencies ($f_{\rm H}$, \simeq f $f_{\rm H}$, \sim 0.5 f₀.). However, the threshold flow modulation co-efficient at the injection frequency rises considerably.

The character of the nonlinearity of the waveguide system is considerably complicated if the electron flow permeetes the spiral retarding system. 4 considerable role can be played by the energy exchange between the electron flow and the highfrequency fields of the spiral. Thus, the powerful injection wave can bring the RWT into a radically nonlinear regime (with an accelerating voltage which is optimal for amplification). As a result of this, there is a disruption of the synchronism between the slow waves in the beam and the spiral waves; the spiral potential optimal for amplification rises, and the intensity of combination frequency generation increases substantially. The above facts lead to a sharp suppression of the signal upon the introduction of a powerful injection wave (Fig 6).

The wave synchronism in the flow and spiral is reestablished upon some increase of the accelerating voltage; this fact may be one of the causes of the appearance of a right-hand meximum of parametric regeneration (Fig 5).

On the other hand, a definite role may be played by the interaction of space charge signal and injection waves in the beam itself and the interaction of the powerful injection wave in the beam with the signal wave in the spiral. The latter michanism apparently predominates in the paremetric regeneration region of the wave in the spiral by the fast wave of the injectic space charge. The relatively weak dispersion of the beam-spiral sys-

The relatively weak dispersion of the beam-spirel systom is the cause of the band breadth of the system. The band of amplified frequencies of the signal is about 40% with a parametric amplification of up to 20 db. The interaction of the injection and signal waves with higher-frequency combination waves leads to a periodic dependence of the intensity of the regenerated signal wave on the power of the injection wave.

It is becessary to note that the described experimental systems were made up of RWT auplifiers whose operating point was on the downward portion of the spiral dispersion characteristic, while the relatively high acceleration voltage in the spiral optimal for amplification assured low beam dispersion. The increasing of the dispersion of such a system is advisable in view of the possibility of cutting off the undesirable combination frequencies.

<u>Conclusion</u>

The results of the above study indicate the possibility of obtaining varied nonlinear effects in waveguide systems with long electron flows (parametric amplification with low- and high frequency injection, suppression, cross-modulation, limiting, etc An especially significant effect on the character of the indicate phenomena is exerted by the dispersive properites of the system. It should be emphasized that in a system of the type described, wave interaction is as a rule associated with the generation of a wide combination-frequency spactrum.

12

Many of the effects considered can be explained on the basis of en analysis of the dispersive characteristics of system and general assumptions of the theory of wave interaction in nonlinear wave-systems encompassing : large number of combinatio frequencies.

A number of observed phenomen can, in our view, be of some practical interest and requires further experimental and theoretical investigation.

The authors take this opportunity to express their sincere appreciation to D.K. Akulin and I.A. Dubov for their assistance in carrying out the press t study and for valuable discussion.

References

Ł

- 1. I.K. Tien, J. Appl. Phys. 29, 10 pt., No 9, 1347-1357, 1958. 2. R.V. Khckhlov, Radiotechnike 1 11 extronike (Radio and Elec-tronics), VI, No 7, 1115-1127, 19 61.
- 3. C.V. Bell, G.E. Wade, TRE Trans, OT-7, Mcroh, Bo 1, 4-11, 1960.

- 1960.
 4. H. Suhl, Phys. Rev., 105, Apr. 15, No 2, 384-385, 1957.
 5. G.S. Kino, Appl. Phys., 31, Ko 1, 1960.
 6. A. Ashkin, Appl. Phys., 29, 10 12, 1958.
 7. N.C. Shang, A.W. Shaw, D.A. Wettlns, IRE Trans. Electr. Devices, 6, No 4, 437-442.
 8. H. Botol, Proc. IRE, 48, No 4, 192-793, 1960.
 9. M.H. Louisell, C.F. Quate, Proc. INE, 46, No 4, 707-716, 19
 10. V.M. Lopukhin, Radiotekhnika 1 [Lektronike, 6, 5, 1961.
 11. A.S. Teger, 100 Years Since the Dirth of A.S. Popor (jubile. Session), Pub. by Acedemy of Solences USSR, 176-187, 1960.
 12. S.S. Cook, W.H. Louisell, C.F. Quate, Electr. and Control. 8, No 1, 1-18, 1960.
 13. V.A. Solntber, Irvestiva Vuzov, Esclofizika (News of the Higher Educational Institutions, Radiophysice), 4, 712-725, 1961. 1961.
- 14. V.F. Tychinskiy, Radiotakhrika 1 Elektronika. 3, 9, 1182-115 1953.
- 15. V.M. Lopukhin, V.L. Martynov, 10-14., 7, No 7, 1962.

10.106 0S0: 2549-5 -END

13

Received Moscow State University 3 December 1961 Physics Department