NOTICE: When government or other drawings, specifications or other data are used for any purpose other than in connection with a definitely related government procurement operation, the U. S. Government thereby incurs no responsibility, nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use or sell any patented invention that may in any way be related thereto.

N-63-4-6

USAELRDL TECHNICAL REPORT 2350

LINEWIDTH OF NONORIENTED POLYCRYSTALLINE HEXAGONAL FERRITES WITH

9

え

63

-

 \mathbf{C}

((

C/1

2

LARGE MAGNETIC ANISOTROPY FIELDS

ISIDORE BADY



MARCH 1963

UNITED STATES ARMY ELECTRONICS RESEARCH AND DEVELOPMENT LABORATORY

FORT MONMOUTH, N.J.

DISCLAIMER NOTICE

THIS DOCUMENT IS BEST QUALITY AVAILABLE. THE COPY FURNISHED TO DTIC CONTAINED A SIGNIFICANT NUMBER OF PAGES WHICH DO NOT REPRODUCE LEGIBLY.

> REPRODUCED FROM BEST AVAILABLE COPY

U. S. ARMY ELECTRONICS RESEARCH AND DEVELOPMENT LABORATORY

FORT MONMOUTH, NEW JERSEY

March 1963

USAELRDL Technical Report 2350 has been prepared under the supervision of the Director, Electronic Components Department, and is published for the information and guidance of all concerned. Suggestions or criticisms relative to the form, content, purpose, or use of this publication should be referred to the Commanding Officer, U. S. Army Electronics Research and Development Laboratory, Attn: Chief, Microwave and Inductive Devices Branch, Electronic Parts and Materials Division, Fort Monmouth, New Jersey.

> J. M. KIMBROUGH, JR. Colonel, Signal Corps Commanding

OFFICIAL: HOWARD W. KILLAM Major, SigC Adjutant

DISTRIBUTION: Special

QUALIFIED REQUESTERS MAY OBTAIN COPIES OF THIS REPORT FROM ASTIA.

THIS REPORT HAS BEEN RELEASED TO THE OFFICE OF TECHNICAL SERVICES. U. S. DEPARTMENT OF COMMERCE, WASHINGTON 25, D. C., FOR SALE TO THE GENERAL PUBLIC.

LINEWIDTH OF NONORIENTED POLYCRYSTALLINE HEXAGONAL FERRITES WITH

LARGE MAGNETIC ANISOTROPY FIELDS

Isidore Bady

Gilbert McCall

DA Task No. 3A99-15-006-02

Abstract

Theoretical calculations are made of the linewidth of nonoriented, polycrystalline, hexagon ferrites with large magnetic anisotropy fields, including both uniaxial and planar ferrites. The motivation for this work arises from an attempt to find an explanation as to why oriented polycrystalline uniaxial ferrites have been found to have, in general, much wider linewidth than that of planar ferrites.

The nonoriented ferrites are considered to be composed of crystallites whose C axes are randomly oriented over all possible solid angles. For a given biasing field, the solid angle \mathbb{Z} is calculated within which the C axis of a crystallite must lie in order that its resonant frequency will differ from the test frequency by a chosen amount. All crystallites within this angle are presumed to absorb energy equally; all other crystallites are presumed not to absorb any energy. The loss term of susceptibility is proportional to \mathbb{Z} , and a linewidth can be calculated. It is shown that the linewidth of a nonoriented uniaxial ferrite is considerably wider than the linewidth of a nonoriented planar ferrite. Since imperfect orientation is a major contributor to the linewidth of oriented hexagonal ferrite — it is seen that imperfect orientation will affect the linewidth of uniaxial ferrites far more than that of planar ferrites. This is supported by test data which show that nonoriented planar ferrites can have a linewidth considerably narrower than the narrowest linewidth obtained with oriented uniaxial ferrites.

U. S. ARMY ELECTRONICS RESEARCH AND DEVELOUMENT LABORATORY

FORT MONMOUTH, NEW JERSEY

CONTENTS

		Page
ABSTRACT		
INTRODUCTION		1
METHOD OF CALCULATION		1
DISCUSSION		2
CONCLUSIONS		3
REFERENCES		3

FIGURES

1.	Plot of X" (Relative)vs Shifted Biasing Field for a Uniaxial Ferrite	15
2.	Plots of X" (Relative) vs Shifted Biasing Field for Planar Ferrite	16
3.	Crystallite with Magnetization at an Angle $ \mathcal{E} $ with Respect to C Axis	17
4.	Crystallite with C Axis at an Angle ψ with Respect to the Biasing Field	18
5.	δ vs ψ for a Uniaxial Ferrite with $H_a = -8,500$ Oersteds and $-4^{-1}\gamma = -10,500$ Oersteds	19
6.	S vs. 4 for Planar Ferrite with H_{a} = 9,000 Oersteds and $\alpha \rightarrow$ = 5,000 Oersteds	20
? .	$c_{\rm e}vs_{\rm e}$, for Planur Ferrite with $\rm H_{g}$ = 9,000 Oersteds and $\rm e_{e}vs_{\rm e}$ = 12,750 Oersteds	21

APPENDIX

Calculation of the Linewidth of Nonoriented Hexagonal Ferrites

Best Available Copy

LINEWIDTH OF NONORIENTED POLYCRYSTALLINE HEXAGONAL FERRITES WITH LARGE MAGNETIC ANISOTROPY FIELDS

INTRODUCTION

Data on the linewidth of oriented, polycrystalline, hexagonal ferrites with large magnetic anisotropy fields have shown that uniaxial ferrites (easy direction of magnetization along the C axis) have a considerably larger linewidth than that of planar ferrites (easy plane of magnetization perpendicular to the C axis). For example, in work performed at Philips¹ on uniaxial barium and strontium ferrites of magnetoplumbite structure with aluminum or titanium-cobalt substitutions, the linewidth varied over a range of 1600 to 3300 oersteds for materials with anisotropies ranging from 7000 to 52,000 oersteds. There was no strong correlation between linewidth and anisotropy field. In work done at Sperry² on uniaxial nickel-W compounds with cobalt substitutions, linewidth ranged from 2200-3000 oes for materials with anisotropies ranging from 7000 to 12,800 oersteds. On the other hand, in work performed by RCA on planar ferrites, a linewidth as low as 110 oersteds was obtained,³ and a large number of compounds had a linewidth less than 500 oersteds.⁴

It is very unlikely that the large linewidth of polycrystalline uniaxial ferrites is due to the crystallite's linewidth. Though relatively little work has been done on single crystals of hexagonal ferrites, a linewidth of 50 oersteds was achieved on a single crystal of barium ferrite⁵ and on a single crystal of aluminum substituted strontium ferrite.⁶ A linewidth of 18 oersteds was obtained on a single crystal of planar ferrite Zn_2Y .⁷ However, there has been considerably more research done on single crystals of Zn_2Y ferrites than on those of uniaxial ferrites to reduce linewidth.

A major contribution to the linewidth of oriented hexagonal ferrites, both of uniaxial and planar types, was considered to be imperfect orientation. It was therefore desimable to study the extreme case of imperfect orientation, i.e., completely nonoriented materials, and compare the theoretically calculated linewidths of the uniaxial and planar ferrites for this case.

METHOD OF CALCULATION

This section contains only a brief outline of the method used to calculate the linewidth of the nonoriented uniaxial and planar ferrites. A detailed procedure is included in the appendix.

The nonoriented ferrite was assumed to be composed of small, singledomain crystallites whose C axes were randomly oriented over all possible solid angles. It was further assumed that the crystallites did not interact with each other. Demagnetizing factors were disregarded for the sake of simplicity.

Let us consider a resonant cavity containing the nonoriented ferrite. A biasing field is applied in a direction perpendicular to the rf magnetic field in the cavity. The resonant frequency of each crystallite will be determined by its anisotropy field, the biasing field, and the angle ψ' its C axis makes with the biasing field. At one particular angle ψ_n for a given biasing field, the resonant frequency of the crystallite will be exactly the same as the test frequency and have the maximum interaction with the cavity. As the angle of the C axis departs from ψ_{1} , the resonant frequency becomes increasingly different from the test frequency, and the interaction with the cavity decreases. We calculate the angles ψ_{\star} and ψ_{\pm} between which a crystallite must lie in order that its resonant frequency will differ from the test frequency by no more than a chosen amount. All crystallites within this angle are presumed to absorb energy equally; all other crystallites are presumed not to absorb energy. Let \mathcal{N} be the solid angle subtended between the cones defined by ψ_1 and ψ_2 . The loss term of magnetic susceptibility is proportional to $-\Lambda$, and therefore a plot of Λ vs biasing field is a plot of the relative value of χ ", the loss term of susceptibility, vs biasing field. The linewidth is readily determined from such a curve.

DISCUSSION

A plot of χ " (relative) for a nonoriented uniaxial ferrite is shown in Fig. 1, and plots for nonoriented planar ferrites are shown in Fig. 2. The abscissa in both figures is the shifted biasing field H₀-H_r, where H₀ is the applied biasing field and H_r is the biasing field required for ferromagnetic resonance for a crystallite whose easy direction is parallel to the biasing field (for the uniaxial ferrite) or whose easy plane is parallel to the biasing field (for the planar ferrite).

A comparison of Fig. 1 and 2 shows that the linewidth of the nonoriented uniaxial ferrite is indeed very much larger than that of the planar ferrite. The most suitable comparison is between curve I of Fig. 2 and the curve in Fig. 1, since both have approximately the same value of anisotropy field and the same value of H_r . We note that the linewidth of the uniaxial ferrite is almost five times that of the planar ferrite.

The relatively narrow linewidth of nonoriented planar ferrites has been confirmed experimentally. Schlömann⁸ has reported a linewidth of 500 oersteds for a nonoriented zinc Y. Of six nonoriented planar ferrites measured here three had linewidths of 1500 oersteds or less. It is interesting to find that completely nonoriented planar ferrites can have a linewidth narrower than the narrowest linewidth that has up to now been obtained with oriented polycopstalline uniaxial ferrites.

An understanding as to why the linewidth of nonoriented uniaxial ferrites is so much greater than that of nonoriented planar ferrites can be obtained from the following reasoning. The magnitude of \mathcal{I}_{\perp} and hence the magnitude of the loss term of the susceptibility are proportional to two factors. Factor 1 is the magnitude of $||\psi_{1} - \psi_{2}||$; factor 2 is the solid angle

2

 Λ subtended between the cones defined by Ψ_{Λ} and $\Psi_{\Lambda} + \Delta \Psi_{\Lambda}$ where $\Delta \Psi_{\Lambda}$ is a small increase in Ψ_{Λ} .

Let us consider the variation of the two factors as a function of biasing field. Factor 1 is maximum when the biasing field is such that crystallites that are at ferromagnetic resonance are those whose easy direction of magnetization, or easy plane of magnetization (as applicable), is parallel to the biasing field. This biasing field has previously been designated as H_r . Factor 1 decreases as the biasing field is increased by each H_r . Thus, factor 1 is relatively large when ψ is close to 0° for the uniaxial ferrites and close to 90° for the planar ferrites.

The solid angle subtended between the cones defined by Ψ_{h} and Ψ_{h} + $\Delta \Psi_{h}$ is proportional to sin Ψ_{h} . Thus, factor 2 is small for biasing fields close to the H_r for uniaxial ferrites and increases as the biasing field is increased beyond H_r. In the case of planar ferrites, factor 2 is large for biasing fields close to H_r and decreases as the biasing field is increased beyond H_r.

Thus, in the case of uniaxial ferrites, as the biasing field is increased beyond H_r , factor 1 decreases and factor 2 increases. This tends to reduce the dependence of \mathcal{M} on H_r as the biasing field is increased beyond H_r , and results in a relatively broad linewidth. In the case of the planar ferrites, however, both factors are large in the vicinity of H_r , and both decrease as the biasing field is increased beyond H_r . Thus, there is a relatively sharp peak of \mathcal{M} in the vicinity of H_r , and this results in a relatively.

CONCLUSIONS

Theoretical calculations show that nonoriented uniaxial ferrites have a much wider linewidth than that of nonoriented planar ferrites. Thus, the imperfect orientation that will inevitably occur when processing oriented polycrystalline hexagonal ferrites will have a greater effect on broadening the linewidth of uniaxial ferrites than that of planar ferrites. This explains at least part of the reason why oriented planar ferrites generally have a much narrower linewidth that that of oriented uniaxial ferrites. In that, a number of completely nonoriented planar ferrites were prepared which have a substantially narrower linewidth than the narrowest linewidth achieved so far with polycrystalline oriented uniaxial ferrites.

REFERENCES

- "Hexagonal Engnetic Materials for Microwave Applications," Final Report. Contract DA 36-039 20-05275. Philips Laboratories, Invington-In-Hudson, New York, July 1901.

- 3. "Hexagonal Magnetic Compounds," Quarterly Report No. 6, Contract DA36-039 SC-87433, RCA Laboratories, Princeton, N. J. (December 1962).
- 4. "Hexagonal Magnetic Compounds," Final Report, Contract DA36-039 SC-78288, RCA Laboratories, Princeton, N. J. (June 1961).
- Bady, Collins, DeBitetto and DuPré, "Ferromagnetic Linewidth of Single Crystals of Barium Ferrite (BaFe₁₂O₁₉)," Proceedings of the IRE, Vol. 58, p. 2033 (December 1960).
- 6. "Hexagonal Magnetic Ma erials for Microwave Applications," Final Report, Contract DA36-039 SC-78071, Philips Laboratories, Irvington-On-Hudson, N. Y. (July 1961).
- 7. Tauber, Savage, Gambino, and Whinfrey, "Growth of Single Crystal Hexagonal Ferrites Containing Zn," Journal of Applied Physics, Supplement to Vol. 33, No. 3, p. 1381 (March 1962).
- 8. Schlömann and Jones, "Ferromagnetic Resonance in Polycrystalline Ferrites with Hexagonal Crystal Structure," Journal of Applied Physics, Supplement to Vol. 30, No. 4, p. 177 (April 1959).

3est Available Copy

APPENDIX: CALCULATION OF THE LINEWIDTH OF NONORIENTED HEXAGONAL FERRITES

In calculating the linewidth of nonoriented hexagonal ferrites, it was assumed that the ferrite was composed of small, single-domain, crystallites, whose C axes were randomly oriented over all possible solid angles. It was further assumed that the crystallites did not interact with each other. Demagnetizing factors were disregarded for the sake of simplicity.

RESONANCE EQUATION FOR CFYSTALLITES

Uniaxial Ferrites

In order to calculate the linewidth of nonoriented polycrystalline ferrites, it is necessary to determine the resonance equation for a single crystallite. This will first be done for a uniaxial ferrite.

The first step is to determine the equivalent magnetic field due to the anisotropy. Let us consider the crystallite shown in Fig. 3. The C axis is oriented along the Z direction. The equilibrium position for the magnetization is parallel to the C axis. When the magnetization is displaced from its equilibrium position by an angle Θ , the energy stored is shown in the following equation:

F=Ksin20

(1)

where the dimensions of E and K are energy per unit volume. K is called the anisotropy constant.

The magnitude of the torque per unit volume due to the anisotropy can be determined by "fferentiating the above equation. This yields

TA = RHAin GLOD D.

(2)

The above torque is due to the crystallographic properties of the ferrite. Let us possible an equivalent magnetic field Her that will exert the same torque. Her is the originated parallel to the 2 axis, and will to taken as pointing in the positive? Sincetion. Since, in general, the torque due to a magnetic field is equal to the product of the magnetic field, the magnetic moment, and the sine of the magnetic between the magnetic field.

and the magnetic moment, the magnitude of the torque per unit volume due to ${\rm H}_{\rm eq}$ is given by

$$T_{eq} = H_{eq} M_{S} \sin \Theta.$$
(3)

Equating T_a and T_{eq} gives

$$H_{eq} = \frac{2\pi}{M_s} \cos \Theta. \tag{4}$$

The term $2K/M_S$ is generally designated as H_2 , the anisotropy field. From Eq. (4), we note that H_2 is equal to H_{eq} for small values of Θ . From Fig. 3, we note that $\cos \Theta$ is the ratio of the 2 component of magnetization to the total magnetization, i.e., $\cot \Theta = M_2/M_S$. Thus, we can write π_1 . (4) as,

$$\overline{H}_{eq} = H_a \frac{M_3}{M_5} \hat{\mathcal{F}}.$$
 (5)

The bar above H_{eq} designates a vector quantity, and the caret above the z, a unit vector. (

Let us now determine the resonance equation with static biasing fields $2 + \frac{1}{2} +$

$$\frac{1}{3} \int c \sigma \bar{m} = \bar{M} \times \bar{H}$$
(6)

n conse e

Capital letters represent de components and small letters rf components. Expanding the above equation yields three equations:

$$\frac{J\omega_{\chi}}{\chi} M_{\chi} - M_{\chi} (H_{3} + H_{\alpha} \frac{M_{3}}{M_{5}}) = 0$$
(8a)
$$\frac{M_{\chi}}{\chi} (H_{3} + H_{\alpha} \frac{H_{3}}{M_{5}}) + \frac{J\omega_{\chi}}{J} \frac{M_{\chi}}{\chi} + \frac{M_{3}}{M_{3}} (H_{\alpha} \frac{M_{\chi}}{M_{5}} - H_{\chi})$$

$$+ M_{\chi} H_{\chi} - M_{\chi} H_{2} - H_{\alpha} \frac{M_{\chi} M_{3}}{M_{5}} = 0$$
(8b)
$$\frac{M_{\chi}}{M_{5}} + \frac{M_{\chi}}{M_{5}} \frac{M_{\chi}}{M_{5}} = 0$$
(6c)

In the above equations, pressure of two riverms were disregarded. Equation (cl) contains a group of no verms and a group of de terms, each of which must be equated to zero separately. Considering the de terms only, and defining $\alpha_{ij} = M_{ij}/M_{ij}$: we can readily derive,

e un development of the source of the concernation of the concerna

Best Available Copy

(C)

 $\left(\begin{array}{c} 1\\ -\end{array}\right)$

The resonance equation can be obtained by setting the determinant of Eq. (8) to zero, including only the rf terms, i.e.,

$$\begin{vmatrix} Jw \\ S \\ H_3 + H_a d_3 \\ H_x + H_a d_3 \\ H_x \\ H_$$

This yields

$$H_{\chi}(H_{\chi} - \mathcal{A}_{\chi}H_{\alpha}) + (H_{3} + \mathcal{A}_{3}H_{\alpha})^{2} = \left(\frac{\omega_{h}}{\gamma}\right)^{2}.$$
 (12)

We use the notation ω_r in Eq. (12) instead of ω to designate that this is the frequency at which resonance will occur for given values of $H_{\rm E}$, $H_{\rm X}$, $H_{\rm Z}$.

Planar Ferrites

In determining the equivalent field due to the anisotropy, Fig. 3 can be used. The easy plane of magnetiziation will be taken as the YZ plane; hence, the equilibrium position of the magnetization is in the YZ plane; i.e., $\Theta = 90^{\circ}$. Equation 1 applies to planar ferrites too. However, since the energy is at a minimum at $\Theta = 90^{\circ}$, K is negative for planar ferrites. Corresponding to Eq. (2), we have

9

$$T_{\alpha} = 3|\kappa| \sin \theta \cos \theta.$$

(13)

Let us now postulate an equivalent magnetic field $\rm H_{eq}$ that will exert the same torque. $\rm H_{eq}$ will clearly be oriented in the YZ plane, and the magnitude of the torque due to $\rm H_{eq}$ is given by

$$T_{eq} = H_{eq} M_{s} cor \mathcal{C}.$$
(14)

Equating $\mathbf{T}_{\mathbf{a}}$ and $\mathbf{T}_{\mathbf{eq}}$ gives

$$H_{eq} = \frac{2kd}{M_s} \sin \varphi = H_{eq} \sin \varphi$$
 (15)

where we have written H_{a} for $\frac{2|K|}{|K_{15}|}$.

 ${\rm H_{eq}}$ is oriented along the component of magnetization in the YZ plane; i.e., along ${\rm M_{eq}}$. We can therefore write

$$H_{eq} = H_{a} \sin E \left[\frac{M_{y}}{M_{y3}} \right] + \frac{M_{3}}{M_{y3}} \left[\hat{3} \right]$$

$$= H_{a} \left[\frac{M_{y}}{M_{y3}} \right] + \frac{M_{3}}{M_{5}} \left[\hat{3} \right].$$
(16)

Let us now determine the resonance equation with static biasing fields of $H_{\rm c}$ % and $H_{\rm c}$ f. The dynamic equation of motion becomes

$$\frac{1}{2} \left[\left(M_{x} - M_{x} \right) \hat{x} + m_{21} \hat{y} + \left(M_{3} + m_{3} \right) \hat{y} \right] \\ \times \left[m_{x} \hat{y} + m_{x} \right] \hat{x} + m_{21} \hat{y} + \left(M_{3} - m_{3} \right) + H_{3} \right] \hat{y} \right].$$

Expending the above equation yields

$$\frac{J\omega m_{\chi}}{8} - m_{\chi}(H_{3} + H_{\alpha}\alpha_{3}) + \alpha_{3}H_{\alpha}m_{\gamma} = 0 \quad (18a)$$

$$\frac{\int w m_{y}}{\chi} - m_{3} H_{x} + m_{x} H_{3} + m_{x} H_{a} d_{3} - M_{3} H_{x} + M_{x} H_{3} + \frac{H_{a} M_{3} M_{x}}{H_{5}} = 0$$
(18b)

$$\frac{\mathcal{J}_{\mathcal{W}}}{g} - \mathcal{A}_{\mathcal{X}} H_{a} m_{g} + m_{g} H_{\mathcal{X}} = 0.$$
(18c)

Equating the dc terms in Eq. (18b) to zero yields

$$\frac{\alpha'_3}{\alpha'_{\chi}} = \frac{H_3 + H_a \alpha'_3}{H_{\chi}}$$
(19)

The above equation, together with Eq.(10), enables us to solve for ∞_{χ} and α_{χ} , and so determine the static equilibrium position of the magnetization.

The resonance equation can be determined by setting the determinant of Eq. (18) to zero, including only the rf terms, i.e.,

$$\begin{array}{cccc} H_{3} + H_{\alpha} d_{3} & \frac{J\omega}{8} & H_{\alpha} d_{x} - H_{x} \\ O & H_{x} - d_{x} H_{\alpha} & J\omega \\ \frac{J\omega}{8} & -H_{3} & O \end{array}$$

$$(20)$$

This yields

$$H_{3}(H_{3}+H_{\alpha}d_{3})+(H_{\chi}-H_{\alpha}d_{\chi})^{2}=\left(\frac{cc_{2}}{\gamma}\right)^{2}.$$
 (21)

We use U_{Λ} in Eq.(21) instead of U for the same reason as given in connection with Eq. (12).

CALCULATION OF LINEWIDTH

Uniaxial Ferrites

Consider a sphere of nonoral ted uniaxial ferrite, whose linewidth it is desired to measure. The blasing field is applied along the Z' direction, and the rimignetic field along the Y' direction. The blasing field H_0 is varied to obtain a resonance curve.

Also consider a particular crystallite whose C axis is oriented at an ungle (1) to the C' axis, as shown in Fig. 4. For the purpose of determining the recommence condition of this crystallite, it is necessary to express the binning field in terms of components parallel to or perpendicular to the C axis. These correspond respectively to $H_{\rm c}$ and $H_{\rm x}$ of Eqs. (9) and (12). From Fig. 4, we note that

11

$$H_3 = H_0 \cos \psi$$
$$H_x = H_0 \sin \psi$$

.

(22)

For a particular set of values of H_a , H_o , and ω , there is only one value of $(\bigcup$ at which exact resonance is obtained, i.e., where $\omega = \omega_n$ exactly. However, let us permit ψ' to vary a little on either side of the value at which exact resonance is obtained, and determine the difference $\delta = ((U_0 - (U_0))/(V_0)$ as a function of ψ' . This is plotted in Fig. 5

 $\delta = (W_2 - W)/|Y|$ as a function of Ψ . This is plotted in Fig. 5 for a value of $H_a = 8500$ coersteds, and $|\Psi/Y| = 10,500$ coersteds for several values of H₀. From Fig. 5, we note that for a crystallite whose C axis is aligned along the direction of the biasing field $\Psi = 0$, the biasing field required for resonance is 2000 coersteds.

We will now assume that if $|\delta|$ is less than some chosen value ϵ , the crystallite will absorb energy, and so reduce the Q of the cavity. Furthermore, we will make the simplifying assumption that all the crystallites that are criented so that $|\delta| \leqslant \epsilon$ absorb an equal amount of energy. Also, it is assumed that any crystallite that is oriented so that $|\delta| > \epsilon$ will not absorb any energy from the cavity, and will not affect the cavity Q. The choice of a value for ϵ is somewhat arbitrary. A value of 200 was chosen for convenience in calculation.

For a particular value of H_0 , let ψ_1 be the value of ψ at which $\delta = -\epsilon$. For this value of H_0 , the number of crystallites that will absorb energy is proportional to the angle subtended between the cones defined by ψ_1 and ψ_2 ; i.e., to $\int_{-\pi}^{\pi} \omega_{nn} \psi d \psi$. Thus, the absorption and hence the loss component of the susceptibili χ " are proportional to the above integral. A plot of the relative value of χ " is shown in Fig. 1. The abscissa in Fig. 1 is the shifted biasing field H_0 - H_r , where H_r is the field required for resonance for a crystallite oriented in such a way that its easy direction is approximately 2800 oersteds.

Figure 1 was replotted with values of E taken as 400 and 100 oersteds. In both cases, it was found that the curve of relative absorption differed very little from the curve for $E \approx 200$ oersteds. Thus, in this case, the linewidth was substantially independent of the choice of E.

If H_x , H_z , and H_a were all multiplied by a common factor, it is apparent from Eq. (9) and (10) that \bowtie_X and \bowtie_3 would be unchanged, and it is apparent from Eq. (12) that ϖ_N would be multiplied by the same

factor. Hence, if we choose values of H_a and $|\omega/S|$ of 8500A oersteds and 10,500A oersteds, respectively, where A is some numerical factor, Fig. 5 will apply, provided \ddot{O} and the values of H_0 are each multiplied by A. Since, as noted above, the shape of the curve of relative absorption is relatively little affected by the value chosen for ϵ , the linewidth will be proportional to the factor A.

Planar Ferrites

Consider a sphere of nonoriented planar ferrite whose linewidth it is desired to measure. The biasin; field H_0 is applied along the Z' axis, and the rf magnetic field along the Y' axis. The biasing field is varied to obtain a resonance curve.

Consider a particular cyrstallite whose C axis is oriented at an angle Ψ with respect to the Z' axis, as shown in Fig. 4. For the purpose of determining the resonance of this crystallite, it is necessary to express the biasing field in terms of components parallel to or perpendicular to the easy plane. These correspond, respectively, to H_z and H_x of Eq. (19) and (21). From Fig. 4, we note that

$$H_3 = H_0 \sin \Psi$$

$$H_x = H_0 \cos \Psi$$

We now proceed in the same manner as we did in the case of the uniaxial ferrites. For a particular set of values of H_a , H_0 , and ω , there is only one value of ψ at which exact resonance is obtained. However, let us permit ψ^{\dagger} to vary a little on either side of the value at which exact resonance is obtained, and determine the difference $\delta = (\omega_A - \omega)/M$ as a function of ψ^{\dagger} . This is plotted in Fig. 6 for a value of $H_a = 9000$ corsteds, and $|\omega|/|| = 5000$ corsteds for a series of values of H_0 . Similarly, Fig. 7 shows ξ^{\dagger} as a function of ψ^{\dagger} for $H_a = 9000$ corsteds. From Fig. 6 and 7, we note that for a crystallite oriented so that its easy plane is parallel to the biasing field ($\psi = 90^{\circ}$), the biasing field required for resonance is 2210 corsteds in the case of Fig. 6 and 9000 corsteds in the case of Fig. 7.

Again, as in the case of the uniaxial ferrites, we will assume that if 1/2 is less than some chosen value \mathcal{E}_{-} , the crystallite will absorb energy and as reduce the ∂ of the cavity, and that all such crystallites will absorb an equal amount of energy. Also any crystallite that is oriented so that $|\langle d \rangle| > \mathcal{E}_{-}$ will be assumed not to absorb any energy from the cavity.

Best Available Copy

(23)

Let us take $\epsilon = 200$ oersteds, and define ψ_1 and ψ_2 as in the case of the uniaxial ferrites. The absorption and hence the loss component of susceptibility χ " are proportional to

 $\int_{\omega}^{\psi_2} \sin \psi d \psi.$

We note that ψ_1 and ψ_2 are interchanged in this case when compared to the corresponding expression for uniaxial ferrites. Plots of the relative absorption are given in Fig. 2. The abscissa in Fig. 2 is the shifted biasing field H₀ - H_r where H_r i: the field required for resonance for a crystallite oriented so that its easy plane is parallel to the biasing field. As noted above, H_r = 2210 and 9000 oersteds for the cases where | w/M = 5000and 12,750 oersteds, respectively.

In the case of uniaxial ferrites, it was noted that the linewidth was relatively insensitive to the value of ϵ . This is not so in the case of planar ferrites. For example, for $\epsilon = 200$ oersteds, the linewidth, as can be seen from Fig. 2, is 600 oersteds. However, if ϵ were chosen as 100 oersteds, the linewidth would be 400 oersteds.

As in the case of the uniaxial ferrites, Fig. 6 and 7 will also apply for the case where H_a and $|\omega/\gamma|$ are both multiplied by a factor A, provided the values \mathcal{L} and of H_o are also multiplied by A. Since the linewidth varies with \mathcal{E} , the linewidth will vary as A^n , where n lies between zero and 1.







FIG 2 PLOT OF X "(RELATIVE) VS SHIFTED BIASING FIELD FOR PLANAR FERRITE WITH H_0 = 9,000 OERSTEDS. ω/γ =5,000 AND 12,750 OERSTEDS.

CRYSTALLITE WITH MAGNETIZATION AT AN ANGLE θ with respect to c axis. ŝ FIG



THE BIASING FIELD. BIASING FIELD IS APPLIED PARALLEL TO $Z^{i}AXIS$, AND THE rf MAGNETIC FIELD IS APPLIED PARALLEL TO $Y^{i}AXIS$. CRYSTALLITE WITH C AXIS AT AN ANGLE ψ WITH RESPECT TO F1G 4









FIG 6 δ VS ψ FOR PLANAR FERRITE WITH H_a = 9,000 OERSTEDS AND ω/γ = 5,000 OERSTEDS.





ī

DISTRIBUTION LIST Copies

Copies

Commanding General U. S. Army Electronics Command ATTN: AMSEL-AD Fort Monmouth, New Jersey

Office of the Assistant Secretary of Defense (Research and Engineering) ATTN: Technical Library Room 3E1065, The Pentagon Washington 25, D. C.

Chief of Research and Development Department of the Army Washington 25, D. C.

Chief, United States Army Security Agency ATTN: ACefS, Ch (Technical Library) Arlington Hall Station Arlington 12, Virginia

Commanding Officer U. S. Army Electronics Research and Development Activity ATTN: Technical Library Fort Huachuca, Arizona

Cormanding Officer U. S. Army Electronics Research and Development Activity ATTK: SELWS-AJ White Sands, New Mexico

Commanding Officer U. S. Army Electronics Research Unit P. O. Box 205 Mountain View, California

Commanding Officer U. S. Army Electronics Materiel Support Agency ATTN: SELUS-ADJ Fort Monmouth, New Jersey

3	Commanding General U. S. Army Satellite Communications Agency ATTN: Technical Documents Center	1
1	Fort Monmouth, New Jersey	
	Commanding Officer U. S. Army Engineer Research and Development Laboratories ATTN: Technical Documents Center	1
2	Fort Belvoir, Virginia	
1	Commanding Officer U. S. Army Chemical Warfare Laboratories ATTN: Technical Library, Building 330 Army Chemical Center, Maryland	l
1	Commanding Officer Harry Diamond Laboratorios ATTN: Library, Building 92, Room 211 Washington 25, D. C.	1
1	Headquarters, United States Air Force ATTN: AFCIN Washington 25, D. C.	2
٦	Rome Air Development Center ATTR: RAALD Griffiss Air Force Base New York	1
1	Headquarters Ground Electronics Engineering Installation Agency ATTN: ROZPEL Griffiss Air Force Base New York	1
	Commanding General U. S. Army Nateriel Command ATTN: RED Directorate Washington 25, D. C.	2

Distribution List (Cont) Copies

1

1

1

ŀ

1

2

2

1

1

(2)

Aeronautical Systems Division ATTN: ASAFRL Wright-Patterson Air Force Base Ohio

U. S. Air Force Security Service ATTN: ESD San Antonio, Texas

Headquarters Strategic Air Command ATTN: DOCE Offutt Air Force Base, Nebraska

Headquarters Research & Technology Division ATTN: RTH Bolling Air Force Base Washington 25, D. C.

Air Proving Ground Center ATTN: FGAPI Eglin Air Force Base, Florida

Air Force Cambridge Research Laboratories ATTN: CRXL-R L. G. Hanscom Field Bedford, Massachusetts

Headquarters Electronic Systems Division ATTN: ESAT L. G. Hanscom Field Fedford, Massachusetts

AFDC Scientific/Technical 1 Limiton Office U. C. Naval Air Development Center Johnsville, Fa.

Chief of Naval Research ATM: Code L27 Department of the Navy Warhington 25, D. C.

Pureau of Ships Technical Library ATT': Code 312 Main Navy Building, Room 1528 Washington 25, D. C.

- Chief, Bureau of Ships ATTN: Code 454 Department of the Navy Washington 25, D. C.
- Chief, Bureau of Ships ATTN: Code 686B Department of the Navy Washington 25, D. C.
- Director U. S. Naval Research Laboratory ATTN: Code 2027 Washington 25, D. C.

Commanding Officer & Director 1 U. S. Navy Electronics Laboratory ATTN: Library San Diego 52, California

Commander U. S. Naval Ordnance Laboratory White Oak Silver Spring 19, Maryland

Commander Armed Services Technical Information Agency ATTN: TISIA Arlington Hall Station Arlington 12, Virginia

USAELEDL Liaison Officer 1 U. S. Army Tank-Automotive Center Detroit Arsenal Center Line, Michigan

USAELRIL Liaison Officer Naval Research Laboratory ATTN: Code 1071 Washington 25, D. C.

USAELEDL Liaison Officer Massachusetts Institute of Technology

- Ruilding 26, Room 131 77 Massachusetts Avenue Cambridge 39, Massachusetts

Best Available Copy

Copies

1

1

1

1

20

1

Distribution List (Cont) Copies

1

1

1

1

1

1

1

1

1

2

USAELRDL Liaison Office 1 Aeronautical Systems Division ATTN: ASDL-9 Wright-Patterson Air Force Base Ohio

U. S. Army Research Liaison Office Lincoln Laboratory P. O. Box 73 Lexington, Massachusetts

USAELRDL Liaison Officer Rome Air Development Center ATTN: RAOL Griffiss Air Force Base New York

USAELADL Liaison Officer U. S. Army Combat Developments Command, CDCLN-EL Fort Belvoir, Virginia

USATASA Liaison Engineer USASCAJ AFO 343 San Francisco, California

Technical Dir., SELRA/OS Hendquarters, USAELRDL

USADIADA-White Sands Maison Office Spu A/100, USABIANE

Art: Scientific/Technical Liaison Office SELRA/INA, WSARIEDI

Corpo of Engineers Naicen Office Shikk/102, USTRLift

Narine Corys Minisco Office. SMLAADER, SCANOSCI

forde Mairon Office. Frinzling, tearing Chief, Technical Information Division Headquarters, USAELRDL Copies

6

1

1

1

1

USAELRDL Technical Documents Center SELRA/ADT, Hexagon

Commanding Officer J. S. Army Security Agency Processing Center Fort Monmouth, N. J.

Chief Scientist U. S. Army Electronics Command ATTN: AMDEL-SC Fort Menmouth, N. J.

File Unit Nr. 1 Rm. 3D-116, Hexagon

Director, Electronic Components 1 Dept.

Director, Electronic Parts & 1 Materials Division

Microwave and Inductive Devices Branch 35

(3)

Best Available Copy

أدرو سعويه الجار ويعجز

Sest Available Copy

TUCLASSIFIED	L. Fertomametic Resonance 2. Ferties 3. Hevagonal Ferties	 Bady, Is.dore VicCail, Gilbert Army Electronics Research and Development I abratory. 	For Mormouth, N. J. III. DA Task 3493-15 (08-02			UNCLASSIFIED UNCLASSIFIED		Fertomagnetic Resonance 2. Fertusa 3. Hexagonal Fertusa	I. Ra.ly, Isidore McCall, Gibert II. Army Electronics Research	For Monmouth, N. J. For Monmouth, N. J. III. D.1 Task 3499-15-078-02			CNCLASSIFIED
	Army Electronors Research and Development Luboratory, Fort Montrouth, N. J. LINE ADTH OF NONORIENTED POLYCRYSTALLINE URV ACON REPORTED ANTHAL AOCE MACANET	MEN VION FLAMMILLS THE LAWIE WARD AND THE VANDATION AND AND AND AND AND AND AND AND AND AN	Theoretical calculations are made of the linewidth of nonormoted, polycrystalline, heragonal ferrites with large magnetic antisotropy fields, including both uniaxial and planar ferrites. It is shown that the linewidth of a	reneriented unjaktal ferrite is considerably wider than that of a nonurented planar ferrite. Since imperfect orientation is a major contributor to the linewidth of oriented frexagonal ferrites, it is seen that imperfect orientation will affect the	Inewidth of uniaxial ferrates far more than that of planar ferrates. This is supported by test data which show that populated planar ferrates can fare at linewidth considerably concreted planar ferrates can have a linewidth considerably.	ranower than the narrowest thewisting outlined with deteriors.		AFFY Electronics Research and Development Laboratory, Fort Morthouth, N. J. LINEWIDTH OF NONORTENTED POLYCRYSTALLINE	HEXAGON FERRITES WITH LARGE WAGNEILL ANISOTROPY FIELDS, by Isidore Bady, Gibert McCall, ANISOTROPY FIELDS, by Isidore Bady, Gibert McCall, Mar 53, 21 n. incl. Jius. 5 refs. (AELRDL Technical Report 2356) (DA Task 3A99-15-005-02) Unclassified report	Theoretical calculations are made of the linewidth of nonoriented, polycrystalline, hexagonal ferates with large magnetic anisotropy fields, including both uniarial large magnetics. It is shown that the linewidth of a	and plants during a ferrite is considerably wider than that of a noncreated planar ferrite. Since imperfect orientsiton of a major contributor to the linewidth of oriented hexagonal is a major contributor to the linewidth of oriented hexagonal	ferrites, it is seen that imperfect one making many of the second market in evidth of unmaxial ferries far more than that of planar ferries. This is supported by used data which show that the second market for the second market by the secon	nononenteu plana, fortunes di linewidth oblained with oriented narrower than the narrowest linewidth oblained with oriented uniaxial ferrites.
T.NCLASSIFIED	Ferromagnetic Resonance 2. Ferrizes 3. Hexagonal Ferrizes	 Bady, Isudore VicCall, Gilbert Army Electronics Research 	and Development Laboratory. Fort Monmouth, N. J. II. DA Task 3A99-15-006-62			UNCLASSIFIED	UNCLASSIFIED	1. Fertomagnetic Resonance 2. Fertites 3. Havaronal Fertites	I. Bady, Isudore NcCall, Glibert Marw Flectronics Research	and Development Laboratory. Fort Nonmouth. N. J. III. DA Task 3439-15-006-02			UNCLASSIFIED
	Verg. Elligent of the Presench and Development Laterative, Flott Wormouth, V. J. And Markett of SciencificaTED POLL CRYSTALLINE	<pre>UNATION FERRITSS MITH LARGE MAGNETIC ANTACTEDPT FIELDSTEV F-120m Bady, Gibber McCall, ANTACTED FOR FIELDSTEV F-120m Bady, Gibber McCall, Warford Line and Miles 5 refer (AELROL Technical Public Configer Text 31(3), 175 Aug), Uschassified report</pre>	Trucces	<pre>set prices formers. It is shown that the interview of a preferenced univeral ferrice is considerably wider that that if a oth when's bland formus. Since imperfect orentation if a nois report or to the intervieth of orented betaknow is a mujor condition of the intervieth of orented betaknows in a mujor condition of the intervieth of orented betaknows intervieth of one with a formation of the orented betaknows intervieth of one with a formation of the orented betaknows intervieth of one with a formation of the orented betaknows intervieth of one with a formation of the orented betaknows intervieth of the orented betaknows of the orented betaknows intervieth of the orented betaknows of</pre>	<pre>/umiles it is seen that in perfect on induction with an inverted in new with of unavial fernics far more that of planar [</pre>	noncreated plane through thewidth obtained with oriented another that the through the three of an and the three of a second seco	10	Army Electronics Research and Development Laboratory, Fort Monrouth, N.J. Armyon veryon veryon Arm	LINEWIDTH OF NONORIEX (LD FOLTOR ISTALLING HENAGON FERRITES WITH LARGE VIAGMETIC ANISOTROPY FIELDS, by Isidore Bady, Gibert VicCall, Viar 63, 21 p. 1861, Blues, Stefe, (AELROL Technical) Viar 63, 21 p. 1861, Blues, Stefe, (AELROL Technical)	Report 2350) (DA LASK 3439-1) - UN-02) Unitassing report Theoretical calculations are made of the linewidth of nonoriented, polycrystalline, heragonal ferries with "are marknetic anisotropy fields, including both uniaxial	and planer ferrices. It is shown that the linewidth of a neuroriented unaxial ferrice is considerably wider than that of a neuroriented planar ferrice. Since imperfect orientation	Is a major construction that the function will affect the formulation of uniaxial formers far more than that of planar functions. This is supported by test data which show that	noncreated planar ferrites can have a linewidth considerably narrower than the narrowest linewidth obtained with oriented uniaxial ferrites.

Best Available Copy