

AD-A046 681

NAVY UNDERWATER SOUND LAB NEW LONDON CONN
REVERBERATION CORRECTION VALUES FOR TWO SPECIFIC ARRAYS. (U)
MAR 69 B F CRON


F/G 17/1

UNCLASSIFIED

USL-TM-2211-75-69

NL

1 OF 1
AD
A046681



END
DATE
FILMED
12-77
DDC

OOV LIBRARY COPY

MOST Project *108-2*

Code No.

Copy No. 54

USL Problem No.
9-A-403-00-00

SF 11 552 001-11285

16 F11552

1
NW

17

AD A U 46681

00188

22 11-75-69

U. S. NAVY UNDERWATER SOUND LABORATORY
FORT TRUMBULL, NEW LONDON, CONNECTICUT

6 REVERBERATION CORRECTION VALUES FOR TWO SPECIFIC ARRAYS.

by

10

Benjamin F. Cron

14

USL-TM-

USL Technical Memorandum No. 2211-75-69

11

10 Mar 1969

13 *10 P.*

DDC
NOV 21 1977
R
A

INTRODUCTION

Experimental studies are often conducted to obtain the scattering strength of volume reverberation. The received reverberation level has to be corrected in order to obtain the scattering strength. One of these correction factors is determined by the intensity pattern of the array. The purpose of this study is to evaluate this correction factor for two specific arrays. The arrays are specified and the corresponding correction factors are obtained.

ARRAYS

The first array contains 20 squares. The side of each square is one half wavelength long. (See. Fig. 1).




FIG. 1

DISTRIBUTION STATEMENT A

Approved for public release;
Distribution Unlimited

This document is subject to special export controls and each transmittal to foreign governments or foreign nationals may be made only with prior approval of the U. S. Navy Underwater Sound Laboratory.

254 200

AD NO. _____
DDC FILE COPY

001188
88-91

mt

The second array contains 12 squares. The side of each square is one half wavelength long. The configuration is shown in Fig. 2.




FIG. 2

PATTERN OF THE ARRAY

Let $I(\theta, \phi)$ be the intensity pattern of an array in the θ, ϕ direction. See Fig. 3.




FIG. 3

The pattern of the plane array may be obtained from the equation

$$I(\theta, \phi) = \left| \sum_i \exp \left[-j \frac{2\pi}{\lambda} (\alpha x_i + \beta y_i) \right] \right|^2 f(\theta, \phi) \quad (1)$$

ACCESSION for	
NTIS	White Section
DDC	Buff Section
UNANNOUNCED	
JUSTIFICATION	
<i>letter on file</i>	
BY	
DISTRIBUTION/AVAILABILITY	
Dist.	AVAIL. and/or SPE
A	

where
$$f(\theta, \phi) = \left(\frac{\sin \frac{\pi \alpha}{2}}{\frac{\pi \alpha}{2}} \frac{\sin \frac{\pi \beta}{2}}{\frac{\pi \beta}{2}} \right)^2$$

$$\alpha = \sin \theta \cos \phi$$

$$\beta = \sin \theta \sin \phi$$

x_i and y_i are the center positions of the squares referenced to the origin, which is the center of the array. Equation (1) is obtained by the usual Fraunhofer method for point sources and the product theorem.

PATTERN RESULTS

In Figs. 4, 5, 6 we show the intensity patterns versus θ for $\phi=0^\circ$, 44° and 90° respectively for the 20 element array. As expected, the pattern for $\phi = 0^\circ$ (the plane containing the long axis) is narrower than the pattern for $\phi = 90^\circ$. In Figs. 7, 8, the intensity patterns are drawn for the 12 element array. The patterns for $\phi = 0^\circ$ and $\phi = 90^\circ$ are identical. It is interesting to note that the pattern for $\phi = 90^\circ$ for this array is narrower than the corresponding 20 element array pattern. Along the y axis, the 12 element array has an aperture of about 2λ , whereas for the 20 element array it is more like λ . As more and more elements are added on the x axis, the effective aperture approaches λ .

CORRECTION FACTOR

Urlick¹ defines a correction factor that is

$$\psi = \int_0^{2\pi} d\phi \int_0^{\pi/2} d\theta I^2(\theta, \phi) \sin \theta d\theta \quad (2)$$

in our notation.

In equation (2), we consider only energy emitted and returned from one side of the plane array.

Equation (2) may be evaluated numerically by

$$\psi \cong 4 \sum_{i=1}^{90} \sum_{j=1}^{90} I^2(\theta_i, \phi_j) \sin \theta_i \left(\frac{\pi}{180}\right)^2$$

The 8100 values of $I^2(\theta_i, \phi_j)$ were computed on the 1108 UNIVAC and the double sum was obtained. For the large array

$$\psi_{db} = -10.7 \text{ db}$$

For the 12 element array, $\psi_{db} = -8.2 \text{ db}$.

Let us consider the small array as a square, 2λ on each side. From Urlick¹

$$\psi_{db} \cong 10 \log_{10} \frac{\lambda^2}{4\pi a b} + 7.4, \quad \text{for } a, b \gg \lambda$$

For $a = b = 2\lambda$, $\psi_{db} \cong -9.6 \text{ db}$. By using this equation instead of a computer computation, the correction factor and thus the computed scattering strength would differ by -1.4 db .

For 2° increments on θ and ϕ , the answer in ψ_{db} differed about 0.1 db . For $I(\theta, \phi) = 1$, for all θ and ϕ , equation 2 can be integrated analytically. The answer is $\psi_{db} = 10 \log_{10} (2\pi)$. The numerical integration was within $.1 \text{ db}$ of this answer. Accuracy could be increased by the use of Simpson's rule.

CONCLUSIONS

The use of large scale computers provides an excellent method for obtaining correction factors for reverberation. Urlick provides approximate equations for configurations such as a rectangular array or a circular array. These approximations are good for given relationships between the size of the array and λ . The size of the array must be large, sometimes much larger, than λ . These conditions are not always met in practice.

ACKNOWLEDGEMENT

This problem was stated by R. Martin and N. Fisch.

USL Tech Memo
2211-75-69

REFERENCES


1. "Principles of Underwater Sound for Engineers" by R. J. Urick,
McGraw-Hill Book Co.

Benjamin F. Cron

BENJAMIN F. CRON
Research Associate


CODER BOOK COMPANY, INC. NEWWOOD, MASSACHUSETTS.
PRINTED IN U.S.A.

NO. 1-24 POLAR COORDINATE.




CODEX BOOK COMPANY, INC. NORWOOD, MASSACHUSETTS.
PRINTED IN U.S.A.

N.J. 3124 POLAR CO ORDINATE.




CODING BOOK COMPANY, INC. NORWOOD, MASSACHUSETTS.
PRINTED IN U.S.A.

NO. 3124. POLAR COORDINATE



SAFETY BOOK COMPANY, INC. NORWOOD, MASSACHUSETTS.
PRINTED IN U.S.A.

NO. 3124. POLAR COORDINATE.



CODER BOOK COMPANY, INC. NORWOOD, MASSACHUSETTS.
PRINTED IN U.S.A.

NO. 3124. POINT TO COORDINATE.




FIG. 8