

AL-SR-1992-0025

# BRAIN ACTUATED CONTROL OF A ROLL AXIS TRACKING SIMULATOR (U)

Andrew M. Junker

Armstrong Aerospace Medical Research Laboratory Wright-Patterson AFB OH 45433-6573

> John H. Schnurer David F. Ingle Craig W. Downey

Logicon Technical Services, Inc. P.O. Box 317258 Dayton OH 45431-7258

# **Best Available Copy**

November 1989

Final Report for Period 4 November 1988 to 31 August 1990

20062626001

Approved for public release; distribution is unlimited.

94

165

03

2

AIR FORCE SYSTEMS COMMAND VRIGHT-PATTERSON AIR FORCE BASE, OHIO 45433-6573

A RMSTRONG ABORATORY

# NOTICES

When US Government drawings, specifications, or other data are used for any purpose other than a definitely related Government procurement operation, the Government thereby incurs no responsibility nor any obligation whatsoever, and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data, is not to be regarded by implication or otherwise, as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use, or sell any patented invention that may in any way be related thereto.

Please do not request copies of this report from the Armstrong Laboratory. Additional copies may be purchased from:

National Technical Information Service 5285 Royal Road Springfield, Virginia 22161

Federal Government agencies and their contractors registered with the Defense Technical Information Center should direct requests for copies of this report to:

Defense Technical Information Center Cameron Station Alexandria, Virginia 22314

## DISCLAIMER

This Special Report is published as received and has not been edited by the Technical Editing Staff of the Armstrong Laboratory.

# TECHNICAL REVIEW AND APPROVAL

## AL-SR-1992-0025

This report has been reviewed by the Office of Public Affairs (PA) and is releasable to the National Technical Information Service (NTIS). At NTIS, it will be available to the general public, including foreign nations.

The voluntary informed consent of the subjects used in this research was obtained as required by Air Force Regulation 169-3.

This technical report has been reviewed and is approved for publication.

FOR THE COMMANDER

**KENNETH R. BOFF,** Chief<sup>1</sup> Human Engineering Division Armstrong Laboratory DTIC QUALITY INSPECTED S

Locos	saion For	
NTIS	PRALI	
DTIC	TAB	ō
Vnam	nounced	ō
Just	ification_	
By Diety Avai	ibation/ Jebility (	กเงื่อ
Dist	AVELL CHE.	19-01 1
	apeer	
In '	1	·
i and the second second	L	لمستست

			() – ( ) – ( ) – ( )	an a
			18 9 m	
	Nov 1989	Final	Rpt (4	Nov 88-31 Aug 90)
Brain Actuated Con Tracking Simulator	trol of a Roll Axis		C PE PR	F33615-85-C-0541 : 61101F : 7184
Andrew M. Junker, J David F. Ingle*, C	John H. Schnurer*, raig W. Downey*		TA WU	. 14 1 D7
-	· · · · · · · · · · · · · · · · · · · ·	· · · · · · · · · · · · · · · · · · ·		
Systems Research La 2800 Indian Ripple Dayton OH 45440	aboratories, Inc. Road			•
			waa saa sa si s	na koluny come i skarta nicana acamata a cara a s
Armstrong Aerospace Human Engineering D Wright-Patterson AB	≥ Medical Research Labor; Division, AFSC, HSD FB OH 45433-6573	atory	AL	-SR-1992-0025
Published in the 19 Systems, Man, and C	989 IEEE International Co Cybernetics, pp 714-717.	onference on		
Published in the 19 Systems, Man, and C Approved for public distribution is unl	989 IEEE International Co Cybernetics, pp 714-717. release; imited.	onference on		
Published in the 19 Systems, Man, and C Approved for public distribution is unl	089 IEEE International Co Cybernetics, pp 714-717. : release; .imited.	onference on		
Published in the 19 Systems, Man, and C Approved for public distribution is unl lock-in Amplifier S resonance signal at gain signal was inv Coll Axis Tracking control/feedback en hethodology for usi signal in the kines	289 IEEE International Co Cybernetics, pp 714-717. release; .imited. ding the possibility of the cystem (LAS-3) was used to a specified frequency. estigated as a means to Simulator (RATS) was use vironment. This paper of ng the derivative of sel thetically salient envir	croencephalog successful importin actuated to obtain an a Lead-lag cor produce the b ad as a kinest liscusses effo ected brain r	raphic p plementa d contro artifact mpensatio orain ac thetical orts to p resonance a RATS.	otentials as tion of a closed- l. A three-channel -free brain on of the LAS-3 tuated control. A ly salient make use of a es as a control
Published in the 19 Systems, Man, and C Approved for public distribution is unl Investigations of s indicators of menta loop paradigm allow Cock-in Amplifier S resonance signal at gain signal was inv Roll Axis Tracking control/feedback en methodology for usi signal in the kines	289 IEEE International Co Cybernetics, pp 714-717. E release; Simited. Steady-state evoked elect of workload have led to se ring the possibility of the System (LAS-3) was used to a specified frequency. Simulator (RATS) was use vironment. This paper of ng the derivative of sel thetically salient envir	croencephalog successful importin actuated to obtain an a Lead-lag cor produce the b ad as a kinest liscusses effo ected brain r conment of the	raphic p plementa d contro artifact mpensatio orain ac thetical orts to p resonance a RATS.	otentials as tion of a closed- l. A three-channel -free brain on of the LAS-3 tuated control. A ly salient make use of a es as a control
Published in the 19 Systems, Man, and C Approved for public distribution is unl Investigations of s indicators of menta loop paradigm allow Lock-in Amplifier S resonance signal at gain signal was inv Roll Axis Tracking control/feedback en methodology for usi signal in the kines	289 IEEE International Co Cybernetics, pp 714-717. E release; imited. teady-state evoked elect l workload have led to so ying the possibility of h ystem (LAS-3) was used to a specified frequency. estigated as a means to Simulator (RATS) was use vironment. This paper do ng the derivative of sel thetically salient envir	croencephalog successful imporain actuated to obtain an a Lead-lag comproduce the h ad as a kinest liscusses effo ected brain m conment of the	raphic p plementa d contro artifact mpensatio orain ac thetical orts to p resonance a RATS.	otentials as tion of a closed- l. A three-channel -free brain on of the LAS-3 tuated control. A ly salient make use of a es as a control
Published in the 19 Systems, Man, and C Approved for public distribution is unl Investigations of s indicators of menta loop paradigm allow lock-in Amplifier S resonance signal at gain signal was inv Roll Axis Tracking control/feedback en methodology for usi signal in the kines	289 IEEE International Co Cybernetics, pp 714-717. release; imited. teady-state evoked elect workload have led to s ring the possibility of the ystem (LAS-3) was used to a specified frequency. estigated as a means to Simulator (RATS) was use vironment. This paper of ng the derivative of sel thetically salient envir ponse, loop closure, phic signals	croencephalog successful importin actuated to obtain an a Lead-lag comproduce the k d as a kinest liscusses effo ected brain monment of the	raphic p plementa d contro artifact mpensatio orain ac thetical orts to p resonance RATS.	otentials as tion of a closed- 1. A three-channel -free brain on of the LAS-3 tuated control. A ly salient make use of a es as a control 4

# BRAIN ACTUATED CONTROL OF A ROLL AXIS TRACKING SIMULATOR

Andrew M. Junker Armstrong Aerospace Medical Research Laboratory Wright-Patterson AFB, Ohio 45433

John H. Schnurer, David F. Ingle. Craig W. Downey Systems Research Laboratories Dayton, Ohio 45440

#### ABSTRACT

Investigations of steady-state evoked EEG potentials as indicators of mental workload have led to successful implementation of a closed-loop paradigm allowing the possibility of brain actuated control. A three channel Lock-in Amplifior System (LAS-3) was used to obtain an artifact free brain resonance signal at a specified frequency. Lead-lag compensation of the LAS-3 gain signal was investigated as a means to produce the brain actuated control. A Roll Axis Tracking Simulator (RATS) was used as a kinesthetically salient control/feedback environment. This paper discusses efforts to make use of a methodology for using the derivative of selected brain resonances as a control signal in the kinesthetically salient environment of the RATS.

#### 1. INTRODUCTION

Investigations of steady-state evoked potentials as indicators of mental workload have led to successful implementation of a closed-loop paradigm allowing the possibility of brain actuated control (Junker et. al., 1987). Hardware has been developed which permits timely and frequency specific feedback to human operators of the resonances embedded in their ongoing EEG. Control of these resonances has been demonstrated by all subjects tested. These efforts have led to an ongoing research program designed to quantify mental resource allocation during performance of the Criterion Task Set (Shingledecker, 1984). In addition, a system which rejects broadband noise and nonspecific broadband control artifacts has been developed.

While engaged in the above research an interest to explore two new questions developed. The first addresses the feasibility of developing a more sensory compelling feedback environment. This need arises from observations that Brain Actuated Control (BAC) success is sensitive to the salient nature of the feedback cuss provided to achieve loop closure. The more involving the loop closure cues are, the more effective the training of BAC appears to be. This increase in effectiveness should yield a corresponding decrease in the training time necessary to learn BAC. Therefore it is hypothesized that kinesthetic cues, in this case acceleration cues resulting from control of a motion environment, would enhance the learning of BAC.

Secondly, the question of what the BAC signal represents in a control context needs to be addressed. In other words, how should the process of controlling one's EEG resonance be utilized for machine control? Previous experimentation has revealed that subjects are better at controlling change of resonance (increase/decrease) rather than holding constant resonance levels (Junker. Schnurer, Ingle, Downey, 1988). This mode of control (i.e. undershoot and overshoot) can be observed when subjects are engaged in tracking tasks involving the control of a lagging or sluggish system. From our previous results we concluded that the BAC signal was lagging the subject's 'desired control' at the neural level resulting in the inability to keep the BAC at a constant level. This is reasonable to hypothesize since there is an inherent integration or filtering effect from the scalp and the equipment used to produce the present BAC signal. Lead compensation, in the form of differentiation, of the BAC signal should reduce this problem. Thus the lead compensated EEG resonance signal was used as the BAC and as feedback to the subjects.



Figure 2.1 Lock-in Amplifier System

#### 2. METHODOLOGY

## 2.1 Loop-Closure and EEG Detection Apparatum

Equipment development proceeded along the following lines. A three channel Lock-in Amplifier System (LAS-3), shown in figure 2.1, was created to obtain an artifact free brain resonance signal at a specified frequency. The LAS-3 is an analog device which provides near realtime frequency domain gain and phase information for a signal (EEG in this case) at a reference frequency. Lead-Lag compensation of the LAS-3 gain signal was added as a means to produce a responsive brain actuated control signal.

Gold cup surface electrodes. manufactured by Grass, are placed on the scalp over the occipital cortex Ol-O2 and mastoid process for ground (according to the 10-20 International system). In order to achieve good electrical contact, the scalp is mildly abraded by brisk rubbing with an alcohol soaked gauze pad. A nonabrasive electrode paste, Grass EC2 Electrode Cream, is put on the cleansed area, with electrode affixed to the subjects' scalps with the same electrode cream. No adverse reactions to these procedures or materials have been encountered in our laboratory.

#### 2.2 Control/Feedback Environment

A Roll Axis Tracking Simulator (RATS) is used in a kinesthetically salient control paradigm. Within the RATS. subjects employ a manually operated actuating mechanism as a means of engaging/disengaging their brain actuated control. The direction of the BAC input is indicated with a horizontal light bar (zero input referenced to center) and a left/right audio feedback tone. The interior layout of the RATS cab is illustrated in Figure 2.2. The evoking stimulus is provided by two fluorescent tubes mounted within lexan tubes. A video monitor provides roll position and roli velocity cues. As indicated in Figure 2.2 the light bar and audio displays are intended to provide cues equivalent to those that would normally be available kinesthetically from manipulation of a manual controller.



Figure 2.2 Interior Layout of RATS cabin

# 2.3 Experimental Plan

Closed-loop tracking with visual only, visual and kinesthetic, and kinesthetic only cues is performed. In each case roll disturbance regulation is added. A digitally generated low frequency sum-of-sine waves is used as the disturbance input. The resulting closedloop block diagram for this system is illustrated in Figure 2.3.

Data is collected which is frequency coupled to the sum-of-sines disturbance. This allows computation of various system transfer functions. Performance scores and system transfer functions provide a basis for evaluation of the LAS-3/RATS equipment (bandwidth, stability) and human BAC capabilities.

Subjects are exposed to static conditions or nonhazardous angular motion on the RATS while observing a CRT display and performing BAC tracking control. During experimental sessions in the RATS subjects are secured with a five point seat belt and shoulder harness. The experimenter is in continuous contact with the subject at all times through an intercom which has a live subject mike.

The experiment is divided into three phases: Phase I-Subject Introduction to BAC and RATS control; Phase II Training With BAC and RATS; and Phase III- Data collection During BAC Closed-Loop Disturbance Regulation.

Phase I. The basis of this phase is to introduce subjects to the experimental equipment and the concept of brain actuated control. At first subjects have the opportunity to control the RATS with a manual controller to become comfortable with the motion capabilities of the RATS. Subjects are allowed to select a resonance frequency at which they will accomplish BAC (between 13Hz and 20Hz). At this time the experimenter is able to characterize the subject's evoked EEG response. This phase normally takes two experimental sessions to complete.

Phase II. The results from the first phase are used to set parameters for the second phase in which subjects train in BAC on the RATS. Initially, training consists of simply learning to control the RATS with no external disturbance. AS subjects become comfortable with BAC control a simplified disturbance is added to the closed-loop system. As subjects become proficient at disturbance regulation using BAC, introduction of a sum-of-sines disturbance occurs marking the beginning of Phase III. Phase II training requires approximately 7 experimental sessions for each subject tested.

Phase III. This phase involves data collection and training with the computer generated sum-of-sines disturbance input. Data collection continues until performance scores (RMS error) reach consistent levels. Three conditions are tested; static tracking with visual cues using BAC, motion tracking with visual cues using BAC, and motion tracking with no visual cues using BAC.

Data analysis consists of tabulation and analysis of RMS error scores for quantifying learning rates and effectiveness of accomplishing closed-loop control. Frequency analysis of disturbance regulation data provides transfer functions of human and machine systems. From these transfer functions effectiveness of BAC control relative to current manual control is evaluated.



# Figure 2.3 Closed-loop RATS/LAS-3 system

## 3. PRELIMINARY RESULTS AND DISCUSSION

At present the pilot study is in its initial data collection stage. However, even at this preliminary stage participants subjectively claim they feel the onset of control in the kinesthetically salient environment (RATS) at an earlier point than subjects who trained in a totally static mode. This, if true, could be from two possible sources. First, the RATS provides a subject with feedback imperative of a much higher magnitude than can be found under static conditions. Including a subject's kinesthetic sense in a feedback loop allows an individual to respond and compensate for his dynamic environment in much the same way people learn to regain their equilibrium and 'right' themselves after stumbling. The second cause could be the effectiveness of lead-lag compensation of the physiological measure (specific frequency EEG). This lead-lag compensation results in a bandwidth increals of the measure such that feedback of the sensed physiological signal comes fast enough in terms of RATS responsiveness.

#### 4. REFERENCES

Junker, A.M., Levison, W.H., and Gill. R.T., 1987. A Systems Engineering Based Methodology For Analyzing Human Electrocortical Responses. AAMRL-TR-87-030, Armstrong Aerospace Medical Research Laboratories. WPAFB, Ohio, 1987.

Junker, A.M., Downey, C.W., Schnurer, J.H., Ingle, D.F., 1988. Loop-Closure Of The Visual-Cortical Response. 40th NAECON Proceedings, 23-27 May, 1988. Dayton. Ohio.

Regan, D. 1972. Evoked Potentials in Psychology, Sensory Physiology and Clinical Medicine. Chapman and Hall Ltd., London, SBN 412-100920-4, 1972.

Shingledecker C.A., 1984. A Task Battery For Applied Human Performance Assessment Research. AFAMRL-TR-84-071. Air Force Aerospace Medical Research Laboratory, WPAFB, Nov., 1984.

÷.

Spekreijse, H. 1986. Analysis of EEG Response in Man Evoked by Sine Wave Modulated Light. Dr. W. Junk Publishers. The Hague, Netherlands. 152 pp.

Wilson, G.F. and O'Donnell, R.D. 1980. Human Sensitivity to High Frequency Sine Wave and Pulsed Light Stimulation as Measured.by the Steady State Cortical Evoked Response. Technical Report AFAMRL-TR-80-133.