UNCLASSIFIED

AD NUMBER

AD827959

LIMITATION CHANGES

TO:

Approved for public release; distribution is unlimited. Document partially illegible.

FROM:

Distribution authorized to U.S. Gov't. agencies and their contractors; Critical Technology; FEB 1968. Other requests shall be referred to Air Force Technical Application Center, VELA Seismological Center, Washington, DC 20333. Document partially illegible. This document contains export-controlled technical data.

AUTHORITY

aftac ltr, 12 may 1969

THIS PAGE IS UNCLASSIFIED

HIGH-RESOLUTION FREQUENCY-WAVENUMBER SPECTRA

0

16 February 1968

Prepared For

AIR FORCE TECHNICAL APPLICATIONS CENTER Washington, D. C.

By

D. W. McCowan TELEDYNE, INC.

P.R. Lintz TELEDYNE, INC.

Under

Project VELA UNIFORM



Sponsored By

ADVANCED RESEARCH PROJECTS AGENCY Nuclear Test Detection Office ARPA Order No. 624

BEST AVAILABLE COPY

*

•

HIGH-RESOLUTION FREQUENCY-WAVENUMBER SPECTRA SEISMIC DATA LABORATORY REPORT NO. 206

VELA T/6702 AFTAC Project No .: Seismic Data Laboratory Project Title: 624 ARPA Order No.; 5810 ARPA Program Code No.: TELEDYNE, INC. Name of Contractor: F 33657-67-C-1313 Contract No.: 2 March 1967 Date of Contract: \$ 1,736,617 Amount of Contract: 1 March 1968 Contract Expiration Date: William C. Dean Project Manager: (703) 836-7644

P. O. Box 334, Alexandria, Virginia

AVAILABILITY

This document is subject to special export controls and each transmittal to foreign governments or foreign nationals may be made only with prior approval of Chief, AFTAC.

MASh.S.e.

This research was supported by the Advanced Research Projects Agency, Nuclear Test Detection Office, under Project VELA-UNIFORM and accomplished under the technical direction of the Air Force Technical Applications Center under Contract F 33657-67-C-1313.

Neither the Advanced Research Projects Agency nor the Air Force Technical Applications Center will be responsible for information contained herein which may have been supplied by other organizations or contractors, and this document is subject to later revision as may be necessary.

ABSTRACT

The method of high-resolution spectral analysis has been applied to one- and two-dimensional wavenumber spectra. In this method a prediction operator is used to extend the length of the spatial correlation functions in order to obtain higher resolution of the resulting spectra in wavenumber space. It is most useful in the case of small arrays, where the spatial correlation functions are too short to give adequate resolution for the ordinary frequency-wavenumber spectra. A theoretical description of the method, its procedures, and its relation to ordinary wavenumber spectra is given. In particular, an analytical expression is derived for the resolution and the response of the process in the case of an input plane wave, where the high-resolution method is averaged over all reference sensors.

Disadvantages of the high-resolution method are discussed, in particular an unrecoverable distortion of the true amplitude spectrum. Finally, examples are given for data recorded at the Wichita Mountains Seismic Observatory surface array and the Apache, Oklahoma, vertical array.

TABLE OF CONTENTS

		C
ABSTRACT		
INTRODUCTION		1
PROCEDURES		6
EXAMPLES		8
BIBLIOGRAPHY		10

Page No.

LIST OF FIGURES

Figure	1.	Constant Velocity Loci in Frequency-Wavenumber Space
Figure	2.	WMSO Surface Array
Figure	3.	WMSO Array Response
Figure	4.	Ordinary Frequency-Wavenumber Spectra of WMSO Noise
Figure	5.	High-Resolution Frequency-Wavenumber Spectra of WMSO Noise
Figure	6.	Ordinary Frequency-Wavenumber Spectra of a WMSO Signal
Figure	7.	High-Resolution Frequency-Wavenumber Spectra of a WMSO Signal
Figure	8.	APOK Array Response
Figure	9a.	Ordinary Frequency-Wavenumber Spectrum of APOK Noise
Figure	9Ъ.	High-Resolution Frequency-Wavenumber Spectrum cf APOK Noise
Figure	10a.	Ordinary Frequency-Wavenumber Spectrum of an APOK Signal
Figure	10Ъ.	High-Resolution Frequency-Wavenumber Spectrum of an APOK Signal

LIST OF TABLES

Table	1.	Event Data
Table	2.	Sensor Coordinates

INTRODUCTION

Burg (1967) has shown that high-resolution power spectra can be computed from relatively short correlation functions by first least-squares predicting larger correlation lags from those already known. The resulting high-resolution power spectrum is inversely proportional to the power spectrum of the corresponding prediction error operator. However, with the advent of the Cooley-Tukey fast Fourier transform algorithm and related methods for estimating power spectra, the high-resolution technique for ordinary power spectra is no longer economical. It is now feasible to compute power spectra as if they were Fourier transforms of the 100%-lag correlation functions; various kinds of smoothing can then be applied to reduce the spectra to the desired length and stability.

We feel that the most promising application of the highresolution procedure lies in estimating frequency-wavenumber spectra. Here the length of the spatial correlation functions, which ultimately determines the resolution, is limited by the size of the array. The high resolution method is therefore the appropriate way to obtain frequency-wavenumber spectra which are sharp in wavenumber space from data recorded over small arrays.

Ordinary frequency-wavenumber spectra (Spieker <u>et al</u>., 1961) are computed directly from the spectral matrix elements by the expression:

 $P(\omega,k) = \sum_{i=1}^{N} \sum_{j=1}^{N} S_{ij}(\omega) \exp \left[-ik \cdot (x_{i} - x_{j})\right]$ (1)

In the case of two-dimensional arrays (for example, LASA) P is a function of three variables: ω , k_x , and k_y . The standard way of displaying this function is to produce a succession of contour plots, each at a particular frequency, with P contoured against k_x and k_y . On the other hand, for one-dimensional

- 1 -

arrays (for example, arrays of instruments in deep wells) only the vertical wavenumber is involved and P can be contoured against ω and k_z in one plot. Loci of constant velocity

$$y = \frac{\omega k}{k \cdot k}$$

are circles about the k_x , k_y origin as shown in Figure 1a or lines of constant slope as shown in Figure 1b.

A measure of the resolution or capability of the array is its response to an infinite-velocity plane wave. If the instrument frequency response is neglected, the spectral matrix of the wave is constant. Therefore this function, usually called the array response function (Spieker <u>et al</u>., 1961), is given by:

$$R(\underline{k}) = \sum_{i=1}^{N} \sum_{j=1}^{N} \exp\left[-i\underline{k}\cdot(\underline{x}_{i} - \underline{x}_{j})\right]$$
(3)

Any single finite-velocity plane wave of the form

$$\exp \left[i(\underline{k}, \cdot \underline{x} - \omega t)\right]$$

will produce a frequency-wavenumber spectrum consisting of the array response function centered on the value k_o modulated in frequency by the corresponding frequency power spectrum.

The high-resolution technique consists of using the spectral matrix of the data to design a multichannel prediction error operator. High-resolution frequency-wavenumber spectra are then computed from the spectral matrix of this multichannel filter (Haney, 1967). The appropriate matrix equation is:

$$[S(\omega) + cI] f^{m}(\omega) = g^{m}$$

Here $S(\omega)$ is the spectral matrix of the data, I is an N-by-N identity matrix, $f^{m}(\omega)$ is the filter vector, and g^{m} is the righthand side vector consisting of N-l zeros and a one in the $m\frac{th}{r}$ row. This equation defines the filter which is optimum, in the least-squares sense, for "whitening" the $m\frac{th}{r}$

2

(2)

(4)

(5)

channel. Another way of interpreting equation (5) is to recognize it as a multichannel Wiener-Hopf equation with $S(\omega)$ the noise spectral matrix, cI the signal model, and g^{m} proportional to the cross spectra between the desired output, white noise, and the input. The constant c is a convenient means of adjusting the signal-to-noise ratio of the input.

The spectral matrix of the filter is then

$$H^{m}(\omega) = E \left[f_{\omega}^{m}(\omega) f_{\omega}^{m}(\omega)^{+} \right]$$
(6)

where the dagger indicates Hermitian conjugation and the brackets specify that expected values are to be taken. High-resolution frequency-wavenumber spectra of the original data channels are inversely proportional to the ordinary frequency-wavenumber spectra of this spectral matrix:

$$P'_{m}(\omega,k) = \left\{ \sum_{i=1}^{N} \sum_{j=1}^{N} H^{m}_{ij}(\omega) \exp\left[-ik \cdot (x_{i} - x_{j})\right] \right\}^{-1}$$
(7)

In practice, we have found that high-resolution frequencywavenumber spectra computed this way (from single-output "whitening" filters) sometimes suffer an angular distortion (Lintz, 1968). In other words, the resolution in wavenumber space is a function of $k-k_0$. Furthermore, it is undesirable to have the technique depend on the choice of the reference data channel. This difficulty can be circumvented by using the average spectral matrix of the filters, H, computed by averaging over all reference data channels. This procedure is also a convenient means for taking the expected value.

Thus:

$$H(\omega) = \sum_{m=1}^{N} H^{m}(\omega) = \sum_{m=1}^{N} f^{m}(\omega) f^{m}(\omega)^{+}$$
(8)

Since each filter vector $\underline{f}^{m}(\omega)$ is merely the $\underline{m}^{\underline{th}}$ column of the

- 3 -

inverse matrix:

$$S(\omega) + cI$$

the required averaged spectral matrix $H(\omega)$ is easily shown to be:

$$H(\omega) = S(\omega) + cI^{-2}$$

This modification of the original procedure is used for the examples given below. It should be noted that computing highresolution frequency-wavenumber spectra this way is only negligibly more expensive than computing ordinary frequency-wavenumber spectra. Both techniques require computing the spectral matrix. The only other computations required by the high-resolution technique are the addition of some white noise, one Hermitian matrix inversion, and one Hermitian matrix multiplication.

The actual improvement in resolution gained by using the averaged high-resolution technique can be demonstrated by applying it to a plane wave. Neglecting the frequency part, the spectral matrix of this wave is:

$$S_{ij}(\omega) = \exp \left[ik_{0} \cdot (x_{i} - x_{j})\right]$$
(11)

which can be factored into the outer product of two vectors:

$$S(\omega) = q q^{\dagger}$$
 (12)

where the vector q is given by:

$$\begin{bmatrix} \underline{q} \\ \underline{i} \end{bmatrix}_{i} = \exp\left(i \underbrace{k}_{0} \cdot \underbrace{x}_{i}\right)$$
(13)

The matrix to be inverted is:

$$(q q' + cI)$$
 (14)

which is equal to:

$$\frac{1}{c} \left(I - \frac{q q^{+}}{c + N} \right)$$
(15)

Squaring this matrix gives, to terms of order c³,

$$\frac{1}{c^{2}}\left[I - \frac{2S}{c+N} + \frac{NS}{(c+N)^{2}}\right] = \frac{1}{c^{2}}\left[I - S\left(\frac{1}{N} - \frac{c^{2}}{N^{3}}\right) + O(c^{3})\right] (16)$$

(9)

(10)

Substituting equation (16) into equation (7) gives the result:

$$P'(k) = \frac{c^2}{N - P(k) \left(\frac{1}{N} - \frac{c^2}{N^3}\right)}$$
(17)

Now when P(k) reaches a maximum value of N^2 , P'(k) has the value N.

However when P(k) has fallen off to N^2/a , P'(k) is:

$$P'(k) = \frac{c^2}{N - \frac{N}{a} + \frac{c^2}{Na}}$$
(18)

which, by choosing c to be much less than N;

makes P'(k) very small indeed. The resolution of this technique therefore is dependent upon both N, the number of data channels, and the constant c.

PROCEDURES

All of the spectral matrix elements computed for the examples given below were done so by the Cooley-Tukey method (McCowan, 1967). The data was Fourier transformed together with a sequence of zeros equal to its entire length and then cross-multiplied to produce the raw auto- and cross-spectra. These raw spectra were then subjected to a number of smoothing operations. Each operation consisted of convolving the spectra with the three-point operator (1/4, 1/2, 1/4) and taking every other point of the result. The effects of this window are described elsewhere (McCowan, 1967). Typically the original data channels were of the order of 4096 digital points for noise samples and 256 digital points for signals, both sampled at twenty points per second. This gave 4097point and 257-point raw spectra, respectively, which were then smoothed and reduced to 65 and 33 actual frequency values respectively. Thus the number of degrees of freedom included in each spectral estimate was 64 in the case of noise samples and 8 in the case of signals.

Both to alleviate the problem caused by instrument gain anomalies (Baldwin, 1964) and the question of physical units in choosing the constant c in equation (5), we have used normalized spectral matrices (coherence matrices) throughout. Our spectral matrix elements are thus:

$$S_{ij}(\omega) = \frac{E\{F_{i}(\omega)F_{j}(\omega)^{*}\}}{E\{|F_{i}(\omega)|^{2}\} E\{|F_{j}(\omega)|^{2}\}}$$
(20)

Otherwise, choosing the constant c, and hence determining the resolution of the technique, would depend on the actual magnitude of the auto-spectra.

In the examples below we have chosen frequency in cps instead of angular frequency as an independent variable. Consequently, we have re-defined the wavenumber k as:

$$\left|\frac{k}{2}\right| = \frac{1}{\lambda} \tag{21}$$

- 6 -

so that equation (2) now reads:

$$v = \frac{fk}{k \cdot k}$$
(22)

This was done purely as a matter of convenience in reading the countour plots.

Finally, the contour plots displayed below were computed on a grid of 21-by-21 k_x and k_y values for the surface array and 21-by-33 k_z and frequency values for the vertical array. Both were then linear-interpolated in each direction, to a 100-by-60 grid to be printed by the computer printer. These pages were then traced to produce the figures. Any details smaller than 1/20 of the whole figure are therefore strongly colored by the linear interpolation.

EXAMPLES

Two events (P wave signals summarized in Table 1) and samples of noise immediately preceding them were selected as examples of high-resolution frequency-wavenumber data processing. The first event and its corresponding noise sample were used to illustrate the application of the technique to a two-dimensional surface array, in this case the WMSO array, while the remaining data were used to illustrate results from a one-dimensional vertical array, the APOK deep well. Both arrays are described by the coordinates of their elements, which are listed in Table 2, and their array response functions, which are shown as contour-plots in Figures 3 and 8 respectively. A map of the WMSO array is included as Figure 2.

J

Ordinary frequency-wavenumber spectra of both pairs of noise samples and signals are shown in Figures 4, 6, 9a, and 10a. Figures 4 and 9a are the noise samples and Figures 6 and 10a are the sig-The WMSO noise seems to be coming from the northeast with a nals. velocity ranging between 3 and 6 km/sec. This characteristic behavior has been noted by other investigators (Rizvi et al., 1967). On the other hand, the WMSO signal appears to be coming from the south or southeast with a velocity somewhere between 16 and 20 The APOK noise sample displays a tilted pattern also km/sec. characteristic of the site. One explanation for this phenomenon is suggested by the geological structure in the vicinty of the well (Geotechnical Corp., 1964), which consists of Paleozoic intrusives and sediments dipping 30-40° towards the northeast. The APOK signal is very strange indeed, composed of a wave travelling down the well with an apparent vertical velocity of approximately 3.5 km/sec and a horizontally travelling wave with infinite vertical velocity. One possible explanation of this result is again suggested by the dip of the structure (Sax, 1967). The incoming P wave might be refracted by the tilted interface so that the wave front would be a leaking suface wave when it reached the well.

- 8 -

High-resolution frequency-wavenumber spectra are shown for all these data samples in Figures 5, 7, 9b, and 10b. These were computed with a signal-to-noise ratio of 2, which seemed to be a good balance between high resolution and excessive distortion. For the WMSO examples, the technique decreased the width of the -3db contour by more than a factor of two for both the cases of noise and signal. The results are more difficult to assess for the vertical array data because of the "whitening" in frequency done by the filters. However, for the noise sample at 0.25 cps, a decrease by a factor of two in the width of the -3 db contour can again be seen.

A marked disadvantage and a difficulty still to be solved in the application of this technique is illustrated in Figure 10b. The high-resolution technique, when applied to short samples of data, can produce spurious peaks in the frequency-wavenumber spectra. These are due to the limited smoothing done when computing spectra from short samples of data. Figure 10b shows several of these peaks. This is regarded as an unrecoverable distortion and in a certain sense, an inevitable result of using a high-gain procedure.

- 9 -

BIBLIOGRAPHY

- Baldwin, R., 1964, A re-evaluation of S/N improvement for CPO using local noise: Special Report No. 5, Project VT/4053, Contract No. AF-33(657)-12747: Texas Instruments, Inc., Dallas, Texas.
- Burg, J.P., 1967, Maximum entropy spectral analysis: Paper presented at the 37th Meeting of the Society of Exploration Geophysicists, Oklahoma City, Oklahoma.
- Geotechnical Corp., 1964, Semi-annual Report No. 6, Project VT/1139 (Deep-hole seismometer), Contract No. AF-33(600)-43369: The Geotechnical Corporation, Garland, Texas.
- Haney, W.P., 1967, Research on high-resolution frequency wavenumber spectra: Special Scientific Report No. 2, Project VT/6707, Contract No. AF-33(657)-16678: Texas Instruments, Inc., Dallas, Texas.
- Lintz, P.R., 1968, An analysis of a technique for the generation of high-resolution wavenumber spectra: Seismic Data Laboratory Report (in press), Project VT/6702, Contract No. F33657-67-c-1313: Earth Sciences Division, Teledyne, Inc., Alexandria, Virginia.
- McCowan, D.W., 1967, Finite Fourier transform theory and its application to the computation of correlations, convolutions, and spectra: Seismic Data Laboratory Report No. 168 (Revised), Project VT/6702, Contract No. F33657-67-c-1313: Earth Sciences Division, Teledyne, Inc., Alexandria, Virginia.
- Rizvi, S.A., et al., 1967, Analysis of K-line wavenumber spectra from three WMO noise samples: Advanced Array Research Special Report No. 2, Project VT/7701, Contract No. F33657-67-c-0708-P001: Texas Instruments, Inc., Dallas, Texas.

- Sax, R.L., 1967, Frequency-wavenumber analysis of signals and noise recorded at the vertical array at Apache, Oklahoma: Seismic Data Laboratory Report No. 196, Project VT/6702, Contract No. F33657-67-c-1313: Earth Sciences Division, Teledyne, Inc., Alexandria, Virginia.
- Spieker, L.J., et al., 1961, Seismometer array and data
 processing system: Final Report Phase I, Project
 No. VT/977, Contract No. AF-33(600)-41840: Texas
 Instruments, Inc., Dallas, Texas.









J







Figure 6. Ordinary frequency-wavenumber spectra of a WMSO signal





Figure 8. APOK array response



9

wavenumber spectrum of APOK noise



Table 1

EVENT DATA

	WMSO Event	APOK Event
Latitude	41.4° S.	52.0° N.
Longitude	88.6° W.	175.0° W.
Origin Time	14:51:55.0	19:05:04.1
Depth (km)	33	67
Magnitude	4.9	5.2
Region	W. Chile Rise	Aleutians

Data taken from USCGS Preliminary Determination of Epicenters

Table 2

SENSOR COORDINATES

WMSO SURFACE ARRAY

<u>Sensor</u>	X(km.)	Y(km.)
v _l	0.00	0.00
v ₂	0.67	0.74
v ₃	0.94	-0.17
v ₄	0.27	-0.70
v ₅	-0.99	0.12
v ₆	-0.34	0.71
V 7	0.08	1.41
v ₈	1.35	1.33
۷ ₉	1.68	0.34
V ₁₀	1.19	-1.02
v ₁₁	-0.54	-0.78
V ₁₂	-1.51	-0.59
v ₁₃	-1.29	0.95

APOK VERTICAL ARRAY

Sensor	Depth (km.)
DW ₅	0.02
DW4	1.68
DW 3	1.99
DW2	2.29
DW1	2.91

Unclassified			
Security Classification			
	NTROL DATA - REE		
I. ORIGINATING ACTIVITY (Corporate author)		2. REPO	RT BECURITY CLARBIFICATION
TELEDYNE, INC.		Unc	classified
ALEXANDRIA, VIRGINIA 22314		25 GROU	P
S REPORT TITLE			
HIGH-RESOLUTION FREQUENCY-WAVE	NUMBER SPECTE	RA	
Scientific			
s. AUTHOR(S) (Looi name, firel name, Anitie))			·····
Lintz, P.R., McCowan D.W.			
Linely line, necowan, b.w.			
. REPORT DATE	70. TOTAL NO. OF PA		75. NO. OF REFS
16 February 1968	26		9
SA. CONTRACT OR GRANT NO.	S. ORIGINATOR'S REI	PORTNUM	BER(3)
F 33657-67-C-1313			No. 200
A PROJECT NO.	SDI, R	eport	NO. 206
VELA 176702			
ADDA Order 624	this report)	O(3) (Any	other numbers that may be seeigned
ARFA OLGET 024			
10. A VA IL ABILITY/LIMITATION NOTICES	·····		
This document is subject to spec	cial export c	ontro	ls and each trans-
mittal to foreign governments of	r f <mark>o</mark> reign nat	ional	may be made only
with prior approval of Chief, A	FTAC.		
11. SUPPLEMENTARY NOTES	12. SPONSORING MILIT	ARY ACT	VITY
	ADVANCED RE	SEARC	H PROJECTS AGENCY
	NUCLEAR TES	T DET	ECTION OFFICE
	WASHINGTON,	D.C.	
is assured. The method of high-resolut	tion spectral	analys	is has been ap-
od a prediction operator is us	hal wavenumber	spect	ra. In this meth-
Correlation functions in order	to obtain him	ne ier	igth of the spatial
resulting spectra in wavenumber	co obcain nig	most	usoful in the
case of small arrays, where the	spatial corr	elatic	n functions are
too short to give adequate reso	olution for th	e ordi	nary frequency-
wavenumber spectra. A theoreti	cal description	on of	the method, its
procedures, and its relation to	ordinary wave	enumbe	er spectra is given.
In particular, an analytical ex	pression is d	erived	for the resolu-
tion and the response of the pr	OCess in the	case o	f an input plane
erence sensors.	method is avo	eraged	over all ref-
Disadvantages of the high-	resolution me	thod a	re discussed, in
particular an unrecoverable distortion of the true amplitude spec-			
Mountains Seismic Observatory surface array and the bracks out			
vertical array.	dilace allay a	and th	e Apache, Oklahoma,
14. KEY WORDS			
Frequency-Wavenumber Spectra			
High-Recolution Execution March	mban G		
night-Resolution rrequency-Wavenumber Spectra			
Seismic Array Data Processing			

Unclassified

Security Classification

SUPPLEMENTARY

INFORMATION

NOTICE OF CHANGES IN CLASSIFICATION, DISTRIBUTION AND AVAILABLITY

69-18 15 SEPTEMBER 1969

AD-827 959 Teledyne Industries Inc., Alexendria, Va. Earth Sciences Div. Rept. no. SDL-206 16 Feb 68 Contract F33657-67- C-1313	No Foreign without approval of Air Force Technical Applications Center, Washington, D. C.	No limitation	AFTAC ltr, 12 May 69
--	---	---------------	-------------------------