

# AFRL-RY-WP-TP-2020-0061

## ENHANCED NON-LINEAR INSTABILITIES IN PHOTONIC CIRCUITS WITH EXCEPTIONAL POINT DEGENERACIES (Preprint)

Ilya Vitebskiy and Nicholaos Limberopoulos EO/IR Components Branch Aerospace Components & Subsystems Division

Tsampikos Kottos, R. Kononchuk, and S. Suwunnarat Wesleyan University

Andrey Chabanov University of Texas at San Antonio

APRIL 2020 Final Report

> Approved for public release; distribution is unlimited. See additional restrictions described on inside pages

## **STINFO COPY**

AIR FORCE RESEARCH LABORATORY SENSORS DIRECTORATE WRIGHT-PATTERSON AIR FORCE BASE, OH 45433-7320 AIR FORCE MATERIEL COMMAND UNITED STATES AIR FORCE

REPORT DOCUMENTATION PAGE								Form Approved OMB No. 0704-0188	
The public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Department of Defense, Washington Headquarters Services, Directorate for Information Operations and Reports (0704-0188), 1215 Jefferson Davis Highway, Suite 1204, Afrigoton, VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to any penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number. <b>PLEASE DO NOT RETURN YOUR FORM TO THE ABOVE ADDRESS</b> .									
1. REPORT DA	2. REPORT TYPE 3. DA				3. DATES	TES COVERED (From - To)			
	Journal Article Preprint 3			3 De	December 2019 –3 December 2019				
4. TITLE AND S ENHAN CIRCU	SUBTITLE NCED NON- ITS WITH E	LINEAR IN XCEPTION	STABILITIES IN PHOTONIC AL POINT DEGENERACIES				5	a. CONTRACT NUMBER HR00111820042/N00014-19-1- 2480	
(Preprint)							5	b. GRANT NUMBER	
							5	c. PROGRAM ELEMENT NUMBER N/A	
6. AUTHOR(S)							5	d. PROJECT NUMBER	
Ilya Vitebskiy and Nicholaos Limberopoulos								N/A	
Tsampikos Kottos, R. Kononchuk, and S. Suwunnarat (Wesleyan							5	e. TASK NUMBER	
University)								N/A	
Andrey Chabanov (University of Texas at San Antonio)							5	f. WORK UNIT NUMBER	
								N/A	
7. PERFORMIN		D ADDRESS(ES	(ES)			8.	PERFORMING ORGANIZATION REPORT NUMBER		
Univers	ity of Cincin	nati	1	AFRL/RYDH					
45 Wyll	ys Ave.								
Middletown, CT 06459									
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)       10. SPONSORING/MONITORING AGENCY ACRONYM(S)									
Air Force		Defense Advanced Research Projects Agency (DAPPA)		1	AFRL/RYDH				
Wright-Pa	5433-7320 Office of Naval Research Air Force Office of Scien Research Public Affairs (		Office of Naval Research (ONR)		NR) 1	11. SPONSORING/MONITORING AGENCY REPORT NUMBER(S)			
United St			ntifi (AF	c OSR)	AFRL-RY-WP-TP-2020-0061				
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release; distribution is unlimited.									
13. SUPPLEMENTARY NOTES PAO case number 88ABW-2019-5845, Clearance Date 3 December 2019. To be submitted to Physical Review, Applied. This work was funded in whole or in part by Department of the Air Force. The U.S. Government has for itself and others acting on its behalf an unlimited, paid-up, nonexclusive, irrevocable worldwide license to use, modify, reproduce, release, perform, display, or disclose the work by or on behalf of the U.S. Government. Report contains color.									
14. ABSTRACT									
A conceptual design of optical power limiter based on a photonic circuit with a second-order exceptional point degeneracy (EPD) is proposed. The design is based on a pair of coupled cavities with judiciously tailored differential Q-factors. One of the cavities includes a Kerr-like non-linear material. At low input intensities (in the linear regime) the two cavities are optically identical, and the transmittance of the entire photonic circuit is close to unity. As the input intensity is increased, the nonlinearity introduces a resonant detuning which lifts the degeneracy and results in formation of two distinct resonant modes. One of them (the high-Q mode) is abruptly destroyed due to nonlinear instabilities, while the low-Q mode experiences an underdamping-to-overdamping transition, rendering the entire photonic circuit highly reflective. The design allows to significantly lower the limiting threshold, while enhancing the power-handling capabilities due to the absence of absorption. A similar approach can be applied to optical power switching, Q-switching, routing, etc.									
15. SUBJECT TERMS nonlinear optics, optical limiters									
16 SECURITY CLASSIFICATION OF: 17 LIMITATION 18 NUMBED 102 NAME OF DESPONSIBLE BEDSON //									
a. REPORT Unclassified	b. ABSTRACT Unclassified	c. THIS PAGE Unclassified	OF ABSTR SAR	ACT:	OF PAGES	19a. 19b.	Ilya Vit TELEPHO N/A	ebskiy DNE NUMBER (Include Area Code)	

1

# Enhanced Non-linear Instabilities in Photonic Circuits with Exceptional Point Degeneracies

S. Suwunnarat<sup>1</sup>, R. Kononchuk<sup>1</sup>, A. Chabanov<sup>2</sup>, N. I. Limberopoulos<sup>3</sup>, I. Vitebskiy<sup>3</sup>, and T. Kottos<sup>1,\*</sup>

<sup>1</sup>Department of Physics, Wesleyan University, Middletown CT 06459, USA

<sup>2</sup> Department of Physics and Astronomy, University of Texas at San Antonio, San Antonio, TX 78249, USA

<sup>3</sup> Air Force Research Laboratory, Sensors Directorate, Wright-Patterson Air Force Base, OH 45433, USA

\*Corresponding author: tkottos@wesleyan.edu

Compiled November 14, 2019

A conceptual design of optical power limiter based on a photonic circuit with a second-order exceptional point degeneracy (EPD) is proposed. The design is based on a pair of coupled cavities with judiciously tailored differential *Q*-factors. One of the cavities includes a Kerr-like non-linear material. At low input intensities (in the linear regime) the two cavities are optically identical, and the transmittance of the entire photonic circuit is close to unity. As the input intensity is increased, the nonlinearity introduces a resonant detuning which lifts the degeneracy and results in formation of two distinct resonant modes. One of them (the high-Q mode) is abruptly destroyed due to nonlinear instabilities, while the low-Q mode experiences an underdamping-to-overdamping transition, rendering the entire photonic circuit highly reflective. The design allows to significantly lower the limiting threshold, while enhancing the power-handling capabilities due to the absence of absorption. A similar approach can be applied to optical power switching, Q-switching, routing, etc. © 2019 Optical Society of America under the terms of the OSA Open Access Publishing Agreement

http://dx.doi.org/10.1364/optica.XX.XXXXXX

### 1. INTRODUCTION

Spectral singularities have always been an interdisciplinary research theme, offering exciting opportunities to mathematicians, physicists, and engineers [1-3]. While most of the effort has up to now been focused on Hermitian spectral singularities (also known as diabolic points)[4–6], the recent interest in non-Hermitian wave physics has brought to the center of attention a class of spectral singularities known as exceptional point degeneracies (EPDs). Theoretically discussed more than fifty years ago [7], EPDs are non-Hermitian degeneracies emerging when the variation of a control parameter of the system enforces two (or more) eigenvalues, and their corresponding eigenvectors, to coalesce [7, 8]. In fact, the study of EPDs has revealed a variety of fundamental phenomena, which spawned the next generation technological developments [9]. Examples range from hypersensitive bio-sensing [10, 11] and navigation devices [12, 13] to lasing control [14–16] and unidirectional invisibility [17].

In this paper, we consider the possibility of using EPD-based

photonic circuits for optical limiting and switching. A typical optical limiter is supposed to transmit low-intensity input light, while blocking the light with excessively high intensity, thereby protecting sensitive optoelectronic components or the human eye from laser induced damage. One common problem with the existing optical limiters is that their limiting threshold (LT) is often too high for some important application. The challenge is to lower the LT, while maintaining the ability to withstand high input power without damaging the limiter itself. Here we show that the EPD-based approach allows to do just that. In addition, the proposed conceptual design can provide an abrupt and fast transition from high transmittance below the LT to nearly total reflectance above the LT. The high reflectance (as opposed to high absorptance) above the LT can prevent overheating and thus drastically increase the limiter damage threshold (LDT).

In the proposed design, we implemented a second-order EPD, combined with a non-linear detuning mechanism, in a one-dimensional photonic crystal (see Fig. 1). The EPD degen-



**Fig. 1.** Multilayer structure involving two optically identical coupled cavities with judiciously chosen differential *Q*-factors. (a) At low input intensity (in the linear regime), the photonic circuit supports an EPD and displays resonant transmittance. (b) If the input intensity exceeds the LT, the nonlinearity causes an abrupt lift of the EPD, rendering the photonic circuit highly reflective.

eracy is achieved by judiciously tailoring differential Q-factors of two optically identical defect components of the photonic crystal. One of the defect components is made of a non-linear (e.g. Kerr-effect-like) material that produces a resonance detuning when the input intensity exceeds the LT. At low input intensity, such that the self-induced non-linear resonance detuning is proportional to the differential *Q*-factor, the photonic structure is transparent over a frequency range around the EPD. When, however, the incident intensity exceeds the LT, the two distinct resonant modes emerge when the EPD is lifted due to the non-linear detuning. One mode undergoes an underdampingto-overdamping transition due to the differential Q-factor, while the other acquires a narrow resonance width that leads to strong bi-stability effects, resulting in an abrupt resonance destruction. The EPD-based photonic circuits are therefore excellent candidates for transceiver and other sensitive opto-electronic components protection. Not only do they show an abrupt limiting action, but their dynamical range is enhanced due to zero (or minimal) absorption and nearly total reflection of the incident high -power radiation.

In Section 2 we describe the basic idea of the EPD-based approach to optical limiting and demonstrate its efficiency by using a coupled mode theory (CMT) [18]. The analysis first focus at the linear CMT system. Then, in subsection B we proceed with the transport properties of the corresponding non-linear CMT model. In Section 3 we consider a specific design of a free space optical limiter based on an one-dimensional multilayer photonic crystal supporting an EPD. Finally, our conclusions are given at the last Section 4.

## 2. PRINCIPLE OF OPERATION AND THEORETICAL ANALYSIS OF AN EPD OPTICAL LIMITER USING COUPLED MODE THEORY

## A. Transport via two Linear Coupled Modes at EPD

We start our analysis by considering two coupled degenerate modes with differential *Q*-factors. The underlying physical system can be a multilayered photonic crystal with two defect layers (as in Fig.1) or two coupled optical resonators (as in the transparent box in Fig. 2a). Using a coupled mode theory (CMT) formalism, the system is described by the following effective Hamiltonian  $\hat{H}$ 

$$\hat{H} = \begin{pmatrix} -\Omega - i\gamma_1 & -\kappa \\ -\kappa & -\Omega - i\gamma_2 \end{pmatrix}, \quad (1)$$

where  $\kappa$  denotes the coupling between the two modes,  $-\Omega$  is the resonance frequency of each individual cavity (i.e. in the absence of coupling), and  $\gamma \equiv \gamma_2 - \gamma_1$  is the differential loss between the two cavities. The underlying physical mechanism of the mode losses  $\gamma_{1,2}$  can be due to Ohmic or radiative dissipation (or any other type of loss). We assume, without loss of generality, that  $\gamma_1 < \gamma_2$ .

The supermodes of the composite structure are found via direct diagonalization of Eq. (1). Specifically, we get:

$$\omega_{\pm} = -\Omega - i\bar{\gamma} \pm \sqrt{\kappa^2 - \left(\frac{\gamma}{2}\right)^2},\tag{2}$$

where  $\bar{\gamma} \equiv \frac{\gamma_1 + \gamma_2}{2}$ . The corresponding eigenvectors are:

$$v_{-} \propto \left(\begin{array}{c} -\frac{i\gamma - \sqrt{4\kappa^2 - \gamma^2}}{2\kappa} \\ 1 \end{array}\right); \quad v_{+} \propto \left(\begin{array}{c} -\frac{i\gamma + \sqrt{4\kappa^2 - \gamma^2}}{2\kappa} \\ 1 \end{array}\right) \quad (3)$$

Equations (2,3) imply that at  $\kappa_{EPD} = \frac{\gamma}{2}$  the two modes are degenerate, forming a second order EPD with  $\omega_{\pm} = \omega_{EPD} = -\Omega - i\bar{\gamma}$  and the corresponding degenerate eigenvectors  $v_{-} = v_{+} = \frac{1}{\sqrt{2}} (-i, 1)^{T}$ . In the following, we will use the dimensionless ratio,  $\alpha \equiv \gamma/2\kappa$ , as the EPD parameter ( $\alpha = 1$  will indicate the formation of an EPD).

Next, we assume that one of the modes experiences a detuning  $\Delta$  under the condition  $\alpha = 1$ . To be specific, we assume that the detuning mechanism is associated with the first cavity. The corresponding CMT Hamiltonian  $\hat{H}(\Delta)$ , is then of the same form as the one of Eq. (1), but with the substitute  $\Omega \rightarrow \Omega_{\Delta} \equiv \Omega + \Delta$  in the matrix element  $\hat{H}_{11}$ . Direct diagonalization of  $\hat{H}(\Delta)$  allows us to evaluate the influence of the detuning  $\Delta$  on the supermodes  $\omega_{\pm}(\Delta)$ . We have that:

$$\omega_{\pm}(\Delta) = \omega_{EPD} - \frac{\Delta}{2} \pm \frac{\sqrt{-2i\gamma\Delta + \Delta^2}}{2}$$
(4)

which in the two limiting cases of  $\Delta \ll \gamma$  and  $\Delta \gg \gamma$  takes the following forms:

$$\omega_{+}(\Delta) \approx \begin{cases} \omega_{EPD} + \left(\frac{1-i}{2}\right)\sqrt{\gamma\Delta}, & \Delta \ll \gamma \\ -\Omega - i\gamma_{2}, & \Delta \gg \gamma \end{cases}$$
(5)

and similarly for  $\omega_{-}$ :

$$\omega_{-}(\Delta) \approx \begin{cases} \omega_{EPD} - \left(\frac{1-i}{2}\right)\sqrt{\gamma\Delta} & \Delta \ll \gamma \\ -(\Omega + \Delta) - i\gamma_{1} & \Delta \gg \gamma \end{cases}$$
(6)

Further analysis of Eqs. (5,6) reveals that the two supermodes  $\omega_{\pm}$  are initially ( $\Delta < \gamma$ ) shifted in opposite directions, away from the EPD frequency  $\mathcal{R}e(\omega_{EPD}) = -\Omega$  with a rate  $\propto \sqrt{\Delta}$ . When  $\Delta > \gamma$ , the  $\omega_{-}$  mode keeps moving away from  $-\Omega$  with an increased rate  $\propto \Delta$  while  $\omega_+$  comes back at  $-\Omega$  and stays there. In parallel, the linewidth of  $\omega_{-}$  is initially ( $\Delta < \gamma$ ) decreasing with a rate  $\propto \sqrt{\Delta}$ , while the linewidth of  $\omega_+$  increases with the same rate. Since for  $\Delta < \gamma$ , the mode linewidth and the modal spacing scales with  $\Delta$  in a similar fashion, the two modes can be treated as quasi-degenerate. Under these conditions, the transmittance acquires high values for a frequency range  $\propto \sqrt{\gamma \Delta}$ around the EPD. In the opposite limit of  $\Delta > \gamma$ , the linewidths of  $\omega_{\pm}$  approaches asymptotically the values  $\gamma_{2,1}$  respectively. Therefore, the quality factor of the mode ( $\omega_+$ ) decreases, while that of the mode  $\omega_{-}$ ) increases. Consequently, the resonant transmission via the mode  $\omega_+$  will degrade, while the mode  $\omega_$ will demonstrate a relatively sharp resonance peak.



**Fig. 2.** a) Schematic of a two coupled cavity system (inside transparent box) connected to two transmission lines. The coupling is asymmetric i.e.  $|w_1| < |w_2|$ , enforcing differential radiative losses (and therefore *Q*-factors) between the first and the second resonator. The system is designed to support an EPD. b) Parametric evolution of the frequency difference  $\Delta \omega \equiv |\omega_+ - \omega_-|$  and the corresponding imaginary parts of the two eigenmodes versus the linear detuning  $\Delta$ . The solid black line has slope 1/2 while the dashed black line has slope 1 and are drawn in order to guide the eye. Notice that  $\Delta \omega \leq \max \{|\mathcal{I}m(\omega_{\pm})|\}$  in the domain where the frequency difference scales as  $\propto \sqrt{\Delta}$ . c) Transmission spectrum for various detuning strengths  $\Delta$  (see labels in the inset).

The characteristic responses of the eigenmodes to small detunings  $\Delta$  (see Eqs. (4,5,6)), also manifest themselves in the case of scattering set-up, i.e. when each resonator is coupled to a transmission line, see Fig. 2a. In this setting, the eigenmodes turn to resonant modes, whose resonant frequencies and linewidths are associated with the real and imaginary parts of the poles of the scattering matrix  $S(\omega)$ . The latter is expressed in terms of the Hamiltonian  $\hat{H}(\Delta)$  of the isolated system [19], as:

$$\hat{S} = -\hat{l}_2 - i\hat{W}^T \frac{1}{\hat{H}_{\text{eff}} - \omega\hat{l}_2} W; \quad \hat{H}_{\text{eff}} = \hat{H}(\Delta) + \Lambda - \frac{i}{2}\hat{W}\hat{W}^T$$
(7)

where  $\hat{l}_2$  is the 2 × 2 identity matrix and  $\hat{W}$  describes the

resonators-lead coupling. Its elements are  $W_{nm} = \sqrt{v_g} w_n \delta_{nm}$ where  $w_n$  are dimensionless coupling strengths and  $v_g = \frac{\partial w(k)}{\partial k}$ . Finally, the renormalization matrix  $\Lambda$  originates from the coupling of the system to the leads and it is specific to the properties of the transmission line. For example, when the transmission lines consist of CROW arrays (see Fig. 2a), supporting propagating waves with a dispersion relation  $\omega(k) = 2t_l \cos(k)$  (*k* is the wavevector and  $t_l = -1$  is the coupling constant between the resonators in the leads), the group velocity is  $v_g = -2t_l \sin(k)$ while  $\Lambda = -\frac{1}{2} \cot(k)WW^T$ .

Equation (7) allow us to identify the poles  $\omega_{\pm}$  of the scattering matrix  $\hat{S}$  as the zeros of the secular equation

$$\det[\hat{H}_{\rm eff} - \omega I_2] = 0 \tag{8}$$

which, in the case of CROW transmission lines, needs to be evaluated numerically. In fact, the analysis can be further simplified if we consider a wide band approximation corresponding to  $k \approx \pi/2$ . In this case, the tight-binding dispersion reduces to the free space dispersion and the analysis of the poles of  $\hat{S}$  boils down to the study of the eigenvalues of  $\hat{H}_{eff}^{fs} = \hat{H}(\Delta) - \frac{i}{2}\hat{W}^{fs}(\hat{W}^{fs})^T$ . Since  $\hat{W}^{fs}$  is diagonal with coupling elements  $W_{nm}^{fs}(k = \pi/2) = \sqrt{2}w_n\delta_{nm}$ , the eigenvalues of  $\hat{H}_{eff}^{fs}$  are essentially the same as the eigenvalues of  $\hat{H}(\Delta)$  with the substitution  $\gamma_1 \rightarrow \gamma_1 - w_1^2/t_l$  and  $\gamma_2 \rightarrow \gamma_2 - w_2^2/t_l$ . Therefore the resonant modes are affected, by the detuning  $\Delta$ , in the same manner as the eigenfrequencies of  $\hat{H}_{\Delta}$ .

We have calculated the resonances of the scattering set-up of Fig. 2a by solving numerically Eq. (8) for CROW transmission lines. Furthermore, we assumed that the underlying physical origin of the differential *Q*-factor of the two modes, is due to their asymmetric coupling with the transmission lines  $w_1 = -1.9 \times 10^{-2}$  and  $w_2 = -4.43 \times 10^{-2}$  while  $\gamma_1 = \gamma_2 = 0$  (in Eq. (1)) and  $\kappa = \kappa_{EPD} = 8 \times 10^{-4}$ . In our simulations we assumed that the resonant frequency of the two resonators is  $\Omega = 0$ . Our results for the frequency splitting  $\mathcal{R}e(\Delta\omega)$  versus  $\Delta$  are shown with symbols in Fig. 2b. In the same figure, we also report the parametric evolution of  $\mathcal{I}m(\omega_{\pm})$  of the eigenmodes of  $\hat{H}(\Delta)$  (see Eq. (1)) with equivalent mode losses  $\gamma_{1,2} = -w_{1,2}^2/t_l$ . The nice overlap validates the prediction that the parametric behavior with  $\Delta$ , of the resonant modes and the eigenmodes of  $\hat{H}(\Delta)$ , is the same.

The effect of  $\Delta$  on the resonance splitting has direct consequences to the shape of the transmittance spectrum  $T(\omega) \equiv$  $|S_{1,2}(\omega)|^2$ , see Fig. 2c. Specifically, for  $\Delta = 0$ ,  $T(\omega)$  shows only one resonance peak associated with the EPD. The position of this peak is at  $\omega = -\Omega$  and its linewidth is  $\bar{\gamma}$ . As  $\Delta$  increases, the EPD is lifted. However, the emerging two resonant peaks at  $\omega_{\pm}$  are not resolved as long as  $\Delta < \gamma$ . This is because the resonant mode linewidths are larger than the mode spacing  $\mathcal{R}e(\Delta\omega)$ , see Fig 2b. For larger values of  $\Delta > \gamma$  the resonance peaks are shifted apart from each other and their linewidths acquire fixed values  $\gamma_{1,2}$  where  $\gamma_1 < \bar{\gamma} < \gamma_2 < \mathcal{R}e(\Delta \omega)$ . In this  $\Delta$ -regime, the transmittance peak associated with the resonant mode  $\omega_+$  broadens to the linewidth  $\gamma_2$  and gets suppressed due to the decrease of the Q-factor of the mode. On the other hand, the resonance peak associated with  $\omega_{-}$  narrows to the linewidth  $\gamma_1 < \bar{\gamma} < \gamma_2$ . Either way, both modes acquire reduced transmittance due to the strong resonance detuning  $\Delta > \gamma$  between the modes. Alternatively, the reduced transmittance for large  $\Delta$ -values can be seen as a consequence of an increasing impedance mismatch between the two resonators which leads to an enhanced reflection.

#### B. Transport via two Non-linear Coupled Modes at EPD

In the previous analysis we did not discuss the physical origin of the mode detuning  $\Delta$  in one of the cavities/modes. For example, it can be induced externally by a temperature or a pressure variation, an injected current that changes the permittivity of the resonator, or be a consequence of an externally applied electric field, etc. In this subsection, we will focus on the case where the detuning is self-induced via a non-linear light-matter interaction. Specifically, we will assume that the detuning is associated with a non-linear mechanism, like the Kerr effect, i.e.  $\Delta = \chi |C_1|^2$  where  $|C_n^2|$  is the field intensity at the n = 1, 2 cavity.



**Fig. 3.** Parametric evolution of the frequency deference  $\Delta \omega$ and of the imaginary parts  $\mathcal{I}m(\omega_{\pm})$  of the two nonlinear stationary modes of a non-linear dimer (see Eq. (9)) with  $\alpha = 1, \chi = 10^{-4}, \gamma_1 = 0, \gamma_2 = \gamma = 1.6 \times 10^{-3}, \Omega = 0$  versus (a) the non-linear detuning  $\Delta = \chi |C_1|^2$  and (b) normalized power N. The solid black line has slope 1/2 while the dashed black line has slope 1 and are drawn in order to guide the eye. Notice that  $\Delta \omega \leq \max \{ |\mathcal{I}m(\omega_{\pm})| \}$  in the domain where the frequency difference scales as  $\propto \sqrt{\Delta}$ . In the inset of (a) we plot the dependence of  $\chi |C_1|^2$  versus N for each of the two modes  $\omega_{\pm}$ . (c)Transmission spectrum of the non-linear dimer for four representative values of incident power. (d) Transmission T versus incident power  $|I|^2$  for four representative frequency detunings. Notice that the transmission T associated with the resonant frequency  $\omega = -\Omega$  defines the boundary for all other cases. It drops from unit value at small incident powers to (essentially) zero for high incident powers. In (c-d) the parameters of the dimer are the same ones used in Fig. 2c.

First, we will analyze the stationary nonlinear super-modes of the two coupled resonators. For simplicity we will assume that  $\gamma_1 = 0$  and  $\gamma_2 = \gamma$ . We request the total power normalization such that  $|C_1|^2 + |C_2|^2 = N$ . The stationary nonlinear eigenmodes of this system, can be evaluated using the following CMT equations

$$\begin{bmatrix} -\Omega - \chi |C_1|^2 & -\kappa \\ -\kappa & -\Omega - i\gamma \end{bmatrix} \begin{bmatrix} C_1 \\ C_2 \end{bmatrix} = \omega \begin{bmatrix} C_1 \\ C_2 \end{bmatrix}, \quad (9)$$

where, without loss of generality, we will assume that  $C_1$  is real and  $C_2 = \sqrt{N - |C_1|^2}e^{i\phi}$ . Straightforward manipulations of Eqs. (9), together with the normalization condition, lead to the following transcendental equation

$$(\eta + \frac{\eta}{y})^2 + \alpha^2 = \frac{1}{1 - y^2}; \quad \tan(\phi) = \frac{\alpha y}{\eta(1 + y)}$$
 (10)

where  $C_{1,2}$  have been parametrized in terms of the variable y as  $|C_{1,2}|^2 = (1 \pm y)N/2$  while their relative phase  $\phi$  is given by the second equation in Eq. (10). Above, we have defined  $\eta = \chi N/4\kappa$  and  $\alpha = \gamma/2\kappa$ . We note that for  $\chi = 0$ , the EPD is formed when  $\alpha = 1$ .

We request the solutions  $y_{\pm}$  of the first Eq. (10) to be real. Their direct substitution in one of the Eqs. (9) allows us to calculate the non-linear stationary eigenfrequencies of the system described by Eq. (9). The latter are given as

$$\omega_{\pm}/\kappa = -\Omega/\kappa - \eta (1+y_{\pm})^2/y_{\pm} - i\alpha(1-y_{\pm}).$$
(11)

In Fig. 3a, we show (for  $\alpha = 1$ ) the behavior of  $\mathcal{R}e(\Delta \omega)$  (stars) and  $\mathcal{I}m(\omega_{\pm})$ , (triangles and circles) resulting from Eq. (11), versus the non-linear detuning  $\Delta = \chi |C_1|^2$ . In this calculation, the value of  $|C_1|^2$ , and therefore of the detuning, determines the total power N. The latter might have two different values for a fixed  $\Delta$  (see inset). In the same figure, we also plot (solid lines of the same color) the predictions from the linear analysis (see Eq. (4)) assuming a specific  $\Delta$ -value. We also report in Fig. 3b the same quantities versus N by identifying the  $\Delta$ -values (see inset in Fig. 3a) which are associated with a fixed N. In both cases, the resonance shift  $\mathcal{R}e(\Delta\omega)$  is initially smaller than the resonance linewidths, indicating that the two modes  $\omega_{\pm}$  are indistinguishable from one another. We find that the behavior of  $\omega_{\pm}$  versus the detuning is essentially the same as the one found for the corresponding linear system. In fact, the similarities with the linear problem extend also to the regime where  $\Delta > \gamma$ . We find that  $\omega_+$  is stabilized at  $-\Omega$  and acquires a broad linewidth,  $|\mathcal{I}m(\omega_{+})| \rightarrow \gamma_2$  which indicates a decrease of the Q-factor and therefore suppression of the transmittance (see Fig. 3c). On the other hand,  $\omega_{-}$  moves away from  $-\Omega$  while its linewidth narrows to  $|\mathcal{I}m(\omega_{-})| \rightarrow \gamma_1$ . In the following, we will show that the enhancement of the Q-factor of  $\omega_{-}$  has dramatically different consequences on the transmittance spectrum as compared to the linear case (see below).

Next, we analyze the transport properties of the CMT system described by Eq. (9). We consider the same scattering set-up with semi-infinite CROW transmission lines, as in Fig. 2a. We assume that the differential *Q*-factor is due to an asymmetric coupling to the leads  $w_1 \neq w_2$  while  $\gamma_1 = \gamma_2 = 0$ . We also assume the same parameter values as in the case of the linear scattering set-up analyzed in Fig. 2c.

For the calculation of the transmittance  $T(\omega)$ , we employ the so-called backward transfer map [20, 21], where we have assumed that the incident wave is entering the dimer structure from the left transmission line. We also assume that the outgoing field at the right transmission line takes the form  $C_n = te^{ikn}$ (n > 2), where *t* is the transmission amplitude and  $C_n$  indicates the field amplitude at the *n*-th resonator. A backward iteration of the CMT equations describing the set-up allows us to evaluate the wave at the left transmission line,  $C_n = Ie^{ikn} + re^{-ikn}$  $(n \le 0)$ , where (I, r) are the incident and reflected amplitudes, respectively. Thus, the  $|I|^2$  represents the incoming intensity and  $R = |r|^2$  is the reflectance. Straightforward algebra leads to the following expression for the transmittance  $T \equiv |t/I|^2$ :

$$T = \left| \frac{2\sin(k)}{\frac{F \cdot G(T)}{\kappa t_l} - \frac{\kappa t_l}{w_1 w_2}} \right|^2, \quad k > 0$$
(12)

where  $F = (\omega + \Omega) \frac{t_l}{w_2} - w_2 e^{-ik}$ ,  $G = (\omega + \Omega + \chi |C_0|^2) \frac{t_l}{w_1} - w_1 e^{ik}$  and  $|C_0|^2 = \left| \frac{IF}{\kappa} \right|^2 T$ . Equation (12) is a transcendental equation with respect to *T* and has to be solved numerically. Since no dissipative losses are involved, the reflectance can be evaluated as R = 1 - T.



**Fig. 4.** Transmittance spectra of the system of Fig. 2a when the first resonator experiences a nonlinear detuning ( $\chi = 10^{-4}$ ) and the coupling to the leads is asymmetric. We have used the same parameters as the one used in Fig. 3c. Various incident powers (see inset) are shown. (a) The control parameter is  $\alpha = \gamma/2\kappa = 0.4$ . Notice that the transmittance for incident power  $|I|^2 = 10^{-2}$  remains unaffected while the corresponding case in Fig. 3c we observe a drop by  $\Delta T/T = 60\%$ . (b) The control parameter is  $\alpha = 3$ . In this case the transmittance T = 34% is already too low for low incident powers. One needs to compare with the corresponding case in Fig. 3c where T = 1.

In Fig. 3c, we report some representative transmittance spectra  $T(\omega)$  for the non-linear dimer at  $\alpha = 1$  and  $\chi = 10^{-4}$ . All other parameters are the same as the ones used in Fig. 2c. For low incident powers, the transmittance shows the same behavior as in the linear case ( $\chi = 0$ ), i.e., a single quasi-degenerate peak at  $\omega \approx -\Omega$ , where  $T \approx 1$ . As the incident power increases, the two resonance peaks at  $\omega_{\pm}$  separate from each other: the frequency position of  $\omega_{+} = -\Omega$  remains unaffected from the incident power and the self-induced non-linear detuning, while its linewidth increases until it reaches its asymptotic value  $\gamma = -w_2^2/t_l$ . This decline in the Q-factor of the resonant mode leads eventually to a gradual suppression of the transmittance peak. The other emerging resonant mode, associated with  $\omega_{-}$ , is "pushed away" from  $-\Omega$  and becomes "sharper" due to the narrowing of its linewidth. In the non-linear scenario, however, this "upgrade" to a high-Q triggers a nonlinear bi-stability which leads to an abrupt suppression of the resonance peak. As a result, the structure demonstrates a (near) unity reflectance at  $\omega_{-}$ for high-power incident radiation (large non-linear detuning). An overview of the transmittance versus the incident power  $|I|^2$ , for various frequencies is shown in Fig. 3d. The results indicate that the optimal limiting behavior (high transmittivity for low powers and transmittivity drop for high incident powers) occurs for a range of frequencies,  $\pm \sqrt{\Delta \gamma}$ , around the EPD at  $\omega \approx -\Omega$ .



**Fig. 5.** (a) Resonant split  $\Delta f$  as a function of  $n_{D1}$  refractive index perturbation when loss is higher (red diamonds), lower (blue triangles) than losses at EPD and when the system is at EPD (purple circles). (b) Transmittance spectra of the freespace multilayer at different incident field intensities. c) Spatial field intensity distribution within the multilayer at low incident field intensity  $10^4 W/m^2$  (dark red line) and high incident field intensity  $10^{12} W/m^2$  (bright red line).

We stress that the transition from a (near-) unity transmittance to a (near-) unity reflectance is associated with the presence of the EPD. In order to clarify this point, we present an analysis of the transport properties of the two nonlinear coupled resonant modes for  $\alpha < 1$  and  $\alpha > 1$ , see Figs. 4a,b. A further insight is gained by an extended analysis of the parametric evolution of the non-linear stationary modes  $\omega_{\pm}$  of Eq. (9) versus the nonlinear detuning  $\Delta = \chi |C_1|^2$  (and also the total mode power *N*). This analysis is reported in the Supplement; see also Fig. 7). For  $\alpha < 1$  (Fig. 4a), both modes have the same linewidth  $ar{\gamma} = -0.5 \cdot (w_1^2 + w_2^2)/t_l$  (under-damped regime) up to a nonlinear detuning  $\Delta \sim \gamma$ . As a result the transmission spectrum is unaffected in this  $\Delta$ -range. It is instructive to compare the transmittance data shown by the blue and purple filled circles in Fig. 4a with the transmittance spectra at the same incident powers for  $\alpha = 1$  (see the same color symbols in Figs. 3c). In the latter case, the increase in the incident power led to a transmittance drop by  $\Delta T/T = 60\%$ . When  $\Delta$  increases further ( $\alpha < 1$ ), the  $\mathcal{I}m(\omega_{\pm})$  bifurcates to their asymptotic values. Similarly to the  $\alpha = 1$  case, one of the modes acquires a narrow linewidth and gets destroyed due to non-linear effects while the other one is "spoiled" due to an increase of its linewidth. This linewidth increase, though, is less steep, as compared to the  $\alpha = 1$  case, and therefore the suppression of the corresponding resonance peak is gradual. When  $\alpha > 1$  (see Fig. 4b), the  $\omega_{-}$  mode is extremely sharp even for small incident powers (non-linear detuning  $\Delta$ ), and therefore it becomes bistable and is immediately destroyed due to the presence of non-linearities (see lthe purple line drops on the left of Fig. 4b). At the same time,  $\omega_+$  has the maximum linewidth  $-w_2^2/t_1$  due to the strong coupling to the leads, and its resonance peak is well below unity ( $\sim 35\%$ ). We conclude that the presence of an EPD (i.e.  $\alpha = 1$ ) combined with the non-linear bi-stabilities can be used in order to design a power limiters with optimal transport characteristics: (almost) perfect transmittance at low incident powers and (almost) perfect reflectance at high incident powers.

### 3. FREE-SPACE MULTILAYER LIMITER DESIGN

The theoretical understanding of the interplay between the nonlinearities and the existence of EPDs in the transport properties of two coupled resonant modes, allow us to propose a design for a free space photonic limiter. The structure consists of a multilayer one-dimensional photonic crystal with two optically identical defect cavities placed symmetrically with respect to a mirror plane, see Fig. 1. The geometric arrangement of the photonic crystal is  $(AB)^n AD_1 (AB)^m AD_2 (AB)^n A$ , where A and B denote quarter-wave thick layers. The two cavities are designed in a way that they support defect modes in the middle of the band-gap of the photonic crystal. Under such condition, the two degenerate defect modes are isolated from the rest of the Fabry-Perot modes and thus they can be described by the two level system of Eqs. (1,9). Finally, the coupling strength that controls their mutual interaction is dictated by the number of layers between the two cavities. Specifically we have that  $\kappa \sim \frac{1}{\tilde{\epsilon}} e^{-L/\xi}$  where *L* is the number of in-between layers and  $\xi$  is the so-called localization length of these defect modes.

The designed Fabry-Perot cavities are both tuned at  $f_0 = 563.9THz$  resonant frequency ( $\lambda_0 = 532nm$ ) and A and B layers denote quarter-wave thick layers of  $TiO_2$  with refractive index  $n_A = 2.45$  [22] and  $LaF_3$  with refractive index  $n_B = 1.59$  [23]. The first cavity  $D_1$  has a nonlinear half-wave thick ZnS defect layer with intensity dependent refractive index  $n_{D1} \approx$ 

2.4 + 6.67 · 10<sup>-16</sup> $m^2/V^2 \cdot |E^2|$  [24] ( $|E(z)|^2$  is the electric field intensity at position *z* inside the layer), which is responsible for the nonlinear detuning  $\Delta$ . The second Fabry-Perot cavity  $D_2$  has tiny (radiative or Ohmic) losses  $\gamma$  modeled in our simulations via a complex refractive index  $n_{D_2} = 2.45 \times (1 + i\gamma)$  of the halfwave thick doped *TiO*<sub>2</sub> defect layer. The coupling coefficient  $\kappa$  between two Fabry-Perot cavities is controlled via the number *m* of bi-layers (*AB*) between the two defect layers  $D_1$  and  $D_2$ .

First, we identify the number n, m of bilayers and loss strength  $\gamma$ , which lead to the formation of an EPD in the low incident power limit. In this case, the system is linear i.e.  $n_{D_1}$ is essentially constant and independent of the incident power. The EPD condition  $\alpha = 1$  has been identified via a detail scaling analysis of the resonance splitting  $\Delta f = |f_+ - f_-|$  versus  $\Delta$  for various values of  $\alpha = \gamma/2\kappa$ . The detuning has been controlled by changing "manually" the value of  $n_{D_1}$  i.e.  $\Delta \propto \frac{\Delta n_{D_1}}{n_{D_1}}$ . The photonic design that supports an EPD has been identified as the configuration where  $\Delta f \sim \sqrt{\Delta}$  for  $\Delta < \gamma$  while  $\Delta \sim \Delta$  for  $\Delta > \gamma$ . In our case, this behavior is achieved when  $\gamma \approx 1.424 \cdot 10^{-6}$  and for n = 10, m = 22 number of bi-layers. In Fig. 5a we show the results of this analysis for three different cases corresponding to  $\alpha = 0.8, 1$  and 1.2. In the former case, the resonant modes are not degenerate for  $\Delta = 0$ , and acquire a fixed resonant split which remains unaffected from any index modulation up to  $\Delta \sim \gamma \approx 10^{-6}$ . Above this value, the frequency difference between the two resonant modes increases linearly with  $\Delta$ , see Fig. 5a. In contrast, for  $\alpha = 1.2$  the resonant modes are degenerate for  $\Delta = 0$  and their degeneracy is lifted very slowly, following a linear relation with detuning  $\Delta$  i.e.  $\Delta f \sim \Delta$ .



**Fig. 6.** (a) Transmittance and (b) reflectance of the non-linear multilayer photonic structure as functions of incident intensity at different frequencies in the vicinity of the resonant frequency of the multilayer  $f_0$ . The colors indicate the frequency f of the incident wave and are "correlated" with the vertical lines of the same color from Fig. 5c. The photonic crystal is designed in a way that supports an EPD (i.e.  $\alpha = 1$ ) for low incident powers.

Next we consider the non-linear transport properties of the multilayer system once it is brought at the EPD ( $\alpha = 1$ ). We assume that the defect  $D_1$  has a non-linear index of refraction  $n_{D_1}$  corresponding to ZnS material (see above). In our simulations, we have involved a backward transfer matrix approach [20, 21] for the evaluation of transmittance T and reflectance R. Figure 5b shows the transmission spectra for three representative incident powers. The results confirm the predictions of the two-mode CMT modeling (see Fig. 3c). Namely, for low incident powers the transmittance is (almost) unity at the EPD frequency  $f_0$ ; for higher incident powers the resonant peak splits in two, with the first one remaining at  $f_0$  while the other one being shifted away. The first peak broadens, leading to a deterio-

7

ration of the resonant mode and a consequent suppression of the transmittance. The second transmission peak is abruptly suppressed, showing a bistable behavior due to the presence of the nonlinearity. The destruction of the resonant defect modes are also evident from the spatial intensity distribution, illustrated in Fig. 5c. In this figure we show the low intensity incident scattering profile (dark red line) at resonant mode  $f_0$  together with the scattering field corresponding to high incident powers (bright red line). In the former case, the intensity is exponentially enhanced at the vicinity of the defect layers  $D_1$  and  $D_2$ , leading to a strong enhancement of the nonlinearity, and therefore to strong nonlinear detuning. Further increase of the latter due to higher incident radiation powers, is the source of the resonance destruction (bright red line) and consequent transmission resonant peak suppression. As a result, the structure turns to (almost) complete reflective one at high incident powers.

An overview of the transmittance (*T*) and reflectance (*R*) in the vicinity of the resonant frequency  $f_0$ , as functions of input intensity is shown in Figs. 6a,b. At the resonant frequency  $f_0$  (yellow lines on panels 6a and 6b) the transmittance decay at high intensities is correlated with an abrupt growth of the reflectance. At lower frequencies (blue and orange lines on panels 6a and 6b)), the transmittance demonstrates bi-stable behavior at high incident intensities, and its magnitude is highly suppressed over a broad intensity range, implying that in this region the multilayer provides high reflectivity at any incident intensity level. At frequencies above  $f_0$  the system does not show any bi-stable behavior (purple line on panels 6a and 6b)) and the transmittance is highly suppressed across a broad incident irradiance range.

We can therefore conclude that the proposed photonic structure can be utilized as a power limiter with an extremely sharp transition from a high (near-unity) resonant transmittance to a broadband reflectance. As opposed to other reflective photonic limiters, this proposal does not involve absorption growth growth at any incident intensity levels, and therefore has an enhanced dynamical range.

### 4. CONCLUSIONS

In this paper we have analyzed an EPD-based photonic circuit and demonstrated its efficiency for optical limiting and switching. The circuit consisted of two optically identical cavities with differential Q-factors embedded in a multilayer structure. One of the cavities involves a non-linear component which is responsible for triggering a resonant detuning once the incident radiation intensity is above a critical value. For low input intensities (linear regime) the structure displays strong EPD-related resonant transmittance. For high input intensities the light-induced detuning lifts the EPD. Specifically, one of the emerging resonances, is abruptly suppressed due to non-linear instabilities while the other becomes overdamping. This renders the photonic circuit highly reflective for a broad frequency range, with negligible absorption, preventing the circuit from overheating at high input light intensities. The limiting threshold which defines the transition from resonant transparency to broad-band nearcomplete reflectivity can be tailored by arranging the thickness of the two defect cavities. Specifically, an increase in non-linear layer thickness results in enhanced detuning of non-linear resonant frequency and sharper transition to the reflective state. The advantages of the proposed design include the possibility of a much lower limiting threshold (LT) and much higher limiter damage threshold (LDT), compared to those achievable with

passive limiters or switches using optical materials with nonlinear absorption. Finally, based on a non-linear coupled mode theory, we have developed analytical designing tools for the photonic structures with EPD.

#### FUNDING INFORMATION

Partial funding from DARPA NLM program via grant No. HR00111820042, ONR via grants N00014-16-1-2803 and N00014-19-1-2480, and AFOSR via grant FA9550-19-1-0359 and LRIR 18RYCOR013.

#### ACKNOWLEDGMENTS

The authors acknowledge useful discussions with S. Ali who participated at the initial stage of the project. We also acknowledge useful discussions with Dr. R. Sher on material properties.

Disclosures. The authors declare no conflicts of interest.

## SUPPLEMENTAL DOCUMENTS

For completeness, we have also analyzed the behavior of the non-linear stationary modes  $\omega_{\pm}(\Delta)$  for the cases of  $\alpha < 1$  and  $\alpha > 1$ , see Figs. 7a,b. A parallel analysis on the behavior of  $\omega_{\pm}(N)$  is shown in Figs. 7c,d and reveals the same qualitative characteristics. We will therefore focus our discussion in the analysis of the behavior of the stationary modes as a function of the non-linear detuning. For comparison purposes we also present the results of the  $\alpha = 1$  case. We point out that the analysis of the stationary modes  $\omega_{\pm}(\Delta)$  can provide a useful insight on the behavior of the transmission spectrum and specifically on the resonant peaks. In the numerical analysis below we assume that  $\gamma_1 = 0$  and  $\gamma_2 = \gamma = 1.6 \cdot 10^{-3}$ .

Similar to the case of  $\alpha = 1$ , the evaluation of  $\omega_{\pm}$  requires to solve numerically Eqs. (10,11). For  $\alpha > 1$ , we find that the  $\omega_+$  mode acquired the maximum linewidth  $\gamma_2 = \gamma$ , even for small values of  $\Delta = \chi |C_1|^2$ , see Fig. 7a. The corresponding supermode resides, mainly at the low-*Q* resonator n = 2 and does not "tunnel" to the first resonator because of the impedance mismatch ( $\gamma/2 > \kappa$ ) between them. In contrast, the supermode associated with  $\omega_{-}$  resides mainly at the first site which has  $\gamma_1 = 0$ . Therefore the imaginary part  $|\mathcal{I}m(\omega_-)| \ll \gamma_2$  of the corresponding stationary frequency is very small, see Fig. 7b. The increase of the detuning  $\Delta$  increases further the impedance mismatch between the two sites and enforces a complete decoupling between the resonators. The two supermodes reside exclusively at their corresponding resonator and acquire frequencies  $\omega_+ = -\Omega - i\gamma$  and  $\omega_- = -\Omega$  associated with the resonant frequencies of these resonators. This scenario is analogues to the one observed in  $\mathcal{PT}$ -symmetric systems in the symmetry-broken phase (see for example [25]) and has its roots to a superradiant-subradiant phenomenon familiar to us from the framework of nuclear physics.

In the case of  $\alpha < 1$ , both modes have the same linewidth  $\bar{\gamma} = (\gamma_1 + \gamma_2)/2$  up to a non-linear detuning  $\Delta \sim \gamma$ , see Fig. 7a,b. In this detuning regime the corresponding supermodes are supported symmetrically by both sites n = 1, 2 and therefore experience the same amount of losses. For larger values of  $\Delta$  an impedance mismatch between the two resonators starts to develop. As a result the  $|\mathcal{I}m(\omega_{\pm})|$  of the two modes bifurcate to their asymptotic values  $\gamma_1$  and  $\gamma_2$ . The latter is achieved when the detuning  $\Delta$  is large enough in order to enforce a complete decoupling between the resonators. This scenario

is shown in Figs. 7a,b where we see that one of the modes acquires a narrow linewidth while the other one is "spoiled" due to an increase of its linewidth. This increase, though, is slower as compared to the  $\alpha = 1$  case where the differential *Q*-factor is optimal. In fact, our analysis indicates that  $|\mathcal{I}m[\omega_{+}(\alpha > 1)]| \geq |\mathcal{I}m[\omega_{+}(\alpha = 1)]| \geq |\mathcal{I}m[\omega_{+}(\alpha < 1)]|$  while  $|\mathcal{I}m[\omega_{-}(\alpha > 1)]| \leq |\mathcal{I}m[\omega_{-}(\alpha = 1)]| \leq |\mathcal{I}m[\omega_{-}(\alpha = 1)]| \leq |\mathcal{I}m[\omega_{-}(\alpha < 1)]|$  for all values of  $\Delta$  and *N*.



**Fig. 7.** (a) The  $\mathcal{R}e(\Delta\omega)$ ,  $\mathcal{I}m(\omega_+)$  of the non-linear stationary modes  $\omega_{\pm}$  versus the non-linear detuning  $\Delta = \chi |C_1|^2$  for three representative values of  $\alpha$ . (b) Same as in (a) but now we report the  $\mathcal{I}m(\omega_-)$ ; (c) The same as in (a) but now versus N; (d) The same as in (b) but now versus N.

#### REFERENCES

- 1. A. Mostafazadeh, "Physics of spectral singularities," in *Geometric Methods in Physics*, (Springer, 2015), pp. 145–165.
- H. Ramezani, H.-K. Li, Y. Wang, and X. Zhang, "Unidirectional spectral singularities," Phys. review letters 113, 263905 (2014).
- 3. J. Schindler, A. Li, M. C. Zheng, F. M. Ellis, and T. Kottos, "Experimental study of active lrc circuits with pt symmetries," Phys. Rev. A **84**, 040101 (2011).
- E. Teller, "The crossing of potential surfaces." J. Phys. Chem. 41, 109–116 (1937).
- 5. T. Kippenberg, S. Spillane, and K. Vahala, "Modal coupling in traveling-wave resonators," Opt. letters **27**, 1669–1671 (2002).
- Ş. K. Özdemir, J. Zhu, X. Yang, B. Peng, H. Yilmaz, L. He, F. Monifi, S. H. Huang, G. L. Long, and L. Yang, "Highly sensitive detection of nanoparticles with a self-referenced and self-heterodyned whispering-gallery raman microlaser," Proc. Natl. Acad. Sci. 111, E3836–E3844 (2014).
- 7. T. Kato, *Perturbation theory for linear operators,* vol. 132 (Springer Science & Business Media, 2013).
- 8. N. Moiseyev, *Non-Hermitian quantum mechanics* (Cambridge University Press, 2011).
- C. E. Rüter, K. G. Makris, R. El-Ganainy, D. N. Christodoulides, M. Segev, and D. Kip, "Observation of parity-time symmetry in optics," Nat. physics 6, 192 (2010).
- 10. W. Chen, Ş. K. Özdemir, G. Zhao, J. Wiersig, and L. Yang,

"Exceptional points enhance sensing in an optical microcavity," Nature **548**, 192 (2017).

- H. Hodaei, A. U. Hassan, S. Wittek, H. Garcia-Gracia, R. El-Ganainy, D. N. Christodoulides, and M. Khajavikhan, "Enhanced sensitivity at higher-order exceptional points," Nature 548, 187 (2017).
- J. Ren, H. Hodaei, G. Harari, A. U. Hassan, W. Chow, M. Soltani, D. Christodoulides, and M. Khajavikhan, "Ultrasensitive micro-scale parity-time-symmetric ring laser gyroscope," Opt. letters 42, 1556–1559 (2017).
- Y.-H. Lai, Y.-K. Lu, M.-G. Suh, and K. Vahala, "Enhanced sensitivity operation of an optical gyroscope near an exceptional point," arXiv preprint arXiv:1901.08217 (2019).
- L. Feng, Z. J. Wong, R.-M. Ma, Y. Wang, and X. Zhang, "Single-mode laser by parity-time symmetry breaking," Science 346, 972–975 (2014).
- M. Liertzer, L. Ge, A. Cerjan, A. Stone, H. E. Türeci, and S. Rotter, "Pump-induced exceptional points in lasers," Phys. Rev. Lett. 108, 173901 (2012).
- H. Hodaei, M. A. Miri, A. U. Hassan, W. Hayenga, M. Heinrich, D. Christodoulides, and M. Khajavikhan, "Parity-timesymmetric coupled microring lasers operating around an exceptional point," Opt. letters 40, 4955–4958 (2015).
- Z. Lin, H. Ramezani, T. Eichelkraut, T. Kottos, H. Cao, and D. N. Christodoulides, "Unidirectional invisibility induced by p t-symmetric periodic structures," Phys. Rev. Lett. 106, 213901 (2011).
- 18. H. A. Haus and W. Huang, "Coupled-mode theory," Proc. IEEE **79**, 1505–1518 (1991).
- U. Kuhl, F. Mortessagne, E. Makri, I. Vitebskiy, and T. Kottos, "Waveguide photonic limiters based on topologically protected resonant modes," Phys. Rev. B 95, 121409 (2017).
- 20. D. Hennig and G. P. Tsironis, "Wave transmission in nonlinear lattices," Phys. Reports **307**, 333–432 (1999).
- E. Lidorikis, K. Busch, Q. Li, C. Chan, and C. M. Soukoulis, "Optical nonlinear response of a single nonlinear dielectric layer sandwiched between two linear dielectric structures," Phys. Rev. B 56, 15090 (1997).
- T. Siefke, S. Kroker, K. Pfeiffer, O. Puffky, K. Dietrich, D. Franta, I. Ohlídal, A. Szeghalmi, E.-B. Kley, and A. Tünnermann, "Materials pushing the application limits of wire grid polarizers further into the deep ultraviolet spectral range," Adv. Opt. Mater. 4, 1780–1786 (2016).
- L. V. R. de Marcos, J. I. Larruquert, J. A. Méndez, and J. A. Aznárez, "Self-consistent optical constants of mgf2, laf3, and cef3 films," Opt. Mater. Express 7, 989–1006 (2017).
- S. M. Polyakov, E. Karhu, R. Zamiri, C. Moisset, K. Iliopoulos, P. E. Vullum, U. L. Osterberg, and U. J. Gibson, "Nonlinear optical response and structural properties of mbegrown fe:zns films," Opt. Mater. Express 8, 356–367 (2018).
- 25. D. Christodoulides and J. Yang, *Parity-time Symmetry and its Applications*, vol. 280 (Springer, 2018).