

Breakdown Performance Statistics of a Nanoparticle Composite System

Dave Sanders, Ed Cook, Rick Anaya, Lisa Wang, Steve Sampayan and George Caporaso

Lawrence Livermore Lab, Livermore, CA, USA

Kirk Slenes, Jeff Jacquin and Rafael De La Fuente

TPL Inc, Albuquerque, NM, USA

ABSTRACT

The Dielectric Wall Accelerator (DWA) is an approach for manufacturing particle accelerators that can be an order of magnitude more compact than conventional accelerators. To realize the associated high level of electric field gradient it is necessary to develop and characterize materials that can maintain electric fields in excess of 100 MV/m (=1MV/cm). This high value for the breakdown strength must be maintained for many thousands of pulses under conditions of voltage reversal. The present work reports the performance of a candidate composite material composed of high dielectric constant nanoparticles dispersed in an epoxy matrix loaded to achieve a dielectric constant = 10. The effect of peak voltage on number of pulses that can be sustained is given. In addition the effects of electrode gap spacing and charging rate are explored.

INTRODUCTION

Electron accelerators can make high energy x-rays for tomography, x-ray based cancer treatment as well as for such diverse applications as medical diagnostics and baggage inspection. Particle accelerators can also be used to accelerate protons used for cancer therapy. Deuterium accelerators can be used to produce neutrons which, in turn, can be used in the detection of explosives and special nuclear material. All of these applications will benefit from the existence of more compact accelerators that are made possible with DWA designs. One of the determining factors in a DWA's compactness is the voltage holding ability of the materials used in their construction. In the present work a candidate material system using

high dielectric nanoparticles suspended in an epoxy matrix. The loading of the nanoparticles was adjusted to achieve a dielectric constant = 10.

The insulating materials in a DWA will be subject to many thousands of pulses with voltage reversal. An automated system was constructed to subject the insulating materials under test to multiple pulses with similar fields and voltage reversals that they would experience in actual use.

EXPERIMENTAL

Figure 1a shows a schematic for the circuit model where the MARX generator is represented by capacitors C1 and C2 and inductors L1 and L2.




Figure 1a: Test circuit SPICE model schematic

This work was performed under the auspices of the U.S. Department of Energy by University of California, Lawrence Livermore National Laboratory under Contract W-7405-Eng-48

Report Documentation Page

Form Approved
OMB No. 0704-0188

Public reporting burden for the collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to a penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number.

1. REPORT DATE JUN 2007		2. REPORT TYPE N/A		3. DATES COVERED -	
4. TITLE AND SUBTITLE Breakdown Performance Statistics of a Nanoparticle Composite System				5a. CONTRACT NUMBER	
				5b. GRANT NUMBER	
				5c. PROGRAM ELEMENT NUMBER	
6. AUTHOR(S)				5d. PROJECT NUMBER	
				5e. TASK NUMBER	
				5f. WORK UNIT NUMBER	
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) Lawrence Livermore Lab, Livermore, CA, USA				8. PERFORMING ORGANIZATION REPORT NUMBER	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)				10. SPONSOR/MONITOR'S ACRONYM(S)	
				11. SPONSOR/MONITOR'S REPORT NUMBER(S)	
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release, distribution unlimited					
13. SUPPLEMENTARY NOTES See also ADM002371. 2013 IEEE Pulsed Power Conference, Digest of Technical Papers 1976-2013, and Abstracts of the 2013 IEEE International Conference on Plasma Science. IEEE International Pulsed Power Conference (19th). Held in San Francisco, CA on 16-21 June 2013., The original document contains color images.					
14. ABSTRACT The Dielectric Wall Accelerator (DWA) is an approach for manufacturing particle accelerators that can be an order of magnitude more compact than conventional accelerators. To realize the associated high level of electric field gradient it is necessary to develop and characterize materials that can maintain electric fields in excess of 100 MV/m (=1MV/cm). This high value for the breakdown strength must be maintained for many thousands of pulses under conditions of voltage reversal. The present work reports the performance of a candidate composite material composed of high dielectric constant nanoparticles dispersed in an epoxy matrix loaded to achieve a dielectric constant = 10. The effect of peak voltage on number of pulses that can be sustained is given. In addition the effects of electrode gap spacing and charging rate are explored.					
15. SUBJECT TERMS					
16. SECURITY CLASSIFICATION OF:			17. LIMITATION OF ABSTRACT SAR	18. NUMBER OF PAGES 5	19a. NAME OF RESPONSIBLE PERSON
a. REPORT unclassified	b. ABSTRACT unclassified	c. THIS PAGE unclassified			




Figure 1b: Corresponding photograph.

For DWA versions employing liquid breakdown switches a pulsed charge system is required since the liquid cannot sustain high electric fields for longer periods of time. Under these conditions the voltage waveform should have a charge time peaking at several hundred nanoseconds immediately followed by a high frequency oscillatory voltage. The voltage source for testing the samples was a multi-stage MARX generator (not shown) having a voltage rise-time on the order of 20ns followed by a RC decay time. To generate the appropriate test waveform, waves-shaping components were needed. A load resistor (R3) was added across the MARX output to establish a RC time constant on the order of 500ns. Also connected in parallel with the MARX was a series combination of a large inductor (L3), resistor (R3), and the insulator test sample (essentially a small capacitance (C3) as compared to the MARX equivalent capacitance). The inductor/resistor combination served multiple purposes: it isolated the MARX from the test sample in the event of a fault thereby limiting voltage reversal on the MARX capacitors; it slowed down the rise-time of the charge voltage across the sample; and it allowed the sample voltage to resonantly charge to a voltage exceeding the MARX output.

To generate the required ringing voltage, another circuit was placed in parallel with the

sample. This circuit consisted of a series combination of small inductance, resistance, and switch. In the SPICE simulation, a transistor (Q1) was used to simulate the spark gap switch used in the actual circuit shown in Figure 1b. The spark gap was designed to break down at the voltage peak across the test sample at which time the circuit rang with a frequency of oscillation set by the sample's capacitance and the parallel inductance with damping as determined by the resistor.

In the actual experimental setup shown in Figure 1b, the main components are the voltage monitor (A), the input from the MARX generator (B), the pulse shaping inductors and resistors (C) the switch (D) and the sample to be tested (E).

The ball-to-ball test sample configuration (E in Figure 1b) is shown schematically in Figure 2a and the result of an electric field modeling calculation for this geometry is presented. Figure 2b.




Figure 2a: Ball test schematic for field calculation.




Figure 2b: Calculated field as a function of lateral distance.

It can be concluded that the electric field enhancement resulting from this geometry is a

relatively small value of 9% making it useful for establishing the electrical characteristics of the material. An additional advantage of the ball-to-ball electrode geometry was the ability to prepare multiple samples of the dielectric under nearly identical conditions. This was necessary to allow the statistical characteristics of breakdown to be established. (The relatively small test area at maximum field will require subsequent testing of larger area samples once the general breakdown behavior of a particular material is established).

Figure 3 shows the characteristic waveforms before, during, and after breakdown that were obtained.




Figure 3: Scope traces of voltage monitor.

A computer-based data collection system allowed multiple pulses to be applied to each test sample until breakdown was detected. Each waveform was compared with the preceding waveform before executing the next shot. If a difference between waveforms exceeded pre-established limits, the system alerted the experimenter. The maximum, minimum and peak-to-peak values were collected in a table along with all of the traces for subsequent inspection.

RESULTS

The first observation concerning breakdown behavior can be made from the oscilloscope trace shown in Figure 3 since it is representative of all observed failures. In all cases the failure occurred at the positive maximum in the trace rather than during the voltage reversal. This suggests that the voltage reversal was not cause of insulator failure, at least with the extent of reversal that we were able to achieve with the test setup used in this study.

The results of testing 12 samples with a nominal 2 mm gap are given in Figure 4.




Figure 4: Number of shots held vs. applied field for 2 mm gap.

The vertical axis gives the number of shots that a particular sample was able to hold vs. the electric field calculated by dividing the maximum voltage during a shot divided by the gap between the ball electrodes. (The relatively small field enhancement is ignored at this point since it does not change from sample to sample).

As expected, the number of shots that can be held increased as the electric field decreased. The apparent bimodal character of the data suggests that there may be defect sites in the material. (The existence and characterization of such sites will be the subject of future work should we determine that this material is a suitable candidate for DWA construction).

The statistical analysis of the data was done using software that came with a book on Weibull Analysis[1]. Figure 5a shows Weibull hazard plots for 1 and 2 mm electrode spacing at electric fields around 1 MV/cm.




Figure 5a: Accumulated hazard plots.




Figure 5b: Reliability plots

Clearly the material under consideration will not meet our stated goal for reliability with these particular operational conditions.

To explore conditions where the material might be expected to perform better, we considered smaller electrode gaps. It is known that materials in general are able to withstand greater electric fields if they are thinner[2]. Figure 6 shows the effect of electrode spacing on breakdown field.




Figure 6: Effect of gap on breakdown strength.

It is clear that the reducing the electrode spacing helps to improve voltage holding performance. For instance, with a 0.25mm spacing under pulse charge conditions, the breakdown field is double that found with 1 mm spacing.

In addition to considering electrode spacing, we also investigated the effect of charging the dielectric more slowly. (Such slower charging is possible with solid state switches that can withstand high fields for longer times than liquid switches). Since charging systems can be less expensive if the system being charged can be charged more slowly, we wanted to know if our candidate material could withstand high electric fields for longer periods of time. To make this measurement we programmed a high voltage DC power supply to ramp to full voltage in 1 second. The full voltage value was increased in 5 kV increments.

In our particular test the maximum voltage capability of our programmable power supply (86kV) was reached and we were not able to break our insulator material with a 0.25mm gap. We were able to break the same material with a smaller .076mm gap at a lower voltage.

These two slower charge measurements are included in Figure 6 for comparison with the faster charging results. The voltage holding ability is seen to be increased by a further amount when the same 0.25mm gap was charged at a 1 second rate compared to charging at a 100ns rate. (The arrow on the plot indicates that the sample did not break due to limitations with our programmable DC power supply). In contrast to the behavior of dielectric fluids where slower charging normally leads to diminished voltage holding capability, in the case of dielectric solids the opposite is sometimes found [3, 4]. Apparently this was the case for our particular material.

SUMMARY AND PLANNED FUTURE WORK

We have measured the dielectric breakdown performance of a nanoparticle composite material with a dielectric constant = 10. Our ultimate goal is to determine if a set of operational conditions exist where this material might provide sufficient breakdown strength to be considered as a candidate material for construction of Dielectric Wall Accelerators. At this point it appears that if such conditions exist, they will involve the use of electrode spacing values around 0.25mm.

While it is clear that the slower charging does not adversely affect breakdown performance and might in fact improve it, further measurements will be required to quantify the effect of charging rate on breakdown performance.

Our next set of experiments will involve establishing the reliability curves for this material with the electrode spacing around 0.25 mm to determine if there is sufficient performance to justify further testing with larger areas.

REFERENCES

1. Dodson, *The Weibull Analysis Handbook*. 2nd ed. 2006, Milwaukee: American Society for Quality, Quality Press.
2. Martin, J.C., *J.C. Martin on Pulsed Power*. Advances in Pulsed Power Technology, ed. T.H. Martin, G. A.H., and M. Kristiansen. 1996, New York: Plenum Press. pp. 227-253.
3. Dissado, L.A. and J.C. Fothergill, *Electrical Degradation and Breakdown in Polymers*. IEE Materials and Devices Series 9, ed. G.C. Stevens. 1992, London, United Kingdom: Peter Peregrinus Ltd.
4. Kwan, C.K., *Dielectric Phenomena in Solids with Emphasis on Physical Concepts of Electronic Processes*. 2004, New York: Elsevier.