

MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963-A

ADE 930 739

(2)

AD-A160 623



TECHNICAL REPORT RR-85-2

TRANSLATION, ROTATION, SCALE AND ASPECT INVARIANT
MATCHED FILTER AND SCENE COMBINATION

Don A. Gregory and James C. Kirsch
Research Directorate
Research, Development, and Engineering Center

June 1985



U.S. ARMY MISSILE COMMAND

Redstone Arsenal, Alabama 35898-5000

Approved for public release; distribution unlimited.

DTIC FILE COPY

DTIC
ELECTE
OCT 17 1985
S A D

DISPOSITION INSTRUCTIONS

DESTROY THIS REPORT WHEN IT IS NO LONGER NEEDED. DO NOT RETURN IT TO THE ORIGINATOR.

DISCLAIMER

THE FINDINGS IN THIS REPORT ARE NOT TO BE CONSTRUED AS AN OFFICIAL DEPARTMENT OF THE ARMY POSITION UNLESS SO DESIGNATED BY OTHER AUTHORIZED DOCUMENTS.

TRADE NAMES

USE OF TRADE NAMES OR MANUFACTURERS IN THIS REPORT DOES NOT CONSTITUTE AN OFFICIAL INDORSEMENT OR APPROVAL OF THE USE OF SUCH COMMERCIAL HARDWARE OR SOFTWARE.

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER RR-85-2	2. GOVT ACCESSION NO. AD A166 623	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) Translation, Rotation, Scale and Aspect Invariant Matched Filter and Scene Combination		5. TYPE OF REPORT & PERIOD COVERED Technical Report
7. AUTHOR(s) Don A. Gregory and James C. Kirsch		6. PERFORMING ORG. REPORT NUMBER
9. PERFORMING ORGANIZATION NAME AND ADDRESS Commander, US Army Missile Command ATTN: AMSMI-RR Redstone Arsenal, AL 35898-5248		8. CONTRACT OR GRANT NUMBER(s)
11. CONTROLLING OFFICE NAME AND ADDRESS Same as item 9.		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office)		12. REPORT DATE June 1985
		13. NUMBER OF PAGES 25
		15. SECURITY CLASS. (of this report) UNCLASSIFIED
		15a. DECLASSIFICATION/DOWNGRADING SCHEDULE
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Pattern Recognition Matched Filters Optical Correlation		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) An interesting pattern has been discovered, which when used as the input scene to a Vander Lugt type correlator, possesses almost complete invariance to the usual problems associated with pattern recognition. The scene may be translated, rotated, scaled, or tilted without total loss of the correlation signal. This, of course, is a specialized scene, but interesting applications for such a pattern do exist.		

DD FORM 1 JAN 73 1473

EDITION OF 1 NOV 65 IS OBSOLETE

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

ACKNOWLEDGMENTS

The authors would like to thank Dr. Richard L. Hartman of the Research, Development, and Engineering Center's Research Directorate for suggesting this investigation. Credit is also given to Mr. Tracy Hudson of the University of Alabama in Huntsville Co-op Program for his assistance in producing the drawings in this report.



Accession For	
NTIS ORNA	<input checked="" type="checkbox"/>
DTIC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
By	
Distribution/	
Availability Codes	
Dit	Avail and/or Special
AI	

TABLE OF CONTENTS

	<u>Page</u>
LIST OF ILLUSTRATIONS.....	
I. INTRODUCTION AND THEORY.....	
II. EXPERIMENTAL RESULTS.....	
III. CONCLUSIONS.....	
REFERENCES.....	

LIST OF ILLUSTRATIONS

<u>Figure No.</u>	<u>Title</u>	<u>Page</u>
1	A photograph of the "spoked wheel" pattern (angular Ronchi ruling).....	2
2	The real-time optical correlator - experimental arrangement.....	2
3	A photograph of the matched filter of the angular Ronchi ruling.....	3
4	The transmission function for the angular Ronchi ruling....	3
5	A photograph of the "phase shifted" angular Ronchi ruling..	6
6	The transmission function for the "phase shifted" Ronchi ruling.....	6
7	A photograph of the matched filter of the "phase shifted" angular Ronchi ruling.....	7
8	Correlation intensity vs rotation of the "phase shifted" angular Ronchi ruling input scene.....	7
9	Measured correlation intensity vs magnification for "phase shifted" angular Ronchi ruling.....	9
10	Measured correlation intensity vs aspect angle for "phase shifted" angular Ronchi ruling.....	9

I. INTRODUCTION AND THEORY

Many of the problems associated with coherent Fourier transform matched filters are well known [1] [2]. The autocorrelation signal detected is quite sensitive to the rotation, scale, and tilt of the scene to be recognized. The extent of the sensitivity is dependent upon the spatial frequency content of the scene [3]. The correlation signal is, however, translationally invariant; explained by the shift theorem of Fourier optics [4]. In specialized applications it would be advantageous to be able to recognize a predetermined scene for location identification. As an example, consider an aircraft landing without radar information. A scene, painted on the runway, could provide optical correlation information to the pilot in addition to the other information provided by ground personnel. Consider also the problems associated with landing a helicopter on a moving object, such as an aircraft carrier. A pattern on the landing (or hovering) location could provide automated information to the pilot about his general position. One can think of many other applications where such a pattern would be useful.

Several patterns were considered for this type of application, and two were investigated experimentally and found to be of possible use. The first pattern was a "spoked wheel" design (essentially an angular Ronchi ruling) consisting of black and white (or opaque and transparent) areas, separated by equal angles. A photograph is given in Figure 1. This scene was used as the input to a real-time optical correlator, sketched in Figure 2 and described in detail elsewhere [5]. The matched filter was recorded on a high resolution Kodak 649F plate and developed using standard procedures. A photograph of the filter is given in Figure 3. This is a Vander Lugt type correlator, therefore Figure 3 can also be viewed as the optical Fourier transform of the pattern given in Figure 1. The transmission function describing the pattern of Figure 4 [6]:

$$t(\theta) = [\text{Rect} \left(\frac{\theta}{\alpha} \right) * \text{Comb} \left(\frac{\theta}{2\alpha} \right)] \quad (1)$$

In general

$$\text{rect} (z) = \begin{cases} 1 & |z| \leq \frac{1}{2} \\ 0 & \text{otherwise} \end{cases} \quad (2)$$

and

$$\text{Comb} (z) = \sum_{n=-\infty}^{\infty} \delta (z-n) \quad (3)$$

The intensity recorded on the photographic plate can be written as: [7]

$$I \propto | F [t(\theta)] |^2 \quad (4)$$

where F denotes the Fourier Transform.

The form of Equation (1) lends insight into what this intensity should be: [8]




Figure 1. A photograph of the "spoked wheel" pattern (angular Ronchi ruling).





Figure 2. The real-time optical correlator - experimental arrangement.



— 1 mm —

Figure 3. A photograph of the matched filter of the angular Ronchi ruling.





Figure 4. The transmission function for the angular Ronchi ruling.

$$F \left[\text{rect} \left(\frac{\theta}{\alpha} \right) \right] = \alpha \text{ sinc}(\omega\alpha) \quad (5)$$

where

$$\text{sinc}(\omega\alpha) = \frac{\sin(\pi\omega\alpha)}{\pi\omega\alpha} \quad (6)$$

and ω is the angular spatial frequency. Also: [9]

$$F \left[\text{Comb} \left(\frac{\theta}{2\alpha} \right) \right] = 2\alpha \text{ Comb}(2\omega\alpha) \quad (7)$$

and

$$\text{Comb}(2\omega\alpha) = \sum_{n=-\infty}^{\infty} \delta(2\omega\alpha - n), \quad (8)$$

which determines the allowed angular spatial frequencies:

$$\omega = \frac{n}{2\alpha} \quad (9)$$

The fundamental frequency is

$$\omega_f = \frac{1}{2\alpha}, \quad (10)$$

which appears to be reasonable when compared to the same formulation for a Ronchi ruling [10].

Thus the intensity pattern observed should consist of dark radial spokes (corresponding to the fundamental angular frequency), separated by the angle 2α (the inverse of ω_f), with lighter spokes on either side of the dark spokes (due to the sinc^2 term).

II. EXPERIMENTAL RESULTS

Matched filters, such as the one in Figure 3, were addressed with the angular Ronchi ruling pattern and the correlation signal observed with the TV camera shown in Figure 2. Tests were done for translation, rotation, scale, and aspect angle sensitivity. It was found that the scene did possess the usual translation invariance and was quite insensitive to scale and aspect angle changes. The scene was then rotated. The correlation signal decreased in intensity and completely disappeared after about + 7 degrees of rotation. The 10-degree separation of the spokes in the matched filter was too great. To correct this problem, two possibilities existed. The angle α in the image could be halved so that the angle between the spokes in the matched filter would also be smaller by a factor of 2. Another idea which takes advantage of the symmetry of the optical Fourier transform proved to be a better solution [7]. Figure 5 is a photograph of a "phase" shifted angular Ronchi ruling pattern. It is produced by cutting two of the patterns of Figure 1 into two equal pieces each, then reassembling two of the halves. The transmission of such a pattern may be modeled with the use of Figure 6.

Let $t_1(\theta)$ be the transmission function for the "A" pattern (see Equation (1)) and $t_2(\theta)$ be the transmission for the "B" pattern. Then the transmission of the combined patterns may be written as:

$$T(\theta) = t_1(\theta) + t_2(\theta) \quad (11)$$

The Fourier transform may then be written as:

$$F[T(\theta)] = F[t_1(\theta) + t_2(\theta)] \quad (12)$$

$$= F[t_1(\theta)] + F[t_2(\theta)] \quad (13)$$

Both terms of Equation (13) produce fundamental radial spokes in the Fourier transform plane separated by the angle 2α , but the spokes corresponding to the "A" pattern are displaced angularly from the spokes due to the "B" pattern. The amount of displacement corresponds to the angle α - the amount of shift in the photograph of Figure 5. Therefore, the Fourier transform of Figure 5 should look very similar to Figure 3; with twice the number of spokes. The matched filter actually obtained is shown in Figure 7. The separation between spokes is α , (5 degrees).

This matched filter/scene combination was then tested for translation, rotation, scale, and aspect angle correlation sensitivity. As expected, the scene could be linearly translated with little or no loss in signal. The input scene was then rotated 360 degrees. The correlation signal decreased only slightly through the entire rotation. This is shown in Figure 8. A large improvement was seen over the "unshifted" pattern. The correlation signal did decrease in intensity, but only about 25 percent over the entire 360 degrees of rotation. A large correlation is still present at any rotational position.

In previous experiments, the sensitivity to a change in scale of the input scene has been observed and found to be a serious limitation[11]. The "shifted" angular Ronchi ruling and matched filter were tested to observe the




Figure 5. A photograph of the "phase shifted" angular Ronchi ruling.





Figure 6. The transmission function for the "phase shifted" Ronchi ruling.



_____ 1 mm _____

Figure 7. A photograph of the matched filter of the "phase shifted" angular Ronchi ruling.




Figure 8. Correlation intensity vs rotation of the "phase shifted" angular Ronchi ruling input scene.

variation in correlation intensity as the size of the input scene image was changed using a motorized zoom lens. The magnification factor ranged from about .5 to about 2.5. A plot of the intensity of the correlation signal as a function of the magnification is given in Figure 9. The range of magnification was as large as possible using the zoom lens available. For a magnification of about .5, the television image covered about one-third of the monitor, or about 170 TV lines, and for a magnification of about 2.5, the overall image was not very intense, which the liquid crystal light valve could not respond to very efficiently [12]. This problem could have been avoided, perhaps, by incorporating an automatic iris and gain control in the television camera.

The final test consisted of changing the aspect angle (tilt) of the scene as the correlation signal was observed and recorded. It is known that, for many scenes, the correlation signal is not as sensitive to aspect angle changes as it is to rotation and magnification. Figure 10 gives the correlation intensity as the scene was tilted from +45 degrees through 0 degrees to -45 degrees. The filter was made at 0 degrees tilt. The decrease in correlation is not critical for a very large aspect angle. Even at the two extremes of aspect, the signal is still present; and, although down in intensity an order of magnitude, still maintains a good signal to noise ratio. The scene must be tilted by about ± 20 degrees before the correlation signal decreases by 50 percent.

In an actual application, the previous parameters (translation, rotation, scale, and tilt) may all change simultaneously. It was possible to do this simulation and the results appear promising. The signal was lost only for large aspect angles combined with maximum scale changes. Rotation and translation were not serious limitations.




Figure 9. Measured correlation intensity vs magnification for "phase shifted" angular Ronchi ruling.




Figure 10. Measured correlation intensity vs aspect angle for "phase shifted" angular Ronchi ruling.

III. CONCLUSIONS

The ideas and results presented in this report show promise - perhaps a solution waiting for a problem. The "shifted" angular Ronchi ruling matched filter has demonstrated a much greater tolerance of parameter changes than more usual patterns. The usual translational invariance is present, as should be expected, and the correlation signals also are quite insensitive to a rotation, magnification, or tilt of the angular ruling scene. The initial success of this experiment is promoting further investigations using this type scene. Many of the results presented here can probably be improved upon by maximizing parameters used in making the matched filters, such as reference to object beam ratios, exposure times, etc. The fundamental angular spatial frequency of the scene should also be maximized so as to provide the lowest loss in correlation intensity while still preserving the uniqueness of the matched filters. Angular Ronchi ruling with a high fundamental spatial frequency (small angle spokes) could not be resolved at a distance (scale change), while rulings with extremely low fundamental frequencies (large angle spokes), would not preserve the desired rotational invariance.

REFERENCES

1. Casasent, D., and Furman, A., Appl. Opt., 16: 1662, (1977).
2. Leib, K., Bondurant, R., Hsiao, S., Wohlers, R., and Herold, R., Appl. Opt., 17: 2893, (1978).
3. Kozma, A., and Vanderlugt, A., "Optical Data Processing for Terminal Guidance", Final Technical Report, Contract No. DAAH01-72-C-0297, prepared for MICOM, Redstone Arsenal, AL by Harris Electro-Optics Center, Ann Arbor, MI (1972).
4. Goodman, J. W., Introduction to Fourier Optics, McGraw Hill, New York, (1968), p. 9.
5. Guenther, B., Christensen, C., and Upatnieks, J., IEEE, J. Quant. Elect. QE-15: 1348, (1979).
6. Gregory, D., Real-Time, Large Memory, Optical Pattern Recognition, Technical Report RR-84-9, MICOM, Redstone Arsenal, AL (1984).
7. Shulman, A., Optical Data Processing, Wiley and Sons, New York, (1970) p. 76.
8. Goodman, J., Introduction to Fourier Optics, McGraw Hill, New York, (1968), p. 14.
9. Ibid, p. 14.
10. Gregory, D., Real-Time, Large Memory, Optical Pattern Recognition, Technical Report RR-84-9, MICOM, Redstone Arsenal, AL, (1984).
11. Casasent, D., and Furman, A., Appl. Opt., 16: 1662, (1977).
12. Beard, T., Bleha, W., and Wong, S., Appl. Phys. Lett., 22: 90, (1973).

DISTRIBUTION

	No. of Copies
Commander US Army Research Office ATTN: AMXRO-PH, Dr. R. Lontz P. O. Box 12211 Research Triangle Park, NC 27709	5
US Army Research and Standardization Group (Europe) ATTN: AMXSN-E-RX, LTC D. R. Reinhard Box 65 FPO New York 09510	1
Commander US Army Materiel Development and Readiness Command ATTN: Dr. James Bender Dr. Gordon Bushey 5001 Eisenhower Avenue Alexandria, VA 22333	1 1
Headquarters, Department of the Army Office of the DCS for Research, Development & Acquisition ATTN: DAMA-ARZ Room 3A474, The Pentagon Washington, DC 20301	1
OUSDR&E Room 3D1079, The Pentagon Washington, DC 20301	1
Director Defense Advanced Research Projects Agency 1400 Wilson Boulevard Arlington, VA 22209	1
OUSDR&E ATTN: Dr. G. Gamota Deputy Assistant for Research (Research in Advanced Technology) Room 3D1067, The Pentagon Washington, DC 20301	1
Director of Defense Research and Engineering Engineering Technology Washington, DC 20301	1

Director Defense Advanced Research Projects Agency/STO ATTN: Commander T. F. Weiner D. W. Waish 1400 Wilson Boulevard Arlington, VA 22209	 1 1
Commander US Army Aviation Systems Command 12th and Spruce Streets St. Louis, MO 63166	 1
Director US Army Air Mobility Research & Development Laboratory Ames Research Center Moffett Field, CA 94035	 1
Commander US Army Electronics Research & Development Command ATTN: AMSEL-TL-T, Dr. Jacobs DELEW-R, Henry E. Sonntag Fort Monmouth, NJ 07703	 1 1
Director US Army Night Vision Laboratory ATTN: John Johnson John Deline Peter VanAtta Fort Belvoir, VA 22060	 1 1 1
Commander US Army Picatinny Arsenal Dover, NJ 07801	 1
Commander US Army Harry Diamond Laboratories 2800 Powder Mill Road Adelphi, MD 20783	 1
Commander US Army Foreign Science and Technology Center ATTN: W. S. Alcott Federal Office Building 220 7th Street, NE Charlottesville, VA 22901	 1
Commander US Army Training and Doctrine Command Fort Monroe, VA 22351	 1

Director	
Ballistic Missile Defense Advanced Technology Center	
ATTN: ATC-D	1
ATC-O	1
ATC-R	1
ATC-T	1
P.O. Box 1500	
Huntsville, Al 35808	
Commander	
US Naval Air Systems Command	
Missile Guidance and Control Branch	1
Washington, DC 20360	
Chief of Naval Research	
Department of the Navy	1
Washington, DC 20301	
Commander	
US Naval Air Development Center	1
Warminster, PA 18974	
Commander, US Naval Ocean Systems Center	
Code 6003, Dr. Harper Whitehouse	1
San Diego, Ca 92152	
Director, Naval Research Laboratory	
ATTN: Dave Ringwolt	1
Code 5570, T. Gialborinzi	1
Washington, DC 20390	
Commander, Rome Air Development Center	
US Air Force	
ATTN: James Wasielewski, IRRC	1
Griffiss Air Force Base, NY 13440	
Commander, US Air Force, AFORSR/NE	
ATTN: Dr. J. A. Neff	1
Building 410, Bolling Air Force Base	
Washington, DC 20332	
Commander, US Air Force Avionics Laboratory	
ATTN: D. Rees	1
W. Schoonover	1
Dr. E. Champaign	1
Dr. J. Ryles	1
Gale Urban	1
David L. Flannery	1
Wright Patterson Air Force Base, OH 45433	

Director Defense Advanced Research Projects Agency/STO ATTN: Commander T. F. Weiner D. W. Waish 1400 Wilson Boulevard Arlington, VA 22209	1 1
Commander US Army Aviation Systems Command 12th and Spruce Streets St. Louis, MO 63166	1
Director US Army Air Mobility Research & Development Laboratory Ames Research Center Moffett Field, CA 94035	1
Commander US Army Electronics Research & Development Command ATTN: AMSEL-TL-T, Dr. Jacobs DELEW-R, Henry E. Sonntag Fort Monmouth, NJ 07703	1 1
Director US Army Night Vision Laboratory ATTN: John Johnson John Deline Peter VanAtta Fort Belvoir, VA 22060	1 1 1
Commander US Army Picatinny Arsenal Dover, NJ 07801	1
Commander US Army Harry Diamond Laboratories 2800 Powder Mill Road Adelphi, MD 20783	1
Commander US Army Foreign Science and Technology Center ATTN: W. S. Alcott Federal Office Building 220 7th Street, NE Charlottesville, VA 22901	1
Commander US Army Training and Doctrine Command Fort Monroe, VA 22351	1

Commander, AFATL/LMT
ATTN: Charles Warren 1
Eglin Air Force Base, FL 32544

Environmental Research Institute of Michigan
Radar and Optics Division
ATTN: Dr. A. Kozma 1
Dr. C. C. Aleksoff 1
Juris Upatnieks
P. O. Box 8618
Ann Arbor, MI 41807

IIT Research Institute
ATTN: GACIAC 1
10 West 35th Street
Chicago, IL 60616

Dr. J. G. Castle
9801 San Gabriel, NE 1
Albuquerque, NM 87111

Commander, Center for Naval Analyses
ATTN: Document Control 1
1401 Wilson Boulevard
Arlington, VA 22209

Dr. J. W. Goodman
Information Systems Laboratory
Department of Electrical Engineering 1
Stanford University
Stanford, CA 04305

Eric G. Johnson, Jr. 1
National Bureau of Standards
325 S. Broadway
Boulder, CO 80302

Dr. Nicholas George
The Institute of Optics 1
University of Rochester
Rochester, NY 14627

Naval Avionics Facility 1
Indianapolis, IN 46218

Dr. David Cassasent
Carnegie Mellon University 1
Hamerschage Hall, Room 106
Pittsburg, PA 15213

Professor Anil K. Jain
Department of Electrical Engineering
University of California, Davis
Davis, CA 95616 1

Terry Turpin
Department of Defense
9800 Savage Road
Fort George G. Meade, MD 20755 1

Dr. Stuart A. Collins
Electrical Engineering Department
Ohio State Univeristy
1320 Kennear Road
Columbus, OH 43212 1

US Army Materiel Systems Analysis Activity
ATTN: AMXSU-MP
Aberdeen Proving Ground, MD 21005 1

US Army Night Vision Laboratory
ATTN: DELNV-L, Dr. R. Buser
Ft. Belvoir, VA 22060 1

Dr. F. T. S. Yu
Penn State University
Department of Electrical Engineering
University Park, PA 16802 1

Dr. William P. Bleha
Liquid Crystal Light Valve Devices
Hughes Aircraft Company
6155 El Camino
Carlsbad, CA 92008 1

AMSMI-R, Dr. McCorkle	1
Dr. Rhoades	1
-RN, Jerry Hagood	1
-RE, W. Pittman	1
-RG, J. A. McLean	1
-RR, Dr. R. L. Hartman	1
Dr. J. S. Bennett	1
Dr. J. G. Duthie	1
Dr. D. A. Gregory	80
-RD	1
-RPR, Reference	15
-RPT, Record Copy	1
-O	1
-Y	1
-LP, Mr. Voigt	1
AMCPM-PE-E, John Pettitt	1
-PE	1

END

FILMED

12-85

DTIC