

AD-A200 421

DTIC FILE COPY

②

OFFICE OF NAVAL RESEARCH

Contract N00014-83-K-0470-P00003

R&T Code NR 33359-718

Technical Report No. 110

The Behavior of Microdisk and Microring Electrodes.
Mass Transport to the Disk in the Unsteady State:
Chronopotentiometry

by

M. Fleischmann and S. Pons

Prepared for publication in J. Electroanal. Chem.

Department of Chemistry
University of Utah
Salt Lake City, UT 84112

July 15, 1988

DTIC
UNCLASSIFIED
NOV 14 1988
CE

Reproduction in whole, or in part, is permitted for
any purpose of the United States Government

This document has been approved
for public release and sales to
distribution is unlimited.

88 11 10 08 p

REPORT DOCUMENTATION PAGE

1a. REPORT SECURITY CLASSIFICATION Unclassified		1b. RESTRICTIVE MARKINGS	
2a. SECURITY CLASSIFICATION AUTHORITY		3. DISTRIBUTION/AVAILABILITY OF REPORT Approved for public release and sale. Distribution unlimited.	
2b. DECLASSIFICATION/DOWNGRADING SCHEDULE		4. PERFORMING ORGANIZATION REPORT NUMBER(S) ONR Technical Report No. 110	
4. PERFORMING ORGANIZATION REPORT NUMBER(S) ONR Technical Report No. 110		5. MONITORING ORGANIZATION REPORT NUMBER(S)	
6a. NAME OF PERFORMING ORGANIZATION University of Utah	6b. OFFICE SYMBOL (if applicable)	7a. NAME OF MONITORING ORGANIZATION	
6c. ADDRESS (City, State, and ZIP Code) Department of Chemistry Henry Eyring Building Salt Lake City, UT 84112		7b. ADDRESS (City, State, and ZIP Code)	
8a. NAME OF FUNDING/SPONSORING ORGANIZATION Office of Naval Research	8b. OFFICE SYMBOL (if applicable)	9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER N00014-83-K-0470-P00003	
8c. ADDRESS (City, State, and ZIP Code) Chemistry Program, Code 1113 800 N. Quincy Street Arlington, VA 22217		10. SOURCE OF FUNDING NUMBERS	
		PROGRAM ELEMENT NO.	PROJECT NO.
		TASK NO.	WORK UNIT ACCESSION NO.
11. TITLE (Include Security Classification) The Behavior of Microdisk and Microring Electrodes. Mass Transport to the Disk in the Unsteady State: Chronopotentiometry			
12. PERSONAL AUTHOR(S) M. Fleischmann and S. Pons			
13a. TYPE OF REPORT Technical	13b. TIME COVERED FROM 9/87 TO 7/88	14. DATE OF REPORT July 15, 1988 (Month, Day)	15. PAGE COUNT
16. SUPPLEMENTARY NOTATION			
17. COSATI CODES		18. SUBJECT TERMS (Continue on reverse if necessary and identify by block number)	
FIELD	GROUP	SUB-GROUP	
		microelectrodes , mass transport	
19. ABSTRACT (Continue on reverse if necessary and identify by block number) Attached.			
20. DISTRIBUTION/AVAILABILITY OF ABSTRACT <input checked="" type="checkbox"/> UNCLASSIFIED/UNLIMITED <input type="checkbox"/> SAME AS RPT <input type="checkbox"/> OTC USERS		21. ABSTRACT SECURITY CLASSIFICATION Unclassified	
22a. NAME OF RESPONSIBLE INDIVIDUAL Stanley Pons		22b. TELEPHONE (Include Area Code) (801)581-4760	22c. OFFICE SYMBOL

Copy available to DTIC does not permit fully legible reproduction

ABSTRACT

We describe the time dependent response of a finite disk electrode under conditions of constant applied flux (chronopotentiometry). The exact solution is recovered by solving the differential equations in the circular cylindrical coordinate system with the use of suitable discontinuous integrals. In addition, we present the result for the case of linear sweep amperometry, which will generally be more useful for controlled current experiments with microelectrodes.

Accession No.		
NTIS	DTIC	X
DTIC		
Unannounced		
Justification		
By		
Distribution		
Availability Codes		
Dist		
A-1		



The behavior of microdisk and microring electrodes. Mass transport to the disk in the unsteady state

Chronopotentiometry

Martin Fleischmann

Department of Chemistry, The University, Southampton, Hants. SO9 5NH (Great Britain)

Stanley Pons

Department of Chemistry, University of Utah, Salt Lake City, UT 84119 (U.S.A.)

(Received 9th February 1988; in revised form 3rd May 1988)

ABSTRACT

We describe the time dependent response of a finite disk electrode under conditions of constant applied flux (chronopotentiometry). The exact solution is recovered by solving the differential equations in the circular cylindrical coordinate system with the use of suitable discontinuous integrals. In addition, we present the result for the case of linear sweep amperometry, which will generally be more useful for controlled current experiments with microelectrodes.

INTRODUCTION

There has been much recent work on the analysis of mass transport to finite electrode geometries. One reason for this activity lies in the increased interest in new applications of microelectrodes [1]. The applicability of the preferred spherical microelectrode geometry has so far been somewhat restricted e.g., to the electrodeposition of ensembles [2,3] or single mercury droplets [4-6], the electrolysis of dispersions [7,8], and the dropping mercury microelectrode [9]. Disk, band, and the recently introduced ring microelectrodes [5,10-12], are in general more easily constructed, but the necessary mathematical analysis has so far proved to be rather intractable. The mathematical difficulties are due to the discontinuities at the edges of the electrodes (e.g. constant concentration or flux over the surface of the electrode, zero flux over the adjacent insulating surface). The diffusion limited flux becomes infinite at these discontinuities (the combined effects of the finite rates of the surface reactions and of the distribution of potential and concentration across

the surface i.e., the "tertiary current distribution," however, will limit the rates at the edges for real systems). Disk and ring microelectrodes have the advantage that quasi-spherical diffusion fields are established at relatively short times; in contrast, diffusion to line or band electrodes does not reach a steady state, the flux varying as $1/\ln t$. Spherical diffusion fields at small electrodes give rise to high rates of mass transport to the surface so that the kinetics of fast heterogeneous reactions and of fast reactions in solution can be studied under steady state conditions (e.g., see the previous analysis, [13]). While it is clear that fast reactions can always be studied by decreasing the size of the electrode, there are some applications that are amenable to study at "larger" microelectrodes. A variety of analytical and simulation procedures have been used in attempts to develop adequate descriptions of the chronoamperometric and chronopotentiometric responses at disk and ring electrodes e.g., see [11,13-26]. In this series of papers, we develop a general approach to the analysis of the non-steady state, and we apply the method here to the chronopotentiometric case for constant and uniform flux over the surface. The result is an exact expression that is valid at all times, and for any size disk, and is therefore applicable to conventional electroanalytical experiments, as well as those at microelectrodes. The approach to the problem is based on the properties of discontinuous integrals (see e.g., refs. 13, 28 and 29) which we have extended from the previous analysis (the prediction of the mass transfer coefficients for constant concentration and constant flux conditions in the steady state) to include time dependent mass transfer. In addition, we include the results for a linearly swept current experiment.

— Please
make sure
refs 27 & 30
are mentioned

27 and 28

THEORETICAL CONSIDERATIONS

General time dependent solution

For any simple electrochemical experiment involving a single reactant, we must solve the time dependent diffusion equation in circular cylindrical coordinates:

$$\frac{\partial c}{\partial t} = D \frac{\partial^2 c}{\partial r^2} + \frac{D}{r} \frac{\partial c}{\partial r} + D \frac{\partial^2 c}{\partial z^2} \quad (1)$$

where c is the concentration of the reactant, and r is the radial distance coordinate measured from the center of the disk electrode which is imbedded in the insulating plane at $z = 0$. The general initial condition is, at

$$r > 0, z > 0, t = 0 \quad c = c^\infty \quad (2)$$

where c^∞ is the bulk concentration. Laplace transformation of eqn. (2) gives

$$\frac{\partial^2 \bar{c}}{\partial r^2} + \frac{1}{r} \frac{\partial \bar{c}}{\partial r} + \frac{\partial^2 \bar{c}}{\partial z^2} - q^2 \bar{c} + \frac{c^\infty}{D} = 0 \quad (3)$$

where

$$q^2 = s/D \quad (4)$$

and s is the Laplace transformation variable. The last term on the LHS of eqn. (3) is

a constant and hence determines the particular integral of eqn. (1). We then seek the solution for the complementary function from

$$\frac{\partial^2 \bar{c}_{CF}}{\partial r^2} + \frac{1}{r} \frac{\partial \bar{c}_{CF}}{\partial r} + \frac{\partial^2 \bar{c}_{CF}}{\partial z^2} - q^2 \bar{c}_{CF} = 0 \tag{5}$$

Separations of variables of the form

$$c_{CF} = v \exp[-f(\lambda, q)z] \tag{6}$$

simplify the differential equation (5) to the familiar Bessel form

$$\frac{d^2 \bar{v}}{dr^2} + \frac{1}{r} \frac{d\bar{v}}{dr} + \alpha^2 \bar{v} = 0 \tag{7}$$

where

$$\alpha^2 = [f(\lambda, q)]^2 - q^2 \tag{8}$$

For instance, we can choose the simple form

$$f(\lambda, q) = (\alpha^2 + q^2)^{1/2} \tag{9}$$

so that

$$\bar{c}_{CF} = \bar{v} \exp[-(\alpha^2 + q^2)^{1/2} z] \tag{10}$$

and eqn. (7) is recovered from eqn. (5) with α independent of q . (The factors involved when considering a choice for this function will be discussed elsewhere.) Therefore, the solution to Bessel's differential equation (3) becomes

$$\bar{c} = \frac{c^\infty}{s} - \int_0^\infty g(\lambda, q) \exp(-f(\lambda, q)z) J_0(\alpha r) d\alpha \tag{11}$$

where J_0 is the Bessel function of the first kind, order 0, and we choose $g(\lambda, q)$ to satisfy the boundary conditions.

Chronopotentiometry

We consider here the solution for eqn. (11) for the chronopotentiometry problem for a constant a constant uniform flux $-Q(\text{mol cm}^{-2} \text{s}^{-1})$ over the surface at all $t > 0$. The boundary conditions at the surface of the electrode become

$$\begin{aligned} 0 \leq r < a, z = 0, t > 0 & \quad D \left[\frac{\partial c}{\partial z} \right] = -Q \\ r > a, z = 0, t > 0 & \quad D \left[\frac{\partial c}{\partial z} \right] = 0 \end{aligned} \tag{12}$$

From eqn. (11) we get eqn. (12)

We take the Laplace transform of eqns. (12), and substitute in eqn. (11) after differentiation under the integral and obtain, for $t > 0$,

$$D \left[\frac{\partial \bar{c}}{\partial z} \right] = -\frac{Q}{s} = -\int g(\lambda, q) f(\lambda, q) J_0(\alpha r) d\alpha \quad 0 < r < a, z = 0 \tag{13}$$

and

$$D \left[\frac{\partial \bar{c}}{\partial z} \right] = 0 \quad r > a, z = 0 \quad (14)$$

The boundary conditions suggest that we can apply the discontinuous integrals

$$\int_0^\infty J_0(\alpha r) J_1(\alpha a) d\alpha = \begin{cases} 0 & r > a \\ 1/2a & r = a \\ 1/a & r < a \end{cases} \quad (15)$$

in the solution of the problem. We determine the conditions for which $g(\lambda, q)$ fits the boundary conditions (13) and (14). From eqn. (13), we see that

$$\int_0^\infty g(\lambda, q) f(\lambda, q) J_0(\alpha r) d\alpha = \frac{Q}{Ds} \quad 0 < r < a, z = 0 \quad (18)$$

or

$$\frac{Ds}{Qa} \int_0^\infty g(\lambda, q) f(\lambda, q) J_0(\alpha r) d\alpha = \frac{1}{a} \quad (19)$$

Therefore if we let

$$g(\lambda, q) = \frac{J_1(\alpha a)}{f(\lambda, q)} \quad (20)$$

the complete solution to eqn. (3) having boundary conditions (13) and (14) is

$$\bar{c} = \frac{c^\infty}{s} - \frac{Qa}{Ds} \int_0^\infty \exp[-f(\lambda, q)z] J_0(\alpha r) J_1(\alpha a) \frac{d\alpha}{f(\lambda, q)} \quad (21)$$

and at $z = 0$,

$$\bar{c} = \frac{c^\infty}{s} - \frac{Qa}{Ds} \int_0^\infty J_0(\alpha r) J_1(\alpha a) \frac{d\alpha}{f(\lambda, q)} \quad (22)$$

We point out here that the interpretation of the arguments of the Bessel functions depends on the nature of the assumption of the form of $f(\lambda, q)$ and, indeed, on the nature of the experiment (e.g. compare with the discussion of the chronoamperometric case (31)). The use of the simple form (9) gives

$$\bar{c} = \frac{c^\infty}{s} - \frac{Qa}{Ds} \int_0^\infty J_0(\alpha r) J_1(\alpha a) \frac{d\alpha}{(\alpha^2 + q^2)^{1/2}} \quad (23)$$

for galvanostatic conditions with α now independent of q ; we can therefore invert immediately to the t -domain:

$$c = c^\infty - \frac{Qa}{D} \int_0^\infty J_0(\alpha r) J_1(\alpha a) \operatorname{erf}(D^{1/2} \alpha t^{1/2}) \frac{d\alpha}{\alpha} \quad (24)$$

where $\operatorname{erf}(y)$ denotes the error function.

[22]

We can evaluate the average concentration at $z = 0$ by integrating eqn. (24) over the surface of the disk:

$$c_{Av} = c^\infty - \frac{2Q}{D} \int_0^\infty [J_1(\alpha a)] \operatorname{erf}(D^{1/2} \alpha t^{1/2}) \frac{d\alpha}{\alpha^2} \quad (25)$$

With the substitutions

$$l^2 = Dt \quad (26)$$

$$\beta = \alpha l \quad (27)$$

eqn. (25) can be written in terms of dimensionless variables and parameters

$$\begin{aligned} c_{Av} &= c^\infty - \frac{2Qa}{D} \cdot \frac{1}{a} \int_0^\infty \left[J_1\left(\frac{\beta a}{l}\right) \right]^2 \operatorname{erf}(\beta) \frac{d\beta}{\beta^2} \\ &= c^\infty - \frac{2Qa}{D} \cdot \Phi_1\left(\frac{Dt}{a^2}\right) \end{aligned} \quad (28)$$

Av

The function Φ_1 is tabulated in Table 1 as a function of the dimensionless parameter (Dt/a^2) .

At long times and sufficiently small values of the flux, we do not observe a transition time and always reach the steady state value [13]

$$c_{Av} = c^\infty - \frac{8Qa}{3\pi D} \quad (29)$$

If Q is sufficiently large we will get a sharp transition time as the surface concentration of the reactant approaches zero; for this condition eqn. (28) can be written

$$\frac{2Qa}{Dc^\infty} \cdot \frac{1}{a} \int_0^\infty \left[J_1\left(\frac{\beta a}{l}\right) \right]^2 \operatorname{erf}(\beta) \frac{d\beta}{\beta^2} = \frac{2Qa}{Dc^\infty} \cdot \Phi_1\left(\frac{Dt}{a^2}\right) = 1 \quad (30)$$

from which the transition time can be obtained. The problems to be discussed in this series of papers are always cast in the form of such definite integrals, and these frequently converge slowly. Accurate evaluation is readily obtained, however, through the use of standard Bulirsch-Stoer numerical integration methods. In addition, convergence can always be speeded by suitable rearrangements. For instance, eqn. (30) can be rewritten in the equivalent form

$$\frac{2Qa}{Dc^\infty} \cdot \frac{1}{a} \left\{ \int_0^\infty \left[J_1\left(\frac{\beta a}{l}\right) \right]^2 \frac{d\beta}{\beta^2} + \int_0^\infty \left[J_1\left(\frac{\beta a}{l}\right) \right]^2 (\operatorname{erf}(\beta) - 1) \frac{d\beta}{\beta^2} \right\} \quad (31)$$

[27]

The value of the first integral is known to be $4a/3\pi l$ [25]. The second integral converges rapidly since the error function approaches 1 with increasing β . Figure 1 illustrates the square root of the dimensionless transition times Dt/a^2 as a function of the inverse of the dimensionless flux $2Qa/Dc^\infty$. The values are close to those predicted by Aoki and Osteryoung [18] even though these authors based their analysis on a uniform surface concentration boundary condition; the expressions

TABLE 1

Values of the function $\Phi_1(Dt/a^2)$

Dt/a^2	$\Phi_1(Dt/a^2)$	Dt/a^2	$\Phi_1(Dt/a^2)$
4.0000×10^0	2.1217×10^{-4}	2.7778	2.0533×10^{-1}
2.7778×10^0	2.5460×10^{-4}	2.0408	2.3064×10^{-1}
2.0408×10^0	2.9702×10^{-4}	1.5625	2.5372×10^{-1}
1.5625×10^0	3.3944×10^{-4}	1.2346	2.7473×10^{-1}
1.2346×10^0	3.8186×10^{-4}	1.0000	2.9381×10^{-1}
1.0000×10^0	4.2427×10^{-4}	2.5000×10^{-1}	4.1045×10^{-1}
2.5000×10^3	8.4826×10^{-4}	1.1111×10^{-1}	4.5961×10^{-1}
1.1111×10^3	1.2720×10^{-3}	6.2500×10^{-2}	4.8524×10^{-1}
6.2500×10^4	1.6954×10^{-3}	4.0000×10^{-2}	5.0085×10^{-1}
4.0000×10^4	2.1185×10^{-3}	2.7778×10^{-2}	5.1132×10^{-1}
2.7778×10^4	2.5414×10^{-3}	2.0408×10^{-2}	5.1883×10^{-1}
2.0408×10^4	2.9640×10^{-3}	1.5625×10^{-2}	5.2448×10^{-1}
1.5625×10^4	3.3863×10^{-3}	1.2346×10^{-2}	5.2888×10^{-1}
1.2346×10^4	3.8083×10^{-3}	1.0000×10^{-2}	5.3240×10^{-1}
1.0000×10^4	4.2300×10^{-3}	2.5000×10^{-3}	5.4828×10^{-1}
2.5000×10^3	8.4318×10^{-3}	1.1111×10^{-3}	5.5358×10^{-1}
1.1111×10^3	1.2605×10^{-2}	6.2500×10^{-4}	5.5623×10^{-1}
6.2500×10^2	1.6751×10^{-2}	4.0000×10^{-4}	5.5783×10^{-1}
4.0000×10^2	2.0868×10^{-2}	2.7778×10^{-4}	5.5889×10^{-1}
2.7778×10^2	2.4957×10^{-2}	2.0408×10^{-4}	5.5964×10^{-1}
2.0408×10^2	2.9018×10^{-2}	1.5625×10^{-4}	5.6021×10^{-1}
1.5625×10^2	3.3051×10^{-2}	1.2346×10^{-4}	5.6065×10^{-1}
1.2346×10^2	3.7055×10^{-2}	1.0000×10^{-4}	5.6101×10^{-1}
1.0000×10^2	4.1032×10^{-2}	2.5000×10^{-5}	5.6260×10^{-1}
2.5000×10^1	7.9259×10^{-2}	1.1111×10^{-5}	5.6313×10^{-1}
1.1111×10^1	1.1472×10^{-1}	6.2500×10^{-6}	5.6340×10^{-1}
6.2500	1.4749×10^{-1}	4.0000×10^{-6}	5.6356×10^{-1}

they derived could not be inverted exactly over the entire time range whereas eqn. (30) is exact. It should be noted that the constant flux condition is more likely to apply for most of the duration of the experiment rather than the constant surface concentration condition, the actual behavior lying between these two limiting conditions. A more correct formulation of the boundary condition on the disk for an irreversible reaction, say, would be

$$\partial c / \partial z = kc \quad 0 < r < a, z = 0 \quad (32)$$

For a cathodic reaction, say, we would write

$$k = k_0 \exp[\alpha EF/RT] = \text{constant} \quad 0 < r < a \quad (33)$$

provided we neglect the effects of the distribution of potential in the solution k , i.e. we neglect the primary or secondary current distribution. Equation (32) shows that we cannot strictly speaking assume either the flux or the concentration to be constant over the surface of the disk. However, the close agreement of the transition




Fig. 1. Plot of the square root of the dimensionless transition time $(Dt/a^2)^{1/2}$ as a function of the inverse of the dimensionless flux $(2Qa/Dc^\infty)$.

[29]

times derived using these two approaches shows that the interpretation is not very sensitive to the nature of the assumptions; subsequent papers (31) will show that this is also the case for other types of experiment. We note that the constant flux condition will hold at low current densities (as in relaxation experiments) while the constant concentration condition may be approached in the limiting current region (see, however, below) so that the actual behavior must lie between these two limits. Thus, while it would be possible to develop the conditions (31) and (32), it is unlikely that the accuracy of the experimental data would allow an assessment of the range of validity of the various assumptions. Furthermore, the application of eqn. (31) would also require the consideration of the distribution of the potential in the solution, i.e. we have to consider the tertiary current distribution. We can predict, to some extent, the probable outcome of such analyses: it is unlikely that the "throwing power" of any practicable system would ever be sufficiently low that the current density could deviate appreciably from uniformity over the surface of a microdisk (note that an infinite flux to the edge of the disk is clearly impossible even on the limiting current plateau!). We therefore consider that the constant flux boundary condition will hold under most experimental conditions.

S
analysis based on

Figure 1 shows the expected linear dependence at high values of $2Qa/Dc^\infty$ where we observe essentially linear diffusion to the electrode followed by a rapid rise at low values of $2Qa/Dc^\infty$ as this parameter approaches the condition required for the observation of a steady state

$$\frac{2Qa}{Dc^\infty} \approx \frac{4}{3\pi} = 0.4244 \quad \frac{3\pi}{4} = 2.3562 \quad (34)$$

Dc^∞

The calculated values of c_{∞} may be used to derive the potential-time curves for appropriate models of the electrode reactions. For instance, in the case of simple Butler-Volmer kinetics, we obtain

$$\frac{FQ}{i_0} + \frac{2Qa}{Dc^{\infty}} \Phi_3 \left(\frac{Dt}{a^2} \right) \left\{ \exp\left(\frac{-\alpha\eta F}{RT}\right) + \exp\left(\frac{(1-\alpha)\eta F}{RT}\right) \right\} \\ = \exp\left(\frac{-\alpha\eta F}{RT}\right) - \exp\left(\frac{(1-\alpha)\eta F}{RT}\right) \quad (35)$$

which shows that the transients are a function of α , FQ/i_0 and $2Qa/Dc^{\infty}$.

Linear sweep amperometry

It is clear that since there is rapid attainment of steady state diffusion to microdisk electrodes, constant current experiments may not be generally useful. It is difficult to determine the appropriate galvanostatic condition that will give a transition time within a convenient experimental time scale. It is therefore more straightforward to apply time dependent fluxes to the surface. If we consider, for example, the simplest case of a linear current ramp

$$Q(t) = \gamma t \quad (36)$$

we can immediately rewrite eqn. (23) in the general form [1,13,31]

$$\bar{c} = \frac{c^{\infty}}{s} - \frac{\gamma a}{Ds^2} \int_0^{\infty} J_0(ar) J_1(aa) \frac{d\alpha}{(\alpha^2 + q^2)^{1/2}} \quad (37)$$

and by the same methods obtain the transition time

$$\frac{4\gamma ta}{Dc^{\infty}} \cdot \frac{1}{a} \int_0^{\infty} \left[J_1\left(\beta \frac{a}{r}\right) \right]^2 \left[\int_0^{\beta} y \operatorname{erf}(y) dy \right] \frac{d\beta}{\beta^4} = 1 \quad (38)$$

or

$$\frac{4\gamma ta}{Dc^{\infty}} \cdot \Phi_3 \left(\frac{Dt}{a^2} \right) = 1 \quad (39)$$

If now the current is swept from zero, a very sharp transition is observed in the potential-time plot. For simple Butler-Volmer kinetics, the shape of the response can be determined from

$$\frac{F\gamma t}{L_0} + \frac{FQ}{i_0} + \frac{4\gamma ta}{Dc^{\infty}} \cdot \Phi_3 \left(\frac{Dt}{a^2} \right) \left\{ \exp\left(\frac{-\alpha\eta F}{RT}\right) + \exp\left(\frac{(1-\alpha)\eta F}{RT}\right) \right\} \\ = \exp\left(\frac{-\alpha\eta F}{RT}\right) - \exp\left(\frac{(1-\alpha)\eta F}{RT}\right) \quad (40)$$

Table 2 gives values of Φ_3 as a function of Dt/a^2 .

The application of other boundary conditions representing other electrochemical experiments (e.g. cyclic amperometry, ac impedance measurements, and to cases involving reactions in solution coupled to the electrode processes) to this form of

TABLE 2

Values of the function $\Phi_1(Dt/a^2)$

Dt/a^2	$\Phi_1(Dt/a^2)$	Dt/a^2	$\Phi_1(Dt/a^2)$
2.0000×10^{-2}	7.5112×10^{-5}	5.0000	3.6511×10^{-1}
3.1623×10^{-2}	1.8778×10^{-4}	7.0711	3.9321×10^{-1}
3.5355×10^{-2}	2.3473×10^{-4}	1.0000	4.0842×10^{-1}
3.7796×10^{-2}	2.6826×10^{-4}	1.1180	4.1155×10^{-1}
4.4721×10^{-2}	3.7556×10^{-4}	1.1952	4.1313×10^{-1}
5.0000×10^{-2}	4.6945×10^{-4}	1.4142	4.1631×10^{-1}
7.0711×10^{-2}	9.3831×10^{-4}	1.5811	4.1792×10^{-1}
1.0000×10^{-1}	1.8728×10^{-3}	2.2361	4.2116×10^{-1}
1.1180×10^{-1}	2.3385×10^{-3}	3.1623	4.2277×10^{-1}
1.1952×10^{-1}	2.6706×10^{-3}	3.7796	4.2327×10^{-1}
1.4142×10^{-1}	3.7299×10^{-3}	4.4721	4.2360×10^{-1}
1.5811×10^{-1}	4.6526×10^{-3}	5.0000	4.2376×10^{-1}
2.2361×10^{-1}	9.2073×10^{-3}	7.0711	4.2409×10^{-1}
3.1623×10^{-1}	1.8023×10^{-2}	1.0000×10^2	4.2425×10^{-1}
3.5355×10^{-1}	2.2285×10^{-2}	1.1180×10^2	4.2428×10^{-1}
3.7796×10^{-1}	2.5269×10^{-2}	1.1952×10^2	4.2430×10^{-1}
4.4721×10^{-1}	3.4486×10^{-2}	1.4142×10^2	4.2433×10^{-1}
5.0000×10^{-1}	4.2138×10^{-2}	1.5811×10^2	4.2435×10^{-1}
7.0711×10^{-1}	7.4851×10^{-2}	2.2361×10^2	4.2438×10^{-1}
1.0000	1.1751×10^{-1}	3.1623×10^2	4.2440×10^{-1}
1.1180	1.3151×10^{-1}	3.5355×10^2	4.2440×10^{-1}
1.1952	1.3971×10^{-1}	3.7796×10^2	4.2440×10^{-1}
1.4142	1.5820×10^{-1}	4.4721×10^2	4.2440×10^{-1}
1.5811	1.7040×10^{-1}	5.0000×10^2	4.2441×10^{-1}
2.2361	2.2654×10^{-1}	7.0711×10^2	4.2441×10^{-1}
3.1623	2.9695×10^{-1}	1.0000×10^3	4.2441×10^{-1}
3.5355	3.1727×10^{-1}	3.1623×10^3	4.2441×10^{-1}
4.4721	3.5219×10^{-1}	1.0000×10^4	4.2441×10^{-1}

These replace
with new
values
Attached.

[30]

analysis, as well as extension of the analysis to include the ring geometry will be discussed elsewhere [32].

ACKNOWLEDGEMENT

We thank the Office of Naval Research for support of this work.

GLOSSARY OF SYMBOLS USED

a	Radius of disk, cm
c	Concentration, mol cm ⁻³
c^∞	Bulk concentration, mol cm ⁻³
c_{AV}	Average concentration, mol cm ⁻³
c_{CF}	Concentration complementary function
c^s	Surface concentration, mol cm ⁻³

D	Diffusion coefficient, $\text{cm}^2 \text{s}^{-1}$
E	Electrode potential, V
F	Faraday constant, 96485 C mol^{-1}
i_0	Exchange current density, A cm^{-2}
J_0, J_1	Bessel functions
k	Heterogeneous rate constant, cm s^{-1}
k^0	Heterogeneous standard rate constant, cm s^{-1}
l	$(Dr)^{1/2}$
q	$(s/D)^{1/2}$
Q	Flux, $\text{mol cm}^{-2} \text{s}^{-1}$
R	Gas constant, $8.314 \text{ J mol}^{-1} \text{K}^{-1}$
r	Radial coordinate, cm
s	Laplace transform variable
t	Time, s
T	Temperature, K
v	Concentration amplitude
z	Coordinate normal to plane of disk, cm
α	Transfer coefficient (when in exponent)
α	Continuous dummy integration variable
β	al
γ	Flux sweep rate, $\text{mol cm}^{-2} \text{s}^{-2}$
λ	Continuous dummy integration variable
η	Overpotential, V
Φ_1	$\frac{l}{a} \int_0^a \left[J_1 \left(\frac{\beta a}{l} \right) \right]^2 \text{erf}(\beta) \frac{d\beta}{\beta^2}$
Φ	$\frac{l}{a} \int_0^\infty \left[J_1 \left(\beta \frac{a}{l} \right) \right]^2 \left[\int_0^\beta y \text{erf}(y) dy \right] \frac{d\beta}{\beta^4}$
τ	Transition time, s

REFERENCES

- 1 M. Fleischmann, S. Pons, D. Rolison and P. Schmidt, *Ultramicroelectrodes*, Datatech Science, Morganton, NC, 1987.
- 2 P. Bindra, A.P. Brown, M. Fleischmann and D. Pletcher, *J. Electroanal. Chem.*, 58 (1975) 31.
- 3 P. Bindra, A.P. Brown, M. Fleischmann and D. Pletcher, *J. Electroanal. Chem.*, 58 (1975) 39.
- 4 G. Gunawardena, G.J. Hills and B. Scharifker, *J. Electroanal. Chem.*, 130 (1981) 99.
- 5 A.M. Bond, M. Fleischmann, S.B. Khoo, S. Pons and J. Robinson, Extended Abstracts 165th Meeting of the Electrochemical Society, May 1984, Electrochemical Society, Pennington, NJ, 1984.
- 6 R.M. Wightman and K.R. Wehmeyer, *Anal. Chem.*, 57 (1985) 1989.
- 7 M. Fleischmann, J. Ghoroghchian and S. Pons, *J. Phys. Chem.*, 89 (1985) 5530.
- 8 M. Fleischmann, J. Ghoroghchian, S. Pons and D. Rolison, *J. Phys. Chem.*, 90 (1986) 6392.
- 9 J. Pons, J. Daschbach, M. Fleischmann and S. Pons, *J. Electroanal. Chem.*, 239 (1988) 427.
- 10 J.S. Symanski and S. Bruckenstein, Extended Abstracts 165th Meeting of the Electrochemical Society, May 1984, Electrochemical Society, Pennington, NJ, 1984, p. 527.
- 11 M. Fleischmann, S. Bandyopadhyay and S. Pons, *J. Phys. Chem.*, 89 (1985) 5537.
- 12 M.A. Dayton, J.C. Brown, K.J. Stutts and R.M. Wightman, *Anal. Chem.*, 52 (1980) 946.

- 13 M. Fleischmann and S. Pons, *J. Electroanal. Chem.*, 222 (1987) 107.
 14 J.B. Flanagan and L. Marcoux, *J. Phys. Chem.*, 77 (1973) 1051.
 15 M. Kakihana, H. Ikendi, G.P. Sato and K. Tokuda, *J. Electroanal. Chem.*, 122 (1981) 19.
 16 J. Heinze, *J. Electroanal. Chem.*, 124 (1981) 73.
 17 K.B. Oldham, *J. Electroanal. Chem.*, 122 (1981) 1.
 18 K. Aoki and J. Osteryoung, *J. Electroanal. Chem.*, 122 (1981) 19.
 19 B. Speiser and S. Pons, *Can. J. Chem.*, 60 (1982) 1352.
 20 B. Speiser and S. Pons, *Can. J. Chem.*, 60 (1982) 2463.
 21 K. Aoki, K. Akimoto, K. Tokuda, H. Matsuda and J. Osteryoung, *J. Electroanal. Chem.*, 182 (1985) 281.
 22 J. Cassidy and S. Pons, *Can. J. Chem.*, 63 (1985) 3577.
 23 T. Hepel, W. Plot and J. Osteryoung, *J. Phys. Chem.*, 87 (1983) 1278.
 24 T. Hepel and J. Osteryoung, *J. Phys. Chem.*, 86 (1982) 1406.
 25 D. Shoup and A. Szabo, *J. Electroanal. Chem.*, 140 (1982) 237.
 26 K. Aoki and J. Osteryoung, *J. Electroanal. Chem.*, 160 (1984) 335.
~~27 M. Fleischmann and J. Harrison, *Electrochim. Acta*, 11 (1966) 949.~~
 27 G.N. Watson, *A Treatise on the Theory of Bessel Functions*, 2nd ed., Cambridge University Press, Cambridge, 1948.
 28 H.S. Carslaw and J.C. Jaeger, *Conduction of Heat in Solids*, Clarendon Press, Oxford, 1959.
~~29 M. Fleischmann, F. Lasserre and J. Robinson, *J. Electroanal. Chem.*, 177 (1984) 113.~~
 29 M. Fleischmann, J. Daschbach and S. Pons, *J. Electroanal. Chem.*, JEC9788.
 30 M. Fleischmann and S. Pons, *J. Electroanal. Chem.*, JEC9887, 9786.

J JEC hrs OK?
 yes

TECHNICAL REPORT DISTRIBUTION LIST, GEN

	<u>No. Copies</u>		<u>No. Copies</u>
Office of Naval Research Attn: Code 1113 800 N. Quincy Street Arlington, Virginia 22217-5000	2	Dr. David Young Code 334 NORDA NSTL, Mississippi 39529	1
Dr. Bernard Douda Naval Weapons Support Center Code 50C Crane, Indiana 47522-5050	1	Naval Weapons Center Attn: Dr. Ron Atkins Chemistry Division China Lake, California 93555	1
Naval Civil Engineering Laboratory Attn: Dr. R. W. Drisko, Code L52 Port Hueneme, California 93401	1	Scientific Advisor Commandant of the Marine Corps Code RD-1 Washington, D.C. 20380	1
Defense Technical Information Center Building 5, Cameron Station Alexandria, Virginia 22314	12 high quality	U.S. Army Research Office Attn: CRD-AA-IP P.O. Box 12211 Research Triangle Park, NC 27709	1
DTNSRDC Attn: Dr. H. Singerman Applied Chemistry Division Annapolis, Maryland 21401	1	Mr. John Boyle Materials Branch Naval Ship Engineering Center Philadelphia, Pennsylvania 19112	1
Dr. William Tolles Superintendent Chemistry Division, Code 6100 Naval Research Laboratory Washington, D.C. 20375-5000	1	Naval Ocean Systems Center Attn: Dr. S. Yamamoto Marine Sciences Division San Diego, California 91232	1

ABSTRACTS DISTRIBUTION LIST, SDIO/IST

Dr. Robert A. Osteryoung
Department of Chemistry
State University of New York
Buffalo, NY 14214

Dr. Douglas N. Bennion
Department of Chemical Engineering
Brigham Young University
Provo, UT 84602

Dr. Stanley Pons
~~Department of Chemistry~~
University of Utah
Salt Lake City, UT 84112

Dr. H. V. Venkatesetty
Honeywell, Inc.
10701 Lyndale Avenue South
Bloomington, MN 55420

Dr. J. Foos
EIC Labs Inc.
111 Downey St.
Norwood, MA 02062

Dr. Neill Weber
Ceramatec, Inc.
163 West 1700 South
Salt Lake City, UT 84115

Dr. Subhash C. Narang
SRI International
333 Ravenswood Ave.
Menlo Park, CA 94025

Dr. J. Paul Pemsler
Castle Technology Corporation
52 Dragon Ct.
Woburn, MA 01801

Dr. R. David Rauh
EIC Laboratory Inc.
111 Downey Street
Norwood, MA 02062

Dr. Joseph S. Foos
EIC Laboratories, Inc.
111 Downey Street
Norwood, Massachusetts 02062

Dr. Donald M. Schleich
Department of Chemistry
Polytechnic Institute of New York
333 Jay Street
Brooklyn, New York 01

Dr. Stan Szpak
Code 633
Naval Ocean Systems Center
San Diego, CA 92152-5000

Dr. George Blomgren
Battery Products Division
Union Carbide Corporation
25225 Detroit Rd.
Westlake, OH 44145

Dr. Ernest Yeager
Case Center for Electrochemical
Science
Case Western Reserve University
Cleveland, OH 44106

Dr. Mel Miles
Code 3852
Naval Weapons Center
China Lake, CA 93555

Dr. Ashok V. Joshi
Ceramatec, Inc.
2425 South 900 West
Salt Lake City, Utah 84119

Dr. W. Anderson
Department of Electrical &
Computer Engineering
SUNY - Buffalo
Amherst, Massachusetts 14260

Dr. M. L. Gopikanth
Chemtech Systems, Inc.
P.O. Box 1067
Burlington, MA 01803

Dr. H. F. Gibbard
Power Conversion, Inc.
495 Boulevard
Elmwood Park, New Jersey 07407

DL/1113/87/2

ABSTRACTS DISTRIBUTION LIST, SDIO/IST

Dr. V. R. Koch
Covalent Associates
52 Dragon Court
Woburn, MA 01801

Dr. Randall B. Olsen
Chronos Research Laboratories, Inc.
4186 Sorrento Valley Blvd.
Suite H
San Diego, CA 92121

Dr. Alan Hooper
Applied Electrochemistry Centre
Harwell Laboratory
Oxfordshire, OX11 0RA UK

Dr. John S. Wilkes
Department of the Air Force
The Frank J. Seiler Research Lab.
United States Air Force Academy
Colorado Springs, CO 80840-6528

Dr. Gary Bullard
Pinnacle Research Institute, Inc.
10432 N. Tantan Avenue
Cupertino, CA 95014

Dr. J. O'M. Bockris
Ementech, Inc.
Route 5, Box 946
College Station, TX 77840

Dr. Michael Binder
Electrochemical Research Branch
Power Sources Division
U.S. Army Laboratory Command
Fort Monmouth, New Jersey 07703-5000

Professor* Martin Fleischmann
Department of Chemistry
University of Southampton
Southampton, Hants, SO9 5NH UK