

Reproduced by the

ARMED SERVICES TECHNICAL INFORMATION AGENCY ARLINGTON HALL STATION ARLINGTON 12, VIRGINIA



UNCLASSIFIED

NOTICE: When government or other drawings, specifications or other data are used for any purpose other than in connection with a definitely related government procurement operation, the U. S. Government thereby incurs no responsibility, nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use or sell any patented invention that may in any way be related thereto.

ŀ-

AFCRL-62-763

2

6

949

2

METER NSTIA

THE USE OF STATISTICAL METHODS IN THE DETERMINATION OF THE PARAMETERS OF LINEAR MICROWAVE JUNCTIONS

63-2-3

معالمها والمراجا فتقصف بمحاصيه ووارا والمنار

Ъy

S. W. Maley

UNIVERSITY OF COLORADO Department of Electrical Engineering Boulder, Colorado

SCIENTIFIC REPORT NO. 5

Contract No. AF 19(604)-4556

1 September 1962

Period Covered

Calendar Years 1960-1961

Project No. 4600 Task No. 460004

Prepared for

ELECTRONICS RESEARCH DIRECTORATE AIR FORCE CAMBRIDGE RESEARCH LABORATORIES OFFICE OF AEROSPACE RESEARCH UNITED STATES AIR FORCE BEDFORD, MASSACHUSETTS THE USE OF STATISTICAL METHODS IN THE DETERMINATION OF THE PARAMETERS OF LINEAR MICROWAVE JUNCTIONS ŝ

-

by

S. W. Maley

UNIVERSITY OF COLORADO Department of Electrical Engineering Boulder, Colorado

SCIENTIFIC REPORT NO. 5

Contract No. AF 19(604)-4556

1 September 1962

Period Covered

Calendar Years 1960-1961

Project No. 4600 Task No. 460004

Prepared for

ELECTRONICS RESEARCH DIRECTORATE AIR FORCE CAMBRIDGE RESEARCH LABORATORIES OFFICE OF AEROSPACE RESEARCH UNITED STATES AIR FORCE BEDFORD, MASSACHUSETTS Requests for additional copies by Agencies of the Department of Defense, their contractors, and other Government agencies should be directed to the:

> ARMED SERVICES TECHNICAL INFORMATION AGENCY ARLINGTON HALL STATION ARLINGTON 12, VIRGINIA

Department of Defense contractors must be established for ASTIA services or have their "need to know" certified by the cognizant military agency of their project or contract. All other persons and organizations should apply to the:

> U. S. DEPARTMENT OF COMMERCE OFFICE OF TECHNICAL SERVICES WASHINGTON 25, D. C.

THE USE OF STATISTICAL METHODS IN THE DETERMINATION OF THE PARAMETERS OF LINEAR MICROWAVE JUNCTIONS

1.0 GENERAL ELECTRICAL NETWORKS

1.1 Introduction

A linear network transforms quantities such as impedance, admittance, and reflection coefficient by a linear fractional transformation. A commonly occurring problem is the determination of the parameters of this transformation from measurements on the network. A number of methods of determining the parameters have been discussed in the literature. [Beatty, Macphereson, 1953; Deschamps, 1953; Felson, Oliver, 1954; Mittra, King 1962]. Most of these methods are graphical and have limitations on the accuracy obtainable with them. The method described below makes use of statistical techniques to give values for the parameters which are the best, in the least squares sense, obtainable from the measured data. The use of a greater amount of measured data will reduce the probable error in the results. This is in contract to most other methods in which greater accuracy can be obtained only by increasing the precision of the individual measurements. A particular application of this technique to microwave junctions is discussed in Section 2.

1.2 Theory

Let the quantity X be transformed into the quantity Y by a network which may be described by the parameters A, B, and C. The transformation may be written

$$Y = \frac{A + BX}{-C + X} . \tag{1.1}$$

÷....

12

The problem is to determine the parameters A, B, and C from measured values of X and Y. The reason for the negative sign on the C will become apparent later. Let measured values of X be denoted by X_j , j = 1, 2, ..., and let the corresponding measured values of Y be Y_j , j = 1, 2, ... If three measured sets of corresponding values of X and Y are known, they can be inserted into equation (1.1) to give 3 linear equations which may then be solved for A, B, and C. To use a greater number of measurements and thereby obtain greater reliability of the result, the method of multiple linear regression [Hoel, 1954] may be used. Equation (1.1) may be written

$$A + BX + CY = XY.$$
 (1.2)

Let the measured data consist of the n sets of values, X_i , Y_i , and $X_i Y_i$ where i = i, 2, 3, ..., n. n must be equal to or greater than 3 for a unique solution for A, B, and C to exist. The normal equations [Hoel, 1954] corresponding to equation (1.2) may be written:

An + B
$$\sum_{j=1}^{n} X_{j} + C \sum_{j=1}^{n} Y_{j} = \sum_{j=1}^{n} X_{j} Y_{j},$$

A $\sum_{j=1}^{n} X_{j} + B \sum_{j=1}^{n} (X_{j})^{2} + C \sum_{j=1}^{n} Y_{j} X_{j} = \sum_{j=1}^{n} (X_{j})^{2} Y_{j},$ (1.3)
A $\sum_{j=1}^{n} Y_{j} + B \sum_{j=1}^{n} X_{j} Y_{j} + C \sum_{j=1}^{n} (Y_{j})^{2} = \sum_{j=1}^{n} X_{j} (Y_{j})^{2}.$

These equations can be solved for the 3 unknowns, A, B, and C. The use of the negative sign in equation (1.1) makes the coefficient matrix in (1.3) symmetric; this sometimes simplifies the solution of the equations. This method of determining A, B, and C is the best in the sense of minimizing the sum of the squares of the differences between the measured values of XY and the values of XY as found from equation (1.2) in terms of the corresponding measured values of X and Y, or in symbols, the minimizing of the quantity

$$\sum_{j=1}^{n} (x_j y_j - A - B x_j - C y_j)^2 .$$

A modification of the above procedure sometimes shortens the calculations. Make the following changes of variables in equation (1.2):

$$x = X - \overline{X} ,$$

$$y = Y - \overline{Y} ,$$

$$xy = XY - (\overline{XY}) ,$$

$$\overline{X} = \frac{1}{n} \sum_{j=1}^{n} X_{j} ,$$
(1.4)

$$\overline{Y} = \frac{1}{n} \sum_{j=1}^{n} Y_{j},$$

$$(\overline{XY}) = \frac{1}{n} \sum_{j=1}^{n} X_{j}Y_{j}.$$
(1.5)

Then equation (1.2) becomes

$$a + Bx + Cy = xy$$
, (1.6)

where

.

$$a = A + B\overline{X} + C\overline{Y} - (\overline{XY}). \qquad (1.7)$$

The quantities x_j , y_j , and $(xy)_j$ will be defined as follows:

$$x_{j} = X_{j} - \overline{X} ,$$

$$y_{j} = Y_{j} - \overline{Y} ,$$

$$(1.8)$$

$$(xy)_{j} = X_{j}Y_{j} - (\overline{XY}) .$$

where

Now the normal equations corresponding to equation (1.6) are

an + B
$$\sum_{j=1}^{n} x_{j} + C \sum_{j=1}^{n} y_{j} = \sum_{j=1}^{n} (xy)_{j}$$
,
a $\sum_{j=1}^{n} x_{j} + B \sum_{j=1}^{n} x_{j}^{2} + C \sum_{j=1}^{n} x_{j}y_{j} = \sum_{j=1}^{n} (xy)_{j} x_{j}$, (1.9)
a $\sum_{j=1}^{n} y_{j} + B \sum_{j=1}^{n} x_{j}y_{j} + C \sum_{j=1}^{n} y_{j}^{2} = \sum_{j=1}^{n} (xy)_{j} Y_{j}$.

It is apparent from equations (1.4) and (1.5) that

$$\sum_{j=1}^{n} x_{j} = \sum_{j=1}^{n} y_{j} = \sum_{j=1}^{n} (xy)_{j} = 0.$$
 (1.10)

Therefore the first of equations (1.9) reduces to

$$a = 0$$
 . (1.11)

The second and third of equations (1.9) may now be solved for B and C.

$$B = \frac{\sum_{j=1}^{n} (xy)_{j} x_{j} \sum_{j=1}^{n} y_{j}^{2} - \sum_{j=1}^{n} x_{j}y_{j} \sum_{j=1}^{n} (xy)_{j} y_{j}}{\sum_{j=1}^{n} x_{j}^{2} \sum_{j=1}^{n} y_{j}^{2} - \left[\sum_{j=1}^{n} x_{j} y_{j}\right]^{2}} .$$

$$(1.12)$$

$$C = \frac{\sum_{j=1}^{n} x_{j}^{2} \sum_{j=1}^{n} (xy)_{j} y_{j} - \sum_{j=1}^{n} x_{j}y_{j} \sum_{j=1}^{n} (xy)_{j} x_{j}}{\sum_{j=1}^{n} x_{j}^{2} \sum_{j=1}^{n} y_{j}^{2} - \left[\sum_{j=1}^{n} x_{j} y_{j}\right]^{2}} .$$

Finally A may be obtained from equations (1.7) and (1.11).

$$A = \overline{X}\overline{Y} - B\overline{X} - C\overline{Y} . \qquad (1.13)$$

In general the variables X and Y as well as the parameters A, B, and C in equation (1.1) will be complex. It is usually more convenient to work in terms of the real and imaginary parts of complex quantities. Let the real part of a quantity, say x, be denoted by a single prime and the imaginary part by a double prime; thus x = x' + ix'' where $i = \sqrt{-1}$. Using this notation, definitions (1.4) and (1.5) become

$$x' = X' - \overline{X}', \qquad x'' = X'' - \overline{X}'',$$
$$y' = Y' - \overline{Y}', \qquad y'' = Y'' - \overline{Y}'', \qquad (1.14)$$
$$(xy)' = X'Y' - X''Y'' - (\overline{XY})', \qquad (xy)'' = X'Y'' + X''Y' - (\overline{XY})''$$

where

$$\overline{X}' = \frac{1}{n} \sum_{j=1}^{n} X_{j}', \qquad \overline{X}'' = \frac{1}{n} \sum_{j=1}^{n} X_{j}'',$$

$$\overline{\overline{Y}}' = \frac{1}{n} \sum_{j=1}^{n} Y_{j}', \qquad \overline{\overline{Y}}'' = \frac{1}{n} \sum_{j=1}^{n} Y_{j}'', \qquad (1.15)$$

$$(\overline{XY})' = \frac{1}{n} \sum_{j=1}^{n} X_{j}'Y_{j}' - \frac{1}{n} \sum_{j=1}^{n} X_{j}''Y_{j}', \qquad (\overline{XY})'' = \frac{1}{n} \sum_{j=1}^{n} X_{j}'Y_{j}'' + \frac{1}{n} \sum_{j=1}^{n} X_{j}''Y_{j}'.$$

Equations (1.8) become

$$x_j = X_j - \overline{X}'$$
, $x_j = X_j - \overline{X}''$,

$$y_{j} = Y_{j} - \overline{Y}', \qquad y_{j} = Y_{j}' - \overline{Y}'', \qquad (1.16)$$

$$(\mathbf{x}\mathbf{y})^{\mathbf{i}}_{\mathbf{j}} = X_{\mathbf{j}}^{\mathbf{i}}Y_{\mathbf{j}}^{\mathbf{i}} - X_{\mathbf{j}}^{\mathbf{i}}Y_{\mathbf{j}}^{\mathbf{i}} - (\overline{\mathbf{X}}\overline{\mathbf{Y}})^{\mathbf{i}}, \qquad (\mathbf{x}\mathbf{y})^{\mathbf{i}}_{\mathbf{j}} = X_{\mathbf{j}}^{\mathbf{i}}Y_{\mathbf{j}}^{\mathbf{i}} + X_{\mathbf{j}}^{\mathbf{i}}Y_{\mathbf{j}}^{\mathbf{i}} - (\overline{\mathbf{X}}\overline{\mathbf{Y}})^{\mathbf{i}}.$$

The definitions given in (1.14), (1.15), and (1.16) may now be substituted into (1.12) and (1.13) to give complex expressions for A, B, and C.

$$B = \left\{ \sum_{j=1}^{n} \left[(xy)_{j}^{i} + i(xy)_{j}^{i} \right] (x_{j}^{i} + ix_{j}^{i}) \sum_{j=1}^{n} (y_{j}^{i} + iy_{j}^{i})^{2} - \sum_{j=1}^{n} (x_{j}^{i} + ix_{j}^{i})(y_{j}^{i} + iy_{j}^{i}) \sum_{j=1}^{n} \left[(xy)_{j}^{i} + i(xy)_{j}^{i} \right] (y_{j}^{i} + iy_{j}^{i}) \right\}$$

$$\frac{1}{2} \left\{ \sum_{j=1}^{n} (x_{j}^{i} + ix_{j}^{i})^{2} \sum_{j=1}^{n} (y_{j}^{i} + iy_{j}^{i})^{2} - \left[\sum_{j=1}^{n} (x_{j}^{i} + ix_{j}^{i})(y_{j}^{i} + iy_{j}^{i}) \right]^{2} \right\}$$

$$C = \left\{ \sum_{j=1}^{n} (x_{j}^{i} + ix_{j}^{i})^{2} \sum_{j=1}^{n} [(xy)_{j}^{i} + i(xy)_{j}^{i}] (y_{j}^{i} + iy_{j}^{i}) - \sum_{j=1}^{n} (x_{j}^{i} + ix_{j}^{i}) (y_{j}^{i} + iy_{j}^{i}) \sum_{j=1}^{n} [(xy)_{j}^{i} + i(xy)_{j}^{i}] (x_{j}^{i} + ix_{j}^{i}) \right\}$$

$$\frac{1}{\sqrt{2}} \left\{ \sum_{j=1}^{n} (x_{j}^{i} + ix_{j}^{i})^{2} \sum_{j=1}^{n} (y_{j}^{i} + iy_{j}^{i})^{2} - \left[\sum_{j=1}^{n} (x_{j}^{i} + ix_{j}^{i}) (y_{j}^{i} + iy_{j}^{i}) \right]^{2} \right\}$$

$$(1.17)$$

. .. .

$$A = (\overline{XY})' + i(\overline{XY})'' - B(\overline{X}' + i\overline{X}'') - C(\overline{Y}' + i\overline{Y}'')$$

The real and imaginary parts of B and C may be obtained by rationalizing the above expressions; however the results may be presented in a more concise form by going back to the last two of equations (1.9). Taking (1.11) into consideration and separating these equations into real and imaginary parts results in the following system of equations:

$$B^{t}d - B^{t}e + C^{t}f - C^{t}g = h ,$$

$$B^{t}e + B^{t}d + C^{t}g + C^{t}f = k ,$$

$$B^{t}f - B^{t}g + C^{t}f - C^{t}m = p ,$$

$$B^{t}g + B^{t}f + C^{t}m + C^{t}f = q ,$$

(1.18)

where

$$d = \sum_{j=1}^{n} (x_{j}^{i})^{2} - \sum_{j=1}^{n} (x_{j}^{i})^{2},$$

$$e = 2 \sum_{j=1}^{n} x_{j}^{i} x_{j}^{i},$$

$$f = \sum_{j=1}^{n} x_{j}^{i} y_{j}^{i} - \sum_{j=1}^{n} x_{j}^{i} y_{j}^{i},$$

$$g = \sum_{j=1}^{n} x_{j}^{i} y_{j}^{i} + \sum_{j=1}^{n} x_{j}^{i} y_{j}^{i},$$

$$h = \sum_{j=1}^{n} (xy)_{j}^{i} x_{j}^{i} - \sum_{j=1}^{n} (xy)_{j}^{i} x_{j}^{i},$$

$$h = \sum_{j=1}^{n} (xy)_{j}^{i} x_{j}^{i} + \sum_{j=1}^{n} (xy)_{j}^{i} x_{j}^{i},$$

$$(1.19)$$

$$k = \sum_{j=1}^{n} (y_{j}^{i})^{2} - \sum_{j=1}^{n} (y_{j}^{i})^{2},$$

$$m = 2 \sum_{j=1}^{n} y_{j}^{i} y_{j}^{i},$$

$$p = \sum_{j=1}^{n} (xy)_{j}^{i} y_{j}^{i} - \sum_{j=1}^{n} (xy)_{j}^{i} y_{j}^{i},$$

$$q = \sum_{j=1}^{n} (xy)_{j}^{i} y_{j}^{i} + \sum_{j=1}^{n} (xy)_{j}^{i} y_{j}^{i}.$$

1.

-

	h	-0	f	-g	
1	k	đ	g	f	
	p	-g	1	-m	
	Q	f	m	1	;
	d	h	f	-g	
l	e	k	g	f	
$\mathbf{B}^{*} = \mathbf{\overline{D}}$	f	p	l	-m	
	g	q	m	1	;
	d	e	h	-g	
. 1	e	d	k	f	
$C' = \overline{D}$	f	-g	p	-m	
	g	f	q	1	;
	a	-e	f	h i	
1	e	đ	g	k	
C'' = D	f	-g	l	p	
	g	f	m	9	;

where

		d	-8	f	-g
D	=	е	đ	g	f
		f	-g	L	-m
		B	f	m	1

The formulas given above may be used to determine the parameters A, B, and C of the linear fractional transformation (1.1). The parameters are given in terms of sets of measured values of X and Y, and the method makes provision for the use of 3 or more such sets. The use of a larger number of sets of measured values of X and Y will reduce the probable error in the resulting values for A, B, and C. Therefore the use of this method makes it possible to substitute a greater number of measurements for greater precision of measurements.

The solutions for B', B", C', and C" may now be written in terms of determinants.

Any linear four-terminal network can be completely characterized by the parameters of the linear fractional transformation with which it transforms a quantity such as impedance, admittance, or reflection coefficient. If it is necessary to find other sets of parameters for the network, these can be obtained from the A, B, and C.

2.0 TWO-PORT MICROWAVE JUNCTIONS

2.1 Theory

Let the two-port microwave junction be as represented in Fig. 1.





Let the reflection coefficient of the load be Γ_r at the output reference plane, and let the reflection coefficient of the junction together with the load be Γ_g at the input reference plane. Γ_g is related to Γ_r by a linear fractional transformation such as

$$\Gamma_{g} = \frac{A + B \Gamma_{r}}{-C + \Gamma_{r}} . \qquad (2.1)$$

The parameters A, B, and C describe the two-port junction. A, B, and C may be evaluated in terms of a number of experimental measurements of Γ_{σ} and Γ_{τ} . Let the real and imaginary parts of all complex expressions be denoted by single and double primes respectively. Thus, for example, $\Gamma_g = \Gamma_g' + i \Gamma_g''$ where $i = (-1)^{1/2}$. Let n be the number of sets of measurements of Γ_g and Γ_r . The sets of corresponding measured quantities will be denoted by Γ_{gj} and Γ_{rj} where j takes the values 1

through n. In terms of the real and imaginary components we have $\Gamma_{gj} = \Gamma_{gj}' + i \Gamma_{gj}''$ and $\Gamma_{rj} = \Gamma_{rj}' + i \Gamma_{rj}''$.

We now define the following quantities:

- $\overline{\Gamma}_{g}^{*} = \frac{1}{n} \sum_{j=1}^{n} \Gamma_{gj}^{*}, \qquad \overline{\Gamma}_{g}^{*} = \frac{1}{n} \sum_{j=1}^{n} \Gamma_{gj}^{*},$ $\overline{\Gamma}_{r}^{*} = \frac{1}{n} \sum_{j=1}^{n} \Gamma_{rj}^{*}, \qquad \overline{\Gamma}_{r}^{*} = \frac{1}{n} \sum_{j=1}^{n} \Gamma_{rj}^{*},$
- $\overline{(\Gamma_{g}\Gamma_{r})}' = \frac{1}{n} \sum_{j=1}^{n} \Gamma_{gj}' \Gamma_{rj}' \frac{1}{n} \sum_{j=1}^{n} \Gamma_{gj}' \Gamma_{rj}', \quad \overline{(\Gamma_{g}\Gamma_{r})}'' = \frac{1}{n} \sum_{j=1}^{n} \Gamma_{gj}' \Gamma_{rj}''$ $+ \frac{1}{n} \sum_{j=1}^{n} \Gamma_{gj}'' \Gamma_{rj}'', \qquad (2.2)$
- $$\begin{split} \gamma_{gj}^{*} &= \Gamma_{gj}^{*} \overline{\Gamma}_{g}^{*}, & \gamma_{gj}^{*} &= \Gamma_{gj}^{*} \overline{\Gamma}_{g}^{*}, \\ \gamma_{rj}^{*} &= \Gamma_{rj}^{*} \overline{\Gamma}_{r}^{*}, & \gamma_{rj}^{*} &= \Gamma_{rj}^{*} \overline{\Gamma}_{rj}^{*}, \\ (\gamma_{g}\gamma_{r})_{4}^{*} &= \Gamma_{gj}^{*} \Gamma_{rj}^{*} \Gamma_{gj}^{*} \Gamma_{rj}^{*} \overline{(\Gamma_{g}\Gamma_{r})}^{*}, & (\gamma_{g}\gamma_{r})^{*} &= \Gamma_{gj}^{*} \Gamma_{rj}^{*} \end{split}$$

+
$$\Gamma_{gj}^{"}$$
 $\Gamma_{rj}^{'}$ - $\overline{(\Gamma_{g}\Gamma_{r})}^{"}$.

The parameters A, B, and C may now be found from (1.17)

$$\begin{split} \mathbf{E} &= \left\{ \sum_{j=1}^{n} \left[\left(\gamma_{g} \gamma_{r} \right)_{j}^{*} + i \left(\gamma_{g} \gamma_{r} \right)_{j}^{n} \right] \left(\gamma_{gj}^{*} + i \gamma_{gj}^{n} \right)_{j=1}^{n} \left(\gamma_{rj}^{*} + i \gamma_{rj}^{n} \right)^{2} \\ &- \sum_{j=1}^{n} \left(x_{gj}^{*} + i \gamma_{gj}^{n} \right) \left(\gamma_{rj}^{*} + i \gamma_{rj}^{n} \right)_{j=1}^{n} \left[\left(\gamma_{g} \gamma_{r} \right)_{j}^{*} + i \left(\gamma_{g} \gamma_{r} \right)_{j}^{n} \right] \\ &\left(\gamma_{rj}^{*} + i \gamma_{rj}^{n} \right) \right\} \quad \stackrel{\cdot}{\leftarrow} \left\{ \sum_{j=1}^{n} \left(\gamma_{gj}^{*} + i \gamma_{gj}^{n} \right)^{2} \sum_{j=1}^{n} \left(\gamma_{rj}^{*} + \gamma_{rj}^{n} \right)^{2} \\ &- \left[\sum_{j=1}^{n} \left(\gamma_{gj}^{*} + i \gamma_{gj}^{n} \right) \left(\gamma_{rj}^{*} + i \gamma_{gj}^{n} \right) \left(\gamma_{rj}^{*} + i \gamma_{rj}^{n} \right) \right]^{2} \right\}, \\ \mathbf{C} &= \left\{ \sum_{j=1}^{n} \left(\gamma_{gj}^{*} + i \gamma_{gj}^{n} \right)^{2} \sum_{j=1}^{n} \left[\left(\gamma_{g} \gamma_{r} \right)_{j}^{*} + i \left(\gamma_{g} \gamma_{r} \right)_{j}^{*} \right] \left(\gamma_{rj}^{*} + i \gamma_{rj}^{n} \right) \right]^{2} \\ &- \sum_{j=1}^{n} \left(\gamma_{gj}^{*} + i \gamma_{gj}^{n} \right) \left(\gamma_{rj}^{*} + i \gamma_{rj}^{n} \right) \sum_{j=1}^{n} \left[\left(\gamma_{g} \gamma_{r} \right)_{j}^{*} + i \left(\gamma_{g} \gamma_{r} \right)_{j}^{*} \right] \right] \\ &\left(\gamma_{gj}^{*} + i \gamma_{gj}^{n} \right) \right\} \stackrel{\cdot}{\leftarrow} \left\{ \sum_{j=1}^{n} \left(\gamma_{gj}^{*} + i \gamma_{gj}^{n} \right)^{2} \sum_{j=1}^{n} \left(\gamma_{rj}^{*} + i \left(\gamma_{rj}^{*} \right)^{2} \right) \right\}, \\ &A &= \overline{\mathbf{T}_{g}} \overline{\mathbf{T}_{r}}^{*} + i \overline{\mathbf{T}_{g}} \overline{\mathbf{T}_{r}}^{*} - \mathbf{E} \left(\overline{\mathbf{T}_{g}^{*}} + i \overline{\mathbf{T}_{g}}^{*} \right) - \mathbf{C} \left(\overline{\mathbf{T}_{r}^{*}} + i \overline{\mathbf{T}_{r}}^{*} \right) \right\} \end{split}$$

Alternatively the real and imaginary parts of B and C, denoted by single and double primes respectively, can be found by solving the following set of equations:

$$B^{t}d = B^{t}e + C^{t}f - C^{t}g = h,$$

$$B^{t}e + B^{t}d + C^{t}g + C^{t}f = k,$$

$$B^{t}f = B^{t}g + C^{t}f - C^{t}m = p,$$

$$B^{t}g + B^{t}f + C^{t}m + C^{t}f = a.$$
(2.4)

where

$$d = \sum_{j=1}^{n} (\gamma_{gj}^{*})^{2} - \sum_{j=1}^{n} (\gamma_{gj}^{*})^{2}, \qquad \circ = 2 \sum_{j=1}^{n} \gamma_{gj}^{*} \gamma_{gj}^{*},$$

$$f = \sum_{j=1}^{n} \gamma_{gj}^{*} \gamma_{rj}^{*} - \sum_{j=1}^{n} \gamma_{gj}^{*} \gamma_{rj}^{*}, \qquad g = \sum_{j=1}^{n} \gamma_{gj}^{*} \gamma_{rj}^{*} + \sum_{j=1}^{n} \gamma_{gj}^{*} \gamma_{rj}^{*},$$

$$h = \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{gj}^{*} - \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{gj}^{*}, \qquad k = \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{gj}^{*},$$

$$f = \sum_{j=1}^{n} (\gamma_{rj}^{*})^{2} - \sum_{j=1}^{n} (\gamma_{rj}^{*})^{2}, \qquad m = 2 \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{rj}^{*},$$

$$p = \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{rj}^{*} - \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{rj}^{*}, \qquad q = \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{rj}^{*},$$

$$f = \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{rj}^{*}, \qquad f = \sum_{j=1}^{n} (\gamma_{g} \gamma_{r})^{*}_{j} \gamma_{rj}^{*},$$

The solution to equations (2.4) gives values for $B = B^{\dagger} + iB^{\dagger}$ and $C = C^{\dagger} + iC^{\dagger}$. Then A may be found from the last of equations (2.3).

2.2 Conclusions

The network parameters A, B, and C which characterize a two part microwave network by means of equation (2.1) have been determined as functions of a set of corresponding measurements of input and output reflection coefficients. It can be expected, as a result of the statistical averaging inherent in this method, that an increase in the number of measurements used will result in smaller probable errors in the results. This method has been used with good results to determine the parameters of a feed system for an X-band antenna. In this particular application the antenna on the output of the network was replaced by a moveable short circuit so that the output reflection coefficient could be found in terms of the distance between the output reference plane and the short circuit. The input reflection coefficient was then measured for a series of values of the output reflection coefficient. This measured data was then used to find the parameters A, B, and C.

This analysis describes a method for determining the parameters in equation (2.1) which relates the input and output reflection coefficients of a two part microwave network. It is apparent, however, that the method can be used to determine the parameters of the transformation for any quantity which the network transforms by means of a linear fractional transformation. For example a two port microwave network transforms impedance by means of the same ty_1 e of transformation as equation (2.1); therefore the parameters of the impedance transformation could be found from the equations given in this paper simply by substituting the input and output impedance measurements for the input, and output reflection coefficient measurements.

-14-

References

Beatty, R. W., Macphereson, A. C., "Mismatch Errors in Microwave Power Measurements," Proc. I.R.E., vol. 41, pp. 1112-1119; 1953.

Deschamps, G. A., "Determination of Reflection Coefficient and Insertion Loss of a Waveguide Junction," J.A.P. vol. 24, pp. 1046-1050; 1953.

Felson, L. B., Oliver, A. A., "Determination of Equivalent Circuit Parameters for Dissipative Microwave Structures," Proc. I.R.E., vol. 42, pp. 477-482; 1954.

Hoel, P. G., "Introduction to Mathematical Statistics," John Wiley and Sons, Inc., New York, N. Y., chap. 7; 1954.

Mittra, R., King, R. J., "An Impedance Transformation Method for Finding the Load Impedance of a Two-Port Network," Trans. I.R. E., vol. MTT-10, pp. 13-19, 1962.

Master Distribution List for Antenna Laboratory

Contract AF 19(604)-4556

List S-S

(One copy unless otherwise designated)

Code	Organization	Code	<u>Organization</u>
AF 29	APGC (PGAPI) Eglin AFB, Fla.	AF 166	Hq. USAF (AFOAC-S/E) Communications-Electronics Directorate, Washington 25, D.C.
AF 124	RADC (RAALD) Attn: Documents Library Griffiss AFB, N.Y.	AF 63	WADD (WCLRSA, Mr. Portune) Wright-Patterson AFB, Ohio
AF 143	RADC (RCE) Attn: Dr. John S. Burgess Griffiss AFB, N.Y.	AF 68	ASD (ASRNRE-3) Attn: Mr. Paul Springer
AF 139	AF Missile Dev. Cent. (MDGRT)		Wright-Patterson AFB, Ohio
AF 69	Holloman AFB, New Mexico Director of Resident Training	AF 231	Director, Electronics Division Air Technical Intelligence Center Attn: AFCIN-4E1. Colonel H. K.
	3380th Technical Training Group Keesler AFB, Mississippi		Gilbert Wright-Patterson AFB, Ohio
•	Attn: DA-Soll Course	AF 308	WADD (WWDRTR, Mr. A. D. Clark)
AF 86	SAC (Operations Analysis Office) Offutt AFB, Nebraska		Directorate of System Engineering Dyna Soar Engineering Office Wright-Patterson AFB, Ohio
AF 18			
I 913	Maxwell AFS, Ala. General Electric Company, HMED Building 3, Room 37, Court Street Syracuse. New York	AF 348	Lt. Col Jensen (SSRIW) Space Systems Division Air Force Unit Post Office Los Angeles 45, California
	Attn: Mr. N.M. Brown, Communications & Countermeasures Eng.	Ar 42	Director U. S. Army Ordnance Ballistic Research Laboratories
AF 330	HQ. ARDC (RDR-62) Reference 4600 - CA Andrews AFB, Washington 25, D.C.		Aberdeen Proving Ground, Maryland Attn: Ballistic Measurements Lab.
	(3 copies)	Ar 47	Ballistic Research Laboratories Aberdeen Proving Ground, Maryland
AF 5	AF Missile Test Center Patrick.AFB, Fla.		Attn: Technical Information Branch
	Attn: AFMTC, Tech Library, MU-135	Ar 3	Director Evans Signal Laboratory
AF 43	ASD (ASAFRD - Dist) Wright-Patterson AFB, Ohio		Belmar, New Jersey Attn: Mr. O.C. Woodyard
AF 227	USAF Security Service (CLR) San Antonio, Texas	Ar 5	Commanding General USASRDL Ft. Monmouth, N.J. Attn: Tech. Doc. Ctr. SIGRA/SL-ADT

. 4

۰,

List S-S	Page 2	Code
AF 253	Technical Information Office European Office, Aerospace Research Shell Building, 47 Cantersteen Brussels, Belgium	G 103
AR 10	Massachusetts Institute of Technology Signal Corps Liaison Officer Cambridge 39, Mass. Attn: A.D. Bedrosian, Room 26-131	G 8
AR 78	Commanding General, SIGFM/EL-PC USASRDL Fort Monmouth, New Jersey Attn: Dr. Horst H. Kedesdy Deputy Chief, Chem-Physics Branc	G 13 h G 27
Ar 49	Commanding General USASRDL Fort Monmouth, New Jersey Attn: SIGFM/EL-AT	0 27
Ar 39	Commanding General USASRDL Fort Monmouth, New Jersey Attn: Mr. F.J. Triola	G 75
Ar 67	Redstone Scientific Information Center U.S. Army Missile Command Redstone Arsenal, Alabama (4 copies)	M 6
ix 9	Department of the Army Office of the Chief Signal Officer Washington 25, D. C. Attn: SIGRD-4a-2	M 17
Ar 41	Office of Chief Signal Officer Engineering and Technical Division Washington 25, D.C. Attn: SIGNET-5	
Ar 48	Guided Missile Fuze Library Diamond Ordnance Fuze Laboratories Washington 25, D.C. Attn: R.D. Hatcher, Chief Microwave Development Section	N 54
G 59	Advisory Group on Electronic Parts Room 103, Moore School Building 200 South 33rd Street Philadelphia 4, Pennsylvania	м 94
G 2	ASTIA (TIPAA) Arlington Hall Station Arlington 12, Virginia (<u>10 copies</u>)	л 0 4

Organization

National Aeronautical Space Agency Langley Aeronautical Res. Lab. Langley, Virginia Attn: Mr. Cliff Nelson Library National Bureau of Standards Boulder Laboratories Boulder, Colorado (2 copies) National Bureau of Standards U.S. Department of Commerce Washington 25, D.C. Attn: Mr. A.G. McNish National Bureau of Standards U.S. Department of Commerce Washington 25, D.C. Attn: Gustave Shapiro, Chief, Engineering Electronics Section Electricity and Electronics Division Director National Security Agency Fort George G. Meade, Maryland Attn: K31 AFCRL, Office of Aerospace Research CRXRA-Stop 39 L.G. Hanscom Field, Bedford, Mass. (10 copies) AFCRL, Office of Aerospace Research (CRRD) Attn: Contract Files L.G. Hanscom Field, Bedford, Mass. (2 copies) AFCRL, Office of Aerospace Research (CRRD) Attn: Carlyle J. Sletten L.G. Hanscom Field, Bedford, Mass. (3 copies) Hq. ESD (ESRDW, Major John J. Hobson)

L. G. Hanscom Field Bedford, Mass.

Hq. AFCRL, OAR (CRXR, J.R. Marple) L. G. Hanscom Field, Bedford, Mass. X

Code	Organization	Code	Organization
N 3	Chief, Bureau of Ships	N 85	Commanding Officer and Director
	Department of the Navy		U.S. Navy Electronics Laboratory
	Washington 25, D.C.		(Library)
	Attn: Code 690		San Diego 52, California
N 9	Chief, Bureau of Naval Weapons	N 91	Commander
	Department of the Navy		U.S. Naval Air Test Center
	Attn: DLI-31 (<u>2 copies</u>)		Attn: ET-315, Antenna Branch
N 16	Comendar	N 02	Natarial Laboratory Code 032
N 10	U.S. Naval Air Missile Test Center	N 92	Material Laboratory, Code 932 New York News1 Shinward
	Point Mugu. California		Brooklyn 1. New York
	Attn: Code 366		Attn: Mr. Douglas First
N 23	U.S. Naval Ordnance Laboratory	N 93	Commanding Officer
	White Oak, Silver Spring 19, Md.		U.S. Naval Ordnance Laboratory
	Attn: The Library		Corona, Calif.
N 26	Compandan		Attn: Documents Librarian
N 20	U.S. Naval Ordnance Test Station	N 123	Chief, Bureau of Ships
	China Lake, California		Department of the Navy
	Attn: Code 753		Washington 25, D.C.
N 27	Librarian		Attn: Code 817B
	U.S. Naval Postgraduate School	N 141	AFSC Scientific and Technical
	Monterey, California		Lisison Office
			c/o Department of the Navy
N 29	Director U.S. Nevel Besearch Laboratory		Room 2305, Munitions Building
	Washington 25. D.C.		
	Attn: Code 2027 (2 copies)	I 601	Aero Geo Astro Corp.
			1200 Duke Street
N 30	Dr. J.I. Bohnert, Code 5210		Alexandria, Virginia
	U.S. Naval Research Laboratory Washington 25 D.C.		Attn: Library
	washington 25, D.C.	I 940	Asrospace Corp.
N 35	Commanding Officer and Director		Box 95085
	U.S. Navy Underwater Sound Laboratory		Los Angeles 45, Calif.
	Fort Trumbull, New London, Connecticut		Attn: Library
N 37	Chief of Naval Research	I 1	Airborne Instruments Laboratory, Inc.
	Department of the Navy		Division of Cutler Hammer
	Washington 25, D.C.		Walt Whitmen Road
	Attni Code 427		Attn: Library
N 48	Commanding Officer		·····
•	U.S. Naval Air Development Center	I 388	Aircon, Inc.
	Johnsville, Pa.		40 Jummington Street Boston, Mass.
N 73	Office of Naval Research		
	Branch Office, London	I 3	Andrew Alford, Consulting Engineers
	Navy 100, Box 39		299 Atlantic Avenue
	F.F.U. New YOTK, N.Y. (<u>LU COPIES</u>)		BOSTON LU, MASS

Code Code Organization I 374 ACF Industries, Inc. I 250 Southeast Corner, 52nd Ave and Jackson Street Bladensburg, Prince George's County, Maryland Attn: Librarian

- I 205 Battelle Memorial Institute 505 King Avenue Columbus 1. Ohio Attn: Wayne E. Rife, Project Leader Electrical Engr. Division
- I 8 Bell Aircraft Corporation Post Office Box One Buffalo 5, New York Attn: Eunice P. Hazelton, Librarian I 986
- I 469 Bell Telephone Laboratories Murray Hill, New Jersey
- I 13 Bell Telephone Laboratories, Inc. Whippany Laboratory Whippany, New Jersey Attn: Technical Information Library
- I 246 Bendix Corporation Pacific Division 11600 Sherman Way North Hollywood. Calif. Attn: Engineering Library
- I 247 Bendix Radio Division Bendix Aviation Corporation E. Joppa Road Towson 4, Maryland Attn: Dr. D.M. Allison, Jr. Director Engineering and Research I 254 Convair, A Division of General
- I 248 Bjorksten Research Laboratories, Inc. **P.O. Box 265** Madison, Wisconsin Attn: Librarian
- I 249 Boeing Airplane Company Pilotless Aircraft Division P.O. Box 3707 Seattle 24, Washington Attn: R.R. Barber, Library Supervisor (2 copies)

Organization

- Boeing Airplane Company Wichita Division Engineering Library Wichita 1, Kansas Attn: Kenneth C. Knight Library Supervisor
- I 252 Brush Beryllium Company 4301 Perkins Avenue Cleveland 3. Ohio Attn: N.W. Bass
- I 253 Chance Vought Aircraft, Inc. 9314 West Jefferson Street Dallas, Texas Attn: A.D. Pattullo, Librarian
 - Chance Vought Corporation Vought Electronics Division P. O. Box 5907 Dallas 22, Texas (Unclassified only)
- I 470 Chu Associates P.O. Box 387 Whitcomb Avenue Littleton, Mass.
- I 918 Collins Radio Co. 855 35th Street, N.E. Cedar Rapids, Iowa -Attn: Dr. R.L. McCreary
- I 126 Convair, A Division of General Dynamics Corp. Fort Worth, Texas Attn: K.G. Brown Division Research Librarian
 - Dynamics Corp. 3165 Pacific Highway San Diego 12, Calif. Attn: Mrs. Dora B. Burke Engineering Librarian
- I 25 Cornell Aeronautical Laboratory, Inc. 4455 Genesee Street Buffalo 21, New York Attn: Librarian

Code Organization

- I 255 Dalmo Victor Company A Division of Textron, Inc. 1515 Industrial Way Belmont, Calif. Attn: Mary Ellen Addems, Technical Librarian
- I 28 Dorne and Margolin, Inc. 29 New York Avenue Westbury, Long Island, N.Y.
- I 257 Aircraft Div., Douglas Aircraft Co. 3855 Lakewood Boulevard Long Beach, California Attn: Technical Library
- I 258 Douglas Aircraft Company, Inc. 3000 Ocean Park Boulevard Santa Monica, Calif. Attn: Peter Duyan, Jr. Chief, Electrical/Electronics Section
- I 259 Douglas Aircraft Company, Inc. 2000 North Memorial Drive Tulsa, Oklahoma Attn: Engineering Librarian, D-250
- I 145 The Electrada Corporation 11244 Playa Street Culver City, California Attn: S. Stanley Locus Section Head Microwave Engineering
- I 187 Electromagnetic Research Corporation 5001 College Avenue College Park, Maryland Attn: Mr. Martin Katzin
- I 415 Electronics Communication 1830 York Road Timonium, Maryland
- I 299 Electronic Specialty Company 5121 San Fernando Road Los Angeles 39, Calif. Attn: Donald L. Margerum Chief Engineer, Radiating Systems Division

Organization

Code

- I 204 Emerson and Cuming, Inc. 869 Washington Street Canton, Mass. Attn: Mr. W. Cuming
- I 262 Emerson Electric Mfg. Co. 8100 West Florissant Avenue St. Louis 21, Missouri Attn: Mr. E.R. Breslin, Librarian
 - I 147 Emerson Radio-Phonograph Corp. Emerson Research Laboratories 701 Lamont Street, N.W. Washington 10, D.C. Attn: Mrs. R. Corgin, Librarian Classified to: Mrs. Coleen G. Molineu
 - I 264 Fairchild Aircraft-Missiles Division Fairchild Eng. and Airplane Corp. Hagerstown, Maryland Attn: Library
 - I 266 ITT Federal Laboratories Technical Library 500 Washington Avenue Nutley 10, New Jersey
 - I 4 Gabriel Electronics Division Main and Pleasant Streets Millis, Mass. Attn: Dr. Edward Altshuler
 - I 269 General Electric Company Electronics Park Syracuse, New York Attn: Documents Library B. Fletcher, Building 3-143A

Ì

1

à

1 3-

: . |

- I 793 General Electric Company Missile and Space Vehicle Department 3198 Chestnut Street, Philadelphia, Pa Attn: Documents Library
- I 893 General Electric Company 3750 D Street Philadelphia 24, Pa. Attn: Mr. H.G. Lew Missile and Space Vehicle Department

Code Organization

- I 270 General Precision Laboratory, Inc. 63 Bedford Road Pleasantville, New York Attn: Librarian
- I 48 Goodyear Aircraft Corp. 1210 Massillon Road Akron 15, Ohio Attn: Library, Plant G

I 448 Granger Associates Electronic Systems 974 Commercial Street Palo Alto, California Attn: John V.N. Granger, President

- I 273 Hallicrafters Company 4401 West 5th Avenue Chicago 24, Illinois Attn: LaVerne LaGioia, Librarian
- I 737 The Hallicrafters Co. 5th and Kostner Avenues Chicago 24, Illinois Attn: Henri Hodara Head of Space Communication
- I 207 Hughes Aircraft Company Antenna Department Building 12, Mail Station 2714 Culver City, California Attn: Dr. W.H. Kummer
- I 56 Hughes Aircraft Company Florence Ave. and Teale Streets Culver City, California Attn: Louis L. Bailin Manager, Antenna Dept.

Code

Organization

- I 981 Hughes Aircraft Company Attn: Mr. L. Stark, Microwave Dept. Radar Laboratory, P.O. Box 2097 Building 600, Mail Station C-152 Fullerton, California
- G 9 Defence Research Member Canadian Joint Staff 2450 Massachusetts Avenue., N.W. Washington 8, D. C. (3 copies)
- M 59 Electronic Systems Division (AFSC) Technical Information Service Division (ESAT) L. G. Hangcom Field, Bedford, Mass.
- I 265 ITT Laboratories 3700 East Pontiac Street Fort Wayne 1, Indiana Attn: Technical Library
- I 230 Jansky and Bailey, Inc. 1339 Wisconsin Avenue, N.W. Washington 7, D.C. Attn: Mr. Delmer C. Ports
- I 241 Dr. Henry Jasik, Consulting Engineer 298 Shames Drive Brush Hollow Industrial Park Westbury, New York
- I 279 Lockheed Aircraft Corporation 2555 N. Hollywood Way California Division Engineering Library Department 72-25, Plant A-1, Building 63-1 Burbank, California Attn: N.C. Harnois
- I 468 Lockheed Aircraft Corporation Missiles and Space Division Technical Information Center 3251 Hanover Street Palo Alto, California

(2 copies)

<u>Code</u> <u>Organization</u>

- I 136 The Martin Company P.O. Box 179 Denver 1, Colorado Attn: Mr. Jack McCormick
- I 280 The Martin Company Baltimore 3, Maryland Attn: Engineering Library Antenna Design Group
- I 63 Mathematical Reviews 190 Hope Street Providence 6, Rhode Island
- I 66 The W.L. Maxson Corporation 475 10th Avenue New York, New York Attn: Miss Dorothy Clark

I 116 Melpar, Inc. 3000 Arlington Boulevard Falls Church, Virginia Attn: Engineering Technical Library

- I 471 Microwave Associates, Inc. South Avenue Burlington, Mass.
- I 390 Microwave Development Laboratory. 90 Broad Street Wellesley 57, Mass. Attn: N. Tucker, General Manager
- I 648 The Mitre Corporation 244 Wood Street Lexington 73, Mass. Attn: Mrs. Jean E. Claflin, Librarian I 288
- I 85 Motorola, Inc. 8201 East McDowell Road Phoenix, Arizona Attn: Dr. Thomas E. Tice

<u>Organization</u>

<u>Code</u>

- I 934 Motorola, Inc. Phoenix Research Laboratory 3102 N. 56th Street Phoenix, Arizona Attn: Dr. A.L. Aden
- I 641 National Research Council Radio and Elec. Engr. Division Ottawa, Ontario, Canada Attn: Dr. G.A. Miller, Head Microwave Section
- I 284 North American Aviation, Inc. 12214 Lakewood Boulevard Downey, California Attn: Tachnical Information Center (495-12) Space and Information Systems Division
- I 285 North American Aviation, Inc. Los Angeles International Airport Los Angeles 45, Calif. Attn: Engineering Technical File
- I 286 Page Communications Engineers, Inc. 2001 Wisconsin Avenue, N.W. Washington 7, D.C. Attn: (Mrs.) Ruth Temple, Librarian
- I 82 Northrop Corporation Norair Division 1001 East Broadway Hawthorne, California Attn: Technical Information 3924-31
- I 287 Philco Corporation Research Division Union Meeting Pond Blue Bell, Pa. Attn: Research Librarian
- I 225 Pickard and Burns, Inc. 103 Fourth Avanue Waltham 54, Mass. Attn: Dr. Richard H. Woodward
 - Polytechnic Research and Development Co., Inc. 202 Tillary Street Brooklyn 1, New York Attn: Technical Library

Code Organization

- I 232 Radiation Engineering Laboratory Main Street Maynard, Mass. Attn: Dr. John Ruze
- I 289 Radiation, Inc. Melbourne, Florida Attn: RF Systems Division Technical Information Center
- I 914 Radiation Systems, Inc. 440 Swann Avenue Alexandria, Virginia Attn: Library
- I 290 RCA Laboratories David Sarnoff Research Center Princeton, New Jersey Attn: Miss Fern Cloak, Librarian
- I 291 Radio Corporation of America Defense Electronic Products Building 10, Floor 7 Camden 2, New Jersey Attn: Mr. Harold J. Schrader, Staff Engineer Organization of Chief Technical Administrator
- I 473 Radio Corporation of America Missile Control and Electronics Division Bedford St., Burlington, Mass. Attn: Librarian
- I 757 Radio Corporation of America Surface Communications Systems Laboratory 75 Varick Street New York 13, N.Y. Attn: Mr. S. Krevsky
- I 789 Radio Corporation of America West Coast Missile and Surface Radar Division I Engineering Library, Building 306/2 Attn: L.R. Hund, Librarian 8500 Balboa Boulevard, Van Nuys, Calif.

Code

I 930 Radio Corp. of America Defense Electronic Products Advanced Military Systems Princeton, New Jersey Attn: Mr. David Shore

Organization

1

i

- I 292 Director, USAF Project RAND Via: AF Liaison Office The Rand Corporation 1700 Main Street Santa Monica, California
- I 547 The Rand Corporation 1700 Main Street Santa Monica, California Attn: Technical Library
- I 373 Rantec Corporation 23999 Ventura Boulevard Calabasas, California Attn: Grace Keener, Office Mgr.
- I 293 Raytheon Company State Road, Wayland Laboratory Wayland, Mass. Attn: Mr. Robert Borts
- I 294 Raytheon Company Wayland Laboratory Wayland, Mass Attn: Miss Alice G. Anderson, Librarian
- I 472 Raytheon Company Missile Systems Division Hartwell Road, Bedford, Mass. Attn: Donald H. Archer
- I 510 Remington Rand UNIVAC Division of Sperry Rand Corporation P.O. Box 500 Blue Bell, Pennsylvania Attn: Engineering Library
- I 295 Republic Aviation Corporation Farmingdale, Long Island, N.Y. Attn: Engineering Library

<u>Code</u> <u>Organization</u>

- I 184 Ryan Aeronautical Company 2701 Harbor Drive Lindbargh Field San Diego 12, California Attn: Library
- I 391 Sage Laboratories, Inc. 3 Huron Drive Natick, Mass.

I 96 Sandia Corporation P.O. Box 5800 Albuquerque, New Mexico Attn: Records Management and Services Department

- I 682 Scanwell Laboratories, Inc. 6601 Scanwell Lane Springfield, Va.
- I 312 STL Technical Library Document Acquisitions Space Technology Laboratories, Inc. P.O. Box 95001 Los Angeles 45, California
- I 367 Stanford Research Institute Documents Center Menlo Park, California Attn: Acquisitions
- I 104 Sylvania Electric Products, Inc. 100 First Avenue, Waltham 54, Mass. Attn: Charles A. Thornhill, Report Librarian Waltham Laboratories Library
- I 260 Sylvania Elec. Prod. Inc. Electronic Defense Laboratory P.O. Box 205 Mountain View, California Attn: Library

Code

Organization

- I 818 Sylvania Reconnaissance Systems Lab. Box 188, Mountain View, California Attn: Marvin D. Waldman
- I 240 TRG, Inc. 400 Border Street, East Boston, Mass. Attn: Dr. Alan F. Kay
- I 338 A.S. Thomas, Inc. 355 Providence Highway Westwood, Mass. Attn: A.S. Thomas, President
- I 708 Texas Instruments, Inc. 6000 Lemmon Avenue Dallas 9, Texas Attn: John B. Travis Systems Planning Branch
- I 464 Trans-Tech, Inc. P.O. Box 346 Rockville, Maryland Attn: Mr. A.C. Blankenship Chief Electronics Engineer
- I 139 Westinghouse Electric Corp. Electronics Division Friendship Int'l Airport Box 1897 Baltimore 3, Maryland Attn: Engineering Library
- U 1 Library Geophysical Institute of the University of Alaska College, Alaska
- U 61 Brown University Department of Electrical Engineering Providence, Rhode Island Attn: Dr. C.M. Angulo

.

1

- 3

11. 1

- U 157 California Institute of Technology Jet Propulsion Laboratory 4800 Oak Grove Drive Pasadena, California Attn: Mr. I.E. Newlan
- U 99 California Institute of Technology 1201 E. California Street Pasadena, California Attn: Dr. C. Papas

Code	Organization	Code	Organization
<u>U</u> 3	Space Sciences Laboratory Leuschner Observatory University of California Berkeley 4, California Attn: Dr. Samuel Silver, Professor of Engineering Science and Director, Space Sciences Laboratory	U 102 U 54	Harvard University Technical Reports Collection Gordon McKey Library 303 Pierce Hall Oxford St., Cambridge 38, Mass Attn: Librarian Harvard College Observatory
U 100	University of California Electronics Research Lab. 332 Cory Hall, Berkeley 4, California Attn: J.R. Whinnery	U 103	60 Garden Street Cambridge 39, Mass. Attn: Dr. Fred L. Whipple University of Illinois
U 289	University of Southern California University Park Los Angeles, California Attn: Dr. Reymond L. Chuan	U 104	Documents Division Library Urbana, Illinois (Unclassified only) University of Illinois College of Engineering
U 239	Director, Engineering Center Case Institute of Technology Electrical Engineering Department 10900 Euclid Avenue	U 169	Urbana, Illinois Attn: Dr. P.E. Mayes Dept. of Electrical Engineering Illinois Institute of Technology
U 183	Cleveland, Ohio Attn: Professor Robert Plonsey Columbia University	W 940	3301 S. Dearborn Street Chicago 16, Illinois Attn: Dr. George I. Cohn
U 238	Morningside Heights, New York, N.Y. Attn: Dr. Schlesinger University of Southern California	Ų 2 4 0	Technology Center Dept. of Electrical Engineering Chicago 16, Illinois Attn: Paul C. Yuen
	University Park Los Angeles 7, California Attn: Z.A. Kaprielian, Associate Professor of Elec. Engr.	U 22	Electronics Research Laboratory: The John Hopkins University Homewood Campus Baltimore 18, Maryland
U 10	Cornell University School of Electrical Engineering Ithaca, New York Attn: Prof. G.C. Dalman	U 105	Attn: Dr. Donald E. Kerr, Department of Physics The John Hopkins University Applied Physics Laboratory
U 86	University of Florida Department of Electrical Engineering Gainesville, Florida Attn: Prof. M.H. Latour, Library		8621 Georgia Avenue Silver Spring, Maryland Attn: Mr. George L. Seielstad
U 59	Library, Georgia Technology Research Institute Engineering Experiment Station 722 Cherry Street, N.W.	U 228	University of Kansas Electrical Engineering Department Lawrence, Kansas Attn: Dr. H. Uns
	Atlanta, Georgia (Unclassified) Attn: Mrs. J.H. Crosland, Librarian	U 68	Lowell Technological Institute Research Foundation P.O. Box 709, Lowell, Mass. Attn: Dr. Charles R. Mingins

Code	Organization	<u>Code</u>	Organization
U 32	Massachusetts Institute of Technology Research Laboratory of Electronics Building 26, Room 327 Cambridge 39, Mass. Attn: John H. Hewitt (Unclassified only)	U 39	New York University Institute of Mathematical Sciences Room 802, 25 Waverly Place New York 3, New York Attn: Morris Kline, Dr.
	Ollyy	11 96	Northwestern University
U 26	Massachusetts Institute of Technology Lincoln Laboratory P.O. Box 73 Lexington 73, Mass.	• • •	Microwave Laboratories Evanston, Illinois Attn: R. E. Beam
	Attn: Mary A. Granese, Librarian	U 43	Antenna Laboratory Department of Electrical Engineering
U 34	McGill University Department of Electrical Engineering Montreal, Canada Attn: Dr. T. Pavlasek		The Ohio State University 2024 Neil Avenue Columbus 10, Ohio Attn: Reports Librarian
U 107	University of Michigan Electronic Defense Group Engineering Research Institute Ann Arbor, Michigan Attn: J.A. Boyd, Supervisor via: Facility Security Officer	บ 109 _.	The University of Oklahoma Research Institute Norman, Oklahoma Attn: Prof. C.L. Farrar, Chairman Electrical Engineering
Ū 79	University of Michigan Engineering Research Institute	U 45	The Pennsylvania State University Department of Electrical Engineering University Park, Pennsylvania
	Radiation Laboratory 912 N. Main Street Ann Arbor, Michigan Attn: Mr. Ralph E. Hiatt	V 185	University of Pennsylvania Institute of Cooperative Research 3400 Walnut Street, Philadelphis, Pa. Attn: Dept. of Electrical Engineering
U 37	University of Michigan		
	Engineering Research Institute Willow Run Laboratories, Willow Run Airport Ypsilanti, Michigan Attn: Librarian	U 48	Polytechnic Institute of Brooklyn Microwave Research Institute 55 Johnson Street, Brooklyn, N.Y. Attn: Dr. Arthur A. Oliner
		U 97	Polytechnic Institute of Brooklyn
U 108	University of Minnesota Minneapolis 14, Minnesota Attn: Mr. Robert H. Stumm, Library		Microwave Research Institute 55 Johnson Street Brooklyn, New York Attn: Mr. A.E. Legumel
U 194	Physical Science Laboratory		
	New Mexico State University University Park, New Mexico Attn: Mr. H. W. Haas	U 184	Purdue University Dept. of Electrical Engineering Lafayette, Indiana Attn: Dr. Schultz

-,

Code Organization

Code

- U 176 Library U 51 W.W. Hansen Laboratory of Physics Stanford University Stanford, California
- U 110 Syracuse University Research Institute Collendale Campus U 132 Syracuse 10, New York Attn: Dr. C.S. Grove, Jr., Director of Engineering Research
- U 309 Technical University U 133 Oestervoldgade 10 G Copenhagen, Denmark Attn: Prof. Hans Lottrup Knudsen
- U 186 University of Tennessee U 187 Ferris Hall W. Cumberland Avenue Knoxville 16, Tennessee
- U 111 The University of Texas G 126 Electrical Engineering Research Lab. P.O. Box 8026, University Station Austin 12, Texas Attn: Mr. John R. Gerhardt Assistant Director

Organization

- The University of Texas Defense Research Laboratory Austin, Texas Attn: Claude W. Horton Physics Library
 - University of Toronto Department of Electrical Engr. Toronto, Canada Attn: Prof. G. Sinclair
- University of Washington Dept. of Electrical Engineering Seattle 5, Washington Attn: D.K. Reynolds
- 7 University of Wisconsin
 Dept. of Electrical Engineering
 Madison, Wisconsin
 Attn: Dr. Scheibe
- 5 National Aeronautics & Space Administration Attn: Antenna Systems Branch Goddard Space Flight Center Greenbelt, Maryland

in in the second when