1	AD-	A072 05	50 NA CO MAI	VAL POS NVERGEN R 79 R	TGRADUA CE ZONE	TE SCH	OOL MO	NTEREY	CA	OGRAMS	FOR USE	ON HP	G 9/2 ETC(U)
		OF 2				na anti- na anti- ant	- Here and the second s	The second secon	- Mathematica			BT REAL AND A CONTRACT OF A CO		Annumer The State of the State
			A construction of the second s	<section-header><section-header><section-header></section-header></section-header></section-header>										
							A second							
								 I i i i i i i i i i i i i i i i i i i	S.		A construction of the second s			ABARANA ANA ANA ANA ANA ANA ANA ANA ANA AN
						<text><text><text><text><text><text></text></text></text></text></text></text>				$\begin{array}{ccc} 1&2&2&2&2\\ &2&2&2&2\\ &2&2&2\\ &2&2&2\\ &2&2&2\\ &2&2&2\\ &2&2&2\\ &2&2&2\\ &2&2&2&2$				
	<text></text>				KITI TTATION			$\begin{array}{c} \mathbf{y} \in \mathbf{R} \\ \mathbf{y} \in \mathbf{R} \\ \mathbf{d} \in \{1, 2, 3, 3, 4, 5, 5, 5, 5, 5, 5, 5, 5, 5, 5, 5, 5, 5,$		and a second sec		 Annual Annual Annua Annual Annual Annu		
		AND THE OWNER OF THE OWNER OWN	THE CONTRACT OF CONTRACT.											
1.	1		1.58				-					-		. /





DOC FILE COPY

THESIS

CONVERGENCE ZONE PREDICTION MODELS with Programs for Use on HP-67 and HP-97 Programmable Calculators

by

Richard L. Badger

March 1979

Thesis Advisor

A.B. Coppens

JUL 30 1979

Approved for public release; distribution unlimited.

	Entered)	
REPORT DOCUMENTATION	PAGE BEPORE COMPLETING	FORM
	2. GOVT ACCESSION NO. 9	
TITLE (and Bublilla)		OVER
CONVERGENCE ZONE PREDICTION With Programs for Use on HP Programmable Calculators.	MODELS 67 and HP-97 6. PERFORMING ORG. REPORT	-
Richard L. Badger	. CONTRACT OR GRANT NUMB	EN(o)
Naval Postgraduate School Monterey, California 93940	10. PROGRAM EL EMENY, PROJE	RE TAI
1. CONTROLLING OFFICE NAME AND ADDRESS	UL ASPORT DATE	
Naval Postgraduate School Monterey, California 93940	13. NUMBER OF PAGES 99	
. MONITORING AGENCY NAME & ADDRESS(I dillo	nt free Centrelling Office) 18. SECURITY CLASS. (of this ri	(hert)
Naval Postgraduate School Monterey, California 93940	DIPLP. Unclassified Unclassified Unclassified Unclassified	GRADIN
Approved for public release	distribution unlimited.	
Approved for public release	distribution unlimited.	
Approved for public release 7. DISTRIBUTION STATEMENT (of the electron entern 8. SUPPLEMENTARY NOTES	distribution unlimited.	
Approved for public release 7. DISTRIBUTION STATEMENT (of the electrons entern S. SUPPLEMENTARY NOTES M. KEY WORDS (Continue on course side // necessory Convergence Zone Transmission Loss Handheld Calculator Ray Tracing Model	distribution unlimited.	

UNCLASSIFIED

SECURTY CLASSIFICATION OF THIS PAGE/Man Dore Enternet.

model which is based on similar but more elaborate theory and which is designed for use on large digital computers. Agreement of the calculator programs with the FACT model is fairly good when conditions are within the design limitations of the programs and environmental conditions are not unusual.

K

Accession For NTL G.J.&I LDC TAB Unconnsunced Jutific tion Dy Distribution/ Avail and/or Dist special P

UNCLASSIFIED SECURITY CLASSIFICATION OF THIS PAGE (Then Date Entered) Approved for public release; distribution unlimited.

CONVERGENCE ZONE PREDICTION MODELS with Programs for Use on HP-67 and HP-97 Programmable Calculators

by

Richard L. Badger Lieutenant Commander, United States Navy B.S., United States Naval Academy, 1966

Submitted in partial fulfillment of the requirements for the degree of

MASTER OF SCIENCE IN SYSTEMS TECHNOLOGY

from the NAVAL POSTGRADUATE SCHOOL March 1979

nesis Advisor Co-Advisor Chairman, ASW Academic Group Academic Dean

Author

Approved by

ABSTRACT

Convergence zone (CZ) prediction models are developed based on acoustic ray tracing theory as applied to linearly segmented sound velocity profiles (SVP). The models were developed into three calculator programs, two for CZ range predictions under different source and receiver depth conditions and one for CZ gain and transmission loss (TL) predictions. The performance of the models as programmed on Hewlitt-Packard HP-67 or HP-97 programmable calculators was compared to the Fast Asymptotic Coherent Transmission (FACT) model which is based on similar but more elaborate theory and which is designed for use on large digital computers. Agreement of the calculator programs with the FACT model is fairly good when conditions are within the design limitations of the programs and environmental conditions are not unusual.

TABLE OF CONTENTS

1.	THE	NEED FOR GOOD CZ PREDICTIONS	11
	A.	THE PROBLEM OF THE AIRBORNE ASW UNIT	11
	в.	ARE LARGE COMPUTERS NECESSARY?	12
	c.	DESIRABLE CHARACTERISTICS OF A CALCULATOR PROGRAM FOR CZ PREDICTIONS	13
II.	USI	NG ICAPS AS THE STANDARD FOR COMPARISON	15
	Α.	RATIONALE FOR ONLY ONE LOCATION PER OCEAN BASIN	15
	в.	DESCRIPTION OF ICAPS	15
	c.	DESCRIPTION OF HISTORICAL ENVIRONMENTAL DATA FILES	16
	D.	COMPARISON OF DEEP SOUND CHANNEL CHARACTERISTICS	29
	E.	COMPARISON OF CZ CHARACTERISTICS IN THREE OCEANS	31
		 Method Used in Obtaining Data for Comparison 	31
		2. CZ Range and Width Analysis	32
		3. CZ Gain and Transmission Loss Analysis	39
III.	CZ	RAY THEORY ANALYSIS AND MODEL DEVELOPMENT	47
	Α.	CZ RANGE AND WIDTH	47
	в.	RANGE AND WIDTH MODEL	50
	c.	CZ GAIN AND TRANSMISSION MODEL	59
	D.	CALCULATOR PREDICTIONS COMPARED TO ICAPS	66
		1. Choosing the SVP Points for the Program	66
		2. CZ Range and Annulus Width Comparisons	68
		3. CZ Gain Comparisons	74

IV.	CON	CLUSIONS	78
	A.	LIMITATIONS OF THE MODEL DEVELOPED	78
	в.	USEFULNESS OF THE MODEL DEVELOPED	79
APPE	NDIX	- HP-67/97 Calculator Programs for Convergence Zone Range, Width and Transmission Loss Predictions	83
LIST	OF	REFERENCES	97
INIT	IAL	DISTRIBUTION LIST	98

LIST OF TABLES

I.	ICAPS CZ Range & Width Data 33-38
11.	ICAPS CZ Gain Data Observed at the Pacific Ocean Location
111.	ICAPS 300Hz CZ Gain Data Observed at Atlantic & Mediterranean Locations46
IV.	Five Point Sound Velocity Profiles67
v.	CZ Gain Prediction Comparisons75

LIST OF FIGURES

1.	ICAPS Sound Velocity Profiles17-28
2.	Comparison of Pacific, Atlantic, and Mediterranean Deep Sound Channel Characteristics30
3.	Estimating Transmission Loss in a CZ Annulus from an ICAPS TL Profile41
4.	Sound Rays of Interest in CZ Propagation48
5.	Horizontal Distance Traveled Within an Isogradient Layer54
6.	RCZi and RCZo for Deep/Deep, Shal/Shal, and Crosslayer Cases57-58
7.	Geometric Transmission Loss by Ray Tracing Method61
8.	Determining Angular Terms for CZ Gain Algorithm64
9.	Comparisons of ICAPS and Calculator CZ Annuli Predictions70-72

LIST OF SYMBOLS AND DEFINITIONS

۵.	Attenuation coefficient (dB/m).
c ₀ ,c ₁ ,c ₂ ,,c _i	Sound velocities at various points on a linearly segmented sound velocity profile.
C _R	Sound velocity at the receiver depth.
c _s	Sound velocity at the sound source depth.
CZ	Convergence zone.
CZW	Width of the convergence zone annulus.
D ₀ , D ₁ , D ₂ ,, D _i	Depths of various points on a linearly segmented sound velocity profile.
D _R	Depth of the acoustic receiver.
D _S	Depth of the sound source.
DSC	Deep Sound Channel.
$\Delta r_0, \Delta r_1, \cdots, \Delta r_i$	Horizontal distances traveled by a sound ray in traversing various layers of a linearly segmented sound velocity profile.
Δr _s ,Δr _R	Horizontal range corrections made to sound ray cycle ranges to correct for source and receiver depth separation from the sonic layer depth.
Δθ	The angular spread of all sound rays de- parting a sound source which result in convergence zone propagation.
f	Frequency (Hz).
G	Convergence zone gain (dB).
a ⁰ ,a ¹ ,a ⁵ ,,a ⁱ	Sound velocity gradients in a linearly segmented sound velocity profile.
ML	Mixed Layer. The upper, generally iso- thermal, slightly positive sound velocity gradient layer of the ocean.
R	The radius of curvature of a sound ray in an isogradient layer.

R0,R1,,R9; S0,S1,,S9; RA,RB,,RE	Data storage registers in the HP-67 or HP-97 calculators.
RCZI	Horizontal range from a sound source to the inner edge of a convergence zone annulus.
RCZO	Horizontal range from a sound source to the outer edge of a convergence zone annulus.
r	The cycle distance of a sound ray which experiences convergence zone refraction. It is a horizontal distance measured from the point of departure from the SLD to the point of return to the SLD.
r ₀	The cycle distance for a ray which de- parts the SLD at zero degrees depres- sion angle from the horizontal.
r _{min}	The minimum cycle distance of all sound rays experiencing CZ refraction.
rswp	The cycle distance of a sound ray which equals r_0 but which has a positive depression angle from the horizontal at the SLD. The rays with depression angles between those for r_0 and r_{rswp} produce the reswept region in a CZ.
rw	The working cycle distance used in a calculator program when iterating to find a particular r.
SLD	Sonic Layer Depth. The depth of maximum sound velocity above the DSC axis.
TL	Transmission Loss (dB).
TLn	The TL in the n th CZ annulus.
^θ SLD	The angle of departure of a sound ray from the SLD measured downward from the horizontal.
⁹ rmin	The angle of departure of the CZ sound

The angle of departure of the CZ sound ray with minimum cycle distance.

	· ·
^θ rswp	The angle of departure of the CZ sound ray which completes the CZ reswept region.
^θ RO	The angle of arrival of a sound ray at the receiver which departed the SLD at zero depression angle.
^θ RR	The angle of arrival of a sound ray at the receiver which departed the SLD at θ rswp.
°so	The angle of departure of a sound ray from the sound source which reaches the SLD at zero depression angle.
^θ SR	The angle of departure of a sound ray from the sound source which crosses the SLD at $\frac{\partial}{rswp}$.
θw	θ_{SLD} in an iterative calculator routine when searching for r_{min} or θ_{rswp} .
θι	The average angle of departure of the sound rays within $\Delta \theta$.
θ2	The average angle of arrival of CZ sound

I. THE NEED FOR GOOD CZ PREDICTIONS

A. THE PROBLEM OF THE AIRBORNE ASW UNIT

In most of the Pacific Ocean and much of the Atlantic Ocean and Mediterranean Sea, convergence zone (CZ) conditions exist a majority of the time, and they provide passive acoustic sensors with an important means of detecting sounds emitted from submarine targets. In some areas the CZ regions are the most important contact regions considered in planning acoustic searches. Obtaining accurate predictions of CZ sound propagation is therefore vital to the success of acoustic sensor tactical planners.

Currently, the primary source of acoustic predictions for U. S. Navy units is the Fleet Numerical Weather Center, Monterey, California. Propagation loss profiles for four standard frequencies and three source and receiver depth combinations are normally provided in the ASW Range Prediction System (ASRAPS) to air ASW units when requested. The profiles, showing transmission loss (TL) versus distance, are generated on a large digital computer which uses the Fast Asymptotic Coherent Transmission (FACT) model. This model uses as inputs a linearly segmented sound velocity profile (SVP), source and receiver depths, and frequencies of interest. The SVP used can be specified by the user or can come from information stored at FNWC in the form of historical data. This stored data is updated by bathythermograph (BT) reports through a complex weighting scheme as the

reports are received. Without going into further detail, it can be stated that predictions produced are only as good as the data and the computer model used, and only as timely as communications allow.

When entering a search area, a problem often arises concerning the TL profiles obtained from FNWC. Upon taking a BT measurement, the unit often finds the BT profile used to generate the acoustic predictions does not agree with the actual BT conditions in the area. If this situation occurs, the unit tends to lose confidence in the accuracy of the predictions and tactical effectiveness is felt to be diminished by lack of good information. The objective of this study was, therefore, to investigate what could be done with state-of-the-art programmable calculators to improve on the in situ convergence zone predictions available to air ASW units.

The reader only interested in the calculator programs developed may skip immediately to the appendix.

B. ARE LARGE COMPUTERS NECESSARY?

In section 5.6 of Ref. 1, Principles of Underwater Sound, by R.J. Urick, the author discusses the relative merits of two theoretical approaches to obtaining wave equation solutions in order to describe the distribution of sound energy in space and time. Several references are made to the need for digital computers to produce sound propagation descriptions with either theory. Since those comments were made,

however, there has been a revolution in the capabilities of small programmable calculators. Although it is probably true that computers are required to produce a complete description of sound propagation in the ocean with one program, calculators are capable of solving the different modes of propagation one at a time with separate programs to obtain a composite description. Examples of simple but fairly adequate calculator programs for surface duct, bottom bounce, reliable acoustic path, and deep sound channel propagation modes are contained in Refs. 2 and 3. These references also contain simple models for CZ propagation, but they are based on a mix of ray theory, rule-of-thumb, and empirical data. It was felt that a better CZ model needed to be developed.

C. DESIRABLE CHARACTERISITCS OF A CALCULATOR PROGRAM FOR CZ PREDICTIONS

1. The program should require a minimum of easily available input data. The only information not currently available but which would be needed by an airborne ASW unit is an SVP from the permanent thermocline to the ocean bottom in the unit's search area. A chart of this data could easily be included in the environmental package carried aboard the aircraft.

2. The program should be easy to operate and not require the operator to have a great deal of insight into the mathematical model or the internal operations of the calculator.

3. The output should provide ranges to the inner and outer edges of all CZ annuli of interest. It should also present the expected TL for all frequencies of interest in each annulus.

4. The run time of the program should be relatively short. This characteristic recognizes that time is important to an on-station unit.

5. The program should be based on generally accepted acoustic theory. This characteristic is desirable because a user would probably have more confidence in such a model than one based on empirical data and thus applicable only to a specific ocean basin. With empirical models, the user often wonders if the area he intends to search corresponds to the mean set of conditions used to generate the model or is somehow different.

 Ideally, the program's performance should agree closely with the generally accepted large computer models currently in use.

II. USING ICAPS AS THE STANDARD FOR COMPARISON

A. RATIONALE FOR ONLY ONE LOCATION PER OCEAN BASIN

As will be demonstrated, the CZ characteristics of the three locations studied vary considerably. The deep sound channels which produce CZ phenomena are quite different as are the ranges from source to CZ annuli. The objective of this study was to produce a mathematical model for CZ predictions for use on small programmable calculators. It was reasoned that if the model would work for the different conditions of the three locations studied, it would work for all of the variations to be expected within any one of the ocean areas.

B. DESCRIPTION OF ICAPS

The Integrated Carrier ASW Prediction System (ICAPS) is a passive and active acoustic prediction system developed for installation aboard aircraft carriers and other large naval vessels which have digital computers. It contains four sets of historical environmental data, one each for the North Pacific, North Atlantic, and Indian Oceans, and one for the Mediterranean and Black Seas. It also contains several production programs for predicting naval sonar system performance. The FACT model is used in the passive sensor predictions. This is the same model used at FNWC for ASRAPS. Reference 4 contains a description of the installation and operation of ICAPS in the IBM 360 Computer Center at the

Naval Postgraduate School. Reference 5 contains a description of the mathematics used in the FACT model.

C. DESCRIPTION OF HISTORICAL ENVIRONMENTAL DATA FILES

Figures 1(a) through 1(1) depict twelve sound velocity profiles produced by ICAPS from its historical environmental data files. Figures 1(a) through 1(d) show SVP information for the months of February, May, August, and November for 40N 140W in the Pacific Ocean. Figures 1(e) through 1(h) are the same information for 31N 69W in the Atlantic Ocean, and likewise, Figures 1(i) through 1(1) are for 36N 18E in the Mediterranean Sea.

The historical data files used to produce these profiles consist of temperature and salinity values for over thirty depths, for four seasons of the year, and for many locations spaced at one to five degree latitude and longitude intervals in each ocean area covered. When specific latitude, longitude, and date are specified, interpolations are performed to produce the approximate temperature and salinity profiles to be expected at that location and date. This information is then converted to an SVP. The output from this portion of the system consists of seven columns of values, one each for depth in meters and feet, temperature in Celsius and Fahrenheit, salinity, and sound velocity in meters per second and feet per second. The depths associated with these quantities begin at ten meter intervals near the ocean surface and gradually increase through 25, 50, 100, 250, 500, and 1,000 meter intervals as depth increases. The last line









Sound Velocity (meters/second)









Sound Velocity (meters/second)









of values is for the ocean bottom depth which was part of the input data.

D. COMPARISON OF DEEP SOUND CHANNEL CHARACTERISTICS

Figure 2 depicts the deep sound channel (DSC) portion of the May SVP for the Pacific, Atlantic and Mediterranean coordinates mentioned earlier in a composite graph drawn to scale. As can be seen in that figure, DSC characteristics of the three areas differ considerably. The vertical extent of the channels varies from 1100 meters in the Mediterranean to 4200 meters in the Atlantic. The change in sound velocity between sonic layer depth (SLD) and DSC axis (point of minimum velocity) varies from 15 m/sec in the Mediterranean to 38 m/sec in the Atlantic. The depth of the DSC axis varies from 100 meters in the Mediterranean to 1300 meters in the Atlantic. Pacific Ocean values are between the others for all of those characteristics. Sound velocity near the surface is much greater in the Atlantic and Mediterranean than in the Pacific, and sound velocity near the bottom of the three basins (not shown in the figure) is about 6 m/sec greater in the Atlantic than in the Pacific and about 52 m/sec greater in the Mediterranean than in the Pacific at equal depths. Also note the subsurface sound channel located about 100 to 500 meters below the surface in the Atlantic profile.



Figure 2. Comparison of Pacific, Atlantic, and Mediterranean Deep Sound Channel Characteristics.

E. COMPARISON OF CZ CHARACTERISTICS IN THREE OCEANS

1. Method Used in Obtaining Data for Comparison

There were two primary objectives in gathering twelve ICAPS runs from each of the three ocean areas. First, it was desired to obtain sufficient data to determine which CZ characteristics are common to all areas and which characteristics are peculiar to specific basins. Secondly, it was desired to obtain a standard of comparison for any calculator program which might be developed. To fulfill the first objective, it was decided to keep the input variables the same in all areas, varying them one at a time, in order to better compare the differences observed in the various runs. For each of the three locations, the inputs varied were season of the year and source and receiver depth combination. Receiver depths of 60 and 300 feet and source depths of 60 and 400 feet were used. Each of the ICAPS outputs consisted of TL profiles for four frequencies out to a range of 250 kyds.

Originally, it was intended to collect twelve data from each profile. These data were to be the range, width, CZ gain, and Transmission Loss for each of the first three convergence zone annuli. As it turned out, somewhat less data was collected and tabulated. There were several reasons for this. First, the February SVP in the Mediterranean contained no sound channel and therefore no convergence zones existed. Secondly, all of the third CZ data for the Atlantic was thrown out on the grounds that it was almost always the same and that it was inconsistent with information from

the first two CZ annuli in any particular profile. The reason for this occurrence is not know. Finally, it was impossible to obtain some of the desired data because of the smooth way in which the CZ path blended with other competitive propagation modes. One could not tell what was CZ and what was not in those cases.

2. CZ Range and Width Analysis

The transmission loss profiles produced by ICAPS are presented in two formats, a table of TL values for each kiloyard of range from the source and a graph of the same information. Because the TL values are tabulated at kiloyard intervals, it is impossible to be more accurate than that interval in determining where a CZ begins and ends. Also, it was difficult to be consistent in picking the points representing the edges of C2 annuli because of the variety of graph shapes, TL levels, and other propagation mode interferences. In any event, an attempt was made to satisfy one basic criterion in choosing leading and trailing edges of the annuli: Do these ranges best represent the apparent location of the annulus regardless of the TL levels involved? Admittedly, the ranges picked were often based on subjective judgement, and it cannot be stated with complete certainty that only CZ mode propagation contributed to the TL peaks judged to be the CZ annuli.

Table I contains the CZ range and width data that could be gleaned from the ICAPS profiles. In the table, RCZi is the range to the inner edge of the first, second, or

lable	L. LUAL	Data Data		150 02		_	2ND CZ			3RD C.2	
741111	Pacific NN - 160U		RCZ1 (Nm)	CZW (Nm)	CZW (%) RCZO (%)	RCZ1 (Nm)	CZW (Nm)	CZW (%) RCZo (%)	RCZ1 (Nm)	CZW (Nm)	CZW (%) RCZO (%)
Mo.	RCVR/TGT (Ft)	FREQ (Hz)									
		50	25.5	5.0	16	51.0	11.0	18	77.0	16.0	17
	60/60	300	25.0	6.0	19	50.5	11.5	19	76.0	17.0	18
		850	25.5	5.5	18	51.0	10.0	16	76.5	15.5	17
		1700	25.5	5.5	18	51.0	11.0	18	76.5	16.5	18
YAA		50	25.0	6.0	19	50.0	12.5	20	76.0	17.5	19
กษ	60/400	300	24.5	6.5	21	50.0	12.5	20	75.5	18.0	19
EB	port loo	850	24.5	6.5	21	50.5	11.5	19	76.0	17.5	19
I		1700	24.5	6.5	21	50.5	12.0	20	76.0	17.5	19
		50	24.0	7.0	23	49.0	13.5	22	74.5	19.0	20
	300/1400	300	24.0	7.0	23	49.0	13.0	21	74.5	19.0	20
	not looc	850	24.0	7.0	23	49.5	13.0	21	75.0	18.5	20
		1700	24.5	6.5	21	49.5	13,0	21	75.0	18.5	20
		50	26.0	4.5	15	52.0	9.5	15	78.0	14.5	16
	60/60	300	26.0	5.5	18	52.5	0.6	15	0.61	13.5	15
-		850	26.5	4.0	13	53.0	8.5	14	79.5	13.0	14
		1700	26.5	4.0	13	53.0	8.5	14	79.5	13.0	14
		50	25.5	5.5	18	51.0	11.0	18	78.0	14.5	16
X	60/400	300	25.5	5.5	18	51.5	10.5	17	78.5	14.0	15
AM	ant los	850	25.5	5.5	18	52.0	10.0	16	0.97	13.5	15
		1700	25.5	5.5	18	52.0	10.0	16	78.5	14.0	15
-		50	24.0	7.0	23	49.0	13.0	21	74.5	18.5	20
	300/400	300	24.0	7.0	23	49.0	13.0	21	74.5	18.5	20
	and have	850	24.0	1.0	23	0.64	12.5	20	0.61	14.0	15
		1700	24.0	1.0	23	49.0	13.0	21	74.5	18.5	20
Mo. RCVT, Mor. (Nm) (Nm) RC20 (K) (Nm) (Ft.) (Hz) 50 25.0 5.5 15 52.5 60/60 300 26.5 4.0 13 53.5 60/400 300 26.5 4.0 13 53.5 300/400 360 26.5 4.0 13 53.0 300/400 300 26.5 4.0 13 53.0 300/400 350 26.5 4.0 13 53.0 300/400 350 26.5 4.0 13 53.0 1700 26.5 4.0 13 53.0 300/400 350 26.0 4.5 13 53.0 60/60 350 26.0 4.5 13 53.0 60/400 350 26.0 4.5 15 52.0 60/400 350 26.0 4.5 15 52.0 60/400 350 26.0 4.5	h Data	1 10	ST CZ		RC24	2ND CZ	-c24	BC 7 5	3RD CZ	ne J	
--	-------------	--------	-------	----------	------	--------	-----------	--------	--------	------	
Mo. RCVR/TGT FREq. (Ft) 55.0 5.5 15 50.0 52.5 50.0 52.5 50.0 52.5 50.0 52.5 50.0 52.5 50.0 52.5 50.0 52.5 50.0 52.5 50.0		(Nm)	(MM)	RC20 (%)	(MM)	(Nm)	RC 20 (%)	(Mm)	(Nm)	RC20	
60/60 50 25.0 5.5 18 50.0 60/60 850 26.5 4.0 13 53.5 60/400 850 26.5 4.0 13 53.5 60/400 850 26.5 4.0 14 50.0 73.5 25.0 4.0 14 53.5 53.5 73.0 26.5 4.0 13 53.0 53.0 70.0 850 25.0 4.0 14 53.0 53.0 300/400 850 23.5 6.5 2.0 13 53.0 70.0 1700 20.5 4.0 13 53.0 53.0 70.0 1700 23.5 6.5 2.4 146.5 53.0 60/400 850 25.0 4.0 13 53.0 53.0 70.0 1700 20 23.5 4.0 13 53.0 60/400 850 26.0 4.5 13 53.0<	T FREQ (Hz)										
60/60 300 26.0 4.5 15 52.5 1700 26.5 4.0 13 53.5 60/400 350 26.5 4.0 13 53.5 300/400 350 26.5 4.0 13 53.0 300/400 350 26.5 4.0 13 53.0 300/400 350 25.0 4.0 13 53.0 300/400 350 25.5 4.0 13 53.0 300/400 350 25.5 4.0 13 53.0 60/60 350 26.0 4.5 13 53.0 60/400 300 26.0 4.5 13 53.0 60/400 300 26.0 4.5 13 53.0 60/400 300 26.0 4.5 13 53.0 60/400 300 26.0 4.5 13 53.0 60/400 300 26.0 4.5 13 <t< td=""><th>50 2</th><td>5.0</td><td>5.5</td><td>18</td><td>50.0</td><td>11.0</td><td>18</td><td>76.5</td><td>15.0</td><td>16</td></t<>	50 2	5.0	5.5	18	50.0	11.0	18	76.5	15.0	16	
Alicitist 60/400 500 26.5 4.0 13 53.5 60/400 500 26.5 4.0 13 53.0 300/400 850 26.5 4.0 13 53.0 300/400 850 26.0 4.0 13 53.0 300/400 850 26.0 4.0 13 53.0 300/400 850 23.0 5.0 13 53.0 300/400 850 23.5 6.5 2.2 47.0 1700 23.5 6.5 4.0 13 53.0 60/400 850 28.5 4.0 13 53.0 60/400 850 28.5 4.0 13 53.0 60/400 850 28.5 4.0 13 53.0 60/400 850 28.5 4.0 13 53.0 60/400 850 28.5 4.0 13 53.0 60/400 850 28.0	300 2	6.0	4.5	15	52.5	8.5	14	0.61	12.5	14	
I700 26.5 4.0 13 53.5 60/400 950 26.0 4.0 13 52.0 300/400 950 26.5 3.5 12 53.0 300/400 950 25.0 4.0 13 53.0 300/400 950 23.5 6.5 3.5 12 53.0 300/400 950 23.5 6.5 2.2 47.0 13 53.0 300/400 850 23.5 6.5 2.2 47.0 13 53.0 60/60 300 26.0 4.5 13 53.0 52.2 47.0 60/400 850 26.0 4.5 13 53.0 52.5 1700 23.5 6.5 2.5 2.7 47.0 60/400 850 26.0 4.5 13 53.0 60/400 850 28.0 4.5 13 53.0 60/400 850 26.0 4.5	850 2	6.5	4.0	13	53.5	7.5	12	80.0	11.5	13	
Ко/400 50 25.0 4.0 13 50.0 260/400 850 26.5 4.0 13 53.0 300/400 850 23.0 5.0 13 53.0 300/400 850 23.0 5.0 18 46.5 300/400 850 23.0 7.0 23 46.5 300/400 860 23.5 6.5 2.2 47.0 60/60 850 23.5 6.5 2.2 47.0 60/400 860 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.0 47.0 60/400 860 26.0 4.5 15 52.0 300/400 860 25.5 5.0 16 52.0 300/400 850 25.5 15 52.0 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 25.5 7.5	1700 2	6.5	4.0	13	53.5	7.5	12	80.5	11.0	12	
60/400 300 26.0 4.0 13 52.0 300/400 850 26.0 4.0 13 53.0 300/400 850 25.0 4.0 13 53.0 300/400 850 23.0 5.0 18 46.5 300/400 850 23.5 6.5 22 47.0 1700 23.5 6.5 22 47.0 53.0 60/60 300 26.0 4.5 15 52.0 60/400 850 26.0 4.5 15 52.5 60/400 300 26.0 4.5 15 52.5 860/400 300 25.5 5.0 16 52.5 300/400 350 25.5 5.0 16 52.0 300/400 850 25.5 5.0 16 52.0 300/400 350 25.5 5.0 16 52.0 300/400 350 25.5 5.0	50 2	5.0	0.4	14	50.0	8.5	15	77.0	11.0	13	
Allet B50 26.0 4.0 13 53.0 300/400 50 23.0 5.0 18 46.5 300/400 50 23.0 5.0 18 46.5 300/400 50 23.0 5.0 18 46.5 300/400 50 23.5 6.5 22 47.0 1700 23.5 6.5 22 47.0 1700 23.5 6.5 22 47.0 60/60 300 26.0 4.5 15 52.0 60/400 850 26.0 4.5 15 52.0 60/400 300 25.5 5.0 18 52.0 300/400 300 25.5 5.0 16 52.0 300/400 350 25.5 15 52.0 300/400 350 25.5 15 52.0 300/400 350 25.5 16 52.0 300/400 350 <t< td=""><th>300 2</th><td>6.0</td><td>4.0</td><td>13</td><td>52.0</td><td>0.6</td><td>15</td><td>0.61</td><td>12.5</td><td>14</td></t<>	300 2	6.0	4.0	13	52.0	0.6	15	0.61	12.5	14	
A 1700 26.5 3.5 12 53.0 300/400 500 23.0 5.0 18 46.5 300/400 850 23.0 7.0 23 46.5 300/400 850 23.0 7.0 23 46.5 1700 23.5 6.5 22 47.0 1700 26.0 4.5 15 53.0 60/60 300 26.0 4.5 15 52.0 60/400 850 26.0 4.5 15 52.0 60/400 300 25.5 5.0 16 52.0 300/400 350 25.5 5.0 16 52.0 300/400 350 25.5 5.0 16 52.0 300/400 850 23.0 7.5 24 47.0 300/400 850 25.5 16 52.0 300/400 850 23.0 7.5 24 470.5	850 2	6.0	0.4	13	53.0	8.0	13	80.0	11.5	13	
300/400 50 23.0 5.0 18 46.5 300/400 850 23.5 6.5 22 46.5 1700 850 23.5 6.5 22 46.5 60/60 300 26.0 4.5 15 52.0 60/60 300 26.0 4.5 15 52.0 60/400 850 26.0 4.5 15 52.0 60/400 850 26.0 4.5 15 52.5 60/400 300 25.5 5.0 16 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 24.0 7.0 23 47.0	1700 2	6.5	3.5	12	53.0	8.0	13	80.0	11.5	13	
300/400 300 23.0 7.0 23 46.5 1700 850 23.5 6.5 22 46.5 60/60 850 23.5 6.5 22 47.0 60/60 300 26.0 4.5 15 52.0 47.0 1700 26.0 4.5 15 52.0 47.0 53.0 60/60 300 26.0 4.5 15 52.0 52.0 1700 26.0 4.5 15 52.0 52.0 52.0 60/400 300 25.0 5.0 16 52.0 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 24.0 7.0 23 47.0	50 2	3.0	5.0	18	46.5	10.0	18	70.0	12.5	15	
500 23.5 6.5 22 46.5 1700 23.5 6.5 22 46.5 60/60 300 26.0 4.5 13 53.0 60/60 300 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.0 60/400 300 25.0 4.5 15 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 24.0 7.0 23 47.0	300 2	3.0	0.7	23	46.5	14.0	23	70.0	21.5	24	
1700 23.5 6.5 22 47.0 60/60 300 26.0 4.5 15 53.0 60/60 300 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.5 60/400 300 25.0 5.5 18 51.5 300/400 360 25.5 5.0 16 52.0 300/400 360 24.0 7.5 24 47.0 300/400 360 24.0 7.0 23 48.0	850 2	3.5	5.5	22	46.5	14.0	23	70.5	21.0	23	
60/60 300 26.5 4.0 13 53.0 60/60 300 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.5 60/400 300 26.0 4.5 15 52.5 60/400 300 25.5 5.5 15 52.0 300/400 300 25.5 5.0 16 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 24.0 7.5 25 47.0	1700 2	3.5	6.5	22	47.0	13.5	22	70.5	21.0	23	
60/60 300 26.0 4.5 15 52.0 1700 26.0 4.5 15 52.5 50/400 300 26.0 4.5 15 52.5 60/400 300 25.0 4.5 15 52.5 50 26.0 4.5 15 52.5 60/400 300 25.5 5.0 16 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 24.0 7.5 25 47.0	50 2	6.5	0.4	13	53.0	8.0	13	80.0	12.0	13	
300/400 350 26.0 4.5 15 52.5 300/400 300 25.5 5.0 16 52.0 300/400 300 25.5 5.0 16 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 24.0 7.0 23 47.0	300 2	6.0	4.5	15	52.0	0.6	15	78.0	14.0	15	
1700 26.0 4.5 15 52.5 60/400 300 25.0 4.5 15 52.0 1700 300 25.5 5.5 18 51.5 60/400 850 25.5 5.0 16 52.0 300/400 850 25.5 5.0 16 52.0 300/400 850 24.0 7.5 25 47.0 300/400 850 24.0 7.0 23 48.0	850 2	6.0	4.5	15	52.5	8.5	14	0.61	13.0	14	
50 26.0 4.5 15 52.0 60/400 300 25.0 5.5 18 51.5 300/400 850 25.5 5.0 16 52.0 300/400 850 23.0 7.5 25 47.0 300/400 850 24.0 7.0 23 47.0	1700 2	0.9	4.5	15	52.5	8.5	14	19.0	13.0	14	
60/400 300 25.0 5.5 18 51.5 1700 850 25.5 5.0 16 52.0 300/400 300 23.5 7.5 25 47.0 300/400 850 24.0 7.0 23 48.0	50 2	6.0	•.5	15	52.0	9.5	15	78.5	13.5	15	
300/400 350 25.5 5.0 16 52.0 300/400 300 24.0 7.5 25 47.0	300 2	5.0	5.5	18	51.5	10.0	16	78.0	14.0	15	
1700 25.5 5.0 16 52.0 500 47.0 7.5 7.5 25 47.0 300/400 300 24.0 7.5 24 47.0 300/400 850 24.0 7.0 23 48.0	850 2	5.5	2.0	16	52.0	9.5	15	78.5	13.5	15	
50 23.0 7.5 25 47.0 300/400 300 23.5 7.5 24 47.0 300/400 850 24.0 7.0 23 48.0	1700 2	5.5	0.3	16	52.0	9.5	15	78.5	13.5	15	
300/400 300 23.5 7.5 24 47.5 850 24.0 7.0 23 48.0	50 2	3.0	7.5	25	47.0	14.5	24	70.5	21.0	23	
850 24.0 7.0 23 48.0	300 2	3.5	1.5	24	47.5	14.0	23	71.5	20.5	22	
	850 24	4.0	0.7	23	48.0	13.5	22	72.5	20.0	22	
1700 24.0 7.0 23 48.0	1700 24	4.0	0.1	23	48.0	13.5	22	72.5	19.5	21	

Range	& Nidth	PS CZ Data		1ST CZ			2ND CZ			3RD CZ	
· · ·	Atlantic 1N - 69W		RCZ1 (Nm)	CZW (Nm)	$\frac{CZM}{RCZO}(\%)$	RCZ1 (Nm)	CZW (Nm)	$\frac{CZW}{RCZo}(\%)$	RCZ1 (Nm)	CZW (Nm) H	CZW (%)
Mo.	RCVR/TGT (Ft)	FREQ (Hz)									
		50	34.0	3.0	8	68.5	1	1			
	60/60	300	35.0	1	1	70.0	1	,			
	200/000	850	35.0	4.0	10	69.5	10.0	13			
		1700	35.5	5.5	13	69.5	0.6	12			
ARY		50	34.0	3.5	6	68.5	6.5	6			
TAX.	601100	300	34.5	10.5	23	69.5	21.0	23			
EB	not lon	850	34.5	6.5	16	69.5	8.5	п			
E		1700	34.5	3.5	6	69.5	11.0	14			
		50	34.0	8.0	19	68.0	1	1			
	001/100	300	34.0	1	1	0.69	1	1			
	not long	850	34.0	1	1	0.69	1	1			
		1700	34.0	I	1	0.69	1	1			
		50	34.5	5.5	14	0.69	11.5	14			
	60/60	300	34.5	3.5	6	0.69	8.0	10			
•	00/00	850	35.0	2.5	7	69.5	6.0	8			
		1700	35.0	2.5	7	69.5	5.5	7			
X		50	34.0	4.0	11	0.69	8.0	10			
AM	60/100	300	34.5	4.0	10	0.69	6.5	6			
-	004/00	850	34.5	3.5	6	69.5	6.0	8			
		1700	34.5	3.5	9	69.5	6.0	8			
-		50	33.5	2.0	6	68.5	2.5	4			
	300/1400	300	34.0	7.0	17	0.69	1	1			
	ant loof	850	34.0	5.5	14	0.69	7.5	10			
		1700	34.0	5.0	13	0.69	6.0	8			

Table	E I. ICAL	S CZ		150 07		_	20 UNC			360 03
Maile	Atlantic 31N - 69W		RCZI (Nm)	CZW (Nm)	CZM (%) RCZo (%)	RCZ1 (Nm)	CZW (Nm)	C2M (%) RC20 (%)	RCZI (Nm)	CZW CZW (% (Nm) RCZO (%
Mo.	RCVR/FGT (Ft)	FREQ (Hz)								
		50	33.0	4.0	11	66.5	1.0	10		
	60/60	300	35.0	2.0	5	10.0	3.5	5		
	20100	850	35.0	2.0	5	70.5	3.0	4		
		1700	35.5	1.5	4	11.0	2.5	3		
1		50	34.5	3.5	6	68.0	5.0	1		
Sn	60/100	300	34.5	3.5	6	69.5	4.5	9		
DU	00+/00	850	34.5	3.5	6	70.0	4.0	5		
A		1700	35.0	3,0	8	70.5	3.5	5	4	
-		50	34.0	6.5	16	69.5	10.5	13		
	001/000	300	34.0	6.0	15	69.5	10.5	13		
	00+/000	850	34.5	5.5	14	70.0	8.5	11		
		1700	34.5	5.0	13	70.0	8.0	10		
		50	34.5	1.5	4	69.5	2.5	4		
	60/60	300	35.0	4.5	II.	70.0	0.6	11		
•	00/00	850	35.0	4.5	11	70.0	0.6	11		
		1700	35.0	4.5	11	70.0	0.6	11		
BER		50	34.0	3.5	6	0.69	3.0	4		•
	60/1400	300	34.5	4.0	10	69.5	7.5	10		
IAC	not loo	850	34.5	5.0	13	69.5	10.0	13		
N		1700	34.5	6.0	15	70.0	10.0	13		
-		50	34.0	6.0	15	0.69	11.0	14		
	300/400	300	34.0	5.5	14	69.5	8.5	11		
	and look	850	34.0	4.5	12	69.5	6.5	6		
		1700	34.5	4.0	10	69.5	0.9	80		
			the second second second second							

SRD CZ CZW CZ (Nm) RC				2.5 5 1.5 20 3.5 7 3.0 6	4.0 4.5 4.5 3.0 6	3.5 1.5 3.0 6 3.0 6
RCZI (Nm)				46.5 45.0 45.5 46.0	42.0 45.0 44.5 45.5	45.5 47.0 45.5 45.5
C2W (%)				6 24 6	ოთიი	80 m m 90
ZND CZ CZW (Nm)				2.0 9.5 2.0	1.0 3.0 3.0	2.5 1.0 1.0 2.0
RCZ1 (Nm)				30.5 29.5 30.5 30.5	30.5 30.0 30.0	30.5 31.0 30.5 30.5
<u>CZW</u> (%) RCZO (%)				12 22 14 12	3 14 15 15	12 3 9
1ST CZ CZW (Nm)				2.0 4.0 2.5 2.0	0.5 2.5 2.5 2.5	2.0 0.5 1.5 1.5
RCZ1 (Nm)	NONE NONE NONE NONE	NONE NONE NONE NONE	NONE NONE NONE NONE	15.0 14.5 15.0 15.0	14.5 15.0 14.5 14.5	14.5 15.5 14.5 14.5
Data	FREQ (Hz) 300 850 1700	50 300 850 1700	50 300 850 1700	50 300 850 1700	50 300 850 1700	50 300 850 1700
e I. <u>ICAF</u> e & <u>width</u> editerraneau 36N - 18E	RCVR/TGT (Ft) 60/60	60/400	300/400	60/60	60/400	300/400
Table Range	Wo.	FEBRUARY	-		YAM	-

| RCZI <u>CZW</u> <u>CZW</u> (%) RCZI
(Nm) (Nm) <u>RCZo</u> (%) (Nm) | 19.0 1.5 8 37.0 | 18.0 3.0 14 36.5

 | 18.0 2.0 10 36.5 | 18.0 2.0 10 36.5 | 18.0 2.0 10 36.5

 | 17.5 3.0 15 36.0 | 18.0 3.5 16 36.5 | 0.00 CT C.7 C.1T | NONE
NONE
NONE
NONE | 16.5 3.5 18 36.0
 | 16.0 2.5 14 35.0
 | 16.5 3.0 15 35.5 | 16.5 3.0 15 35.5 | 17.0 3.5 17 36.0 | 17.0 2.5 13 35.5 | 17.0 3.0 15 35.0 | 17.0 2.5 13 35.0 | 10.0 2.5 20 20.5 | 9.5 3.0 24 20.0
 | 0 1 20 20 200 |
|---|--
--
--
---|--|--
--
--|--|--|--|--
--
---|--|--|--|--
---|--|--|---|--|---|
| (CZo (%) RCZI (Nm) | 8
13 0 | 14 36.5

 | 10 36.5 | 10 36.5 | 10 36.5

 | 15 36.0 | 16 36.5 | D.00 CT | | 18 36.0
 | 14 35.0
 | 15 35.5 | 15 35.5 | 17 36.0 | 13 35.5 | 15 35.0 | 13 35.0 | 20 20.5 | 24 20.0
 | 24 20.0 |
| $\frac{\text{CZW}}{\text{(Nm)}} \frac{\text{CZW}}{\text{RCZO}} (\%)$ | 1 5 4 | 2.0 5

 | 2.0 5 | 2.0 5 | 1.5 4

 | 3.0 8 | 2.5 6
3.0 8 | 0 0.0 | | 5.0 12
 | 1.5 4
 | 2.0 5 | 3.0 8 | 4.0 10 | 3.5 9 | 5.0 13 | 4.5 11 | 3.5 15 | 4.5 18
 | 3.5 15 |
| RCZ1
(Nm) | \$3 D | 52.5

 | 54.5 | 54.5 | 53.5

 | 53.5 | 54.0 | | | 54.0
 | 53.0
 | 53.5 | 53.5 | 52.0 | 53.5 | 53.5 | 53.5 | 31.5 | 31.0
 | 30.5 |
| CZW
(Nm) | 0 9 | 5.5

 | 3.5 | 3.5 | 4.5

 | 5.0 | 4.5 | | | 7.0
 | 5.0
 | 5.0 | 4.5 | 7.0 | 4.5 | 5.0 | 3.0 | 5.0 | 5.5
 | 3.5 |
| CZM (%)
RCZ0 (%) | 9 | 19

 | 9 | 9 | 80

 | 6 | 8 - | | | 12
 | 6
 | 6 | 8 | 12 | 8 | 6 | 5 | 14 | 15
 | 10 |
| | $ \begin{array}{c cccccccccc} RCZI & CZW $ | RC21 C2M C2M RC21 C2M C2M </td <td>RCZ1 CZW <thczn< th=""> <thczn< th=""></thczn<></thczn<></td> <td>RCZ1 CZW <thczn< th=""> <thczn< th=""></thczn<></thczn<></td> <td>RCZ1CZWCZNCZNS5S5S5S6S4S5S6<th< td=""><td>RCZ1CZW</td><td>RC21CZW</td><td>RCZ1CZW</td><td>RCZ1CZW</td><td>RCZ1 CZM CZM<td>RCZ1 CZW CZW RCZ1 CZM CZM<</td><td>RC21 C2W RC21 C2W RC21 C2W C2W</td><td>RC21 CZM CZM CZM Nm RC21 CZM (%) Nm RC21 CZM RC21 CZM RC21 CZM RC21 KC20 K RC21 CZM RC21 KC2M K RC21 K RC21 K RC21 K R</td><td>RC21 \overline{CZM} \overline{CZM} $\overline{KC21}$ $\overline{KC21}$ $\overline{KC21}$ \overline{CZM} $\overline{KC20}$ KC</td><td>RC21 $\overline{C2W}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC20}$ \overline{K} $\overline{KC20}$ \overline{K} $$</td><td>RC21 C2W Nm RC21 C2W RC21 C2W C2W<</td><td>RC21 $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) $\overline{RC20}$ (%) $\overline{RC21}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 3.0 15 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE 2.0 12 53.5 5.0 9 16.0 2.5 3.5 2.0 5 54.5 4.0 7.0 12 17.0 2.5 3.5 2.0</td><td>RC21 C2M C2M KC21 C2M KC21 C2M C2M KC20 K) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE NONE 17 53.5 5.0 9 16.5 3.0 15 35.5 5.0 7 0</td><td>RC21 C2M C2M<!--</td--><td>RC21 C2M KC2 KC3 KC3<!--</td--></td></td></td></th<></td> | RCZ1 CZW CZW <thczn< th=""> <thczn< th=""></thczn<></thczn<> | RCZ1 CZW CZW <thczn< th=""> <thczn< th=""></thczn<></thczn<> | RCZ1CZWCZNCZNS5S5S5S6S4S5S6 <th< td=""><td>RCZ1CZW</td><td>RC21CZW</td><td>RCZ1CZW</td><td>RCZ1CZW</td><td>RCZ1 CZM CZM<td>RCZ1 CZW CZW RCZ1 CZM CZM<</td><td>RC21 C2W RC21 C2W RC21 C2W C2W</td><td>RC21 CZM CZM CZM Nm RC21 CZM (%) Nm RC21 CZM RC21 CZM RC21 CZM RC21 KC20 K RC21 CZM RC21 KC2M K RC21 K RC21 K RC21 K R</td><td>RC21 \overline{CZM} \overline{CZM} $\overline{KC21}$ $\overline{KC21}$ $\overline{KC21}$ \overline{CZM} $\overline{KC20}$ KC</td><td>RC21 $\overline{C2W}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC20}$ \overline{K} $\overline{KC20}$ \overline{K} $$</td><td>RC21 C2W Nm RC21 C2W RC21 C2W C2W<</td><td>RC21 $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) $\overline{RC20}$ (%) $\overline{RC21}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 3.0 15 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE 2.0 12 53.5 5.0 9 16.0 2.5 3.5 2.0 5 54.5 4.0 7.0 12 17.0 2.5 3.5 2.0</td><td>RC21 C2M C2M KC21 C2M KC21 C2M C2M KC20 K) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE NONE 17 53.5 5.0 9 16.5 3.0 15 35.5 5.0 7 0</td><td>RC21 C2M C2M<!--</td--><td>RC21 C2M KC2 KC3 KC3<!--</td--></td></td></td></th<> | RCZ1CZW | RC21CZW | RCZ1CZW | RCZ1CZW | RCZ1 CZM CZM <td>RCZ1 CZW CZW RCZ1 CZM CZM<</td> <td>RC21 C2W RC21 C2W RC21 C2W C2W</td> <td>RC21 CZM CZM CZM Nm RC21 CZM (%) Nm RC21 CZM RC21 CZM RC21 CZM RC21 KC20 K RC21 CZM RC21 KC2M K RC21 K RC21 K RC21 K R</td> <td>RC21 \overline{CZM} \overline{CZM} $\overline{KC21}$ $\overline{KC21}$ $\overline{KC21}$ \overline{CZM} $\overline{KC20}$ KC</td> <td>RC21 $\overline{C2W}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC20}$ \overline{K} $\overline{KC20}$ \overline{K} $$</td> <td>RC21 C2W Nm RC21 C2W RC21 C2W C2W<</td> <td>RC21 $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) $\overline{RC20}$ (%) $\overline{RC21}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 3.0 15 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE 2.0 12 53.5 5.0 9 16.0 2.5 3.5 2.0 5 54.5 4.0 7.0 12 17.0 2.5 3.5 2.0</td> <td>RC21 C2M C2M KC21 C2M KC21 C2M C2M KC20 K) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE NONE 17 53.5 5.0 9 16.5 3.0 15 35.5 5.0 7 0</td> <td>RC21 C2M C2M<!--</td--><td>RC21 C2M KC2 KC3 KC3<!--</td--></td></td> | RCZ1 CZW CZW RCZ1 CZM CZM< | RC21 C2W RC21 C2W RC21 C2W C2W | RC21 CZM CZM CZM Nm RC21 CZM (%) Nm RC21 CZM RC21 CZM RC21 CZM RC21 KC20 K RC21 CZM RC21 KC2M K RC21 K RC21 K RC21 K R | RC21 \overline{CZM} \overline{CZM} $\overline{KC21}$ $\overline{KC21}$ $\overline{KC21}$ \overline{CZM} $\overline{KC20}$ KC | RC21 $\overline{C2W}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC21}$ $\overline{C2W}$ $\overline{RC20}$ \overline{K} $\overline{KC20}$ \overline{K} $$ | RC21 C2W Nm RC21 C2W RC21 C2W C2W< | RC21 $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) $\overline{RC20}$ (%) $\overline{RC21}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{C2M}$ $\overline{RC20}$ (%) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 3.0 15 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE 2.0 12 53.5 5.0 9 16.0 2.5 3.5 2.0 5 54.5 4.0 7.0 12 17.0 2.5 3.5 2.0 | RC21 C2M C2M KC21 C2M KC21 C2M C2M KC20 K) 18.0 1.5 8 37.0 1.5 4 52.0 6.0 10 18.0 3.0 14 36.5 2.0 5 54.5 5.5 10 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 18.0 2.0 10 36.5 2.0 5 54.5 3.5 6 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 17.5 2.5 13 36.0 3.0 8 54.5 4.0 7 NONE NONE NONE NONE NONE 17 53.5 5.0 9 16.5 3.0 15 35.5 5.0 7 0 | RC21 C2M C2M </td <td>RC21 C2M KC2 KC3 KC3<!--</td--></td> | RC21 C2M KC2 KC3 KC3 </td |

third CZ annulus to the nearest one half nautical mile. CZW is the width of the annulus also the nearest one half nautical mile. The third column of numbers is the ratio of CZW to the range of the outer edge of the annulus (RCZO), expressed as a percentage.

After carefully studying this data, the following conclusions were made concerning CZ propagation:

(1) The range to the first CZ is approximately 14 to 18 nm at the Mediterranean location, 23 to 27 nm at the Pacific location, and 33 to 35 nm at the Atlantic location.

(2) Range to the CZ decreases and annuluswidth increases as source and receiver get deeper in allcases.

(3) The ranges to the second and third annuli are approximately whole number multiples of the ranges to the inner and outer edges of the first annulus in all cases.

(4) The range or width of a CZ annulus does not appear to have any significant frequency dependence.

3. CZ Gain and Transmission Loss Analysis

Convergence zone gain is defined as the difference between the transmission loss expected under conditions of spherical propagation and the actual transmission loss observed. This definition is expressed in Eq. (1).

 $G = 20 \log(r) + a(r) - TL$ (1)

In this equation, G is the CZ gain, r is the range to the

CZ annulus, a is the attenuation coefficient associated with the frequency of interest, and TL is the actual transmission loss observed in the CZ annulus for that frequency. All terms in Eq. (1) are in decibels (dB).

In actual convergence zones, TL (and therefore gain) is by no means a constant value. Contributions of several possible propagation paths at any one point and the time varying nature of sound paths in the ocean cause coherence effects to exist. These effects make TL vary in both space and time. Coherence effects are more pronounced at lower frequencies (longer wavelengths) where the time varying effects are small compared to spatially distributed effects. In ICAPS, the more predictable coherence conditions are included in the mathematical model.

Since a single TL value was desired for the envisioned calculator model, an attempt was made to pick the "average" TL in the ICAPS CZ annuli. As with the range estimates, this called for subjective judgement. Figure 3 shows a typical ICAPS CZ presentation which has coherence effects in evidence. The figure suggests how an "average" TL was chosen as best representing that annulus. 'Two levels were chosen (labeled high and low in the figure) which bracket the majority of the TL points within the annulus. The approximate midpoint between those levels was then picked as "the" TL for that CZ.

As an extra point of interest, the high and low TL levels were studied. It was noted that ICAPS predicts TL





variations from about ± 10dB around the "average" level. If this is truly representative of CZ coherence effects, an ASW unit armed only with an estimate of the "average" TL in a certain CZ annulus should expect to see variations of about that magnitude around the estimate in hand.

Using TL levels estimated by the procedure described above, and employing Eq. (1), CZ gain values predicted by ICAPS were obtained and tabulated. The values produced are contained in Tables II and III. Table II shows all of the data from the Pacific location. Table III contains only 300 Hz data from the Atlantic and Mediterranean locations. (50, 850, and 1700 Hz data were omitted from Table III because it became obvious during data collection that G is not frequency dependent.)

Again after careful study, the following conclusions were drawn concerning CZ gain:

(1) CZ gain values range from about eight to twenty dB in all three areas observed.

(2) CZ gain is the same value for first,second, and third CZ in any given case.

(3) In general, CZ gain is independent of frequency. An exception to this conclusion is that at low frequency (below 300Hz), especially when source or receiver or both are above the SLD and/or near the surface, there is apparently somewhat less gain than evident for higher frequencies. This difference is probably due to stronger diffraction of the longer wavelengths.

(4) CZ gain seems to be highest when source and receiver are at or near the same depth.

Month SLD(ft)	RCVT/Tgt (ft)	Freq (Hz)	lst CZ	CZ Gain (df 2nd CZ	3) <u>3rd Cz</u>
	60/60	50 300 850 1700	7 14 14 15	7 13 13 15	6 12 13 12
FEB 246	60/400	50 300 850 1700	9 12 11 11	9 12 11 11	9 11 12 12
	300/400	50 300 850 1700	12 12 10 12	11 12 11 10	10 11 12 11
	60/60	50 300 850 1700	16 16 16 16	17 17 17 17	16 16 16 17
MAY 33	60/400	50 300 850 1700	10 10. 11 9	10 11 12 11	12 13 15 12
	300/400	50 300 850 1700	14 13 13 12	14 13 14 11	14 14 11 13

Table II. ICAPS CZ Gain Data Observed at the Pacific Ocean Location. (Page 1 of 2)

Month SLD(ft)	Rcvr/Tgt (ft)	Freq (Hz)	<u>lst CZ</u>	Z Gain (dB 2nd CZ	<u>3rd CZ</u>
	60/60	50 300 8 50 1700	11 14 15 16	11 13 18 17	13 12 20 18
AUG 0	60/400	50 300 850 1700	7 9 12 12	7 12 14 13	8 13 15 15
	300/400	50 300 850 1700	14 11 11 12	14 14 12 13	14 12 15 11
	60/60	50 300 850 1700	8 9 15 14	7 12 18 15	6 12 16 15
<u>NOV</u> 98	60/400	50 300 850 1700	9 12 11 11	9 13 11 11	8 11 11 11
	300/400	50 300 850 1700	11 12 9 10	11 11 11 9	11 11 12 11

Table II. ICAPS CZ Gain Data Observed at the Pacific Ocean Location. (Page 2 of 2)

.

.

Ocean	Month SLD(ft)	Rcvr/Tgt (ft)	<u>1st C2</u>	2nd CZ	ain <u>3rd CZ</u>
	FEB 328	60/60 60/400 300/400	17 13 17	14 13 18	r.
TIC	MAY	60/60 60/400 300/400	19 16 13	14 12 17	0
ATLAN	AUG	60/60 60/400 300/400	15 10 14	17 13 15	•
	<u>NOV</u>	60/90 60/400 300/400	13 12 13	11 10 12	
 •	<u>MAY</u> 10	60/60 60/400 300/400	14 12 17	13 10 18	16 10 20
TERRANEAN	AUG	60/60 60/400 300/400	17 11	19 9	17 10
MEDI	NOV 10	60/60 60/400 300/400	11 10 12	13 11 14	15 12 15

Table III. ICAPS 300Hz CZ Gain Data Observed at Atlantic and Mediterranean Locations.

III. CZ RAY THEORY ANALYSIS AND MODEL DEVELOPMENT

A. CZ RANGE AND WIDTH

It was decided to use ray tracing as the method for determining CZ range and width because of the simplicity of the mathematics involved and because of the intuitive appeal of sound rays depicting the propagation of sound. The alternative approach, that of normal mode theory, was rejected on the grounds that it would be much more complicated, requiring capabilities far beyond those available in the calculators at hand.

Figure 4 shows four sound rays of particular interest in CZ propagation. The order of these rays is described for the "typical" case in the following discussion. An "atypical" case will be mentioned later.

Ray #1 departs the SLD at zero degree depression angle. It reaches its greatest depth at the bottom of the DSC and returns to the SLD at some particular range and at horizontal incidence. The horizontal range from SLD to SLD is termed cycle distance. The cycle distance for this ray is designated r_0 .

Ray #2 is the next ray of interest found as the departure angle from the SLD is increased downward. This ray passes down through and below the bottom of the DSC before turning back upward. It returns to the SLD at the shortest range from the starting point of any ray within the bundle of rays





undergoing CZ refraction. This range is designated r_{min} . The angle of departure for this ray is designated θ_{rmin} . Each ray between #1 and #2 crosses all of the previous (lesser departure angle) rays on its way up from its lowest depth.

As departure angle from the SLD is further increased, the next sound ray of interest, #3, is located. This ray has a cycle distance equal to r_0 . Its maximum depth is greater than that for ray #2. It departs from and arrives back at the SLD at an angle designated θ_{rswp} . Rays between #2 and #3 do not cross each other, but they do cross the earlier rays on their way back up to the SLD.

In the CZ annulus, the rays between #1 and #2 sweep inward toward the source as departure angle increases. After ray #2 they sweep out away from the source as angle increases further. For this reason, the region formed by rays between #1 and #3 is called the reswept zone.

Finally, as angle of departure from the SLD is increased to maximum angle for CZ propagation, we observe ray #4. This ray turns upward at a depth equal to the water column depth at that location. It returns to the SLD at the greatest distance of all CZ refracted rays. Rays departing the SLD at angles greater than that for ray #4 would be reflected off the bottom and are not of significance for the CZ propagation path.

As mentioned earlier, this progression of rays exists in a "typical" CZ situation. If, however, the ocean bottom

were more shallow, cycle distance for ray #4 would be reduced. If the bottom were shallow enough, ray #4's cycle distance would be less than r_0 . In that case, the reswept zone would be reduced to the region between rays #2 and #4. This situation is called the "atypical" case.

B. RANGE AND WIDTH MODEL

In the calculator programs developed, provision is made for entering and storing a five point sound velocity profile which defines the DSC only. The first depth and velocity pair entered (D_1, C_1) equate to the appropriate values found at the SLD. The fifth depth entered (D_5) is the depth at the bottom of the DSC where sound velocity is equal to that at the SLD. The other three depth/velocity pairs must be picked subjectively from a graph of the SVP of interest. If a mixed layer exists, the gradient in that layer is taken to be 0.02 sec⁻¹ (a purely pressure induced gradient to two place accuracy). The program calculates the four layer gradients within the DSC profile entered, and uses the fourth (deepest) layer gradient in ray calculations that occur below the DSC. It would have been desirable to allow several more points in the SVP, but calculator data storage capacity and program step limitations preclude more than five depth/velocity pairs.

The overall scheme used to predict CZ range and width is to trace a series of rays starting at the SLD with a zero depression angle ray. That first ray yields r_0 which is stored.

Then an iterative process is begun in which the angle is incremented and each succeeding cycle distance determined is compared to the previous one until r_{min} and θ_{rmin} are found. (θ_{rmin} is stored for use in the CZ gain and TL program, to be discussed later.) Corrections are then made to r_{min} and r_0 to account for surface duct effects (if any) and source and receiver depth separation from the SLD. Range to the inner edge of the CZ is r_{min} plus corrections, and range to the outer edge is r_0 plus corrections.

In the first attempt to produce a calculator program, the cycle distance of ray #4 (the ray just grazing the bottom) was compared to r_0 . The greater of the two was picked as the basic distance for determining range to the outer edge of a CZ. Later on, this portion of the program had to be deleted to save program steps. The final programs developed ignore bottom depth and do not include rays outside the reswept zone in determining annular width. This is probably a shortcoming of the programs but the seriousness of the errors it causes will not be known without further study.

A commonly applied rule-of-thumb states there must be a minimum 300 fathoms of depth excess (water column below the DSC) in order to have "reliable" CZ conditions. It was observed that a fully developed reswept zone existed in every case in the locations studied, and separate calculations showed that somewhat less than 300 fathoms depth excess was required to complete the zone. Therefore, a program user should consider the 300 fathom rule-of-thumb before

running the range and width program. With less than 300 fathoms depth excess, the possibility exists for an "atypical" CZ propagation situation where the reswept zone is reduced in width due to bottom ray limiting.

Another program shortcoming involves an assumption that both source and receiver would be more shallow than the second DSC SVP point chosen (depth D2). In other words, the programs were designed to allow for source/receiver depths within the mixed layer or the first isogradient layer below the SLD. After the five point SVP is entered and the gradients computed, source and receiver depths are entered and converted to velocities. The programs determine these velocities (C_S and C_R) by subtracting an appropriate amount from the velocity at the SLD. The amount subtracted is determined by depth separation from the SLD and by the gradient in either the ML or the first layer below the SLD. If source or receiver depth is greater than D2, sound velocity should be determined by correcting C_2 (the velocity at D_2) and by using g2 (the second layer gradient). Since this is not done, velocities for source/receiver depths below D2 will be in error (usually too low). Source and receiver velocity errors are carried over into Δr_s and Δr_p range corrections. If the velocities are too low, the range corrections will be too large. This is normally a rather insignificant source of total range error, however, since Δr_s and Δr_R errors will be a small fraction of the magnitude of those terms and because the range correction terms are small to begin with.

The mathematics of ray tracing in isogradient layers is quite straightforward. By Snell's Law,

$$\frac{C_1}{\cos \theta_1} = \frac{C_2}{\cos \theta_2} = \frac{(A \text{ constant})}{\text{ for each ray}}$$
(2)

the angle of a ray departing a layer can be determined from the angle of entry into that layer. In Eq. (2), C_1 is the sound velocity where the sound ray enters a layer, θ_1 is the angle of entry, C_2 is the sound velocity where the ray departs the layer, and θ_2 is the angle of departure.

Rays travel in circular arcs within constant gradient layers, and the radius of curvature is:

$$R = \left| \frac{C_1}{g_1 \cos \theta_1} \right|$$
(3)

 C_1 and θ_1 are as defined above and g_1 is the gradient within the layer (in this case, layer 1).

Finally, the horizontal distance traveled by a ray while traversing a layer is:

$$\Delta r = \left| R \left(\sin \theta_2 - \sin \theta_1 \right) \right| \tag{4}$$

Figure 5 demonstrates an example application of Eqs. 2 through 4. It should be noted that absolute value signs are used in Eqs. 3 and 4 because the gradient in Eq. 3 and the difference of sines in Eq. 4 may be positive or negative, while R and Δr are always positive.

The programs use these equations to compute the horizontal range increments each ray accumulates within the four layers, doubles each term (to account for the downward and



Figure 5. Horizontal Distance Traveled Within an Isogradient Layer.

upward passes through each layer), and then sums the terms to obtain cycle distances. The fourth layer requires a slightly different treatment because the rays become horizontal and then turn back upward within that layer. Essentially the same formulas are used, however. The equations are also used to compute the range correction terms.

In considering the various possible ray paths between source and receiver, it was decided there were four basic situations which could occur:

- No mixed layer, both source and receiver below the SLD. (Deep/Deep)
- Mixed layer present, both source and receiver below the SLD. (Deep/Deep/ML)
- Mixed layer present, both source and receiver within the layer. (Shal/Shal)
- Mixed layer present, source or receiver above the SLD, the other below. (Crosslayer)

The only difference between the first two cases is the mixed layer effect in case 2. That effect causes a widening of annuli due to spreading of sound rays as they travel up to the surface and back down to the SLD within the layer. The mixed layer effect is also included in the third and fourth cases above.

It was originally intended to include all four cases in one range prediction program. Again due to calculator limitations, it was necessary to use two programs to cover the four possibilities. The first range program (labeled Deep/ Deep) is for cases 1) and 2) above when both source and receiver are below the SLD whether or not an ML exists. The

second range program (labeled Shal/Shal or Crosslayer) is for use in cases 3) and 4) above when source or receiver or both are above the SLD.

Formulas used to determine range to inner edge of the first CZ (RCZi) and range to the outer edge of the first CZ (RCZo) follow:

RCZi	= $r_{min} - \Delta r_s - \Delta r_R$	Deep/Deep
	= $r_{min} + \Delta r_{S} + \Delta r_{R}$	Shal/Shal
	= $r_{min} + \Delta r_s - \Delta r_R$	Crosslayer
RCZO	$= \mathbf{r}_0 + \{ \begin{smallmatrix} 0 \\ 2 & \Delta \mathbf{r}_0 \end{smallmatrix} \} + \Delta \mathbf{r}_S + \Delta \mathbf{r}_R$	Deep/Deep Deep/Deep/ML
	$= r_0 + 2 \Delta r_0 + \Delta r_s - \Delta r_R$	Shal/Shal
	= $r_0 + 2 \Delta r_0 + \Delta r_s + \Delta r_B$	Crosslayer

In these equations, r_{min} and r_0 have been previously defined, Δr_S and Δr_R are the respective horizontal range corrections which account for source and receiver depth separation from the SLD, and 2 Δr_0 is the correction for mixed layer effect. Figures 6(a) through 6(f) (not to scale) depict the RCZi and RCZo formulas in graphic form. Ranges to second and subsequent CZ annuli are taken to be integer multiples of the ranges produced.

Two items of interest, both evident in Figs. 6(a) - 6(f), are worth mentioning at this point. First, acoustical reciprocity is envoked and the more shallow of source and receiver is always treated as "source" of the sound rays within the calculator programs. Secondly, only those sound rays



Figure 6(a). RCZ_i for Deep/Deep Case.



Figure 6(b). RCZ_i for Shal/Shal Case.



Figure 6(c). RCZ_i for Crosslayer Case.



Figure 6(d). RCZ₀ for Deep/Deep Case.



Figure 6(e). RCZ₀ for Shal/Shal Case.



Figure 6(f). RCZ0 for Crosslayer Case.

which experience no more than one ocean surface reflection between source and receiver are considered in this model. Both of these conventions are commonly applied to ray tracing models. Although they theoretically have little or no effect on model results, they greatly simplify the work of programming a ray tracing model.

C. CZ GAIN AND TRANSMISSION LOSS MODEL

In general, transmission loss is defined as ten times the logarithm of the ratio of sound intensities measured at one meter from a source and at range r from that source.

$$TL = 10 \log \frac{I_1}{I_r}$$

Intensity has units of power per unit area. The change in intensity between one meter and range r is due to geometric spreading of the power over a different amount of area and due to attenuation of some of the power through absorption, scattering, diffusion, etc.

In ray tracing theory, it is assumed there is no sound power transfer across sound rays. Therefore, the power flowing from a source between two sound rays remains between those rays and travels out in a direction parallel to the ray paths. Determining the portion of transmission loss due to geometric spreading (TL_g) under this assumption reduces to finding ten times the logarithm of the ratio of areas (at range r and at one meter) penetrated by the power between the two rays perpendicular to the direction of travel.

$$TL_g = 10 \log \frac{A_r}{A_1}$$

A mathematical development of this technique is contained on pages 119-121 of Ref. 1.

Figure 7 shows how this method was adapted for use in the CZ Gain and Transmission Loss portion of the calculator model developed. The area (A_1) at one meter from the source is the product of area height and area circumference. The sound rays bounding the area above and below are the minimum and maximum departure angle rays which produce the reswept zone in the CZ annulus. The angular spread of those rays $(\Delta \theta)$ in radian units times the sphere radius (1 meter) is the area height. Cosine of the average angle of departure of the rays (θ_1) times the sphere radius times 2π is circumference of the area. Therefore:

 $A_1 = 2\pi \Delta \theta \cos \theta_1 (m^2)$

In the CZ, the area (A_2) over which the same power is distributed is also found by a product of area circumference and area width. Circumference is 2π times range to the CZ (RCZi). Width of the area perpendicular to the sound rays is the product of CZ annulus width (CZW) and the sine of the average angle of arrival of the rays at the receiver depth (θ_2) . Therefore:

 $A_2 = 2\pi RCZi CZW \sin \theta_2 (m^2)$

and the geometric TL expression becomes:





$$TL_{g} = 10 \log \frac{RCZi CZW \sin \theta_{2}}{\Delta \theta \cos \theta_{1}}$$

Substituting this expression back into Eq. 1, which is the definition of CZ gain, and reducing to simplest form yields the algorithm used to determine G in the calculator model:

$$G = 10 \log \frac{RCZi \ \Delta \theta \ \cos \theta_1}{CZW \ \sin \theta_2}$$
(5)

To implement this algorithm, the program has only to determine the angular terms since RCZi and CZW are available from the range program results. After one of the range programs has been run, the user loads the G and TL program into calculator memory without altering the contents of the data storage registers left from the range program. Then the iterative ray tracing process begun in the range program is continued in the gain program. The angle of departure of sound rays from the SLD is incremented beyond θ_{rmin} (left in storage from the range program) and cycle distances produced are checked for approximate equality with ro. In this way, the ray which completes the reswept zone is found, and its angle of departure from the SLD is θ_{rswp} . Then θ_{rswp} and zero degrees (the angle for the ray producing cycle distance r_0) are converted to angles of departure from the source depth, θ_{SR} and θ_{SO} respectively, and angles of arrival at the receiver depth, θ_{RR} and θ_{RO} respectively, using Snell's law. The angular terms in Eq. 5 are then computed using the following formulas:

$h\theta = \theta_{SR} + \theta_{SO}$	Deep "source"
= $\theta_{SR} - \theta_{SO}$	Shal "source"
$\theta_1 = \frac{\theta_{SR} - \theta_{SO}}{2}$	Deep "source"
$=\frac{\theta_{SR}+\theta_{SO}}{2}$	Shal "source"
$\theta_2 = \frac{\theta_{RO} + \theta_{RR}}{2}$	

Recall that "source" in the model refers to the more shallow of source and receiver. Therefore, the deep "source" forms of these formulas are used only after using the Deep/Deep range program. In all other cases, the "source" is considered to be shallow. Figure 8 depicts these angular relationships for the various depth conditions.

It should be pointed out there are two inherent errors in the angular quantities determined. First, the possible source and receiver sound velocity errors mentioned earlier could cause the gain algorithm angles to be slightly off. This would only occur if depths greater than D_2 were entered for source or receiver or both. Secondly, θ_{rswp} is found for the ray which has cycle distance equal to r_0 at the SLD. Since the actual CZ ray bundle departs from the source depth (vice SLD) and arrives at the receiver depth (vice SLD), the ray which completes the reswept zone will probably be different than the ray used and it will have a slightly different angle crossing the SLD. These angular errors will cause the





Figure 8. Determining angular terms for CZ Gain algorithm.

greatest CZ gain error in the sin θ_2 term of the algorithm. Since sine is directly proportional to angle at small angles, an error of a factor of two in θ_2 (a quite possible event) could cause a gain error of approximately 3 dB.

Once CZ gain is computed and stored, the sound frequency of interest is entered, and the attenuation coefficient is calculated using Thorpe's equation (p. 102, Ref. 1):

$$a = (0.001094) \left[\frac{0.1 f^2}{1 + f^2} + \frac{40 f^2}{4100 + f^2} \right] (dB/m)$$
(6)

In Eq. 6, f is in kHz, and the constant in front of the expression converts attenuation coefficient from dB/kyd to dB/m. The program user enters frequency in Hz, and the program performs the conversion to kHz.

Finally, the transmission loss in the n^{th} CZ annulus for the frequency of interest (TL_n) is determined by:

$$TL_n = 20 \log (n RCZi) + z (n RCZi) - G$$
 (7)

In this equation, the subscript n denotes the nth CZ annulus, the range to which is n times RCZi.

After a range program is run, and after the gain portion of the G and TL_n program has been completed, TL_n values for a variety of frequencies and CZ annuli may be rapidly obtained for the SVP, source depth, and receiver depth conditions entered. If, however, a different set of source/receiver depth conditions are also of interest, the entire procedure beginning with the appropriate range program must be performed again.

D. CALCULATOR PREDICTIONS COMPARED TO ICAPS

1. Choosing the SVP Points for the Program

The five point SVP limitation of the ray tracing procedure is a rather serious handicap in many situations. Actual sound velocity profiles not only are curvilinear in overall shape but also have many small scale features and they are time varying functions. Approximating these curves with only four straight line segments presents a difficult challenge.

In general, matching the gradients, sound velocities, and associated depths are all important in choosing SVP points. The greatest potential for causing large range prediction errors occurs when the SVP contains an extensive near surface layer with very slight velocity gradient. The horizontal distance traveled by a shallow depression angle ray within such a layer varies considerably with small changes in the gradient or layer thickness. Under such conditions, then, it is extremely important to match those characteristics as closely as possible.

Another important item to carefully match is the sound velocity at the DSC axis. This velocity determines the maximum angle of depression for each ray prior to commencing upward refraction. The horizontal distance traveled by a ray below the axis is highly dependent on that angle.

Table IV contains the five point sound velocity profiles picked by the author for use in comparing the program performance to ICAPS predictions. Depths in the table

5 Points	FEB	MAY	AUG	NOV
		PACIFIC		
D1	75	10	0	30
C1	1489.8	1500.2	1508.6	1497.7
D2	340	80	100	100
C2	1480.0	1490.0	1483.0	1484.0
D3	500	600	600	600
C3	1476.2	1477.0	1475.5 "	1476.0
D4	1060	1600	1750	1400
C4	1480.0	1485.0	1486.5	1483.0
D5	1940	2610	3120	2460
· · · ·		ATLANTIC		
D1	100	0	0	0
C1	1524.6	1530.9	1541.1	1535.5
D2	550	100	125	125
C2	1522.5	1522.0	1522.5	1522.5
D3	1080	575	550	625
C3	1493.0	1524.0	1524.5	1524.5
D4	1750	1225	1200	1175
C4	1495.0	1488.5	1487.5	1489.0
D ₅	3780	4175	4760	4460
	ME	DITERRANEAN		
D1		10	0	10
C1		1526.6	1537.6	1528.7
D2		30	50	50
C2		1518.0	1517.5	1517.5
D3		100	100	125
C3		1513.0	1513.0	1512.0
D4		800	700	900
C4		1521.5	1519.5	1522.5
D5		1125	1800	1290

Table IV. Five Point Sound Velocity Profiles. (Depths in meters, velocities in m/sec) are in meters, and sound velocities are in meters per second. The reader may want to plot these points on the graphs of Figs. 1(a) through 1(1) so he may see how the four isogradient layers picked match the ICAPS profiles. It should be pointed out that only the initial selection of SVP points was used in the subsequent comparisons of calculator model results to ICAPS predictions. Since an ASW aircrewman using the programs in attempting an in situ prediction of acoustic conditions would not be able to judge whether SVP point adjustments would improve or degrade prediction accuracy, it was felt that comparing resuts of the initial SVP point selection with ICAPS would be more meaningful to the objective of developing the calculator programs.

Comparing calculator model predictions to ICAPS predictions in a definitive statistical manner was not done. The main reason for this was alluded to in the preceding paragraphs. Since the SVP points entered in the calculator program must be picked subjectively by the person using the program and since it is unlikely different people would pick the exact same points off any given SVP, it is clear that calculator results can be expected to vary from operator to operator.

2. CZ Range and Annulus Width Comparisons

The calculator range programs produce one value each for RCZi and RCZo for any given SVP, source depth, and receiver depth situation. Under the same set of conditions, ICAPS yields four sets of RCZi and CZW values, one set for

each of the four frequencies entered. In order to compare the calculator performance to ICAPS it was first necessary to reduce the ICAPS predictions to one value each for RCZi and CZW for each SVP/source/receiver condition. This was done by simple averaging to eliminate the frequency variable from the ICAPS range and width predictions.

Figures 9(a) - 9(c) display range and width comparisons in graphical form for the Pacific, Atlantic, and Mediterranean locations respectively. In each figure the double barred lines represent the ICAPS first CZ annuli predictions (averaged over frequency), and the single barred lines represent the calculator predictions. Numerical values for inner and outer first CZ ranges may be obtained from the scales at the tops of the figures.

In all, there were 32 cases where these graphical comparisons could be made. The following comments pertain to those comparisons:

a) In 30 of the 32 cases the calculator annuli overlap at least a portion of the ICAPS annuli.

b) In 14 of the 32 cases the calculator annuli are completely contained within the limits of the ICAPS annuli.

c) In all 32 cases RCZi ranges predicted by the calculator were greater than those predicted by ICAPS. In the 12 Pacific cases, the calculator RCZi values were approximately 1.7 nm greater than ICAPS on the average. In the 12 Atlantic cases, the average difference was approximately






Comparisons of ICAPS and Calculator CZ Annuli Predictions. Mediterranean Sea.

2.8 nm. And in the eight Mediterranean cases, 1.5 nm was the mean difference.

d) In 27 of the 32 cases the CZ width predictions from the calculator were more narrow than the ICAPS predicted widths. Three of the five cases where calculator CZW exceeded ICAPS CZW were from the February SVP in the Atlantic location. That SVP contained a very deep (500 meter), nearly isovelocity layer near the surface. In such a profile, CZ refraction produces ray paths that are spread over a very wide (in this case 16-20 nm) annulus. Only the rays which return to the SLD within the first few nm at the inner edge of that annulus experience sufficient convergence to produce detectable CZ gain, however. Going from inner to outer edge of such an annulus the CZ refracted rays rapidly fan out experiencing progressively less convergence and producing progressively less CZ gain. Additionally, if the bottom grazing ray were considered, it would be seen to limit the reswept region of this type annulus to something far less than that indicated. Since the calculator model fails to account for either of these factors, it fails rather dramatically to produce a "practical" CZ annular width from this SVP type.

In summary, the calculator model produces CZ annuli that roughly agree with those produced by ICAPS in all three ocean basins considered. Calculator RCZi ranges are 5-10% greater on the average than the ICAPS values. Calculator CZW predictions (excluding the Atlantic February SVP) are

40-50% narrower than ICAPS widths on the average. And, the Atlantic February case indicates there is at least one SVP type in which the calculator model fails to produce even marginally acceptable results for CZW.

3. CZ Gain Comparisons

As with CZ range and width comparisons, it was necessary to average the ICAPS gain data with respect to frequency before calculator gain predictions could be compared. The estimated ICAPS gain values in Tables II and III were thus reduced to one number for each SVP, source, and receiver condition. Table V, CZ Gain Prediction Comparisons, contains numbers that represent the difference between calculator gain predictions and the averaged ICAPS values. Minus signs in the table indicate those cases where calculator gain was less than the ICAPS value.

As with the range and width comparisons, the worst agreement occurred in the Atlantic winter SVP case. Since CZW is a term in the gain algorithm, the extremely wide annuli predicted by the calculator caused gain values to be far too low for the three source/receiver conditions associated with that SVP.

Excluding the Atlantic winter SVP case, the following comments can be made concerning the other 29 CZ gain comparisons:

a) Calculator gain values ranged from 7.3 dB
 lower to 5 dB higher than the averaged ICAPS values.

 $\overline{G_{ICAPS}} / (G_{calc} - \overline{G_{ICAPS}})$

SVP	Source/ Receiver			
Proille	(IT)	Pacific	Atlantic	Mediterranean
	60/60	13.4/-5.4	15.5/-10.5	;
FEB	60/400	11.4/-2.4	13.0/-7.0	
	300/400	11.2/-2.2	17.5/-11.5	;
	60/60	16.4/ 0.6	16.5/-0.5	14.3/ 3.7
MAY	60/400	11.6/-2.6	14.0/-2.0	10.7/-1.7
	300/400	12.7/-0.7	15.0/-3.0	18.3/-6.3
	60/60	15.8/ 2.2	16.0/ 2.0	17.7/-0.7
AUG	60/400	12.8/-1.8	11.5/ 0.5	10.0/ 0.0
	300/400	12.4/ 0.6	14.5/-1.5	
	60/60	14.0/-4.0	12.0/ 5.0	13.0/ 4.0
NOV	60/400	11.3/-7.3	11.0/ 1.0	11.0/-3.0
	300/400	10.7/ 1.3	12.5/ 0.5	13.7/-2.7

Table V. CZ Gain Prediction Comparisons.

the second statement of the local second statement of the

b) In 22 of the 29 comparisons, calculator values were within 3 dB of ICAPS.

c) In nine of the 29 comparisons calculator values were within one dB of ICAPS.

d) On the average, calculator gain values were approximately one dB less than ICAPS. This result is inconsistent with calculator CZW results in light of the gain model used. Since calculator CZW values averaged only slightly more than half the ICAPS widths, it would have been more consistent if calculator gain values turned out two to three dB higher than ICAPS (acoustic power being spread over less area in the CZ annuli, other things being equal). Perhaps an explanation for this apparent discrepancy is that the calculator model does not consider the contribution of surface reflected energy adding to the energy from upward traveling sound rays at the receiver depth. In an actual CZ annulus the downward traveling, surface reflected energy adds approximately three dB to the CZ gain over much of the annulus width. Apparently, the FACT model in the ICAPS system includes this consideration. It is also apparent that neglecting surface reflected energy in the calculator gain model has the effect of canceling errors that should result from CZW values being too narrow.

In summary of the gain results, it can be said that the ray tracing technique used in the calculator model worked reasonably well. Since three fourths of the comparison cases

resulted in gain values within three dB of the estimated ICAPS figures, TL values from the calculator displayed the same close agreement.

IV. CONCLUSIONS

A. LIMITATIONS OF THE MODEL DEVELOPED

The HP-67/97 calculators used in programming the CZ prediction model were stretched to their limits in both data storage and program step capacity. Although not known for certain, the author feels significantly more accurate results would be possible from a calculator with only moderately larger storage capacity.

The data storage limitation which allowed only five SVP points to be entered is quite restrictive and no doubt plays a large role in the CZ range and width inaccuracies obtained.

Program step capacity forced several short cuts to be taken which again would not have been necessary with a moderately larger program memory. Two separate range and width programs were required due to insufficient program space to incorporate tests for different source and receiver depth cases. Also, source and receiver depths are strictly allowed only within the upper two SVP isogradient layers because program space was not available to check for the correct layer if all depths were allowed. Additionally, and perhaps the greatest source of CZW errors observed, program step limitation prevented incorporating a method of considering the bottom limited CZ sound ray in determining the range to the outer edge of a CZ annulus. The program developed ignores the bottom entirely and considers only the reswept zone in

predicting annular width. Since calculator CZW results were considerably shorter than those indicated by ICAPS, it is assumed the discrepancy is due to not considering CZ rays beyond the reswept zone. The first priority in making improvements to the calculator model, should a larger capacity machine be implemented, would be incorporating a better method for selecting the ray which defines the outer limit of the CZ annulus.

B. USEFULNESS OF THE MODEL DEVELOPED

The degree of success in producing a useable CZ prediction model for handheld calculators must be determined by considering the objectives set forth in the first section of this study. The central idea was to ascertain if a calculator model would improve on ASRAPS CZ prediction accuracy in the case where BT conditions determined in situ differed from those used to generate the ASRAPS TL profiles. Inherent in this objective is the assumption that ASRAPS TL profiles generated primarily from climatological data would be in error due to lack of input data accuracy. Also inherently assumed is that given identical input data the calculator model would produce less accurate results than the digital computer model(FACT) used in ASRAPS(and ICAPS) due to obvious differences in data and program capacities. The real question then is a trade-off comparison: Will the basically less accurate calculator model produce better CZ predictions with actual environmental data than the more sophisticated digital computer model which had only climatological input data?

Before addressing the answer to this question, characteristics of the calculator model developed will be compared to the list of six desirable characteristics described in section I.

1. Easily available input data.

The data required are an SVP, assumed source depth, hydrophone depth, and frequency of interest. The only portion of this information not presently available to ASW aircrews is that part of the SVP below the 1,000 ft depth limit of the AN/SSQ-36 bathythermograph buoy. SVP data from the surface to 1,000 ft (the area where seasonal and diurnal variations predominantly occur) is easily obtained from the BT buoy information.

2. Ease of program operation.

Anyone familiar with HP-67/97 calculator use could operate this program without additional training.

3. Output data.

The program provides CZ annulus range and width as well as TL values for all frequencies of interest in all annuli of interest.

4. Short run time.

To run a complete program requires approximately 10 minutes once SVP data is obtained. Deploying a BT buoy and converting the temperature trace to an SVP would take an additional 10-15 minutes.

5. Based entirely on acoustic theory.

The program uses only ray tracing techniques in producing its output terms.

6. Agreement with large computer models.

Calculator CZ ranges obtained averaged 5-10% greater than ranges obtained from ICAPS. CZ width results averaged only 40-50% of those obtained from ICAPS. And, there was one SVP case studied (winter, Atlantic) in which the calculator CZW results were very different from ICAPS. That SVP case was considered a failure of the calculator model, and it must be conceded the model does not work for all CZ situations. Excluding the obvious CZW failure SVP case, TL values from the calculator averaged about one dB lower than ICAPS with extreme deviations observed ranging from -7.3dB to +5dB around the ICAPS values. Additionally, calculator results can be expected to vary from operator to operator since SVP points must be picked subjectively from an SVP graph.

Returning to the main objective of the study, the author feels that only half of the trade-off question has been answered. An easily operated, purely theoretical model was developed which works for most (but not all) CZ producing SVP conditions. And a measure of its accuracy compared to the sophisticated FACT computer model was obtained. Yet to be answered is how inaccurate ASRAPS CZ predictions are when observed BT conditions differ from climatological conditions. This portion of the question is very difficult to answer and

in fact would be a very large study in itself. Generally, inaccuracies must range over a scale from insignificant to considerable as environmental deviations range from slight to great. The most likely variables affecting degree of inaccuracy are surface water temperature, mixed layer depth, and in layer and below layer gradients. The effects of varying these or other possible factors one at a time or in various combinations on CZ range, width, and gain must be known before the entire question can be answered. Further, definite magnitudes of environmental factor deviation must be determined so that a person can judge when ASRAPS inaccuracies are likely to be greater than the calculator model inaccuracies. Until these points are answered it would be inappropriate to recommend use of the calculator model as a routine method of updating ASRAPS CZ predictions in situ.

APPENDIX

<u>HP-67/97 Calculator Programs for Convergence</u> Zone Range, Width and Transmission Loss Predictions

Steps required to use the programs:

 Deploy a bathythermography buoy in the operating area of interest.

2. Convert the BT buoy information to a sound velocity profile of the upper 1,000 ft of the ocean area.

3. Combine the upper SVP data with a graph of climatological SVP data which depicts sound velocity conditions below the 1,000 ft level.

4. Pick five points from the combined SVP graph which best represent the deep sound channel portion of the SVP. The first point should be at the sonic layer depth, the fifth point at the bottom of the DSC where sound velocity equals that at the SLD, and the other three points at points on thegraph such that when straight lines are drawn to connect the five points they create a linearly segmented SVP which matches the actual SVP as closely as possible.

5. Pick the appropriate CZ Range and Width program to be used as follows: If both source and receiver are below the SLD use the Deep/Deep program. If source or receiver or both are above the SLD use the Shal/Shal or Crosslayer program.

 Load and run the appropriate Range and Width program according to the accompanying instructions.

7. Leaving the calculator power on and data storage registers unchanged, load and run the Gain and Transmission Loss program according to its instructions.

A word about units:

As currently written, the programs use metric units; meters for depths, and m/sec for sound velocities. To convert the programs for english unit input data, feet for depths and ft/sec for velocities, the conversion factor 1,852 m/nm should be changed to 6,075 ft/nm where occurring.

User Instructions for CZ Range Programs

Step	Instructions	Input	Keys	Output
1	Enter 5-point SVP which describes the Deep Sound Channel, (D_=SLD, D_=		A A	
	bottom of DSC.)	D ₂	A	D ₂
		C2	A	C ₂
		D ₃	A	D ₃
		С3.	A	C ₃
		D ₄	A	D ₄
		C4	A	C4
		D ₅	A	D ₅
2	Press R/S to perform pre- liminary calculations	none	R/S	10.0
3	Enter Receiver Depth and	DR	ENTER	
	Source Depth.	Ds	R/S	RCZi
4	Range to inner edge of CZ (RCZi) and range to	none	В	RCZi
	outer edge of CZ (RCZO) may be displayed by use of User Control keys B and C respectively. Ranges are in nautical miles.	none	с	RCZO

Stor	Storage Allocation for CZ Range Programs							
Regi	Registers:							
RO:	D ₁ / EAr	so:	al	S: $C_0 / \cos \theta_{rmin}$				
Rl:	c ₁	Sl:	g2	B: $\theta_{SLD} / \theta_{rmin}$				
R2	D ₂ / C _S	S2:	a ³	C: cos θ _w				
R3:	c ₂	S3:	94	D: cos _{0w+1}				
R4:	D ₃ / C _R	S4:		E: r _w				
R5:	c3	S5:		I: Control				
R6 :	D ₄ / r _{min} / RCZi	S6:						
R7:	C ₄	s7:						
R8 :	D ₅ / r ₀ / RCZo	S8:						
R9 :	a ⁰	S9:						
Init	ial Flag Status and	Use:						
0:	Off, Unused		2:	Off, set prior to r ₀				
				calculation in Deep/Deep program only.				
1:	Off, On if RCVR is s in Shal/Shal or Cross	hallow	3.	Off, set by data entry				
	program only.	oral or		S/S or Crosslayer program				
				only.				
Disp	play Status: DSP 1							
User	Control Keys:							
A:	Data entry		a:					
в:	Display RCZi		b.					
C:	Display RCZo		c :					
D:			d:					
E:			e:					

e01 +LEL+ 21 11 enter data e51 $R \cdot S$ 51 Enter DR + DS e02 iSII i6 25 45 is 35 45 Enter data e52 RCL0 36 60 e03 iSII i6 25 45 SI e53 - - - - - - - e53 -	Ste	p Key	s Code	Explanation	Ster	Keys	Code	Explanation
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	001	*LBLH	21 11		051	R/S	51	Enter DR + DS
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	802	STOI	35 45	Enter data	052	RCLO	36 80	
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	003	ISZI	16 26 46		053	-	-45	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	004	R/S	51		854	RCLI	36 45	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	005	•	-62	Compute	055	x	-35	Compute Co
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	896	0	00	Gradients	056	RCLI	36 01	- 3
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	887	2	02	So.	057	+	-55	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	008	STOI	35 45		058	5102	33 82	
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	889	1521	10 20 40		035	R.	75 00	
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	A11	PCLI	30 03		951	RULO	-45	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	A12	PCI 2	76 42		867	PCI :	76 45	Compute C _R
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	817	PCLA	36 44	g ₁	863	X	-35	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	ALA	ESR.	23 16 11		864	RCI 1	36 81	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	815	KCL5	36 85		865	+	-55	
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	016	RCL3	36 83		866	ST04	35 84	
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	017	RCL4	36 84	E	067	SF2	16 21 82	Initializa
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	818	RCL2	36 02	02	868	1	01	initialize
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	819	6SBa	23 16 11		969	STOC	35 13	Ar routine
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	020	RCL7	36 87		870	#LBL2	21 82	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	021	RCL5	36 85		871	ESBc 2	23 16 13	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	822	RCL6	36 06	82	072	RCL3	36 03	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	023	RCL4	36 84	-	073	RCLC	36 13	$^{2}\Delta r_{1}$
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	024	658a	23 16 11		074	ESBd i	23 16 14	-
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	825	RCLI	36 01		875	STUD	35 66	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	020	RCL/	30 01	-	875	DC1 7	76 47	
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	A20	RULO	30 66	84	879	ENTA	-21	
$\begin{array}{c c c c c c c c c c c c c c c c c c c $	829	CCR.	27 16 11		879	ENTA	-21	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	838	ESBL	23 16 12	Set I=10	080	RCLS	36 85	-
032 $x \neq 0$?16-42Mixed layer ?082 $\varepsilon SBd 23$ 16 14033 $\varepsilon T 00$ 22 000083 $S7 \cdot 0$ 35-55 00034 $ST 08$ 35 08If no ML,084 $ST \cdot 0$ 35-55 00035 $\varepsilon T 01$ 22 010 to R8085RCL536 05036 $\varepsilon LBL0$ 21 0000 to R8086ENT τ -21037RCL936 090 e88RCL736 072 Δr_3 038 x -350089RCLD36 142 Δr_3 040RCL136 010090 εSBd 23 16 14041+-550092 $ST + 0$ 35-55 00042ST0A35 11092 $ST + 0$ 35-55 00043 εSBc 23 16 13093RCL136 01043 εSBc 23 16 142 Δr_0 to R8095 $+$ -24046 $C SEd$ 23 15 142 Δr_0 to R8095 $+$ -24046 $ST + 8$ 35-55 08095RCL136 14047ST0835 08095 $+$ -242 Δr_4 048 $ST + 8$ 35-55 08095RCLD36 14049 $* LSL1$ 21 01Set I=10099 εSBe 23 16 15050 εSBb 23 16 12Set I=10100 x -35	831	RCLO	36 80	000 1-10	081	RCLD	36 14	$^{2}\Delta r_{2}$
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	032	X#8?	16-42	Mixed layer ?	882	ESBd .	23 16 14	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	833	STOP	22 00		883	57+0	35-55 00	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	034	STOR	35 88	If no ML,	864	ST+0	35-55 00	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	035	GT01	22 01	O to R8	085	RCL5	36 85	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	036	*LBL8	21 88		886	ENTT	-21	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	037	RCL9	36 89		087	ENTT	-21	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	038	×	-35	10	888	RCL7	36 07	2 12
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	839	CHS	-22	0	689	RULD	30 14	- ,
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	040	RULI	30 81		0.90	6384	25 55 00	
043 052 23 16 13 044 $RCLA$ 36 11 044 $RCLA$ 36 11 044 $RCLA$ 36 11 045 1 01 ML $present$, 095 t -24 046 $CSEd$ 23 16 14 2 Δr_0 to $R8$ 096 $RCLi$ 36 614 046 $CSEd$ 23 16 14 2 Δr_0 to $R8$ 096 $RCLi$ 36 45 2 Δr_4 047 $ST08$ 35 08 096 $RCLi$ 36 45 2 Δr_4 048 $ST+8$ $35-55$ 08 099 $6SBe$ 23 16 15 049 $eLBL1$ 21 01 Set $I=10$ 099 $6SBe$ 23 16 15 050 $6SBb$ 23 16 12 <	842	STOA	75 11		892	ST.A	75-55 44	
044 $PCLA$ 36 11 ML $present.$ 094 $RCLD$ 36 14 045 1 01 ML $present.$ 095 \div -24 046 $6SEd$ 23 16 14 $2 \Delta r_0$ to $R8$ 095 \div -24 046 $6SEd$ 23 16 14 $2 \Delta r_0$ to $R8$ 096 $RCLi$ 36 45 2 Δr_4 048 $ST+8$ $35-55$ 08 097 \div -24 2 Δr_4 049 $eLBL1$ 21 01 Set $I=10$ 099 $eSBe$ 23 16 15 050 $eSBb$ 23 16 12 Set $I=10$ 100 x -35	847	CSEC	23 16 17		897	RCII	36 41	
045 1 01 ML present, 095 $+$ -24 046 6554 23 16 14 2 Δr_0 to R8 096 RCLi 36 45 2 Δr_4 047 5708 35 08 097 $+$ -24 2 Δr_4 048 $5T+8$ $35-55$ 08 098 RCLD 36 14 049 $eLBL1$ 21 01 Set I=10 099 $eSBe$ 23 16 15 050 $6SBb$ 23 16 12 Set I=10 100 \times -35	844	RCLA	36 11		894	RCLD	36 14	
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	845	1		ML present.	895	+	-24	
047 ST08 35 08 097 + -24 2 ΔΓ4 048 ST+8 35-55 08 098 RCLD 36 14 049 <th>846</th> <th>GSBd</th> <th>23 16 14</th> <th>2 Ar to R8</th> <th>896</th> <th>RCLI</th> <th>36 45</th> <th></th>	846	GSBd	23 16 14	2 Ar to R8	896	RCLI	36 45	
048 ST+8 35-55 08 058 RCLD 36 14 049 0LBL1 21 01 Set I=10 099 6SBe 23 16 15 050 6SBb 23 16 12 Set I=10 100 x -35	847	STOR	35 08	-0	897	÷	-24	2 Δr4
049 #L6L1 21 01 Set I=10 099 658e 23 16 15 050 658b 23 16 12 Set I=10 100 x -35	848	ST+8	35-55 08		858	RCLD	36 14	
050 6586 23 16 12 100 x -35	849	#LBL1	21 01	Set I=10	999	esee .	23 16 15	
	850	6586	23 16 12		166	x	-35	

CZ Range Program (Deep/Deep Case)

Ste	p Key	s Code	Explanation	Ste	p Key	s Code	Explanation
101 102 103	ST+0 ST+0 CSBb	35-55 00 35-55 00 23 16 12	Set I=10	151 152 153	GSBa ST+8 DSZI	23 16 14 35-55 08 16 25 46	to r ₀
104 105 106 107	F2? GT03 GT04 #LBL3 RCL 0	16 23 02 22 03 22 04 21 03 36 00	r ₀ found ?	154 155 156 157	GSBC RCL4 RCLA GSBJ ST-6	23 16 13 36 04 36 11 23 16 14 75-45 66	to r _{min}
109 110 111 112 113	ST+8 1 + STOE	35-55 88 81 -55 35 15 21 84	& first r _w	159 160 161 162	1 8 5 2	01 08 05 02 75-24 05	Convert RCZi & RCZo to nm
114	RCLO	36 00 36 15	r _{min} found ?	164 165	ST+8 GSBb	35-24 00 23 16 12	Set I=10
117	GT05 R+	22 05	Store	166 167 168	RCL6 R/S	21 12 36 06 51	Display RCZi
119 120 121	RCLB	35 15 36 12 -62	Increment	169 170 171	#LBLC RCL8 R/S	21 13 36 88 51	Display RCZo
122 123 124	STOB	65 -55 35 12 42	e _{SLD} & cos e _{SLD}	172 173 174	#LBLa R\$	21 16 11 -45 -31	Gradients
126	STOC GTO2	35 13	Next r routin	176	R† +	16-31 -24	Subioutine
129	STO6	35 66 36 12	Store r _{min} Initiate	178 179 180	ISZI RTN	35 45 16 26 46 24	
131 132 133 134	5 COS STOA	-62 85 -45 42 35 11	Δr _S & Δr _R corrections	181 182 183 184	*LBLb 1 STOI	21 16 12 01 00 35 46	Set I=10 Subroutine
136 137 138 139	CSBC RCL2 1 CSBd ST+R	23 16 13 36 82 01 23 16 14 35-55 88	Δr_3 corrections to r	186 187 188 189	#LBLC RCL1 ENT1 ENT1 ENT1	21 16 13 36 01 -21 -21	Ar Initiation Subroutine
141 142 143 144 145 146	OSZI CSBC RCL2 RCLA CSBd ST-6	16 25 46 23 16 13 36 82 36 11 23 16 14 35-45 86	to rmin	191 192 193 194 195 196	#LELd STOC X X 2Y ÷ STOD	21 16 14 35 13 -35 -41 -24 35 14	Δr Subroutine
147 148 149 150	DSZI GSBc RCL4 1	16 25 46 23 16 13 36 04 01	Δr _R corrections	197 198 199 200	CSBe RCLC GSBe	23 16 15 36 13 23 16 15 -45	2

CZ Range Program (Deep/Deep Case)

.

Step Keys Code	Explanation	<u>Step keys Code</u>	Explanation
201 × -35 202 RCLC 36 13 203 + -24 204 RCLi 36 45 205 ISZI 16 26 46 206 + -24 206 + -24 207 ABS 16 31 208 RTH 24	Δr Subroutine (continued)		
209 #LBLe 21 16 15 210 X ² 53 53 211 CHS -22 212 1 01 213 + -55 214 JX 54 215 RTN 24 216 R'S 51	cos to sin Subroutine		
`			

CZ Range Program (Deep/Deep Case)

and a set of the set of the set of the

Ste	<u>Key</u>	s Code	Explanation	Ste	p Key	s Code	Explanation
881	*LELH	21 11		851	RELS	36 89	
002	STOI	35 45	Enter data	052	x	-35	•
883	ISZI	16 26 46		053	RELI	36 01	
884	R/S	51		854	+	-55	
005		-62	Compute	855	\$762	35 82	
886	0	99	Gradients	056	R4	-31	
007		82		857	RCLO	30 00	
668	STUI	35 45	g0	058	X>Y?	16-34	G.+ 31 0
009	1541	10 20 40		059	GTOP	22 00	Set Flag 0
011	RULS DOL 1	30 03		868	GT01	22 01	Ior shallow
011	PCI 2	75 00	-	861	*LBL8	21 00	Receiver
A17	PCL2	30 02	⁵ 1	862	SFI	16 21 01	
ALA	CCP.	27 16 11		063	0521	10 23 40	and
815	Pris	36 45		004	#LBL1	21 01	Commute C
816	PCL 3	36 83		000	201 1	-43	compute CR
017	RCL4	36 84	g.	000	RULI	30 45	
818	RCL2	36 82	⁵ 2	920	pris	76 81	
019	GSBa	23 16 11		969	+	-55	
820	RCLT	36 07		A70	STOA	35 84	
821	PCL5	36 85		871	6586	23 16 12	Set T=10
022	RCL6	36 86	52	672	*LEL2	21 82	000 1-10
023	RCL4	36 84		073	GSBc	23 16 13	
824	658a	23 16 11		874	RCL3	36 03	
025	RCL1	36 01		075	RCLC	36 13	2 Ar.
026	RCL7	36 07		076	GSBd	23 16 14	
827	RCLS	36 88	S4	877	STOP	35 00	
028	RCL6	36 06		078	ST+0	35-55 00	
029	GSBa	23 16 11		879	RCL3	36 03	
030	9	09	Set I=9	080	ENTI	-21	
031	5/01	35 46		881	ENTT	-21	
032	RELO	30 00		082	RCL5	36 85	2 Ar 2
033	RLLS	30 07		083	RCLD	36 14	-
875	CHS	-22	Compute C	084	6564	23 16 14	
875	PCIN	36 41	- 0	685	51+0	33-33 66	
837		-55		080	51+0	30-00 00	
838	STCA	35 11		001 000	ENTA	30 03	
039	6SBc	23 16 13		600	ENTA	-21	
848	RCLA	36 11		200	PCI 7	76 87	0
041	1	01	2 Ar. to R8	891	PCLD	36 14	$2 \Delta r_3$
842	ESEd	23 16 14	- 4-0	842	CSR4	23 16 14	-
843	STOS	35 88		893	ST+A	35-55 AA	
844	57+8	35-55 88		894	ST+0	35-55 00	
845	6SB6	23 16 12	Set I=10	095	RCLI	36 81	
046	R/S	51	Enter DR DS	896	RCLD	36 14	
847	X>Y?	16-34	Reciprocity	897	÷	-24	
848	XZY	-41	test	898	RCLI	36 45	2
049	RCLO	36 00	Compute C.	899	÷	-24	- 4-4
050	-	-45	Sompare S	100	RCLD	36 14	
			· · · · · · · · · · · · · · · · · · ·	1			

CZ Range Program (Shal/Shal & Crosslayer Cases)

Ste	p Key	s Code	Explanation	Ste	P Key	S Code	Explanation
101 102 103	ST+0	23 16 15 -35 35-55 80		151 152 153	OSZI GSBc RCL4	16 25 46 23 16 13 36 04	∆r _R corrections
105 106 107	6586 F3? 6703	23 16 12 16 23 03 22 03 22 04	Set I=10 r ₀ found ?	155 156 157	GSBa DSZI F1?	23 16 14 16 25 46 16 23 01	to r ₀
109 110 111 111 112 113	*LBL3 RCL0 ST+8 1 +	21 03 36 00 35-55 08 01 -55	Store r ₀ & first r _w	159 160 161 162 163	ST+8 GSEc RCL4 RCL4 GSBd	35-55 08 23 16 13 36 04 36 11 23 16 14	to rmin
114 115 116 117	STOE #LBL4 RCL0 RCLE	35 15 21 04 36 00 36 15	r_:_ found ?	164 165 166 167	F1? CHS ST-6	16 23 01 -22 <u>35-45 06</u> 01	
118 119 120 121	XEY? GTOS R4 STOE	16-35 22 05 -31 35 15	Store next rw	168 169 170 171	8 5 2 57+6	08 05 02 35-24 06	Convert RCZi & RCZo to nm
122	RCLE	36 12		172	ST+8	35-24 86	Sot 1-10
125 124 125 126	5 STOB	05 -55 35 12	Increment θ_{SLD} & cos θ_{SLD}	173 174 175 176	#LELB RCL6 R/S	23 16 12 21 12 36 06 51	Display RCZi
127 128 129	COS STOC GTO2	42 35 13 22 82	Next r routin	177 178 e179	*LBLC RCLS R/S	21 13 36 08 51	Display RCZo
130 131 132 133 134 135 136 137	*LBL5 ST06 RCLB 5 COS	21 05 35 06 36 12 -62 05 -45 42	Store r_{min} Initiate $\Delta r_S & \Delta r_R$ corrections	186 181 182 183 184 185 186	*LBLa Rt Rt STO:	21 16 11 -45 -31 -45 16-31 -24 35 45	Gradients Subroutine
138 139 140 141 142 143	GSBC RCL2 1 DSZI GSBd DSZI	23 16 13 36 92 91 16 25 46 23 16 14 16 25 46	$\begin{array}{c} \Delta r_{S} \\ \text{corrections} \\ \text{to } r_{0} \end{array}$	188 189 190 191 192 193	RTN #LBLb 1 3 STOI FTN	21 16 12 01 01 035 46 24	Set I=10 Subroutine
144 145 146 147 148 149	ST+8 GSBC RCL2 RCLA GSBd ST+6	35-55 08 23 16 13 36 02 36 11 23 16 14 35-55 06	to r _{min}	194 195 196 197 198	*LELC RCL1 ENTT ENTT RTN	21 16 13 36 01 -21 -21 -21 24	∆r Initiation Subroutine
150	F1?	16 23 01		200	STOC	35 13	

CZ Range Program (Shal/Shal & Crosslayer Cases)

Step Keys Code	Explanation	Step keys Sode	Explanation
$\begin{array}{cccccccccccccccccccccccccccccccccccc$	Ar Subroutine		
217 *LBLe 21 16 15 218 X² 53 219 CHS -22 220 1 01 221 + -55 222 fX 54 223 RTN 24 224 R/S 51	cos to sin Subroutine		

CZ Range Program (Shal/Shal & Crosslayer Cases)

User	Instructions	for CZ	Gain	and	Transmission	Loss	Program

Step	Instructions	Input	Keys	Output
1	Run one of the CZ Range Programs. Leave the calculator on and all of the data storage regis- ters unchaged.			
2	Load the CZ Gain and Transmission Loss Program.			
3	Enter a zero if the Shal/ Shal or Crosslayer program was used, or enter a one if the Deep/Deep program was used.	0 or 1	A	G (dB)
4	Enter a frequency of in- terest in Hz.	f (Hz) B	a (dB/m)
5	Enter the number of a CZ annulus of interest.(Step 5 may be repeated for as many CZ annuli as desired.)	n	с	TL _n (dB)
6	To determine the TL _n values for different frequencies, return to step 4.			

Stor	age Allocation	for C2	Gair	and	Transm	nission	Loss	Program
Regi	sters:							
RO:	Δr	5	50: g	'ı	P	A: θso	/ 0 R	$/f^2$
Rl:	c ₁	5	51: 9	2	B	ε: θ _{SL}	σ / θ,	rswp
R2:	c _s	5	52: g	13	c	: cos	θ _w /	
R3:	c ₂	5	53: g	4		cos	⁰ rsw	,
R4:	C _R	5	54: a	ter	ms c	: cos	θ _{w+1}	
R5:	C ₃	5	55:		E	: r _o	/ ^θ SR	/θ _{RR}
R6 :	RCZi	9	66:		I	: Con	trol	
R7:	C ₄ / a	S	57:					
R8:	RCZO	S	38:			•		
R9:	G terms / G	S	59:					

Initial Flag Status and Use:

- 0: Off, On for shallow 2: Off, unused. sound source.
- 1: Off, On to decrease the 3: Off, set by data entry increments used in finding θ_{SLD} .

Display Status: DSP 0

User Control Keys:

A: Compute G a: B: Compute a b: C: Compute TL_n C: D: d: E: e:

- until r₀ found.

Step Keys Code	Explanation	<u>.ite</u>	p hey	s Jode	Explanation
001 *LELH 21 11 002 X=07 16-43 003 SF0 16 21 00	Set FO for Shal Source	051 052 053	1 ¢ 6T03	01 -55 22 03	Large θ_{SLD} increment
004 1 01 005 STOC 35 13 006 *LBL0 21 00 007 SCL1 75 01	Initialize r routine	054 055 056	*LBL1 SF1 RCLB	21 01 16 21 01 36 12	First small
008 ENTT -21 009 ENTT -21 010 RCL3 36 03	² Ar ₁	058 059 060	9 GT03	-62 09 -45 22 03	of θ_{SLD}
011 RCLC 36 13 012 GSBa 23 16 11 013 STO0 35 06		061 062 063	*LBL2 X>Y? 6T04	21 02 16-34 22 04	θ_{rswp} found ?
014 RCL3 36 03 015 ENTt -21 016 ENTt -21 017 PCI 5 76	2 45-	064 065 066	RCLB	36 12 -62 01	Small Θ_{SLD} increment
018 RCLD 36 14 019 GSB₄ 23 16 11 020 ST+0 35-55 00	- 2-2	068 069 070	#LBL3 STOB COS	21 03 35 12 42	Store new $\Theta_{\rm SLD}$ &
021 RCL5 36 05 022 ENT1 -21 023 ENT1 -21		071 072 073	STOC GTOB #LBL4	35 13 22 00 21 04	cos O _{SLD}
024 RCL7 36 07 025 RCLD 36 14 026 GSBa 23 16 11 027 CTAB 75-55 99	² Δr ₃	074 075 076	1 8 5	01 08 05	Convert RCZi & RCZo to meters
021 3140 35-33 80 028 RCL1 36 01 029 RCLD 36 14 030 ÷ -24		078 079 080	STX6 STX8 RCLB	35-35 06 35-35 08 36 12	
031 RCL; 36 45 032 ÷ -24 033 RCLD 36 14	² Ar ₄	081 082 083	COS STOC PCL2	42 35 13 36 02	cos erswp
034		084 085 086	RCL1 ÷	-35 36 01 -24	e _{sr}
037 51+0 35-55 00 038 1 01 039 0 00 040 5701 75 4-	Set I=10	887 888 889	STOE RCL2	16 42 35 15 36 82	
040 5101 55 46 041 RCL0 36 00 042 F3? 16 23 03 043 STOE 35 15 15	Store r ₀	091 092 093	COS-	-24 16 42	θ _{SO} (negative if
044 RCLE 36 15 045 X2Y -41 046 F1? 16 23 01	Check for Small inc.	094 095 096	CHS STOA +	-22 35 11 -55	source shal)
047 6T02 22 02 048 X>Y? 16-34 049 6T01 22 01	Decrease OSLD inc. ?	097 098 099	D+R STO9 RCLE	16 45 35 09 36 15	<u>ν</u> θ
050 RCLB 36 12		198	RCLA	36 11	

CZ Gain and Transmission Loss Program

Ste	p Key	s Code	Explanation	Ste	p Key	S Code	Explanation
101 102 103 104 105	2 t COS STX9	-45 82 -24 42 35-35 89	cos 01	151 152 153 154 155	4 1 0 RCLA	04 01 00 00 36 11	Second term
100 107 108 109	RCL4 X RCL1	36 84 -35 36 81	e _{RR}	156 157 158 159	÷ <u>S</u> + RCLI	-55 -24 56 36 56	Store a
110	÷ cos→	-24 16 42		160	<u>5707</u> 2-	<u>35 87</u> 16 56	(Clear S4)
112 113 114 115	RCL4 RCL1 ÷	36 64 36 01 -24 16 42	e _{RO}	162 163 164 165	1	01 -62 00 89	Convert a
116 117 118	* 2 +	-55 82 -24	₽ ₂	166 167 168	4 EEX 3	04 -23 03	to dB/m
120	ST+9 PCL 8	35-24 89	sin θ_2	169	STX7	35-35 07	
122	RCL6 STX9	36 06	RCZi	172	R/S	21 13	Display a
124 125	ST÷9 PCL9	-45 35-24 09 76 99	CZW	174	RCL6	36 06 -35	nRCZi
127 128 129 130	LOG	16 32 01 09 -35	Compute and Display G	177 177 178 179 189	LOG	16 32 02 00	20log(nRCZi)
131 132	STO9 R/S	35 89 51		181	X2Y RCL7	-41 36 87	a(nRCZi)
133 134 135 136	*LBLB EEX 3 ÷	21 12 -23 03 -24	Convert f to kHz	193 184 185 186	x + RCL9	-35 -55 36 09 -45	Compute & Display TL _n
137	STOA	<u> </u>	Store f ²	18.	#LBLa	21 16 11	
139 140 141 142	i × 1	-62 01 -35 01	Attenuation Coefficient	199 190 191 192	\$100 x X2Y ÷	35 13 -35 -41 -24	
143 144 145 146	RCLA + + 5+	36 11 -55 -24 56	First term	193 194 195	STOD GSB6 RCLC	35 14 23 16 12 36 13	∆r Subroutine
147 148 149 150	4 0 RCLA X	04 00 36 11 -35		196 197 198 199 200	RCLC ÷	-45 -35 36 13 -24	

CZ Gain and Transmission Loss Program





Ste	p Key	s Code	Explanation	itep	Keys Jode	Sxplanation
201 202 203 204 205 206 207	RCL: ISZI + ABS 2 X RTN	36 45 16 26 46 -24 16 31 82 -35 24	Ar Subroutine (Continued)			
208 209 210 211 212 213 214 215	*LBLb X2 CHS 1 + SX RTN RZS	21 16 12 53 -22 01 -55 54 24 51	cos to sin Subroutine			
	•					
*						

CZ Gain and Transmission Loss Program

.

LIST OF REFERENCES

- Urick, R. J., Principles of Underwater Sound, p. 114-121, Mcgraw-Hill, 1975.
- Beckes, M. E., Burhans, N. P., and Gump, R. E., Passive Environmental ASW Prediction System (PEAPS), Master's Thesis, Naval Postgraduate School, Monterey, California, March 1975.
- 3. Madden, L. D., <u>POCKET-PROPLOSS Programs and Models for</u> the Computation of Acoustic Transmission Loss on Hand-Held Calculators, Master's Thesis, Naval Postgraduate School, Monterey, California, March 1977.
- 4. U. S. Naval Oceanographic Office Report TN 3700-57-77, User's Manual for the Integrated Carrier ASW Prediction System (ICAPS), by J. D. Pennylegion, p. 9, 10, B-1 -B-4, C-1 - C-3, January 1977.
- Maury Center for Ocean Science Report 109, The FACT Model, Volume I, by C. W. Spofford, p. 2-7, 2-8, 3-7, November 1974.

INITIAL DISTRIBUTION LIST

1.

2.

3.

4.

6.

8.

10.

FPO San Francisco 96601

No. Copies Defense Documentation Center 2 Cameron Station Alexandria, Virginia 22314 Navy Tactical Support Activity 2 P. O. Box 1042 Silver Springs, Maryland 20910 2 Library, Code 0142 Naval Postgraduate School Monterey, California 93940 Associate Professor A. B. Coppens 1 Code 61Cz Department of Physics and Chemistry Naval Postgraduate School Monterey, California 93940 5. Associate Professor R. H. Shudde 5 Code 55Su Department of Operations Research Naval Postgraduate School Monterey, California 93940 COMPATWINGSPAC 1 Attn: Code 51 Naval Air Station Moffett Field, California 94035 7. COMPATWINGSLANT 1 Attn: Code N7 Naval Air Station Brunswick, Maine 04011 1 Commander Antisubmarine Warfare Wing Pacific Naval Air Station North Island San Diego, California 92135 1 9. COMSEABASEDASWWINGSLANT Attn: TD&E Officer Naval Air Station Jacksonville, Florida 32228 1 Commanding Officer (ATTN: LCDR R.L. Badger) Patrol Squadron FIFTY

No. Copies

1

11. Project Manager Antisubmarine Warfare Systems Project (PM-4) Department of the Navy Washington, D.C. 20360

21