



MICROCOPY RESOLUTION TEST CHART NATIONAL BUREAU OF STANDARDS-1963-A

.......



When U.S. Government drawings, specifications or other data are used for any purpose other than a definitely related government procurement operation, the government thereby incurs no responsibility nor any obligation whatsoever; and the fact that the government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or conveying any rights or permission to manufacture, use, or sell any patented invention that may in any way be related thereto.

Do not return this copy. Retain or destroy.

8c. ADDRESS (	City, State, and Zli	P Code)		10 SOURCE OF	FUNDING NUM	BERS	
Electro Hanscon	onic Systems AFB, MA 01	Division, 1731-5000	AFSC	PROGRAM ELEMENT NO 414J	PROJECT	TASK NO	WORK UNIT ACCESSION NO
11 TITLE (Inc.	lude Security Class	ufication)					
Overest	imation of (	On-Axis Pow	ver Density by	the Fraunhofe	r ("Far-Fi	eld") Appr	oximation
12 PERSONAL Weiner,	AUTHOR(S) Melvin M.						
13a TYPE OF REPORT 13b TIME C Final FROM			OVERED TO	14 DATE OF REPORT (Year, Month, Day) 1987 April		<b>th, Day)</b> 15 P/	AGE COUNT
16 SUPPLEME	NTARY NOTATION	<b>v</b>		<u>`````````````````````````````````````</u>			
17	COSATI COL	DES	18 SUBJECT TERMS	(Continue on revers	e if necessary	and identify by	block number)
FIELD	GROUP	SUB-GROUP	Antenna Apert	ure		•	<b>D1</b>
			Aperture Dist Circular Aper	ribution of U ture	nitorm Int	ensity and (conti	Phase nued)

# UNCLASSIFIED

- 18.
- Constructive Interference Destructive Interference Diffraction Far-Field Fraunhofer Fresnel Fresnel-Kirchhoff Integral Fresnel Number Near-Field On-Axis Intensity On-Axis Power Density Optical Aperture Rectangular Aperture

ACC LOUGH

### f

# UNCLASSIFIED

# April 1987

# **M**87-37

## M. M. Weiner



CONTRACT SPONSOR ESD CONTRACT NO. F19628-86-C-0001 PROJECT NO. 414J DEPT. D86

Approved for public release; distribution unlimited.



The MITRE Corporation Bedford, Massachusetts Overestimation of On-Axis Power Density by the Fraunhofer ("Far-Field") Approximation



Accesion For	1
NTIS CRASI	N
DTIC TAB	ā l
Usamou lead	ມ
Ju tilicet i	• • • • • • • • • • •
Ву	••••••••••••••••••••••••••••••••••••••
But the first of	• •• •• •• •• •• ••
•• •• •• • •• •• •• •• •• •• •• •• •• •	· · · · · · · · · · ·
· · · · · · · ·	
iter t	- 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1
	1
H-1	

Department Approval: John t. Lellurge J. F. Sullivan TRE Project Approval

sin MITRE Project Approve

R. B. Stevenson

MANARA AND

ELECTRONIC CONTRACTOR OF THE

### ABSTRACT

The overestimation of power density by the Fraunhofer ("far-field") approximation to the more exact Fresnel ("near-field") diffraction integral is determined as a function of Fresnel number at arbitrary on-axis field points for rectangular and circular aperture illuminations of uniform amplitude and phase. For square and circular apertures, the overestimation is 2.8 percent and 1.3 percent, respectively, at a Fresnel number of 1/8 (corresponding to the far-field boundary distance  $2D^2/\lambda$ ) and 518 percent and 147 percent, respectively, at a Fresnel number of 1.

\*This work was sponsored by the Electronic Systems Division, Air Force Systems Command, Hanscom Air Force Base, Massachusetts.

### TABLE OF CONTENTS

### SECTION

5'

ŗ

1. 18. 18. 18

### PAGE

2.1

1.	Introduction	1-1
2.	Definition of Fresnel Number	2-1
3.	Far-Field Formulation	3–1
4.	Near-Field Formulation	4-1
5.	Comparison of Far-Field and Near-Field Formulations	5–1
Lis	t of References	6–1
Арр	endix A Derivation of the Fraunhofer and Fresnel Diffraction Integrals	<b>A-1</b>

600

### INTRODUCTION

The Fraunhofer and Fresnel diffraction integrals are commonly used analytical tools for the evaluation of fields originating from illuminated apertures. These integrals are derived in appendix A from the Fresnel-Kirchhoff integral subject to small angle conditions. Whereas the exponential factor of the Fresnel integrand retains both linear and quadratic phase terms (as a function of the aperture coordinates) and is applicable to near-field points as well as far-field points, the Fraunhofer integrand retains only linear phase terms and is applicable only to far-field points. The Fraunhofer "far-field" formulation is, therefore, an approximation to the more exact Fresnel "near-field" formulation. (This statement is not applicable at a lens focal point where both linear and quadrature phase terms are zero.)

For on-axis field points and an aperture illumination of uniform phase, the Fraunhofer phase terms are zero, corresponding to totally constructive interference. However, for the same conditions, the Fresnel phase terms are non-zero, corresponding to destructive interference among interfering rays. Consequently, the far-field formulation yields a larger power density at an arbitrary on-axis field point than the more exact near-field formulation for an aperture illumination of uniform phase.

In this paper, the overestimation of power density by the far-field formulation is determined as a function of Fresnel number at arbitrary on-axis field points for rectangular and circular

1-1

5.111

aperture illuminations of uniform amplitude and phase. For square and circular apertures, the overestimation is found to be 2.8 percent and 1.3 percent, respectively, at a Fresnel number of 1/8 (corresponding to the far-field boundary distance  $2D^2/\lambda$ ) and 518 percent and 147 percent, respectively, at a Fresnel number of 1. The 1.3 percent result is compatible with a result reported earlier<sup>(1)</sup>.

The Fresnel number is defined in section II. Far-field and near-field formulations are summarized in sections III and IV, respectively. A comparison of far-field and near-field formulations is given in section V.

### DEFINITION OF FRESNEL NUMBER

Consider a collimated beam, of uniform amplitude and phase with intensity  $I_0^{(W/m^2)}$  at a wavelength  $\lambda(m)$ , which is incident on a limiting aperture. For a rectangular aperture, the clear aperture is of width 2b<sub>x</sub> and height 2b<sub>y</sub> (see figure 1a). For a circular aperture, the clear aperture is of radius b (see figure 1b). In figure 1, a collimated beam corresponds to a source point S at a distance d' =  $\infty$ .

For a circular aperture of radius b, the number N of Fresnel zones, subtended by every point on the edge of the circular aperture at a field point P(0,0,d) on the optical axis at a distance d from the aperture, is defined as

$$N = \frac{(s+s') - (d+d')}{\lambda/2} \approx b^2/\lambda L; b< (1)$$

where

 $s = (b^{2} + d^{2})^{1/2}$ ,  $s' = (b^{2} + d'^{2})^{1/2}$  (see figure 1b)  $L = [(1/d) + (1/d')]^{-1}$ 

For a collimated beam, L = d and equation (1) reduces to

$$N \approx b^2 / \lambda d; b << d, collimated beam$$
 (2)

For points P in the very near field,  $N \rightarrow \infty$ . For points P in the very far field,  $N \rightarrow 0$ . For a collimated beam, the boundary distance between the near field and far field is conventionally chosen as<sup>(1)</sup> d = 2(2b)<sup>2</sup>/ $\lambda$  which corresponds to a Fresnel number  $N = b^2/\lambda d = 1/8$ .



Consider now the rectangular aperture of figure 1a. Not every point on the edge of the rectangular aperture subtends the same number of Fresnel zones (except in the very far field). Consequently, the effect of edge diffraction, on the intensity at a near-field point, is less pronounced for a rectangular or square aperture than for a circular aperture. Edge diffraction by a rectangular aperture is characterized by the Fresnel numbers,  $N_x$  and  $N_y$ , defined by

$$N_{x} = \frac{s_{x} - d}{\lambda/2} \approx b_{x}^{2} / (\lambda d); b_{x} << d, \text{ collimated beam} \quad (3a)$$

$$N_{y} = \frac{s_{y} - d}{\lambda/2} \approx b_{y}^{2} / (\lambda d); b_{y} << d, \text{ collimated beam} \quad (3b)$$

where

$$s_x = (b_x^2 + d^2)^{1/2}$$
,  $s_y = (b_y^2 + d^2)^{1/2}$  (see figure 1a)

The Fresnel number  $N_x$  is the number of Fresnel zones subtended by every point on the edges  $x = \pm b_x$  of the rectangular aperture at the field point P if the point source S were replaced by a line source of infinite extent parallel to the y axis and if the aperture were of infinite extent in the y direction. A similar statement applies to  $N_y$  if x and y are interchanged in the statement for  $N_y$ .

### FAR-FIELD FORMULATION

The on-axis intensity I  $(W/m^2)$  at a far-field point P(x,y,z) = P(0,0,d) is found from the Fraunhofer diffraction integral of appendix A to be<sup>(2)</sup>

$$I(0,0,d) = |U(0,0,d)|^{2} = \frac{I_{o}}{\lambda^{2}d^{2}} \left| \int_{A} \int dx_{o} dy_{o} \right|^{2}$$
$$= \frac{I_{o}}{\lambda^{2}d^{2}} = \frac{P_{t}A}{\lambda^{2}d^{2}} = \frac{P_{t}g}{4\pi d^{2}}, \text{ collimated beam} \qquad (4)$$

where

A = aperture area = 
$$\begin{cases} 4b_x \ b_y \ , \ rectangular \ aperture \\ \pi b^2 \ , \ circular \ aperture \end{cases}$$
Pt = total power radiated = I<sub>o</sub> A
g = aperture (antenna) gain =  $\frac{4\pi A}{\lambda^2}$ 

$$= \begin{cases} \frac{4\pi}{(\lambda/2b_x)(\lambda/2b_y)}, \ rectangular \ aperture \\ [\pi/(\lambda/2b)]^2, \ circular \ aperture \end{cases}$$

It will be noted from equation (4) that the beam is no longer collimated in the far field but appears to be spreading as though the aperture were a point source whose radiation is confined primarily to beam total angles of the order of  $(\lambda/2b_x)$  in the x-z plane and  $(\lambda/2b_y)$  in the y-z plane.

3-1

P. 8. 8 8 8 4 4 4 1 8 9 1 5 5

CONDERCOUNTER DE CONTRACTOR

The intensity I at a field point P(0,0,d) can be expressed in terms of the number of Fresnel zones subtended by the aperture at the field point. Noting from equation (2) and equation (3) that  $A = \pi N \lambda d$  for a circular aperture and that  $A = 4\sqrt{N_x} \sqrt{N_y} \lambda d$  for a rectangular aperture, equation (4) reduces to

 $I = \begin{cases} I_0 \ 16 \ N_X \ Y_Y &, \text{ rectangular aperture} \\ I_0 \ \pi^2 \ N^2 &, \text{ circular aperture} \end{cases} (5a) ; (5b)$ 

collimated beam, N<sub>x</sub>, N<sub>y</sub>, N  $\lesssim 1/8$ 

It will be noted from equation (4) or equation (5) that in the far-field I  $\rightarrow 0$  as  $1/d^2 \rightarrow 0$  or equivalently I  $\rightarrow 0$  as  $N_x N_y$  (or  $N^2$ )  $\rightarrow 0$ .

### NEAR-FIELD FORMULATION

The intensity I  $(W/m^2)$  at any on-axis field point P(0,0,d) of a rectangular aperture with illumination of uniform amplitude and phase, is found from the Fresnel integral to be<sup>(3)</sup>

$$I = 4I_{o} \left[ C^{2}(\sqrt{2N_{x}}) + s^{2}(\sqrt{2N_{x}}) \right] \left[ C^{2}(\sqrt{2N_{y}}) + s^{2}(\sqrt{2N_{y}}) \right]; \quad (6)$$
  
collimated beam,  $b_{x} < d$ ,  $b_{y} < d$ 

where

$$C(w) = \int_{0}^{w} \cos\left[(\pi/2)t^{2}\right] dt = \text{Presnel cosine integral}^{(4)}$$
  
$$S(w) = \int_{0}^{w} \sin\left[(\pi/2)t^{2}\right] dt = \text{Presnel sine integral}^{(4)}$$

 $N_x$ ,  $N_y$  = Fresnel numbers defined by equation (3)  $I_o$  = aperture intensity (M/m<sup>2</sup>)

The Fresnel integrals have the properties that (7)

$$S(w) = -S(-w), C(w) = -C(-w)$$
 (7a)

$$S(\bullet) = C(\bullet) = \frac{1}{2}$$
(7b)

$$S(0) = C(0) = 0$$
 (7c)

5 . 5 . 5

For  $N_x = N_y = -$ , equation (6) reduces to  $I = I_0$  which is to be expected for points in the very near field. For  $N_x = N_y = 0$ , equation (6) reduces to I = 0 which is to be expected for points in the very far field.

Equation (6) reduces to equation (5a) in the limit of small Fresnel numbers. This result is demonstrated by noting that (5)

$$C(w) = w - \frac{(\pi/2)^2}{10} w^5 + \dots$$
 (8a)

$$S(w) = \frac{\pi/2}{3}w^3 - \frac{(\pi/2)^3}{42}w^7 + \dots$$
 (8b)

$$c^{2}(w) + s^{2}(w) = w^{2} - \frac{4}{45} (\pi/2)^{2} w^{6} + \dots$$
 (8c)

$$c^{2}(\sqrt{2N_{x}}) + s^{2}(\sqrt{2N_{x}}) = 2N_{x} - \frac{4}{45} (x/2)^{2}(2N_{x})^{3} + \dots$$
 (9a)

$$c^{2}(\sqrt{2N_{y}}) + s^{2}(\sqrt{2N_{y}}) = 2N_{y} - \frac{4}{45}(\pi/2)^{2}(2N_{y})^{3} + \dots$$
 (9b)

Substituting equations (9a) and (9b) with the condition  $(4\pi^2/45)(N_{\chi}^2 + N_{\gamma}^2) \ll 1$ , into equation (6), I  $\approx$  I<sub>0</sub> 16 N<sub>\chi</sub> N<sub>y</sub> which is the result given by equation 5(a).

For a circular aperture which subtends a small angle at a field point P(0,0,d), the on-axis intensity I is found from the Fresnel integral to be

M36.36.362

$$I = \left| \frac{-2\pi i}{\lambda} \sqrt{T_0} - \frac{\exp(i2\pi d/\lambda)}{d} \int_0^D \exp(i\pi r^2/\lambda d) r dr \right|^2$$
  
=  $I_0 | 1 - \exp(-i\pi N) |^2 = I_0 \left\{ (1 - \cos(\pi N))^2 + \sin^2(\pi N) \right\}$   
=  $4I_0 \sin^2(\pi N/2)$ ; collimated beam, b<

where

$$r = (x^2 + y^2)^{1/2}$$
  
N = b<sup>2</sup>/λd.

For N = 1, 3, 5, ..., I = 4I<sub>0</sub>. For N = 2, 4, 6, ..., I = 0. For N = \*, I = I<sub>0</sub>. [Equation (10) does not extrapolate to this result because equation (10) is not valid for apertures which subtend a large angle at the field point. See reference [6] for circular apertures which subtend a large angle at the field point.] With the substitution exp (-inN)  $\approx$  1-inN for ( $\pi^2N^2/12$ ) << 1, equation (10) reduces to I  $\approx I_0\pi^2N^2$  which is compatible with the far-field result given by equation 5(b).

### COMPARISON OF FAR-FIELD AND NEAR-FIELD FORMULATIONS

The on-axis near-field intensities for square apertures of side length  $2b_x = 2b_y = 2b$  and circular apertures of diameter D = 2b with illumination of uniform amplitude and phase, are compared in figure 2 as a function of the Fresnel number  $N_x = N_y = N = b^2/\lambda d$ . The near-field formulations given by equations (6) and (10) are also compared with those obtained from the far-field formulations given by equations (5a) and (5b).

The peak intensities attained are  $4I_0$  at Presnel numbers N-1, 3, 5, ... for circular apertures and 3.24  $I_0$  at a Presnel number N = 3/4 for square apertures. The minimum intensities attained in the near field are 0  $I_0$  at Presnel numbers N = 2, 4, 6 ... for circular apertures and 0.37  $I_0$  at a Presnel number N = 7/4 for square apertures. The intensities obtained from the far-field formulations exceed those obtained from the more exact near-field formulations.

The ratios of these intensities are given in table 1 as a function of the Fresnel number N. For square and circular apertures, the far-field formulation overestimates the power density by 2.8 percent and 1.3 percent, respectively, at a Freenel number of 1/8 (corresponding to the far-field boundary distance  $2D^2/\lambda$ ) and 518 percent and 147 percent, respectively, at a Freenel number of 1. The overestimation  $[(RE/2)^2/\sin^2(RE/2)] - 1$  for circular apertures has been reported earlier<sup>(1)</sup>. Please note the round-off error in

5-1



Figure 2. On-Axis Intensity for Square and Circular Apertures of Uniform Phase and Amplitude Illumination

# Table 1. On-Aris Intensity from a Far-Field Formulation Normalized to that from a Near-Field Formulation

	On-Axis Intensity Bat	io, I
Freengl Muther, H = b'/)d	Square Aperture of Side Length 2b	Circular Aperture of Diameter 2b
	25.0.26 1.026	1/1.00 11542/0.1522 1.000 0.1542/0.1522 1.013 0.6160/0.5856 1.053 2.4674/2.0000 1.234 5.5516/3.4142 1.656 9.0696/4.0000 2.467 15.4213/3.4142 4.517 22.2066/2.0000 11.103 30.2257/0.5856 51.597 39.4784/0 5856 851.597 30.2257/0.5856 851.597 39.4784/0 5856 851.597 30.2257/0.5856 851.597 30.257705 8558 851.507 30.257705 8558 851.507 30.257705 8558 851.507 30.257705 8558 851.507 30.257705 8558 851.507 30.257705 8558 851.507 30.2577058 851.507 30.257705 8558 851.507 30.257705 8558 851.507 30.257705 8558 851.507 30.257705 8568 851.507 50.257705 8568 851.507 857705 857705 8588 851.507 857705 857705 8588 851.5070000 851.5070000000000000000000000000000000000

reference [1] for a Fresnel number of 1/4 (G/G<sub>0</sub>  $\approx$  0.95 and not 0.94). For Fresnel numbers corresponding to constructive or weakly destructive interference, the overestimation is greater with square apertures than with circular apertures. However, for Fresnel numbers corresponding to totally or almost totally destructive interference, the overestimation is greater with circular apertures (see N=2 and N=2.25 in table 1). Constructive and destructive interference are more pronounced for circular apertures and, therefore, are in better and worse agreement, respectively, with the totally constructive on-axis interference of the Fraunhofer integral.

KALAKENBALA

<u>649,7777786000</u>

### LIST OF REFERENCES

- 1. S. Silver, "Microwave Antenna Theory and Design" (McGraw-Hill, N.Y., 1949, MIT Reduction Lab Series, Vol. 12), p. 199.
- 2. M. Born and E. Wolf, "Principles of Optics" (Pergamon Press, Oxford, 1964), p. 386. Please note that equation (44) of reference 2 omits the factor  $(1/d)^2$  [or equivalently, that the intensities in equation (44) are normalized to  $(1/d)^2$ ].
- 3. G. R. Fowles, "Introduction to Modern Optics "(Holt, Rinehart and Winston, Inc., New York, 1968, p. 131. See also reference 2, pp. 428-433.
- 4. M. Abramovitz and I. Stegun, "Handbook of Mathematical Functions," U.S. Dept. of Commerce, National Bureau of Standards, Applied Mathematics Series 55, tenth printing, December 1972, p. 300, 7.3.1 and 7.3.2.
- 5. op. cit. 4, p. 301, 7.3.11 and 7.3.13.
- 6. op. cit. 2, pp. 370-375.
- 7. op. cit. 4, pp. 321-322

No. of Street, or Stre

<u>ĸĸŗĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸĸ</u>

### APPENDIX A

DERIVATION OF THE FRAUNHOFER AND FRESNEL DIFFRACTION INTEGRALS

For a source point S(x',y',d'), arbitrary aperture point  $Q(x_0, y_0)$  with origin 0, and field point P(x,y,d), the Fresnel-Kirchhoff diffraction integral for the amplitude U(P) (proportional to either the scalar electric or magnetic field intensities) is given in the notation of figure 1 by<sup>(1)</sup>

$$U(P) = -\frac{Bi}{2\lambda} \iint_{A} \frac{\exp[ik(s'+s)]}{s's} \left[\cos(\vec{n},\vec{s}') - \cos(\vec{n},\vec{s})\right] dx_0 dy_0 \quad (A-1)$$

where

- $\vec{s}' = \vec{SQ}, \quad s' = |\vec{SQ}|$
- $\vec{s} = \vec{p} \vec{Q}, \ \vec{s} = |\vec{p} \vec{Q}|$
- $\vec{n}$  = unit vector normal to the aperture in the direction of the +z axis
- A = area of the clear aperture
- B = complex constant = d'  $\sqrt{1}$  e<sup>-ikd'</sup> which satisfies the boundary condition U(0,0,0) =  $\sqrt{1}$ .

(The aperture point  $Q(x_0, y_0)$  is not restricted to the aperture point Q shown in figure 1).

For the small angle conditions

$$(\vec{n},\vec{s}') \approx (\vec{n},\vec{s}\vec{0}), \quad (\vec{n},\vec{s}) \approx (\vec{n},\vec{s}\vec{0})$$
 (A-2)

and the straight line condition

$$(\overrightarrow{SO}, \overrightarrow{PO}) = \pi \text{ radians}$$
 (A-3)

A-1

<sup>(1)</sup> M. Born and E. Wolf, "Principles of Optics "(Pergamon Press, Oxford 1964), pp. 382-383.

then

$$\cos(\vec{n}, \vec{s}') \approx 1$$
,  $\cos(\vec{n}, \vec{s}) \approx -1$ , [conditions (A-2) and (A-3)] (A-4)  
1/s's  $\approx 1/d'd$  [condition (A-2)] (A-5)

Expanding s' and s in a power series,

$$s' + s = d' + d - \frac{(xx_0 + yy_0)}{d} + \frac{x_0^2 + y_0^2}{2L} - \frac{(xx_0 + yy_0)^2}{2d^3} - \dots (A-6)$$

 $\exp [ik(s'+s)] = \exp [ik(d'+d)] \exp (ikf)$  (A-7)

where

$$f = -\frac{(xx_{o} + yy_{o})}{d} + \frac{1}{2} \frac{x_{o}^{2} + y_{o}^{2}}{L} - \frac{(xx_{o} + yy_{o})^{2}}{2d^{3}} + \dots$$
  
$$L = [(1/d) + (1/d')]^{-1}$$

Substituting equations (A-4) - (A-7) and the boundary condition  $U(0,0,0) = \sqrt{I_0}$  into equation (A-11),

$$U(P) = \frac{-i\sqrt{I_o}}{\lambda d} \exp(ikd) \iint_{A} \exp(ikf) dx_o dy_o \qquad (A-8)$$

If only the first term in the above expansion for f is retained, then equation (A-8) reduces to

$$U(P) = \frac{-i\sqrt{I_0}}{\lambda d} \exp(ikd) \iint_{A} \exp\left[(-ik/d) (xx_0 + yy_0)\right] dx_0 dy_0 \quad (A-9)$$

Equation (A-9) is known as the Fraunhofer diffraction integral.

If only the first two terms in the above expansion for f are retained, then equation (A-8) reduces to

$$U(P) = \frac{-i\sqrt{I_o}}{\lambda d} \exp (ikd) \left( \iint_{A} \exp \left[ (-ik/d) (xx_o + yy_o) \right] \right]$$
$$\exp \left[ (ik/2L) (x_o^2 + y_o^2) \right] dx_o dy_o \right)$$
(A-10)

Equation (A-10) is known as the Fresnel diffraction integral.

END DATE FILMED DEC. 1987