

Defense Special Weapons Agency Alexandria, VA 22310-3398



DNA-TR-96-32

Tri-Service Thermal Radiation Test Facility

Quartz High Density Lamp Bank and Computer Data Acquisition Operators Manual

Michael Sweeney University of Dayton 300 College Park Ave Dayton, OH 45469-0999

December 1996

DTIC QUALITY INSPECTACE

Technical Report

CONTRACT No. DNA 001-90-C-0081

Approved for public release; distribution is unlimited.

19961216 013

DISCLAIMER NOTICE



THIS DOCUMENT IS BEST QUALITY AVAILABLE. THE COPY FURNISHED TO DTIC CONTAINED A SIGNIFICANT NUMBER OF PAGES WHICH DO NOT REPRODUCE LEGIBLY.

DESTRUCTION NOTICE:

Destroy this report when it is no longer needed. Do not return to sender.

PLEASE NOTIFY THE DEFENSE SPECIAL WEAPONS AGENCY, ATTN: CSTI, 6801TELEGRAPH ROAD, ALEXANDRIA, VA 22310-3398, IF YOUR ADDRESS IS INCORRECT, IF YOU WISH IT DELETED FROM THE DISTRIBUTION LIST, OR IF THE ADDRESSEE IS NO LONGER EMPLOYED BY YOUR ORGANIZATION.

DISTRIBUTION LIST UPDATE

Add the individual listed to your distribution list.	NOTE: Please return the mailing label from t document so that any additions, change
Delete the cited organization/individual.	For distribution cancellation or mo
□ Change of address.	information call DSWA/IMAS (703) 325-10
NAME:	
ORGANIZATION:	
OLD ADDRESS	CURRENT ADDRESS
TELEPHONE NUMBER: ()	
DSWA PUBLICATION NUMBER/TITLE	CHANGES/DELETIONS/ADDITIONS, etc.) (Attach Sheet if more Space is Required)
DSWA OR OTHER GOVERNMENT CONTRACT NUM	/BER:
CERTIFICATION OF NEED-TO-KNOW BY GOVERN	MENT SPONSOR (if other than DSWA):
SPONSORING ORGANIZATION:	
CONTRACTING OFFICER OR REPRESENTATIVE:	

CUT HERE AND RETURN

DEFENSE SPECIAL WEAPONS AGENCY ATTN: IMAS 6801 TELEGRAPH ROAD ALEXANDRIA, VA 22310-3398

> DEFENSE SPECIAL WEAPONS AGENCY ATTN: IMAS 6801 TELEGRAPH ROAD ALEXANDRIA, VA 22310-3398

						Form Approved		
REPORT D		OMB No. 0704-0188						
Public reporting burden for this collection gathering and maintaining the data neede collection of information, including sugges Davis Highway Suite 1204 Arlington VA	of informati d, and com tions for rec 22202-430	ion is estimated to average 1 hour p pleting and reviewing the collection ducing this burden, to Washington H 2 and to the Office of Managemen	er response inc of information. leadquarters Se and Budget Pa	luding the time for reviewing ins Send comments regarding this rvices Directorate for informatic aperwork Reduction Project (07	struction burden on Opera	s. searching existing data sources, estimate or any other aspect of this ations and Reports, 1215 Jefferson 3) Washington DC 20503		
1. AGENCY USE ONLY (Leave blank) 2. REPORT DATE 3. REPORT TYPE 961201 Technical 9						ND DATES COVERED 0426 – 940717		
4. TITLE AND SUBTITLE	5. FUN	IDING NUMBERS						
Tri-Service Thermal Rad	C	- DNA 001-90-C-0081						
Quartz High Density Lamp Ba	PE	- 62/15H						
6. AUTHOR(S)		- KG						
Michael Sweeney					vvc	- 011307230		
7. PERFORMING ORGANIZATION	NAME(S	S) AND ADDRESS(ES)		٤	B. PER REF	FORMING ORGANIZATION		
University of Dayton						D TD 04 27		
300 College Park Ave	_				UU	R-1R-34-3/		
Dayton, OH 45469-0999	9							
9. SPONSORING/MONITORING A		NAME(S) AND ADDRESS	(ES)	1	10. SP ۵			
6801 Telegraph Boad	ns Age	ency						
Alexandria VA 22310-3	208				DN	NA-TR-96-32		
FST/Chivers								
11. SUPPLEMENTARY NOTES								
This work was sponsore	d by th	ne Defense Special	Weapon	s Agency under F	RDT	&E RMC Code B4662D		
RG RR 00034 TDTR 520	00A 25	5904D.						
12a. DISTRIBUTION/AVAILABILIT	Y STATE	MENT			12	b. DISTRIBUTION CODE		
Approved for public release: distribution is unlimited								
13. ABSTRACT (Maximun	n 200 v	words)						
Safe operational and	servic	ing test procedures	for the C	uartz Lamp Banl	k and	d Windtunnel, and the		
Mobile Quartz Lamp Bar	nk are	described in this do	cument.	The manual guid	des t	est technicians, operating		
a Grid 486 microprocess	sor, in i	using proper safety	and ope	rational procedur	es in	the operation, control		
and data acquisition of the	he Qua	artz Lamp and Winc	ltunnel s	ystems. A safety	che	cklist to be followed prior		
to and during equipment	utiliza	tion is provided. A	descripti	on of instrumenta	ation	used in support of testing		
and procedures for servi	icing th	ne test equipment is	also pro	vided.				
14. SUBJECT TERMS			· · · · · · · · · · · · · · · · · · ·			15. NUMBER OF PAGES		
						38		
Instrumentation Qua	ŀ	16. PRICE CODE						
Safety Checklist Cor	ntrol ar	nd Data Acquisition						
17. SECURITY CLASSIFICATION 1	8. SECL	JRITY CLASSIFICATION	19. SECU	IRITY CLASSIFICATIO	N	20. LIMITATION OF ABSTRACT		
						SAR		
	NCLASSIFIED UNCLASSIFIED UNCLASSIFIED							

NSN 7540-280-5500

.

.

¥

4

UNCLASSIFIED SECURITY CLASSIFICATION OF THIS PAGE

CLASSIFIED BY:

N/A since Unclassified.

DECLASSIFY ON:

N/A since Unclassified.

.

Section			Page
1	INTF	RODUCTION	1
2	SAF	ETY	2
	2.1	Safety Checklist	2
	2.2	Instrumentation	4
		2.2.1 Calibration	4
		2.2.2 Testing	4
		2.2.3 Computer Initiation	4
		2.2.4 Prestart Checklist	5.
3	OPE	RATION	7
	3.1	QLB Control	7
	3.2	Data Acquisition	12
•		3.2.1 Excel 3.0a	12
4	SER	VICING	22
5	HAR	DWARE	23
	5.1	Controls	23
	5.2	Data Acquisition	23
Appendix	٤		A-1

TABLE OF CONTENTS

FIGURES

Figure		Page
2-1	Quartz Lamp System Power Disconnect Locations	3
2-2	Windows Program - Main Menu	6
3-1	Main Menu - QLB CONTROL/DATA ACQ	8
3-2	File	9
3-3	Test Information	10
3-4	Profile	11
3-5	Channel List	13
3-6	TRTF Operation	14
3-7	File Save	15
3-8	Windows Program - Main Menu	16
3-9	Microsoft Excel	17
3-10	File	18
3-11	File Information	20
3-12	File Information (Shaded)	21

iv

SECTION 1 INTRODUCTION

Control and Data Acquisition of the Quartz Lamp Bank, Windtunnel and Mobile Quartz Lamp Bank System is accomplished with a Grid 486 IBM-AT compatible computer, keyboard, color monitor, data acquisition board, and relay control board. The Grid 486 control board consists of 24 off-the-shelf solid state relays, and 24 LED displays to ease fault isolation of equipment.

The quartz lamp system is operated through Microsoft Windows. Acquired data can be graphed using Microsoft Excel. Storage media for the acquired data utilizes one of two hard drives installed in the computer. Data can also be transferred to either 3-1/2 inch or 5-1/14 inch diskettes.

SECTION 2 SAFETY

All procedures in the operation of test equipment within the Tri-Service Thermal Radiation Test Facility will be in accordance with the UDR-TR-94-70, "Tri-Service Thermal Radiation Test Facility Technical Support Plan (TSP) Instructions" which governs all activities within the TRTF.

2.1 SAFETY CHECKLIST.

The following procedures shall be followed to ensure the safety of all personnel and the safe operation of equipment during operation of the Quartz Lamp Bank (QLB) system.

Prior to system startup and operation, it shall be verified that all power to the system is in the "OFF" condition. Power switch locations for all system components are shown in Figure 2-1:

- 1. Ensure that the QLB Power Switch (circuit breaker) in the hallway of Bay 7 is in the "OFF" position.
- 2. Ensure that the Windtunnel Blower Power Switches on the west wall of Room 711 are in the "OFF" position.
- 3. Ensure that the amber indicator lamp on the wall mounted relay control panel in the Control Room 711C is not illuminated. If necessary, activate the fused toggle switch to the left of the panel to extinguish the lamp.
- 4. Push the RED Power Kill switch located on the Control Room wall to the "IN" position.
- 5. Ensure that the Grid 486 computer and monitor are turned "OFF".
- 6. Ensure that all LED displays on the relay control are in the "OFF" state.



Figure 2-1. Quartz Lamp System Power Disconnect Locations.

3

2.2 INSTRUMENTATION.

2.2.1 Calibration.

Select a calorimeter which encompasses the heat flux range specified in the test profile. Ensure that the calorimeter is connected to data acquisition, and that the cooling water circulator is connected to the calorimeter. Install the calorimeter in the sample holder.

2.2.2 Testing.

If the test sample contains thermocouple instrumentation, ensure that the thermocouples are connected to cold junction compensators. The compensators are battery operated, and battery voltage must have a minimum of 1.35 vdc.

The cold junction compensators must be turned ON. Install the test sample in the sample holder.

2.2.3 Computer Initiation.

At computer startup all outputs for control of the quartz lamp system will automatically reset.

2.2.3.1 Calibration:

- 1. Turn ON computer and monitor. Boot up will be verified by the prompt (c\:).
- 2. Type "cd\ad16" The prompt (c:\ad16) will appear.
- 3. Type "cal 16". A list of ranges will appear. Select range 4 by typing "4". Type "768" for board address. Type "16" for channel configuration. Press ENTER.
- 4. Press spacebar. CI016 Calibration Program will appear.
- Type "1" and ENTER. Press spacebar. Select port configuration by typing "8". Press ENTER.
- 6. Type "M" for the menu. Select "4" to exit calibration. Prompt (c:\ad16) will appear.
- 7. Type "cd\". Prompt (c:\) will appear.

2.2.3.2 <u>Windows Program.</u> Type "WIN/S" and ENTER. The monitor will display Program Manager screen (Figure 2-2).

- 2.2.4 Prestart Checklist.
 - 1. Check that the calorimeter or test sample is installed in the sample holder. If the calorimeter is installed, check lead plug-in to amplifier and cooling water circulation is turned ON. If an instrumented test sample is installed, check thermocouple connection to cold junction compensators, and power to compensators. Check compensator connections to amplifiers.
 - 2. Activate QLB Power Disconnect circuit breaker in Bay 7 hallway (Figure 2-1).
 - 3. Activate windtunnel blower switches in test room (Figure 2-1).
 - 4. Activate toggle switch on the relay panel on data acquisition room wall (Figure 2-1). Amber light on panel will illuminate.
 - 5. Pull the red Power Kill button, also located on the data acquisition room wall to the OUT position.
 - 6. Clear the test room of all personnel.



Figure 2-2. Windows Program - Main Menu.

SECTION 3 OPERATION

3.1 QLB CONTROL.

With the computer program in Windows (Figure 2-2), use the mouse to execute the following:

- 1. Position arrow cursor to QLB CONTROL/DATA ACQ. in MAIN menu (Figure 3-1) and execute double click. Figure 3-2 will appear.
- 2. Position cursor to File in upper left corner of screen and execute single click. Position cursor on NEW and execute single click. Figure 3-3 will appear.
- 3. Fill in Customer and Specimen Title. Position cursor on OK and execute single click. Figure 3-4 will appear.
 - NOTE: Operating test profiles are generally accomplished using a sequence of timed events, e.g. Power to QLB, Windtunnel Blowers, Shutter Actuation, Bell Warning Alarm, and QLB Cooling Fan operation. Test parameters for each event sequence on each PROFILE event screen (Figure 3-4). Each event is displayed by positioning cursor on small arrows on right side of screen to advance or to retreat event displays and executing single click. A typical test profile of events is shown in the Appendix.
- 4. Enter Description (e.g. number and type of lamps, lamp wattage), Control Voltage (0 to 3.5 vdc), and A/D Interval (milliseconds).
 - NOTE: Description Distinguishes one test from another, e.g. number of lamps, wattage, reflector in use.

Control Voltage - Zero to 3.5 vdc, varies tri-phaser power from 0 to 480 vac.

A/D Interval - Data collection per millisecond (1000 data points maximum per channel).

Save - Position cursor and single click saves file for future use or modification.



Figure 3-1. Main Menu - QLB CONTROL/DATA ACQ.



Figure 3-2. File.



Figure 3-3. Test Information.



Figure 3-4. Profile.

Load - Position cursor and execute single click to retrieve file that has been saved.

Add - Position cursor and execute single click to add to file.

Delete - Position cursor and execute single click to delete from file.

Pwr, BL1, BL2, Sht, etc. - Position cursor and execute single click to activate (), or deactivate ().

Enter information for each event screen to be used in test profile. Position cursor on OK and execute single click. Figure 3-5 will appear.

5. Enter sample description.

NOTE: Open - Position cursor and execute single click to change file.

Close - Position cursor and execute single click to save file.

Channel 1, 2, etc. - Enter description of instrumentation, e.g. thermocouple type, temperature in degrees F or in degrees C.

Position cursor on OK and execute single click. Figure 3-6 will appear.

- 6. If event and channel information has been correctly entered and verified, position cursor on Yes and execute single click. All test events will automatically start. At end of test sequence, Figure 3-7 will appear.
- 7. Enter file number followed by .xl and position cursor on OK and execute single click.
- 8. Position cursor on EXIT and execute single click. WINDOWS Program Manager (Figure 3-8) will appear.

3.2 DATA ACQUISITION.

- 3.2.1 Excel 3.0a.
 - 1. Position cursor on EXCEL 3.0a of Program Manager and execute double click. Microsoft Excel (Figure 3-9) will appear.
 - Position cursor on FILE in upper left corner and execute single click. Figure 3-10 will appear.



Figure 3-5. Channel List.





- Eilc	Time 30.0 Event 6	
File <u>n</u> ar Directo <u>D</u> irecto [] [-a-] [-b-] [-c-] [-d-]	File Save As ne: 12345.xl_ nry: c:\trtf pries:	Cancel

.

,

Figure 3-7. File Save.



Figure 3-8. Windows Program - Main Menu.

		Micr	osoft Exce	I CAR			
<u>File Edit Formula</u>	Form	a <u>i D</u> ata	Options	Macro	Window	Help	
<u>N</u> ew			ΣΒ				
<u>O</u> pen		<u></u>					
<u>C</u> lose	6	C	D	E	F	G	•
Links							
Save							
Save <u>A</u> s				` 			
Save Workspace			•		·		╡╏
<u>U</u> elete	×						
Print Preview		••••••••••••••••••••••••••••••••••••••					_
Page Setup	§	•	.				
Print	8	<u>.</u>					-
Printer Setup			•				-
1 \TRTF\10.XLS	§						-
2 (TRTF(15.XLS	}	<u>.</u>		•			
<u>3 \TRTF\25.XLS</u>							•
4\(RTF\35.XLS							
Exit							
Create new document	-				N	JM	

Figure 3-9. Microsoft Excel.

	Microsoft Excel	
Eile <u>H</u> elp	· · · E · · E · · · · · ·	
	Open OK File Name: 12345.xl_ Cancel Files: Directory is: c:\excel Performed and the second and the seco	
невау		4.0000000

Figure 3-10. File.

- Position cursor on OPEN and execute single click. A list of files will be displayed in Figure 3-10. Position cursor to file created for the test and execute a single click. Position cursor on OK and execute a single click. Figure 3-11 showing the selected data file will appear.
- 4. Execute and hold mouse click while moving mouse over entire area of data in Figure 3-11 to be plotted. When the entire area is shaded as shown in Figure 3-12, immediately release the click and position the cursor on the bar graph symbol in upper right corner of the screen.
- 5. Position cursor in lower left corner of screen (Figure 3-12). Execute and hold mouse click. Move cursor from lower left to upper right of screen to create data boundaries. Release the click. A small box will appear in the figure. Position cursor to select first column information (usually X-values for XY chart is selected) and execute single click. Position cursor to OK and execute single click. The plot will appear on the screen.
- 6. Position cursor on the plot area and execute a double click. Position cursor on GALLERY at top of screen and execute a single click. A variety of options for plotting will appear. Position cursor on selected option and follow Windows with cursor and single clicks.

					vicrosoft	Excel				<u>•</u> •
Eil	c E	dit Form	ula Forn	nat Dal	a Uptio	ns <u>M</u> acr			<u>353 (n1)</u>	
No	mal									
	<u></u>		Custor	ner						
					TEST1.	XL				
		A	B	С	D	E	F	G	H •	
		Customer	TEST							
	2	Specimen	SAMPLE		•••••			•·····		
	3	Date	mo/d/yr							
	4	Time	h:mi							
	5	Time	Thermo							
	6	Seconds							•	
	7	0.1	74.9805	•••••••						
	В	U.27	74.9805							
		0.44	74.9805	••••••						
	10		710005		•••				•	
	11	0.78	74.3005	•••••••						
	12	U.35 1 1 2	73 01 22							
		1.12	73 01 22							
		1.23						: 		
								NI INA	linstll	
∣-He	ady									

Figure 3-11. File Information.

	Microsoft Excel
<u>File Edit</u> Formula	a Forma <u>t D</u> ata <u>Options Macro Window H</u> elp
Normal	
A1	Customer
	TESTI XL_
	B C D E F G H +
1 Customer TE	EST
2 Specimen SA	
J Date mo	
	First Column Contains
6 Seconds F	First Data Series
7 0.1	Category (X) Axis Labels
£ 20	74.9805
9 21	74.9805
22	
23	74,9805
	74.5005
	73.9133
Ready	NUM

Figure 3-12. File Information (Shaded).

SECTION 4 SERVICING

The Quartz Halogen Infra-Red Heater Lamps (Quartz Lamps) used as the thermal source with the Large Test Section Wind Tunnel (LTS/WT) are to be handled only by qualified Tri-Service Thermal Test Facility personnel. Before removing or changing Quartz Lamps the Quartz Lamp Bank primary disconnect (Figure 3-6) must be pulled down to its OFF position. Voltage measurements across each of the three phases and to ground are to be taken to assure no voltage is present. Cotton gloves and safety eyeglasses, goggles or face shield are to be worn when handling Quartz Lamps and when replacing the Wind Tunnel quartz window. The air hose is to be disconnected from the air cylinder when servicing any part of the shutter mechanism. The Wind Tunnel primary disconnects (Figure 3-6) are to be pulled down to their OFF position whenever the Wind Tunnel must be serviced or opened for cleaning.

When servicing the hydraulic system of the Hydraulic Mechanical Tester, the main disconnect (Figure 3-6) must be pulled down to its OFF position. At no time should hands be placed between the cylinders of the test apparatus even when the hydraulic system has been disarmed since there are pressure accumulators in the system that could hold enough pressure to actuate the cylinder. Since the hydraulic hoses and controlling cables for the Hydraulic Tester may lay on the floor around the test machine, care should be taken not to trip or to slip on the hydraulic oil that could be present on the floor.

SECTION 5 HARDWARE

5.1 CONTROLS:

- 24 2.5-10 vdc Computer controlled 60v 3.5 amp solid state relays
 14 3-32 vdc control 240v 25 amp solid state relays
- 2. Emergency power kill button
- 3. Magnetic contactor
- 4. 0-480 volts ac Tri-Phaser

5.2 DATA ACQUISITION:

- 1. 486 computer with a CIO16 DAS board
- 2. 16 University of Dayton signal conditioning amplifiers
- 3. 16 Omega cold junction compensators type K

APPENDIX



* Type in the DESCRIPTION.

1. Single click on ADD.

- A. Enter the TIME (sec.) of the first event.
 - * Note generally something slightly greater than zero is used . Single click O.K.
 - * Note the time entered in the black shaded area.
 - Click in area titled Control Signal (Volts). Type in the 0 to 3.5 vdc control voltage to control the lamps.
 - 2. Use the mouse to check ON or OFF equipment used for this point in time for EVENT 1.
 - * In this example the **PWR**, **BL1**, **FAN**, and the **WTR** are checked ON
 - If the **ARM** is checked at this point be aware that the control voltage entered will be sent to the lamps.
 - * All options chosen at EVENT-1 will turn on at the time that was specified.
- B. Goto EVENT-2 using ADD.



* The **Description** does not change.

2. Single click on ADD.

A. Enter the TIME (sec.) of the second event.

- * Note that generally a delay of about 18 sec. is used to alow the lamps to warm up . Single click O.K.
- * Note the time entered in the black shaded area.
- Click in area titled Control Signal (Volts). Type in the 0 to 3.5 vdc control voltage to control the lamps.
 * The same voltage is generally used throughout the test.
- 2. Use the mouse to check ON or OFF equipment used for this point in time for EVENT 2.
 - * In this example the PWR, BL1, BEL, ARM, FAN, and the WTR are checked ON.
 - * If the **ARM** is checked at this point be aware that the control voltage entered will be sent to the lamps.
 - * Note the SHT is energized after a 2 second delay.
 - All options chosen at EVENT-2 will turn on at the time that was specified.

B: Goto EVENT - 3 using ADD.



- The **Description** does not change.
- 3. Single click on ADD.
- A. Enter the TIME (sec.) of the third event.
 - Note that generally a delay of about 2 sec. is used to allow the warning Bell to sound. Single click O.K.
 - * Note the time entered in the black shaded area.
 - 1. Click in area titled Control Signal (Volts).
 - Type in the 0 to 3.5 vdc control voltage to control the lamps.
 - The same voltage is generally used throughout the test.
 - 2. Click in area titled A / D Interval (mSec).
 - The length of the test has a direct bearing on this input.
 - Enter 100 mSec. * Example, data collection starts at 20 sec. or event 3 and finishes at the end of the test or 30 sec. This means data collection is 10 seconds long. Remember only 1000 data points per channel. 10 sec. / 100ms or (interval) = 100 total data points.
 - 3. Use the mouse to check ON or OFF equipment used for this
 - point in time for EVENT 3.
 - In this example the PWR, BL1, SHT, ARM, FAN, and the WTR are checked ON.
 - If the **ARM** is checked at this point be aware that the control voltage entered will be sent to the lamps.
 - Note the SHT is energized after 2 seconds of lamp ON or a 2 second delay.
 - All options chosen at EVENT-3 will turn on at the time that was specified.
- B. Goto EVENT - using ADD .



The Description does not change.

4. Single click on ADD.

- A. Enter the TIME (sec.) of the fourth event : Single click O.K.
 - * Note the time entered in the black shaded area.
 - 1. Click in area titled Control Signal (Volts).
 - Type in the 0 to 3.5 vdc control voltage to control the lamps. • The same voltage is generally used throughout the test.
 - 2. Click in area titled A / D Interval (mSec). The length of the test has a direct bearing on this input. Enter 100 mSec. * Example, data collection starts at 20 sec. or event 3 and finishes at the end of the test or 30 sec.
 - This means data collection is 10 seconds long Remember only 1000 data points per channel.
 - 10 sec. / 100ms or (interval) = 100 total data points.
 - 3. Use the mouse to check ON or OFF equipment used for this point in time for EVENT - 4.
 - * In this example the PWR, BL1, ARM, FAN, and the WTR are checked ON.
 - * If the ARM is checked at this point be aware that the control voltage entered will be sent to the lamps.
 - Note the SHT is turned off after 5 seconds of sample exposure.
 - All options chosen at EVENT-4 will turn on at the time that was specified
- B. Goto EVENT-5 using ADD.



* The **Description** does not change.

5. Single click on ADD.

- A. Enter the TIME (sec.) of the fifth event . Single click O.K.
 - * Note the time entered in the black shaded area.
 - 1. Click in area titled Control Signal (Volts).
 - Type in the 0 to 3.5 vdc control voltage to control the lamps. • The same voltage is generally used throughout the test.
 - Click in area titled A / D Interval (mSec).
 - The length of the test has a direct bearing on this input . Enter 100 mSec.
 - Example, data collection starts at 20 sec. or event 3 and finishes at the end of the test or 30 sec.
 This means data collection is 10 seconds long.
 Remember only 1000 data points per channel.
 10 sec. / 100ms or (interval) = 100 total data points.
 - 3. Use the mouse to check ON or OFF equipment used for this point in time for EVENT 5.
 - In this example the PWR, BL1, FAN, and the WTR are checked ON.
 - If the **ARM** is checked at this point be aware that the control voltage entered will be sent to the lamps.
 - Note the ARM is turned off 1 sec. after the shutter closes.
 - This will terminate the 1 vdc control to the lamps.
 - All options chosen at EVENT-5 will turn on at the time that was specified.
- B. Goto EVENT-6 using ADD.



• In this example all equipment is OFF .

Generally the FAN is left ON to cool the lamps.

* All options chosen at EVENT - 6 will turn on at the time that was specified .

- B. Click on SAVE.
 - 1. Enter the file name of the new Profile .
 - Example : *example . pro*
- 2. Select O.K.
- C. When SAVE has been performed use the up and down arrows to right to scroll through the events.
- D. Select LOAD an enter the Profile just SAVED.
- Select O.K. by the check mark if information is good.
- E. DELETE is only used to remove an EVENT .

DISTRIBUTION LIST

DSWA-TR-96-32

DEPARTMENT OF DEFENSE

DEFENSE INTELLIGENCE AGENCY ATTN: DIW-4

ATTN: OGA-4B2

DEFENSE SPECIAL WEAPONS AGENCY ATTN: ESA 2 CY ATTN: ISST

ATTN: WE ATTN: WEL

ATTN: B PRASAD

DEFENSE TECHNICAL INFORMATION CENTER 2 CY ATTN: DTIC/OCP

FIELD COMMAND DEFENSE SPECIAL WEAPONS AGENCY ATTN: MAJ SCHLICHER ATTN: FCTO ATTN: FCTOS ATTN: DR BALADI ATTN: J JABLONSKY ATTN: E MARTINEZ

DEPARTMENT OF THE ARMY

ADVANCED RESEARCH PROJECT AGENCY ATTN: PMO

ARMY RESEARCH LABORATORIES ATTN: TECH LIB ATTN: MARY ABE

MDSTC

ATTN: CSSD-H-SA

NUCLEAR EFFECTS DIVISION ATTN: B HAMILTON ATTN: J OIKUNHA ATTN: A BRIONES ATTN: R PENNY

U S ARMY ENGINEER DIV HUNTSVILLE ATTN: HNDED-CS ATTN: HNDED-SY

U S ARMY ENGR WATERWAYS EXPER STATION ATTN: D RICKMAN ATTN: J WINDHAM ATTN: TECHNICAL LIBRARY

U S ARMY NUCLEAR & CHEMICAL AGENCY ATTN: G LONG

U S ARMY RESEARCH LAB ATTN: TECH LIB

. (

U S ARMY SPACE STRATEGIC DEFENSE CMD ATTN: CSSD-CS ATTN: CSSD-SA-E

U S ARMY TRADOC ANALYSIS CTR ATTN: ATRC-WSSR

DEPARTMENT OF THE NAVY

DAVID TAYLOR RESEARCH CENTER ATTN: P POTTER ATTN: S BARTON

NAVAL COMMAND, CONTROL & OCEAN SURVEILLANCE CTR ATTN: CODE 250

NAVAL RESEARCH LABORATORY ATTN: RESEARCH REPORT ATTN: E FRIEBELE ATTN: CODE 6180

NAWC-WD ATTN: D HERIGSTAD

DEPARTMENT OF THE AIR FORCE

HQ 497 IG/INOT ATTN: INT

DEPARTMENT OF ENERGY

LOS ALAMOS NATIONAL LABORATORY ATTN: D FRY ATTN: D STUPIN ATTN: J FRITT ATTN: J ZAHRT ATTN: L BRYANT ATTN: M THOMPSON ATTN: REPORT LIBRARY ATTN: P WHALEN ATTN: P GINSBERG ATTN: S S HECKER ATTN: W BRUNISH SANDIA NATIONAL LABORATORIES ATTN: B PLUMMER

ATTN: C CAMERON ATTN: H BARRETT ATTN: TECH LIB

OTHER GOVERNMENT

CENTRAL INTELLIGENCE AGENCY ATTN: OSWR/NED

FEDERAL EMERGENCY MANAGEMENT AGENCY ATTN: OFC OF CIVIL DEFENSE

DEPARTMENT OF DEFENSE CONTRACTORS

ABERDEEN RESEARCH CENTER ATTN: J KEEFER ATTN: N ETHERIDGE

APTEK INC ATTN: S SUTHERLAND

BDM FEDERAL INC ATTN: E DORCHAK

DSWA-TR-96-32 (DL CONTINUED)

BERKELEY RSCH ASSOCIATES INC ATTN: J ORENS

BOEING TECHNICAL & MANAGEMENT SVCS INC ATTN: R BRYAN CAIRNS

CARPENTER RESEARCH CORP ATTN: H J CARPENTER

CHARLES NEEDHAM ATTN: CHARLES NEEDHAM

DAYTON UNIVERSITY OF ATTN: B WILT 2 CY ATTN: M SWEENEY ATTN: R SERVAIS

GEO CENTERS INC ATTN: E MARRAM

GEORGIA INSTITUTE OF TECHNOLOGY ATTN: C BROWN

H & H CONSULTANTS INC ATTN: W HALL

INFORMATION SCIENCE INC ATTN: W DUDZIAK

JAYCOR ATTN: J BRYARS

JAYCOR ATTN: CYRUS P KNOWLES

KAMAN SCIENCES CORP ATTN: D CAYNE ATTN: LIBRARY

KAMAN SCIENCES CORP ATTN: A L PHILLIPS ATTN: G PADEREWSKI ATTN: J FANNING ATTN: T DEUTON ATTN: Z LAWRENCE

KAMAN SCIENCES CORP ATTN: D MOFFETT

KAMAN SCIENCES CORPORATION ATTN: DASIAC

KARAGOZIAN AND CASE ATTN: J KARAGOZIAN

LOCKHEED MARTIN CORPORATION ATTN: S SALISBURY

LOCKHEED MARTIN CORPORATION ATTN: TECH INFO CTR LOGICON R AND D ASSOCIATES ATTN: C K B LEE ATTN: D SIMONS ATTN: LIBRARY LOGICON R AND D ASSOCIATES ATTN: G GANONG MAXWELL LABORATORIES INC ATTN: J BARTHEL ATTN: T PIERCE MISSION RESEARCH CORP ATTN: TECH LIBRARY MISSION RESEARCH CORPORATION ATTN: D OHARA ATTN: K WOODS NICHOLS RESEARCH CORPORATION ATTN: R BYRN ATTN: STANLEY R BERRY PACIFIC-SIERRA RESEARCH CORP ATTN: H BRODE PHYSICS INTERNATIONAL CO ATTN: E WILLIS SCIENCE APPLICATIONS INTL CORP ATTN: TECHNICAL REPORT SYSTEM SCIENCE APPLICATIONS INTL CORP ATTN: J GUEST ATTN: J SIMMONS ATTN: W SCHAEFER SCIENCE APPLICATIONS INTL CORP ATTN: J COCKAYNE ATTN: W CHADSEY ATTN: W LAYSON SCIENCE APPLICATIONS INTL CORP ATTN: G BINNINGER SRI INTERNATIONAL ATTN: DR JIM GRAN ATTN: G GREENFIELD TELEDYNE BROWN ENGINEERING ATTN: J RAVENSCRAFT ATTN: TECHNICAL LIBRARY THE AEROSPACE CORP ATTN: L SELZER ATTN: LIBRARY ACQUISITION TITAN CORPORATION ATTN: J THOMSEN TRW SPACE & DEFENSE SECTOR SPACE & ATTN: W WAMPLER