


2

NPS55-77-37

NAVAL POSTGRADUATE SCHOOL Monterey, California





AN INTERACTIVE MODEL TO COMPUTE

THE OFFICER MANPOWER PLAN

FOR THE UNITED STATES MARINE CORPS


by

Kneale T. Marshall

August 1977

Approved for public release; distribution unlimited.

Prepared for: Headquarters Marine Corps Code MPI20 Washington, DC 20380





NAVAL POSTGRADUATE SCHOOL Monterey, California

Rear Admiral Isham Linder Superintendent Jack R. Borsting Provost

This work was supported by the Manpower Planning Division (MPI20) of the Marine Corps through the Navy Personnel Research and Development Lab, San Diego.

Reproduction of all or part of this report is authorized.

Prepared by:

KNEALE T. MARSHALL, Professor

Department of Operations Research

Released by:

MICHAEL G. SOVEREIGN, Chairman

Reviewed by:

Department of Operations Research

ROBERT R. FOSSUM Dean of Research

	UNCLASSIFIED	- Entered)	
	REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS
CHARLE WAY	1. REPORT NUMBER		BEFORE COMPLETING FORM 3. RECIPIENT'S CATALOG NUMBER
(14)	NPS55-77-37		
	4. TITLE (and Subtitle)		5 TYPE OF REPORT & PERIOD COVERED
1	An Interactive Model to Compute		(Technical Report.)
6	Manpower Plan for the United Sta	ites marine corps	6. DERECOMING ORG. REPORT NUMBER
	7. AUTHOR(e)		8. CONTRACT OR GRANT NUMBER(4)
60	Kneale T./Marshall		
1	9. PERFORMING ORGANIZATION NAME AND ADDRESS		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
	Naval Postgraduate School Monterey, CA 93940		
	Political ey, CA 93940		N6822 7 WR 70052
	11. CONTROLLING OFFICE NAME AND ADDRESS Headquarters Marine Corps, Code	MDT20	Aug 77
	Washington, DC 20380	MF120 //	13. NUMBER OF PAGES
	14. MONITORING AGENCY NAME & ADDRESS(II differe	nt from Controlling Office)	15. SECURITY CLASS. (or the report)
			UNCLASSIFIED
	*		15a. DECLASSIFICATION/DOWNGRADING SCHEDULE
			SCHEDULE
	16. DISTRIBUTION STATEMENT (of this Report)		
	Approved for public release; dis	tribution unlimit	ted.
	17. DISTRIBUTION STATEMENT (of the abstract entered	In Block 20, It different from	n Keport)
	18. SUPPLEMENTARY NOTES		
	19. KEY WORDS (Continue on reverse side if necessary a	nd identify by block number)	
	Manage Page 1		
	Manpower Personnel Forecasting Planning		
-			
1	ABSTRACT (Continue on reverse elde if hecessary	nd identify by block number)	
	This report describes a mathemat		
	active APL functions which are u the United States Marine Corps.		
	tion cycle and represents the fu	ture forecasted a	ind planned force structure
	by rank. A complete plan can be minutes. This is a considerable		
	calculations. This increase in		
	DD 1 JAN 73 1473 EDITION OF 1 NOV 65 IS OBSC	LETE UNCLASS	IFIED Santa
	S/N 0102-014-6601	SECURITY CLAS	SSIFICATION OF THIS PAGE (When Date Entered)
	2511	150	donce

LECURITY CLASSIFICATION OF THIS PAGE(When Date Entered)

many alternate plans in a short period of time, and do sensitivity analysis on certain data elements such as loss rates.

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE(When Data Entered)

TABLE OF CONTENTS

		Page
1.	Introduction	1
2.	The Personnel Flow Model	3
3.	The Calculation Procedure	7
4.	APL Data Input Functions	8
5.	APL Calculation and Output Format Functions	20
6.	An Example	34
	References	42

CCESSION FO NTIS DDC UNANNOUNC	White Section
JUSTIFICATION	ON/AVAILABILITY CODES VAIL and/or SPECI
Dist. A	A3 C9-

1. Introduction

This report describes a mathematical model and a set of associated interactive APL functions which are used to calculate an officer manpower plan for the United States Marine Corps. This plan is used during the budget preparation cycle and represents the future forecasted and planned force structure by rank.

A complete plan can be calculated and printed in less than five minutes. This is a considerable reduction from the times involved in hand calculations. This increase in speed allows the planning officers to try many alternate plans in a short period of time, and do sensitivity analysis on certain data elements such as loss rates.

A brief summary of the method of calculation is given here. Details are presented in section 3. End strengths (by month) are given for ranks General through Captain, as well as losses and gains to these ranks. From these the monthly numbers of promotions out of ranks Colonel through 1-st Lieutenant are calculated. For ranks Warrant Officer-1 through 2-nd Lieutenant, the numbers of monthly promotions are given, and thus the monthly end-strengths for these ranks are determined. Finally, once promotions into and out of 1-st Lieutenant have been calculated, the monthly end-strengths are calculated for that rank.

Section 2 contains the mathematical formulation of the flow model which is based on ideas presented in chapter 1 of reference [2]. Section 3 gives a detailed description of the order in which the calculations are made. Section 4 describes a set of data input functions written in APL and intended for interactive use in entering data. Section 5 describes a set of calculation and format functions written in APL and intended for calculation and display of the officer manpower plan. Readers unfamiliar with APL should see reference [1]. Finally, section 6 shows a sample use of the functions and displays a plan.

All the functions in this report are in a workspace called OFFICERPLAN in the

APL+ system of Scientific Time Sharing Corporation. They were prepared at the Naval Postgraduate School through constant communication with the staff in MPP at Headquarters, Marine Corps.

2. The Personnel Flow Model

In this section is described the mathematical flow model and how it is used to determine the officer manpower plan. The model is based on simple conservation of flow equations (see chapter 1 of reference [2] for details of flow models). Let the discrete planning time (typically the end of each month) be numbered $t=0,1,2,\ldots$, with t=0 being the starting point. The time interval between times t and t+1 we call period t+1. At each time t we count the number in each rank and call it the stock level at time t. People are promoted, join, or leave between the accounting time points, and these are called flows in period t. Thus we can write

To express (1) mathematically we use the following notation. Let

 $s_i(t)$ = stock level at time t in rank j

 $g_{i}(t) = gains in period t into rank j$

 $\ell_i(t)$ = losses in period t from rank j

 $x_i(t)$ = promotions in period t into rank j

 $y_{j}(t)$ = promotions in period t out of rank j

The index j ranges over $1,2,\ldots,n$, where n is the number of ranks which are numbered in decreasing seniority. Thus rank 1 is the highest rank and rank n is the lowest. Equation (1) now becomes

(2)
$$s_{j}(t+1) = s_{j}(t) + g_{j}(t+1) - \ell_{j}(t+1) + x_{j}(t+1) - y_{j}(t+1),$$

 $j = 1, 2, ..., n, t \ge 0.$

Let s(t), g(t), $\ell(t)$, x(t) and y(t) represent the n-dimensional vectors for $s_j(t)$, $g_j(t)$, $\ell_j(t)$, $x_j(t)$ and $y_j(t)$ respectively. Then we can write (2) as

(3)
$$s(t+1) = s(t) + g(t+1) - \ell(t+1) + x(t+1) - y(t+1), t \ge 0.$$

Before this general model can be applied to the USMC officer corps, further explanation is required of what we precisely mean by ranks, and for each rank, the definition of gains and losses.

In the computer models described later in this report n has the value 11 and the ranks are:

Number (j)	Rank	
49 y 1 294303 4	General	(GEN)
2	Colonel	(COL)
3	Lieutenant Colonel	(LCOL)
4	Major	(MAJ)
and the state of t	Captain	(CAPT)
6 /	First Lieutenant	(1LT)
7	Second Lieutenant	(2LT)
8	Warrant Officer-4	(CWO-4)
9	Warrant Officer-3	(CWO-3)
10	Warrant Officer-2	(CWO-2)
11	Warrant Officer-1	(WO-1)

For each rank, the sources of gains are:

Rank	Sources of Gains
GEN	None services you (1) not have a consultant
COL-CAPT	Returns from reimbursable billets
1LT-2LT	Accessions into the commissioned officer corps
CWO-4 - CWO-2	None
WO-1	Accessions into the warrant officer corps

For each rank the sources of losses are:

Rank	Sources of Losses
GEN	Natural attrition and retirement
COL-MAJ	Natural attrition, retirement and movement to reimbursable billets
CAPT	Natural attrition, those released from active duty, and movement to reimbursable billets
ILT ment	Natural attrition and those released from active duty
2LT - WO-1	Natural attrition

Promotions into a given rank are of course related to promotions out of lower ranks. Since time periods are typically of one-month length, promotions of more than 1 rank in a time period are assumed not to occur. An exception occurs in promotions from warrant officer status to limit duty officer (LDO) in the rank of 1LT.

For the ranks GEN through CAPT and for CWO-4 through CWO-2, the promotions into a rank are equal to the promotions out of the next lower rank. Thus

(4)
$$x_j(t) = y_{j+1}(t), \quad j = 1,2, ..., 5, \quad t \ge 1.$$

 $j = 8,9,10,$

Note that $y_1(t)$ is zero (no promotions out of the highest rank).

Let $z_j(t)$ be the number in rank j promoted to 1LT as LDO's, for j=8,9,10, $t\geq 1$. Then

(5)
$$x_6(t) = y_7(t) + z_8(t) + z_9(t) + z_{10}(t), t \ge 1.$$

No promotions are possible into 2LT or WO-1, thus $x_7(t)$ and $x_{11}(t)$ are both zero.

Equation (3) can now be simplified by eliminating x(t+1). Let A be an 11 x 11 matrix of 0's and 1's where

- (i) the diagonal immediately above the main diagonal has all elements equal to 1 except for the one on row 6 which is 0,
- (ii) all other elements of A are O.

Let B be an 11 x 11 matrix of 0's and 1's where

- (i) elements in columns 8, 9, and 10 on row 6 are equal to 1,
- (ii) all other elements are equal to 0.

Let z(t) be an 11-vector with $z_8(t)$, $z_9(t)$ and $z_{10}(t)$ in positions 8, 9, and 10 respectively, and all other elements equal to zero. Then from (4) and (5)

(6)
$$x(t) = Ay(t) + Bz(t), t > 1.$$

Substituting this into (3) gives

(7)
$$s(t+1) = s(t) + g(t+1) - \ell(t+1) + (A-I)y(t+1) + Bz(t+1), t > 0.$$

Here I represents an identity matrix. Equation (7) can now be used to determine the officer manpower plan.

3. The Calculation Procedure

For ranks GEN through CAPT (1-5) the end strengths, gains and losses are all given. Denote with a - the system comprising the first 5 equations in (7). Since the 5 x 5 matrix taken from the upper left of B is a zero matrix, we have

(8)
$$\bar{s}(t+1) = \bar{s}(t) + \bar{g}(t+1) - \bar{\ell}(t+1) + (\bar{A}-\bar{I})\bar{y}(t+1), \quad t \geq 0.$$

The only unknowns in this equation are the elements of $\bar{y}(t)$ for $t \ge 1$. Thus we solve (8) to obtain

(9)
$$\bar{y}(t+1) = (I-\bar{A})^{-1} [\bar{s}(t) - \bar{s}(t+1) + \bar{g}(t+1) - \bar{k}(t+1)], \quad t \geq 0.$$

The solution of (9) gives the promotions out of ranks COL through 1LT for each period in the planning horizon.

For ranks 2LT to WO-1, the promotions out are given, together with the gains and losses. Denote with $^{\circ}$ the system comprising the last 5 equations in (7). Then given the starting stocks we determine $\hat{s}(1)$ by

(10)
$$\hat{s}(1) = \hat{s}(0) + \hat{g}(1) - \hat{\ell}(1) + (\hat{A}-I)\hat{y}(1) + \hat{B}\hat{z}(1),$$

then $\hat{s}(2)$, $\hat{s}(3)$ etc. recursively through the planning horizon. The only remaining rank for which calculations have not been made is lLT. For ranks above this, end-strengths are given and promotions calculated. For ranks below lLT, promotions are given and end-strengths calculated. For lLT we have

$$s_6(t+1) = s_6(t) + g_6(t+1) - \ell_6(t+1) + x_6(t+1) - y_6(t+1), \quad t \ge 0.$$

Starting at t=0, $s_6(0)$ is given, as are $g_6(1)$ and $l_6(1)$. Promotions out, $y_6(1)$, are calculated through equation (9), and promotions in, $x_6(1)$, are calculated through (10) and (5). Thus the unknown is the end-strength $s_6(1)$. This and future period end strengths are calculated recursively over the planning horizon after equations (9) and (10) have been solved for all other ranks.

4. APL Data Input Functions

The following page lists eleven matrices and one vector which are used to store input data required in computing the officer manpower plan. The results of the calculations are also stored in these arrays.

There are eight APL input functions used to interactively enter data at a remote terminal. Each one is described on the following pages together with a listing of the function and an illustrative example of its use. Alternative methods of data input are illustrated. The use of the APL operator ρ can save time when repetitive numbers have to be entered. See Gilman and Rose [1] for details of APL operators.

DATA ARRAYS

These arrays are stored as global variables.

APL Name	<u>Dimensions</u>	Description
<i>BS<u>M</u></i>	11 x 12	Matrix of beginning strengths, 11 ranks (GEN - WO-1), 12 periods
ES <u>M</u>	11 x 12	Matrix of end strengths, 11 ranks, 12 periods
LF <u>M</u>	11 x 12	Matrix of loss factors, 11 ranks, 12 periods
$L\underline{M}$	11 x 12	Matrix of losses, 11 ranks, 12 periods
MG <u>M</u>	11 x 12	Matrix of monthly gains, 11 ranks, 12 periods
<i>РО<u>М</u></i>	11 x 12	Matrix of promotions "out", 11 ranks 12 periods
LDO <u>M</u>	11 x 12	Matrix of promotions to LDO from warrant officer ranks, 11 ranks, 12 periods
ARM_	11 x 12	Matrix of numbers in reimbursable billets, 11 ranks, 12 periods
TRM_	11 x 12	Matrix of transfers <u>to</u> reimbursable billets, ll ranks, l2 periods
FR <u>M</u>	11 x 12	Matrix of transfers <u>from</u> reimbursable billets, 11 ranks, 12 periods
RL <u>M</u>	11 x 12	Matrix of numbers released from active duty, 11 ranks, 12 periods
TL <u>V</u>	11	Vector of yearly losses from each rank, 11 ranks

Type) SAVE after data entry completion to ensure that new input data is not lost.

BSINPUT (begin strength input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message EM, the rank vector RANKY, and the data matrix BSM.

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter the numbers in each of 11 ranks (GEN - WO-1) at the beginning of a planning period and store them as the first column of an 11 x 12 BSM.

Example:

BSINPUT

BEGIN STRENGTH?

GEN COL LCOL MAJ CAPT 1LT 2LT W-4 W-3 W-2 W-1

1:
67 573 1471 2909 4348 4086 3381 199 79 411 504

Function Listing:

ESINPUT (end strength input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message $E\underline{M}$, the month matrix \underline{MONTH} , the rank vector \underline{RANKV} , and the data matrix \underline{TSM} .

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter the planned end strengths for ranks GEN, COL, LCOL, MAJ, and CAPT for each of the 12 planning months. These are stored in the first 5 rows of the 11×12 matrix ESM.

Example:

ESINPUT END STRENGTH? OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP □: 67 67 67 67 67 67 67 67 67 67 67 67 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0: 120574 LCOL OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP □: 1201472 MAJ OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP □: (5p2910),2912,6p2913 CAPT OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP □: 1204848

Function Listing:

 $\begin{array}{c|c} \forall ESINPUT[\] \forall \\ \forall ESINPUT; X\\ [1] \quad 'END \quad STRENGTH?' \Leftrightarrow I+0\\ [2] \quad L1:RANK \underline{V}[(6\times I)+16] \Leftrightarrow MONT\underline{H},' \\ [3] \quad +(12=\rho X+\])\rho L2 \Leftrightarrow \underline{EM} \Leftrightarrow +L1\\ [4] \quad L2:ES \underline{M}[I+1;]+X \Leftrightarrow +(4\geq I+I+1)\rho L1\\ \end{array}$

LFINPUT (loss factor input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message EM, the month matrix MONTH, the rank vector RANKY and the data matrix LFM.

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter the desired loss factors for each of 11 ranks (starting with GEN and ending with WO-1) for each of the 12 planning months. The 12 month factors must add to 1.0. These factors are used to spread yearly losses from each rank by month. They are stored in the 11 x 12 matrix LFM.

Example:

LFINPUT
LOSS FACTORS?

GEN

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .04 .03 .02 .01 .06 .06 .06 .04 .05 .077

INCORRECT INPUT

GEN

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .04 .03 .02 .01 .06 .06 .05 .05 .07 .31 .1 .2

COL

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

: .

Function Listing:

\[\forall \text{VLFINPUT}[\pi] \forall \forall \text{VLFINPUT}; I; X \]

\[\forall \text{LOSS FACTORS?'} \leq I+1 \]

\[\forall \text{L1:RANKV}[(6 \times I-1) + 16] \leq \text{MONTH}.' \forall \]

\[\forall \text{L2:PM}[I;] + X \leq \text{+(11≥I+I+1)} \rho L1 \]

\[\forall \text{L2:LFM}[I;] + X \leq \text{+(11≥I+I+1)} \rho L1 \]

MGINPUT (monthly gains input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message EM, the rank vector RANKV, the month matrix MONTH, and the data matrix MCM.

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter the expected gains in each of 12 months into the ranks WO-1, 2LT and 1LT respectively. These are stored in rows 11, 7 and 6 of the 11 x 12 matrix MGM.

Example:

MGINPUT MONTHLY GAINS? W-1 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0 250 0 0 0 0 0 2LTOCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0 19 134 178 363 140 288 242 152 158 102 1LTOCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP **:** 0 2 0 3 6 0

Function Listing:

∇MGINPUT[□]∇
∇ MGINPUT;I;M;V;X

[1] 'MONTHLY GAINS?' ◊ I+1 ◊ M+ 3 6 ρ(60+16),(36+16),30+16 ◊ V+ 11 7 6

[2] L2:RANKV[,M[I;]] ◊ ,MONTH,''

[3] +(12=ρX+□)ρL3 ◊ EM ◊ +L2

[4] L3:MGM[V[I];]+X ◊ +(3≥I+I+1)ρL2

POINPUT (promotions-out input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message EM, the rank vector RANKV, the month matrix MONTH, and the two data matrices POM and LDOM.

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter the planned promotions in each of 12 months out of ranks 2LT, and the warrant officers. These are stored in rows 7 through 11 of the 11 x 12 matrix POM. The function then asks for the numbers in each 12 months who became limited duty officers (LDO) from each of the 4 warrant ranks. These numbers are stored in rows 8 through 11 of the 11 x 12 matrix LDOM.

Example:

POINPUT PROMOTIONS OUT? OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP □: 0 415 14 194 0 4 115 60 750 331 7-4 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP **:** 12p0 W-3 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 39 W-2 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0 0 0 66 0 0 0 0 0 W-1 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 1: (400),234,700 TO LDO? 7-4 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0 0 0 2 W-3 OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0: (8p0),25.(3p0)

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

(8p0),73,3p0

W-1

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

12p0

Function Listing:

REIMINPUT (reimbursable input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message EM, the rank vector RANKV, the month matrix MONTH, and the data matrices TRM and FRM.

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter scores to and from reimbursable billets for each of 12 months for the ranks COL, LCOL, MAJ, and CAPT and store them in rows 2 through 5 of the 11 x 12 matrices TRM and FRM respectively.

Example:

REIMINPUT COL TO REIMB OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0: 1 ,1000 COL FROM REIMB OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP □: 1.1100 LCOL TO REIMB OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0: VALUE ERROR 1200 **1**: 1200 CAPT TO REIMB OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0 0 1 0 0 0 0 0 0 CAPT FROM REIMB OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP 0: 0 0 2 0 0 0 0 1 0 0

Function Listing:

```
VREIMINPUT[ ] V
       M+ 4 6 p6+30+RANKY ◊ I+1
     V REIMINPUT; M; X; I
[1]
      L1:M[I;], TO REIMB' \diamondsuit , MONTH.' 
 \rightarrow (12=\rho X + \Box)\rho L2 \diamondsuit EM \diamondsuit \rightarrow L1
[2]
[3]
[4]
      L2: TRM[I+1;]+X
      L3:M[I;], FROM REIMB' O ,MONTH.'
[5]
[6]
      +(12=pX+\Box)pL4 \diamondsuit EM \diamondsuit +L3
[7]
     L4:FRM[I+1;]+X
[8]
       +(4 \ge I + I + 1) \rho L 1
```

RLDINPUT (released from active duty input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message M, the rank vector RANKV, the month matrix MONTH, and the data matrix RLM.

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter the numbers in each of 12 months who will be released from active duty in the ranks CAPT and 1LT. The data is stored in rows 5 and 6 of the 11×12 matrix RLM.

Example:

RLDINPUT

RELAD?
CAPT

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

1:
4 16 14 6 2 9 4 7 9 8 14 12
1LT

OCT NOV DEC JAN FEB MAR APR MAY JUN JUL AUG SEP

1:
55 55 90 41 35 62 28 48 90 48 62 76

Function Listing:

TLINPUT (total loss input)

Syntax: Niladic, interactively asks for input

Global Variables: It requires the error message EM, the rank vector RANKY, and the data vector TLY.

Files: None

Functions: None

<u>Purpose</u>: This function allows the user to enter the losses from each of the ll ranks for the planning period, and store them in the ll-vector $TL\underline{V}$.

Example:

TLINPUT TOTAL YEAR LOSSES? W-1 COL LCOL CAPT 1LT 2LTW-3 GEN MAJ □: 35 25 8 4 11 95 155 160 593 109 60

Function Listing:

5. APL Calculation and Output Format Functions

The calculation, interactive changing, and formatting of the officer manpower plan require ten APL functions. These are listed on the following pages. Only one is specified by the user, namely OFPLAN. This function calls the other nine at appropriate points and they remain invisible to the terminal user.

OFPLAN (officer manpower plan)

<u>Syntax</u>: Niladic, interactively asks for various changes in variables and for the amount of detail to be printed.

Global Variables: The data arrays: BSM, ESM, LFM, MGM, POM, LDOM, TRM, FRM, RLM, and TLV.

Files: None

<u>Functions</u>: Requires the utilities AYN (answer yes or no) and DATE, the formatting functions FMTI, ESREP, OF1E, OMPREP and ATREIMB, and the calculation functions CHGFM, CHGIM, PLAN1.

<u>Purpose</u>: This is the main interactive function for obtaining the manpower plan. It is the only one (other than functions to input data) that the user specifies when calculating a plan.

Function Listing: See next page.

L1;+(~AYN 'CHANGE LOSS FACTORS?')pL2 ♦ LFM+CHGFM LFM L2;+(~AYN 'DISPLAY END STRENGTHS?')pL3 ♦ FNTI 5 12 +ESM L3;+(~AYN 'CHANGE END STRENGTHS?')pL7 ♦ ESM+CHGIM ESM L7;+(~AYN 'CHANGE REIMB?')pL4 ♦ 'TO REIMB' ♦ TRM+CHGIM TRM ♦ 'FROM REIMB' ♦ FRM+CHGIM FRM CR PLAN
MONTHLY END STRENGTHS' \$\langle LF \$\langle ESREP \$\langle 5\rangle L \rangle +(\sigma IN) \rangle 1-E TABLE?')\rangle L6
OFFICER 1-E' \$\langle LF \$\langle 0F1E \$\langle +(\sigma IN) \rangle INP PLAN?')\rangle L6
OFFICER MANPOWER PLAN' \$\langle 0MPREP \$\langle 2\rangle LF \$\langle 10MPREP \$\ L5:+(~AYN 'DISPLAY LOSS FACTORS?')pL1 ♦ FMTF LFM USMC OFFICER PLAN [11] L6:+(AYN 'CONTINUE?') pL5 L4:PLAN1 & LF V OFPLAN [10] [1] [3] [4] [5] [9] [7] 8] 9]

VOFPLAN[]]V

CHGFM

CHGF14

Syntax: Monadic, $R \leftarrow CHGFM M$

Global Variables: It requires the error message EM.

Files: None

Functions: None

<u>Purpose</u>: It allows the user to change any elements in a fractional matrix, and checks that the new entries are consistent with row sums equal to 1.0. It is used only inside other functions.

Function Listing:

CHGIM

Syntax: Monadic, R + CHGIM M

Global Variables: It requires the error message, EM.

Files: None

Functions: None

 $\frac{\text{Purpose}}{\text{matrix.}}: \quad \text{It allows the user to change any elements in an integer} \\ \\ \text{matrix.}$

Function Listing:

PLAN1

Syntax: Niladic

<u>Global Variables</u>: It requires all the data arrays, $BS\underline{M}$, $ES\underline{M}$, $LF\underline{M}$, $L\underline{M}$, $MG\underline{M}$, $PO\underline{M}$, $LDO\underline{M}$, $TR\underline{M}$, $FR\underline{M}$, $RL\underline{M}$, and $TL\underline{V}$.

Files: None

Functions: Requires the integer rounding function ROUND

<u>Purpose</u>: This function performs all the calculations for the manpower plan discussed in section 3.

Function Listing: See next page for both PLAN1 and ROUND.

 $\begin{array}{l} BSM[IV;1+111] + ESM[IV+15;111] \\ POM[1+IV;1+IV;1] + B + ... \times ESM[IV;1] + LM[IV;1] + RLM[IV;1] + RLM[IV;1] + RLM[IV;1] \\ BSM[6;1+111] + 11 + ESM[6;1+IV] + RIM + ... \times (12 + BSM[6;1]) + MGM[6;1+IV] + (+ \#LDOM) - POM[6;1+LM[6;1] + LMGM[6;1] \\ M + - S + 12 + MGM + ((12p1) \Theta POM) - RLM + LM + POM + LDOM \\ \end{array}$ +(122I+I+1)pL1 \$ BSM[6+IV;1+111]+ESM[6+IV;111] PLAN1; IV; I; V; PEM; NEM; LM; EV LM+ROUND LFM×W 12 11 PTLY L1: 8SM[6+IV; I]+E+E+M[; I] B+BSM[6+IV;1] ♦ I+1 VPLAN1[0]V 0 325 [8] [7]

26

L1:TM[I;J]+TM[I;J+1+VTM[I;]]+EV[I] ♦ +(N≥I+I+1)pL1 ♦ R+TM

N+pEV+(+/M)-+/TM+L0.5+M \$ I+1

[2]

V R+ROUND M;EV;TM;N

FMTF

Syntax: Monadic, R + FMTF M

Global Variables: It requires the month matrix $MONT\underline{H}$ and the rank vector $RANK\underline{V}$.

Files: None

Functions: None

 $\frac{\text{Purpose}}{\text{It is used only within other functions}}. \ \ \, \text{It is used only within other functions}.$

Function Listing:

VFMTF[□]∇
∇ FMTF M
[1] ' RANK',,(12 3 ρ' '),MONTH
[2] (11 6 ρRANKY),'F6.2' □FMT M
∇

FMTI

Syntax: Monadic, R + FMTI M

Global Variables: It requires the month matrix MONTH and the rank vector RANKY.

Files: None

Functions: None

 $\frac{\text{Purpose}}{\text{headers}}. \hspace{3mm} \text{It formats the matrix } \textit{M} \hspace{3mm} \text{into integers with column and row} \\ \text{headers}. \hspace{3mm} \text{It is used only within other functions}.$

Function Listing:

VFMTI[□]V V FMTI M;N [1] N+(pM)[1] [2] ' RANK',,(12 3 p''),MONTH [3] ((N,6)pRANKV),'BI6' □FMT M

ESREP

Syntax: Niladic

Global Variables: It requires the month matrix $MONT\underline{H}$, the rank vector $RANK\underline{V}$, and the data arrays $BS\underline{M}$ and $ES\underline{M}$.

Files: None

Functions: None

<u>Purpose</u>: It formats the "End Strength Report" as part of the manpower plan.

Function Listing:

\text{VESREP[\(\)] \text{V} \text{VESREP; MY A; X} \\
[1] MY A + (+ / BSM + ESM) + 2 + \\
[2] 'BEGIN', 'GRADE', (, (12 3 p''), MONTH), 'MYA' \\
[3] ('I6' \(\)FMT 11 1 + BSM \), (11 6 pRANK\(\)), 'I6' \(\)FMT (ESM \), MYA \\
[4] 'TOTAL',, 'I6' \(\)FMT + \(\)FESM \\
\text{V}

OF1E

Syntax: Niladic

Global Variables: It requires the month matrix $MONT\underline{H}$ and the data arrays $BS\underline{M}$, $ES\underline{M}$, $RL\underline{M}$, and $L\underline{M}$.

Files: None

Functions: None

<u>Purpose</u>: It formats the "Officer 1E Table" as part of the manpower plan.

Function Listing:

```
VOF1E[□]∇

V OF1E;X;Y;M;V

V++fM+Φ 6 12 ρ(+fBSM),X,Y,((Y++fLM)+X++fRLM),(+fMGM),+fESM

LOSSES !'

I LOSSES !'

MONTH BEGIN RELAD OTHER TOTAL GAINS END'

('',MONTH,''),(12 2 ρ''),'BI8' □FMT M

TOTAL ',,'I8' □FMT(M[1;1],(4+1+V),M[12;6])
```

OMPREP

Syntax: Niladic

Global Variables: It requires the month matrix MONTH, rank vector RANKV, the formatting headers H1, H1G, H2, H3, H4, H5, H6, H7, H8, H9, H11, H12, H13, and H14, the line feed LF, and all the data arrays.

Files: None

Functions: None

<u>Purpose</u>: It formats the "Officer Manpower Plan," the main output showing the monthly details of a yearly plan for each rank.

Function Listing: See next page.

```
PM & LF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                #12, #11, BI6 DEMT TW & LF & #14, #13, BI6 DEMT TO+TOI[1 2 3 4 8 9 ;]+(1 0 1 1 0 1)\[
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       M6+ 9 13 \rho(13+V), R, OL, TL, ((+/G), G+MGM[6;1], (-26+^{-}13+V), ((+/L), L+\neq LDOM), ^{-}13+V
(9 6 \rho(24\rho^{-}), 6+30+RANKL), (9 3 \rho^{-}), H_3, BI6 BRM M6 \diamondsuit LF
(5 6 \rho(12\rho^{-}), 6+36+RANKL), (5 3 \rho^{-}), H_4, ^{-}BI6 BRM M7+ 5 13 \rho(26+V), (G+(+/G), G+MGM[7;1], (-13+^{-}26+V), -13+V+M[7;1] \diamondsuit LF
T:1), (-13+^{-}26+V), -13+V+M[7;1] \diamondsuit LF
TO1+ 1 13 \rhoMI[1;1]+M2[1;1]+M4[1;1]+M5[1;1]+M6[1;1]+M7[1;1]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              (5 9 pu5+(18p¹¹), 'CWO-u¹), H7, 'BI6' □FMT M8+ 5 13 p(26+V), (-13+-13+V), ((+/L), L+LDOM[8;]), 13+V+M[8;] ♦ LF
                                                                                                            M+BSM[;1],BSM,(+/TRM),TRM,(+/LM),LM,(+/POM),POM,(+/PI),(PI+(12p1)@POM),(+/FRM),FRM,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             H9,(12 12 pH8), 'BI6' UFMT M9+ 12 13 p(0 13 +V), ((+/L), L+LDOM[8+12;]), 2 13 +V+M[
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         (6 9 \rho54+(18\rho''),'WO-1'),<u>H</u>10,'BI6' []FMT M10 \Diamond LF
TW+(M10[1 2 ;]+M8[1 2 ;]+M9[7 8 ;]+M9[1 2 ;]),[1] M10[3;] \Diamond TW+TW,[1] M8[4;]+M10[
                                                                                                                                                                                                                                    13
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 M10+ 6 13 p(26+V), ((+/G), G+NGM[11;]), ( 13+ 26+V), ((+/L), L+LDOM[11;]), 13+V+M[
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       TM + TW, [1] M10[4; ] + + fM9[3 9 ; ] <math>\Diamond TW + TW, [1] M8[3; ] + + fM9[4 10 ; ] <math>\Diamond TW + TW, [1] M8[
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  (9 6 p(24p' '),6+2u+RANKL),(9 3 p' '),H2,'BI6' UFMT M5+ 9 13 p(26+V),R,L,TL,
                                                                                                                                                                                                                (4 6 \rho(12\rho''), 6+RANKQ), (4 3 \rho''), HIG, BIG! \Box FMT M1+(1 0 1 0 1 0 1)/[1] (7 6 \rho(18\rho''), 6+G+RANKQ), (7 3 \rho''), HI, BIG! \Box FMT M2+ 7 13 \rhoM[2;] \Diamond LF (7 6 \rho(18\rho''), 6+G+RANKQ), (7 3 \rho''), HI, GIG! GIFMT 
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       TO1+TO1,[1] M1[2;]+M2[3;]+M3[3;]+M4[3;]+M5[5;]+M6[4;]+M7[2;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 TO1+TO1,[1] M1[4;]+N2[7;]+M3[7;]+M4[7;]+M5[9;]+M6[9;]+M7[5;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           TO1+TO1,[1] M2[4;]+M3[4;]+M4[4;]+M5[6;]+M6[6;]+M7[4;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 TO1+TO1,[1] M1[3;]+M2[5;]+M3[5;]+M4[5;]+M5[7;]+M6[7;]
                                                  TOTAL' . . (12 3 p' ') . MONTH
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     r01+r01,[1] M6[5;]+W7[3;] ◊ r01+r01,[1] M6[8;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      M+(IN, OUT, (39pIN), (OUT+13p0), (IN+13p1))/M
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 TO1+TO1,[1] M2[2;]+M3[2;]+M4[2;]+M5[2;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            TL+(R+(+/R),R+RLM[6;])+0L+13+13+V+M[6;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           TO1+TO1,[1] M2[6;]+M3[6;]+M4[6;]+M5[8;]
OMPREP; M; V; PI; TL; R; L; OL; G
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               H5.46. BIG □FMT TO1 ♦ LF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             5;]+W10[6;]++#M9[6 12 ;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             5; ]++#N9[5 11 ;]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       8+12;] $ LF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         24]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 [25]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   [27]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           [29]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    10]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              11]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        12]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     17]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         19]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           20]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             21]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     15]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               16]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           18]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   22]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  14]
                                                                                                        [2]
                                                                                                                                                                                                                                                                                                                                                                                                          [9]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                [7]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          8]
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  9
                                                                                                                                                                                                                                                                                      7
                                                                                                                                                                                                                                                                                                                                                    [5]
```

ATREIMB

Syntax: Niladic

Global Variables: It requires the data arrays ARM, TRM and FRM.

Files: None

Functions: None

<u>Purpose</u>: It formats the movement of officers at, to, and from reimbursable billets as part of the manpower plan.

Function Listing:

```
VATREIMB[□] V

VATREIMB

[1] ' OFFICERS IN REIMBURSABLE BILLETS'

[2] ' COL LCOL MAJ CAPT'

[3] 'BEGIN',,'I10' □FMT, ARM[1+14;1]

[4] ' TO',,'I10' □FMT(+/TRM)[1+14]

[5] ' FROM',,'I10' □FMT(+/FRM)[1+14]

[6] ' END',,'I10' □FMT(+/TRM+ARM-FRM)[1+14]
```

6. An Example

The next seven pages give an example of an officer manpower plan. This example does not show every feature of the interactive capability, but should be sufficient to illustrate the use of the model. A complete plan takes less than five minutes of terminal time and less than 1 second CPU time on Scientific Time Sharing's APL+ system. Thus many iterations are possible in the planning cycle.

OFPLA	2	0000										
	LUSS F	ACTOR	٦	•	:		5	•	:	:	:	
	LOO	NON	DE	A	FE	MA	AP	MA	70	70	AU	SE
	n.0.0	0.03	0.0	0.	0	0.	0	0	0			. 2
	.07	0.05	0.0	0.	0.	0.	0.	0	0	• 5	-	7
COL 0	.10	90.0	0.0	0.	0.	0.	0	0.	0.		-1	.1
	80.0	90.0	0.0	0.	0.	0.	0.	0.		۲.	.1	7
CAPT 0	0.07	0.07	0.1	0.	0.		0.	0.	0	0.	0	0
0	80.	0.08	0.1	0.	0.	0.	0.	0.	.1	0	0.	
0	0.08	0.08	0.0	0.	0.	0.	0.	.1	.1	0.		0
	.05	0.05	0	0.08	0.08	0.09	0.07	0.10	0.07	0.08	0.10	0.16
3 0	.11	90.0	0.0	0.		0.	0.	0.	0.	۲.	0.	
2 0	60.	0.05	0.1	0.	0.	۲.	0.	0.	0.		.1	0.
0	60.	0.16	0.0	0.	0.	0.	0.	0.	0.	0.	.2	7.
77	B	CTORS	NO									
~	END ST	RENGT	S? YE	S								
	I	NOV	DEC	JA					JUN	JUL	AUG	
	6.3	67	9	9	9		9	9	9	9	9	9
	574	575	57	1	-	-	-	1	-	-	-	-
-	1472	1472	147	47	47	47	47	47	47	47	47	47
2	2910	2910	291	2910	2910	2910	2910	2910	2910	2910	2910	2910
CAPT 4	8484	8484	484	84	84	8 4	84	84	84	84	84	84
CHANGE END	ST	ENGTH	Z ZE									
ENTER ZERO	O FOR	RANK	IF	MORE	CHANGE	S						
NUMB	٥.											
2												
ENT												
574	575	575	574	574	574	574	574	574	574	574	574	
NEW?												
574	74	-										
	574	575,9	p574									
RANK NUMBER												
	9	On										
CHANGE KEIN	IMPL	107										

USMC OFFICER PLAN

DATE: -20 AUGUST 1977

MONTHLY END STRENGTHS

MY A 67	1472	2910	4103	3358	195	80	481	512	
SEP 67	574	2910	4198	3216	187	4 5	488	516	18521
AUG 67	574	2910	4383	3233	197	8 #	684	517	18738
10L 67	574	2910	4571	2958	203	20	064	518	18661
JUN 67	574	2910	4432	3152	208	53	491	518	18725
MAY 67	574	2910	3776	3543	175	119	999	518	18566
APR 67	574	2910	3841	3427	181	121	264	518	18523
MAR 67	574	2910	3827	3411	185	123	565	518	18500
FEB 67	1472	2910	3992	3399	190	125	999	518	18661
JAN	1472	2910	4095	3401	195	62	398	505	18524
DEC 67	575	2910	4018	3495	200	ħ 9	398	502	18549
NOV 67	1472	2910	4212	3354	204	99	399	505	18608
0CT 67	574	2910	3942	3620	203	72	399	504	18611
GRADE	TCOT	MAJ	1LT	2LT	H+H	N-3	W-2	W+1	TOTAL
BEGIN 67									

1-E TABLE? YES

OFFICER 1-E

		707	SSES	-		
MONTH	BEGIN	RELAD	ID OTHER	TOTAL	GAINS	END
OCT	18518	59	95	154	244	18611
NON	18611	7.1	8 5	156	153	18608
DEC	18608	104	116	220	161	18549
JAN	18549	47	82	129	104	18524
FEB	18524	37	82	119	256	18661
MAR	18661	71	109	180	19	18500
APR	18500	32	79	111	134	18523
MAY	18523	5.5	82	137	180	18566
JUN	18566	66	105	204	363	18725
JUL	18725	99	151	207	143	18661
AUG	18661	16	135	211	288	18738
SEP	18738	88	134	222	2	18521
TOTAL	18518	795	1255	2050	2050	18521

MP PLAN? YES

SEP	6.3	2	2	6.7	574		11	2	13		574	1472		20	13	33		1472	2910		18	33	51		2910
AUG	63	1	1	61	574		13	1	14		574	1472		22	14	36		1472	2910		22	36	28		2910
JUL	63	3	3	67	574		22	9	25		574	1472		28	25	53		1472	2910		25	53	7.8		2910
JUN	63	-	1	6.3	574		80	1	6		574	1472		6	6	18		1472	2910		16	18	34		2910
MAY	67	-	-		574		2	-	9		574	1472		80	9	14		1472	2910		80	14	22		2910
APR	63	-1	-	67	574		3	1	2		574	1472		8	2	13		1472	2910			13			2910
MAR	19 .	-1	-	6.7	574		2		9		574	1472		6	9	15		1472	2910		80	15	23		2910
PEB	67	-1	-1	67	574		1	1	8		574	1472		12	80	20		1472	2910		11	20	31		2910
JAN	6.7			67	575		2		#		574	1472		8	1	12		1472	2910		11	12	23		2910
DEC	67			6.3	574		က		#		575	1472		9	#	10		1472	2910		8	10	18		2910
PLAN	67			6.3	574		2		2		574	1472		6	2	14		1472	2910		10	14	24		2910
WPOWER	67			67	573		1		7	1	574	1471		16	7	23	1 7 1	1472	2909		13	23	36	1	2910
OFFICER MANPOWER TOTAL OCT	67	11	11	67	573		9 5	11	106	1	574	1471		155	106	261	1	1472	2909		160	261	421	1	2910
OF	BEGIN	LOSSES	PROM IN		BEGIN	TO REIMB	LOSSES	PROM OUT	PROM IN	FROM REIMB	END	BEGIN	TO REIMB	LOSSES	PROM OUT	PROM IN	FROM REIMB	END	BEGIN	TO REIMB	LOSSES	PROM OUT		FROM REIMB	END
RANK			GEN					700							7027							MAJ			

8 + 8 +	12	53	6.5	51	116		8 + 8 +		16			2	116	14		4198	3233	3		14	3216	17487		207	2		2	229	1906	17285
8 # 8 #	14	53	6.3	5.8	125		8 + 8 +	4571	62	10	72		125	6		4383	2958	7	288	6	3233	17400		201	288		#	243	171107	104/1
8 # 8 #	8	53			139		8 + 8 +	4432	8 1	80	99	3	3	331		4571	3152	3	140	331	2958	17455		6	143		2	629	171100	11400
8 # 8 #	6	47	99	34	06		8 # 8 #	3776	06	14	104		90	750	0	4432	3543	#	363	750	2	17190		6	9	100	0	0	17455	204/1
8 # 8 #	7	42	6 1	22	7.1		8 + 8 +	3841	8 1	80	9 9	2	7.1	09		3776	3427	2	178		3543	17139		129	8		174	174	17190	11130
8 # 8 #	#	42	9 17	23	69		8 1 8 1	3827	28	#	32			115		3841	3411	9	3	115	2	17109		104	3		226	226	17139	11133
8 † 8 †	6	65		23			8 + 8 +	3992	62	10	72		9.1	#		3827	3399	3	19	7	3411	17262		172				146	17109	60111
8 † 8 †	2	36	38	31	69		8484	4095		2	0 #	9	69			3992	3401	2			3333	17367		111	9		129	129	17969	70711
8 # 8 #	9	42	8 +	23	7.1		8 + 8 +	4018	41	7	8 1	2	71	194		4095	3495	2	102	194	3401	17385		122	104		304	304	17367	10011
8 # 8 #	14	16	90	18	108		8 + 8 +	4212	9.0	13	103	3	108	14		4018	3354	3	158		3495	11437		213	9		154	2	17385	
8 # 8 #	16	42	28	24	82		8 1 8 1		2	6	1 9	-		415		4212	3620	9	2	41	2	1/433		149	2		240	#	17437	2
8 1 8 1	#	42	111000	36	82		8 1 8 1	4086		6	†9	2	82			3942	3381	3	242		3620	17335		149	#		#	148	17433)
8 # 8 #	105	593	869	421	1119		8 # 8 #	4086	069	109	799	24	1119	1906	100	4198	3381	35	1776	1906	3216	1/335		1953	1800	100	3824	3824	17285	,
BEGIN TO RETMR	RELAD	OTHER LOSSES	TOTAL LOSSES			FROM REIMB	END	BEGIN	RELAD	OTHER LOSSES			PROM OUT		FROM W.O.	END	BEGIN	LOSSES	GAINS	PROM OUT	END	BEGIN	TO REIMB	LUSSES	S			PROM IN		
			CAPT									171				30			2LT						TOTAL		2LT - GE			

197	187 4 8	4.89 1.89	8 8 8	517	1251 15 1236
203	197 50 2	4 9 0 1	688	518	1261 19
208	203 53	50 491	06 #	5 18	1270
175 4 39 2	208 1119 2	39 25 56 56	73	518	1376 6 100 39 39 1270
181	175 121 2	119 564	564	518	1384 8 1376
185	181 123 2	121 565	999	518	1391
190	185 125 2	123 566 1	565	5 18	1399 8 1391
195	190 62 3	66 125 398	66 234 566	502 250 234 518	1157 8 250 300 300 1399
200	195 64 2	398	398	502	1164
204	200	64 399	398	502	1171
203	204 72 2	4 99 99	399	504	1178 7 4 1171
199	203	7 72 401	399	504	1183 5 7 7 7 1178
199 60 50 2	187	50 66 25 401 8	66 234 73 488	504 250 234 516	1183 97 250 100 350 350
BEGIN LOSSES PROM IN TO LDO	END BEGIN LOSSES	PROM OUT PROM IN TO LOO END BEGIN LOSSES	PROM OUT PROM IN TO LDO END	BEGIN LOSSES GAINS PROM OUT TO LDO	BEGIN LOSSES GAINS TO LDO PROM OUT
h-0.83		CW0-3	C#0-2 40	W0-1	TOTAL WARRANT OFFICERS

18738	222	3 111 18608 18549 18524 18661 18500 18523 18566 18725 18661 18738 18521
18661	211 288	18738
18725	207	18661
18566	204	18725
18523	137	18566
18500	111	18523
18661	119 180 111 256 19 134	18500
18524	119	18661
18549	129	18524
18608	220	18549
18611	154 156 244 153	18608
18518	154 244	3
18518 18518 18611 18608 18549 18524 18661 18500 18523 18566 18725 18661 18738	2050	3 18521 1861
M.T. Cad	TOTAL LOSSES OFFICERS GAINS	FROM REIMB END

 BEGIN
 OFFICERS IN REIMBURSABLE BILLETS

 COL
 LCOL
 MAJ
 CAPT

 COL
 LCOL
 MAJ
 CAPT

 21
 9
 2
 2

 TO
 0
 0
 0
 0

 TO
 1
 1
 1
 0

 END
 7
 20
 8
 2

REFERENCES

- [1] Gilman, L. and Rose, A. J., APL: An Interactive Approach, J. Wiley, New York, 1974.
- [2] Grinold, R. C. and Marshall, K. T., <u>Manpower Planning Models</u>, Elsevier-North Holland, 1977.